

天利合企業股份有限公司 ADVANCE SECURITY INC.

211新北市汐止區大安街48號3樓

3F, 48 TA AN STREET HSI-CHIH DIST. NEW TAIPEI CITY221, Taiwan (R.O.C.)

Tel: +886-2-8648-1688 Fax: +886-2-8648-1689

Product name: Car alarm 2 way main unit

Product model: 75SL FCC ID: H5OTR75

Table for Carrier Frequencies

| Channel | Frequency(MHZ) | Channel | Frequency(MHZ) |
|---------|----------------|---------|----------------|
| 01 | 908.300 | 14 | 916.040 |
| 02 | 908.895 | 15 | 916.635 |
| 03 | 909.490 | 16 | 917.233 |
| 04 | 910.085 | 17 | 917.825 |
| 05 | 910.680 | 18 | 918.422 |
| 06 | 911.277 | 19 | 919.612 |
| 07 | 911.872 | 20 | 920.805 |
| 08 | 912.467 | 21 | 921.400 |
| 09 | 913.063 | 22 | 921.995 |
| 10 | 913.658 | 23 | 922.590 |
| 11 | 914.255 | 24 | 923.188 |
| 12 | 914.850 | 25 | 923.783 |
| 13 | 915.444 | | |

Hooping Sequence

08 \cdot 16 \cdot 22 \cdot 04 \cdot 12 \cdot 19 \cdot 01 \cdot 09 \cdot 17 \cdot 06 \cdot 14 \cdot 20 \cdot 03 \cdot 11 \cdot 24 \cdot 07 \cdot 15 \cdot 21 \cdot 02 \cdot 10 \cdot 18 \cdot 05 \cdot 13 \cdot 25 \cdot 23

Coordination of hopping sequences to other transmitters

This transmitter does not have the ability of being coordinated with other FHSS system for as soon as the transmitter is in operation, the hopping frequency will follow the selected hopping sequence to transmit independently and no coordination is possible. Especially, this transmitter is used as a duplex car alarm system, so no coordination of hopping frequency is required.

System Receiver Hopping Capability

There are two steps to make the receiver to shift the frequencies in synchronization with the transmitted signals:

First, the Transmitter will emit a preamble signal of 50ms and the receiver will scan this signal by 2ms sweeping until the preamble signal is caught. Second, the preamble signal is coded with the information of hopping sequence and the next transmitting frequency, so the receiver will be able to shift the receiving frequencies in synchronization with the transmitted signals.

Equal Hopping Frequency Use

Due to each hopping frequency will be transmitted in accordance to the frequency tables described above, there is no any frequency will be able to hop more times than others. Therefore each frequency will be used equally.

Michael Chan / Contact pargon

Michael Chen

Michael Chen / Contact person

Address: 3F, 48 TA AN STREET HSI-CHIH DIST. NEW TAIPEI CITY221, Taiwan (R.O.C.)