

## RF EXPOSURE EVALUATION

### EUT Specification

<b>EUT</b>	37" HD Sound Bar with Bluetooth Wireless
<b>Frequency band (Operating)</b>	<input type="checkbox"/> WLAN: 2.412GHz ~ 2.462GHz <input type="checkbox"/> WLAN: 5.18GHz ~ 5.32GHz / 5.50GHz ~ 5.70GHz <input type="checkbox"/> WLAN: 5.745GHz ~ 5825GHz <input checked="" type="checkbox"/> Others(Bluetooth: 2.402GHz ~ 2.480GHz)
<b>Device category</b>	<input type="checkbox"/> Portable (<20cm separation) <input checked="" type="checkbox"/> Mobile (>20cm separation) <input type="checkbox"/> Others _____
<b>Antenna diversity</b>	<input checked="" type="checkbox"/> Single antenna <input type="checkbox"/> Multiple antennas <input type="checkbox"/> Tx diversity <input type="checkbox"/> Rx diversity <input type="checkbox"/> Tx/Rx diversity
<b>Max. output power</b>	0.926 dBm (1.238mW)
<b>Antenna gain</b>	-0.68 dBi
<b>Evaluation applied</b>	<input checked="" type="checkbox"/> MPE Evaluation <input type="checkbox"/> SAR Evaluation

### Limits for Maximum Permissible Exposure (MPE)

Frequency Range(MHz)	Electric Field Strength(V/m)	Magnetic Field Strength(A/m)	Power Density(mW/cm <sup>2</sup> )
300-1500	--	--	F/1500
1500-100000	--	--	1

## Friis transmission formula: $P_d = (P_{out} * G) / (4 * \pi * R^2)$

Where

$P_d$ = Power density in mW/cm<sup>2</sup>

$P_{out}$ =output power to antenna in Mw

$G$ = gain of antenna in linear scale

$\pi=3.1416$

$R$ = distance between observation point and center of the radiator in cm

$P_d$  the limit of MPE, 1mW/cm<sup>2</sup>. If we know the maximum gain of the antenna and total power input to the antenna, through the calculation, we will know the distance where the MPE limit is reached.

## Measurement Result

Channel	Gain	Channel Frequency (MHz)	Max Output power (dBm)	Tolerance	Max Tune-UP power (mW)	Power density at 20cm (mW/ cm <sup>2</sup> )	Power density Limits (mW/cm <sup>2</sup> )
<b>GFSK</b>							
Low	-0.68	2402	-2.612	±0.5	0.61	0.00010	1
Middle	-0.68	2441	-3.818	±0.5	0.47	0.00008	1
High	-0.68	2480	-5.641	±0.5	0.31	0.00005	1
<b>π/4-DQPSK</b>							
Low	-0.68	2402	0.177	±0.5	1.17	0.00020	1
Middle	-0.68	2441	-1.381	±0.5	0.82	0.00014	1
High	-0.68	2480	-3.217	±0.5	0.53	0.00009	1
<b>8DPSK</b>							
Low	-0.68	2402	0.926	±0.5	1.39	0.00024	1
Middle	-0.68	2441	-0.707	±0.5	0.95	0.00016	1
High	-0.68	2480	-2.570	±0.5	0.62	0.00011	1