

### 3. Common mode sensitivity

DASY measurement parameters:

Auto Zero Time: 3 sec,  
High/Low Range

Measuring time: 3 sec

in $\mu\text{V}$	Common mode Input Voltage	High Range Reading	Low Range Reading
Channel X	200mV	5.15	5.17
	- 200mV	-4.35	-4.88
Channel Y	200mV	9.00	8.70
	- 200mV	-10.57	-10.21
Channel Z	200mV	8.93	8.00
	- 200mV	-10.74	-10.51

### 4. Channel separation

DASY measurement parameters:

Auto Zero Time: 3 sec,  
High Range

Measuring time: 3 sec

in $\mu\text{V}$	Input Voltage	Channel X	Channel Y	Channel Z
Channel X	200mV	-	0.87	-0.39
Channel Y	200mV	0.80	-	2.29
Channel Z	200mV	-2.73	-0.30	-

### 5. AD-Converter Values with inputs shorted

in LSB	Low Range	High Range
Channel X	16102	16311
Channel Y	16055	16139
Channel Z	15811	15833

### 6. Input Offset Measurement

DASY measurement parameters:

Auto Zero Time: 3 sec,  
Number of measurements:

Measuring time: 3 sec  
100, Low Range

Input 10M $\Omega$

in $\mu\text{V}$	Average	min. Offset	max. Offset	Std. Deviation
Channel X	0.25	-1.75	1.20	0.43
Channel Y	-1.47	-2.17	0.46	0.35
Channel Z	-1.64	-2.78	0.28	0.45