

FCC TEST REPORT

Name of Sample: Mobile Cellular Phone
Model of Sample: XT2363-1, XT2363-2
Applicant: Motorola Mobility LLC
Issue Date: 2023-11-13



ADR TEST AND CERTIFICATION CENTER
Motorola Mobility LLC, a Lenovo Company

Add: No. 19, Gao Xin 4th Road Wuhan, People's Republic of China 430205
Phone: (86)18702717862
E-mail: lucz1@motorola.com

Name of Client	Motorola Mobility LLC		
Address of Client	222 W, Merchandise Mart Plaza, Chicago IL 60654 USA		
Trademark	Motorola	Type Name or ID	FCC ID: IHDT56AQ1
Applicant No.	RF168662	Sample No.	NFOL240108
Delivering Date	2023-09-27	Test Date	2023-09-27 to 2023-11-13
Sample Illustration	None		
Standard	47 CFR Part 2; 47 CFR Part 22; 47 CFR Part 24; 47 CFR Part 27; 47 CFR Part 90;		
Conclusion	Pass		
Remarks	N/A		

Editor: Wangzhenyu

Auditor: Hexiaolin

Approver: HuangshengLin

Wangzhenyu

Hexiaolin

Huangsheng Lin

Matters Needing Attention

- a) The electronic report shall be valid after encryption.
- b) The paper report shall be valid after being stamped with the official seal of the company.
- c) The report is invalid without the signature of the Editor, Auditor and Approver.
- d) The test report is invalid if there is any evidence of erasure and/or falsification.
- e) If there is any dissidence for the test report, please file objection to the lab within 15 days from the date of receiving the test report.
- f) The test report is only responsible for the tested model/sample. The sample(s) presented in this report are provided by client.
- g) Context of the test report cannot be used partially or in full for publicity and/or promotional purposes without previous written approval of the lab.

Revision History

Report No.	Version	Description	Issued Date
TR-23ADRTCC7002	Rev.01	Initial issue of report	2023-11-02
TR-23ADRTCC7002	Rev.02	Update n41/n78 emission designator frequency range description	2023-11-08
TR-23ADRTCC7002	Rev.03	1, Updated EUT Model name from XT2363-2 to XT2363-2, XT2363-1; 2, Updated emission designer and power information, Add straddle channel for n26. 3, add RSE report number on Page7. 4, Update DC_66A_n41A/DC_38A_n78A spurious data.	2023-11-13
TR-23ADRTCC7002	Rev.04	1, add description for why only n78 ant5 evaluated. 2, add antenna gain for n78 ant1/2/8.	2023-11-17

Catalogue

- 1. TEST SUMMARY 5**
 - 1.1. 5G NR BAND N5/N26 (824-849)..... 5
 - 1.2. 5G NR BAND N2..... 5
 - 1.3. 5G NR BAND N66 5
 - 1.4. 5G NR BAND N7/N38/N41 6
 - 1.5. 5G NR BAND N26 (814-824)..... 6
 - 1.6. 5G NR BAND N78 (3450-3550)..... 6
- 2. MAXIMUM EFFECTIVE RADIATED (ISOTROPIC) POWER AND EMISSION DESIGNATOR..... 8**
 - 2.1. NR SYSTEM..... 8
- 3. GENERAL INFORMATION 11**
 - 3.1. GENERAL DESCRIPTION OF EUT 11
 - 3.2. TEST ENVIRONMENT 11
 - 3.3. SPECIFICATION OF ACCESSORIES 11
- 4. TEST CONFIGURATION OF EQUIPMENT UNDER TEST..... 12**
 - 4.1. TEST MODE CONFIGURATION..... 12
 - 4.2. TEST FREQUENCIES..... 14
- 5. DESCRIPTION OF TESTS 16**
 - 5.1. CONDUCTED OUTPUT POWER MEASUREMENT 16
 - 5.2. EFFECTIVE (ISOTROPIC) RADIATED POWER 16
 - 5.3. PEAK-TO-AVERAGE RATIO MEASUREMENT..... 16
 - 5.4. 99% OCCUPIED BANDWIDTH & 26DB EMISSION BANDWIDTH 17
 - 5.5. CONDUCTED BAND EDGE MEASUREMENT 18
 - 5.6. CONDUCTED SPURIOUS EMISSION MEASUREMENT..... 18
 - 5.7. FREQUENCY STABILITY MEASUREMENT 19
- 6. LIST OF MEASURING EQUIPMENT 20**
- 7. MEASUREMENT UNCERTAINTY 20**
 - 7.1. UNCERTAINTY OF CONDUCTED MEASUREMENT 20
- 8. APPENDIXES..... 20**

1. Test Summary

1.1. 5G NR Band n5/n26 (824-849)

Test Item	Rule No.	Requirements	Test Result	Verdict
Conducted Power	§2.1046	Report Only	Section 1 of Appendix B	Pass
Effective Radiated Power	§22.913(a)(5)	ERP < 7W		
Peak-Average Ratio	§22.913(d)	<13 dB	Section 2 of Appendix B	Pass
Modulation Characteristics	§2.1047	Digital modulation	Section 3 of Appendix B	Pass
Occupied Bandwidth	§2.1049	No limit	Section 4 of Appendix B	Pass
26dB Emission Bandwidth		No limit		
Conducted Band Edges	§2.1051 §22.917(a)	< -13 dBm/1%*EBW, in 1 MHz bands immediately outside and adjacent to the frequency block.	Section 5 of Appendix B	Pass
Conducted Spurious Emission	§2.1051 §22.917(a)	< -13 dBm/100 kHz, from 9 kHz to 10th harmonics but outside authorized operating frequency ranges	Section 6 of Appendix B	Pass
Frequency Stability	§2.1055 §22.355	< ±2.5ppm	Section 7 of Appendix B	Pass

1.2. 5G NR Band n2

Test Item	Rule No.	Requirements	Test Result	Verdict
Conducted Power	§2.1046	Report Only	Section 1 of Appendix B	Pass
Effective Isotropic Radiated Power	§24.232(c)	EIRP < 2W		
Peak-Average Ratio	§24.232(d)	<13 dB	Section 2 of Appendix B	Pass
Modulation Characteristics	§2.1047	Digital modulation	Section 3 of Appendix B	Pass
Occupied Bandwidth	§2.1049	No limit	Section 4 of Appendix B	Pass
26dB Emission Bandwidth		No limit		
Conducted Band Edges	§2.1051 §24.238(a)	< -13 dBm/1%*EBW, in 1 MHz bands immediately outside and adjacent to the frequency block.	Section 5 of Appendix B	Pass
Conducted Spurious Emission	§2.1051 §24.238(a)	< -13 dBm/MHz, from 9 kHz to 10th harmonics but outside authorized operating frequency ranges.	Section 6 of Appendix B	Pass
Frequency Stability	§24.235	< ±2.5 ppm	Section 7 of Appendix B	Pass

1.3. 5G NR Band n66

Test Item	Rule No.	Requirements	Test Result	Verdict
Conducted Power	§2.1046	Report Only	Section 1 of Appendix B	Pass
Effective Isotropic Radiated Power	§27.50(d)	EIRP < 1W		
Peak-Average Ratio	---	<13 dB	Section 2 of Appendix B	Pass
Modulation Characteristics	§2.1047	Digital modulation	Section 3 of Appendix B	Pass
Occupied Bandwidth	§2.1049	No limit	Section 4 of Appendix B	Pass
26dB Emission Bandwidth		No limit		
Conducted Band Edges	§2.1051 §27.53(h)	< -13 dBm/1%*EBW, in 1 MHz bands immediately outside and adjacent to the frequency block.	Section 5 of Appendix B	Pass
Conducted Spurious Emission	§2.1051 §27.53(h)	< -13 dBm/MHz, from 9 kHz to 10th harmonics but outside authorized operating frequency ranges	Section 6 of Appendix B	Pass
Frequency Stability	§27.54	Within authorized bands	Section 7 of Appendix B	Pass

1.4. 5G NR Band n7/n38/n41

Test Item	Rule No.	Requirements	Test Result	Verdict
Conducted Power	§2.1046	Report Only	Section 1 of Appendix B	Pass
Effective Isotropic Radiated Power	§27.50(h) (2)	EIRP < 2W		
Peak-Average Ratio	§27.50(a)	<13 dB	Section 2 of Appendix B	Pass
Modulation Characteristics	§2.1047	Digital modulation	Section 3 of Appendix B	Pass
Occupied Bandwidth	§2.1049	No limit	Section 4 of Appendix B	Pass
26dB Emission Bandwidth		No limit		
Conducted Band Edges	§2.1051 §27.53(m) (4)	For mobile digital stations, the attenuation factor shall be not less than 40 + 10 log (P) dB on all frequencies between the channel edge and 5 megahertz from the channel edge, 43 + 10 log (P) dB on all frequencies between 5 megahertz and X megahertz from the channel edge, and 55 + 10 log (P) dB on all frequencies more than X megahertz from the channel edge, where X is the greater of 6 megahertz or the actual emission bandwidth as defined in paragraph (m)(6) of this section	Section 5 of Appendix B	Pass
Conducted Spurious Emission	§2.1051 §27.53(m) (4)	< -25 dBm/MHz for outside Band Edge Range	Section 6 of Appendix B	Pass
Frequency Stability	§27.54	Within authorized bands	Section 7 of Appendix B	Pass

1.5. 5G NR Band n26 (814-824)

Test Item	Rule No.	Requirements	Test Result	Verdict
Conducted Power	§2.1046 §90.635	Report Only	Section 1 of Appendix B	PASS
Peak-Average Ratio	---	<13 dB	Section 2 of Appendix B	PASS
Modulation Characteristics	§2.1047	Digital modulation	Section 3 of Appendix B	PASS
Occupied Bandwidth	§2.1049	No limit	Section 4 of Appendix B	PASS
26dB Emission Bandwidth		No limit		
Emission Mask	§2.1051 § 90.691	For any frequency removed from the EA licensee's frequency block by up to and including 37.5 kHz, the power of any emission shall be attenuated below the transmitter power (P) in watts by at least 116 Log ₁₀ (f/6.1) decibels or 50+10Log ₁₀ (P) decibels or 80 decibels, whichever is the lesser attenuation, where f is the frequency removed from the center of the outer channel in the block in kilohertz and where f is greater than 12.5 kHz.	Section 5 of Appendix B	PASS
Conducted Spurious Emission	§2.1051 §90.691	< 43 + 10Log ₁₀ (P[Watts]) for all out-of-band emissions	Section 6 of Appendix B	PASS
Frequency Stability	§90.213	< ±2.5ppm	Section 7 of Appendix B	PASS

1.6. 5G NR Band n78 (3450-3550)

Test Item	Rule No.	Requirements	Test Result	Verdict
Conducted Power	§2.1046	Report Only	Section 1 of Appendix B	Pass
Effective Isotropic Radiated Power	§27.50(k) (3)	EIRP < 1W		
Peak-Average Ratio	§27.50(k) (4)	<13 dB	Section 2 of Appendix B	Pass
Modulation Characteristics	§2.1047	Digital modulation	Section 3 of Appendix B	Pass
Occupied Bandwidth	§2.1049	No limit	Section 4 of	Pass

Test Item	Rule No.	Requirements	Test Result	Verdict
26dB Emission Bandwidth		No limit	Appendix B	
Conducted Band Edges	§2.1051 §27.53(n) (2)	< -13 dBm/MHz	Section 5 of Appendix B	Pass
Conducted Spurious Emission	§2.1051 §27.53(n) (2)	< -13 dBm/MHz	Section 6 of Appendix B	Pass
Frequency Stability	§27.54	Within authorized bands	Section 7 of Appendix B	Pass

Remark:

- 1, Only 5G NR Bands conducted test performed and the data displayed in this report, the radiated spurious emission refer to the report (FG392114G).
- 2, The maximum E(I)RP is calculated from max output power and max antenna gain, only the max E(I)RP data displayed in this report.
- 3, 5G NR Bands support SA mode for n2/n5/n7/ n26/n38/n41/ n66/n78 and NSA mode for n2/n5/n7/n38/n41/n66/n78.
- 4, The test has been assessed on SA and NSA mode, but only the worst mode performed the whole conducted test items by referring to the max conducted power.
- 5, The ENDC combination could be referred to the product specification.
- 6, for 5G NR n78, only Ant5 can build signaling connection between the base station and EUT, the power of Ant1/2/8 had been evaluated by non-signaling test in SAR, and the power of Ant 1/2/8 is less than ant5, so, only Ant5 was totally evaluated and the data displayed in this report.

2. Maximum Effective Radiated (Isotropic) Power and Emission Designator

2.1. NR System

2.1.1. NR Band n2 (1850-1910)

5G NR SA (N2A)		Pi/2 BPSK / QPSK		16QAM/64QAM/256QAM	
Bandwidth	Frequency Range (MHz)	Maximum EIRP (W)	Emission Designator (99% OBW)	Maximum EIRP (W)	Emission Designator (99% OBW)
5MHz	1852.5-1907.5	0.170216	4M47G7D	0.130317	4M49W7D
10MHz	1855.0-1905.0	0.158490	9M29G7D	0.127351	9M29W7D
15MHz	1857.5-1902.5	0.159956	14M1G7D	0.125314	14M2W7D
20MHz	1860.0-1900.0	0.157398	18M9G7D	0.124165	19M0W7D

5G NR NSA (DC_66A_n2A)		Pi/2 BPSK / QPSK		16QAM/64QAM/256QAM	
Bandwidth	Frequency Range (MHz)	Maximum EIRP (W)	Emission Designator (99% OBW)	Maximum EIRP (W)	Emission Designator (99% OBW)
5MHz	1852.5-1907.5	0.124451	4M49G7D	0.100231	4M49W7D
10MHz	1855.0-1905.0	0.125314	9M29G7D	0.099770	9M31W7D
15MHz	1857.5-1902.5	0.119950	14M1G7D	0.097051	14M1W7D
20MHz	1860.0-1900.0	0.120227	18M9G7D	0.097275	19M0W7D

2.1.2. NR Band n5 (824-849)

5G NR SA (n5A)		Pi/2 BPSK / QPSK		16QAM/64QAM/256QAM	
Bandwidth	Frequency Range (MHz)	Maximum ERP (W)	Emission Designator (99% OBW)	Maximum ERP (W)	Emission Designator (99% OBW)
5MHz	826.5-846.5	0.056364	4M48G7D	0.044771	4M50W7D
10MHz	829.0-844.0	0.055719	9M29G7D	0.044463	9M29W7D
15MHz	831.5-841.5	0.054200	15M0G7D	0.042954	15M0W7D
20MHz	834.0-839.0	0.054450	19M8G7D	0.042267	21M4W7D

2.1.3. NR Band n7 (2500-2570)

5G NR NSA (DC_4A_n7A)		Pi/2 BPSK / QPSK		16QAM/64QAM/256QAM	
Bandwidth	Frequency Range (MHz)	Maximum EIRP (W)	Emission Designator (99% OBW)	Maximum EIRP (W)	Emission Designator (99% OBW)
5MHz	2502.5-2567.5	0.043152	4M48G7D	0.034914	4M49W7D
10MHz	2505.0-2565.0	0.043752	9M29G7D	0.034834	9M31W7D
15MHz	2507.5-2562.5	0.042658	14M1G7D	0.033962	14M2W7D
20MHz	2510.0-2560.0	0.042756	18M9G7D	0.034041	19M0W7D
25MHz	2512.5-2557.5	0.045082	23M7G7D	0.034995	23M7W7D
30MHz	2515.0-2555.0	0.043752	28M6G7D	0.035481	28M6W7D
40MHz	2520.0-2550.0	0.043652	38M5G7D	0.034754	38M7W7D

2.1.4. NR Band n26 (814-824)

5G NR SA (n26A)		Pi/2 BPSK / QPSK		16QAM/64QAM/256QAM	
Bandwidth	Frequency Range (MHz)	Maximum Output Power (W)	Emission Designator (99% OBW)	Maximum Output Power (W)	Emission Designator (99% OBW)
5MHz	816.5-821.5	0.233346	4M49G7D	0.187932	4M49W7D
10MHz	819.0	0.232274	9M29G7D	0.186638	9M29W7D
15MHz	824.0	0.215774	14M1G7D	0.172584	14M1W7D

2.1.5. NR Band n26 (824-849)

5G NR SA (n26A)		Pi/2 BPSK / QPSK		16QAM/64QAM/256QAM	
Bandwidth	Frequency Range (MHz)	Maximum ERP (W)	Emission Designator (99% OBW)	Maximum ERP (W)	Emission Designator (99% OBW)
5MHz	826.5-846.5	0.054701	4M49G7D	0.044978	4M49W7D
10MHz	829.0-844.0	0.054828	9M27G7D	0.043551	9M29W7D
15MHz	831.5-841.5	0.054075	14M2G7D	0.042560	14M2W7D
20MHz	834.0-839.0	0.054075	18M9G7D	0.042170	18M9W7D

2.1.6. NR Band n38 (2570-2620)

5G NR NSA (DC_2A_n38A)		Pi/2 BPSK / QPSK		16QAM/64QAM/256QAM	
Bandwidth	Frequency Range (MHz)	Maximum EIRP (W)	Emission Designator (99% OBW)	Maximum EIRP (W)	Emission Designator (99% OBW)
20MHz	2580.0-2610.0	0.196336	18M2G7D	0.158489	18M3W7D
30MHz	2585.0-2605.0	0.205116	27M8G7D	0.160325	27M9W7D
40MHz	2590.0-2600.0	0.207970	37M7G7D	0.161436	37M9W7D

2.1.7. NR Band n41 (2496-2690)

5G NR NSA (DC_66A_n41A)		Pi/2 BPSK / QPSK		16QAM/64QAM/256QAM	
Bandwidth	Frequency Range (MHz)	Maximum EIRP (W)	Emission Designator (99% OBW)	Maximum EIRP (W)	Emission Designator (99% OBW)
20MHz	2506.02-2679.99	0.210378	18M2G7D	0.143219	18M2W7D
30MHz	2511.00-2674.98	0.200909	27M8G7D	0.155597	27M9W7D
40MHz	2516.01-2670.00	0.201372	37M7G7D	0.156675	38M0W7D
50MHz	2521.02-2664.99	0.194536	47M4G7D	0.157036	47M5W7D
60MHz	2526.00-2659.98	0.195434	57M7G7D	0.154170	57M7W7D
70MHz	2531.01-2655.00	0.187499	67M3G7D	0.150661	67M4W7D
80MHz	2536.02-2649.99	0.187931	77M2G7D	0.148594	77M4W7D
90MHz	2541.00-2644.98	0.190985	87M2G7D	0.149624	87M4W7D
100MHz	2546.01-2640.00	0.194089	97M1G7D	0.150315	97M3W7D

2.1.8. NR Band n66 (1710-1780)

5G NR SA (N66A)		Pi/2 BPSK / QPSK		16QAM/64QAM/256QAM	
Bandwidth	Frequency Range (MHz)	Maximum EIRP (W)	Emission Designator (99% OBW)	Maximum EIRP (W)	Emission Designator (99% OBW)
5MHz	1712.5-1777.5	0.202768	4M48G7D	0.156675	4M49W7D
10MHz	1715.0-1775.0	0.200909	9M27G7D	0.154882	9M29W7D
15MHz	1717.5-1772.5	0.199526	14M1G7D	0.152757	14M2W7D
20MHz	1720.0-1770.0	0.194536	18M9G7D	0.154170	18M9W7D
30MHz	1725.0-1765.0	0.203236	28M6G7D	0.154525	28M6W7D
40MHz	1730.0-1760.0	0.202302	38M7G7D	0.155955	38M6W7D

5G NR NSA (DC_7A_n66A)		Pi/2 BPSK / QPSK		16QAM/64QAM/256QAM	
Bandwidth	Frequency Range (MHz)	Maximum EIRP (W)	Emission Designator (99% OBW)	Maximum EIRP (W)	Emission Designator (99% OBW)
5MHz	1712.5-1777.5	0.065013	4M50G7D	0.051523	4M49W7D
10MHz	1715.0-1775.0	0.064565	9M29G7D	0.050816	9M29W7D
15MHz	1717.5-1772.5	0.062806	14M1G7D	0.050119	14M2W7D
20MHz	1720.0-1770.0	0.061802	18M9G7D	0.050234	19M0W7D
30MHz	1725.0-1765.0	0.063096	28M5G7D	0.049545	28M5W7D
40MHz	1730.0-1760.0	0.062373	38M5G7D	0.049317	38M6W7D

2.1.9. NR Band n78 (3450-3550)

5G NR NSA (DC_38A_n78A)		Pi/2 BPSK / QPSK		16QAM/64QAM/256QAM	
Bandwidth	Frequency Range (MHz)	Maximum EIRP (W)	Emission Designator (99% OBW)	Maximum EIRP (W)	Emission Designator (99% OBW)
20MHz	3460.02-3540.00	0.174180	18M2G7D	0.137088	18M2W7D
30MHz	3465.00-3534.99	0.158855	27M9G7D	0.125603	27M8W7D
40MHz	3470.01-3529.98	0.156315	37M8G7D	0.122180	37M9W7D
50MHz	3475.02-3525.00	0.147231	47M5G7D	0.116145	47M5W7D
60MHz	3480.00-3519.99	0.149279	57M9G7D	0.116412	57M8W7D
70MHz	3485.01-3514.98	0.146218	67M4G7D	0.115080	67M4W7D
80MHz	3490.02-3510.00	0.145546	77M4G7D	0.114288	77M5W7D
90MHz	3495.00-3504.99	0.146555	87M4G7D	0.118577	87M4W7D
100MHz	3500.01	0.148252	97M1G7D	0.112720	97M5W7D

3. General Information

3.1. General Description of EUT

EUT Description:	Mobile Cellular Phone
Brand Name:	Motorola
Model Name:	XT2363-1,XT2363-2
FCC ID:	IHDT56AQ1
IMEI Code:	350735340022570 (Conducted);
Hardware Version:	DVT2
Software Version:	UUG34.20
NR Modulation:	DFT-s-OFDM: <input checked="" type="checkbox"/> Pi/2BPSK; <input checked="" type="checkbox"/> QPSK; <input checked="" type="checkbox"/> 16QAM; <input checked="" type="checkbox"/> 64QAM; <input checked="" type="checkbox"/> 256QAM CP-OFDM: <input checked="" type="checkbox"/> QPSK; <input checked="" type="checkbox"/> 16QAM; <input checked="" type="checkbox"/> 64QAM; <input checked="" type="checkbox"/> 256QAM
Sample Type:	<input checked="" type="checkbox"/> Portable Device, <input type="checkbox"/> Module
Antenna Type:	<input checked="" type="checkbox"/> External, <input checked="" type="checkbox"/> Integrated
Antenna Gain:	n2: -0.70dBi (Ant0); -1.90dBi (Ant4); n5: -4.10dBi (Ant0); -6.60dBi (Ant4); n7: -0.50dBi (Ant1); n26: -4.11dBi (Ant0); -6.90dBi (Ant4); n38: -0.30dBi (Ant4); n41: -0.30dBi (Ant4); n66: -0.90dBi (Ant0); -4.70dBi (Ant4); n78: -1.30dBi (Ant5); -0.98dBi (Ant1); -4.40dBi (Ant2); -3.30dBi (Ant8);

Remark:

- 1, The information above was declared by manufacture. Please refer to the specifications or user manual for more detailed description.
- 2, The different mode name is for different market purpose.

3.2. Test Environment

Relative Humidity:	52.0% - 62.0%	
Atmospheric Pressure:	101.32 Kpa	
Temperature:	NT (normal temperature)	25.0 °C – 27.5 °C
Voltage:	LV (Low voltage)	3.60V
	NV (Nominal voltage)	3.91V
	HV (High voltage)	4.50V

3.3. Specification of Accessories

Accessory	Brand Name	Model Name
AC Adapter 1 (US)	Motorola(AOHAI)	MC-201L
AC Adapter 2 (EU)	Motorola(AOHAI)	MC-202L
AC Adapter 3 (UK)	Motorola(AOHAI)	MC-203L
AC Adapter 4 (AU)	Motorola(AOHAI)	MC-205L
AC Adapter 5 (AR)	Motorola(AOHAI)	MC-206L
AC Adapter 6 (IN)	Motorola(AOHAI)	MC-204
AC Adapter 7 (US)	Motorola(Salcomp)	MC-201L
AC Adapter 8 (EU)	Motorola(Salcomp)	MC-202L
AC Adapter 9 (UK)	Motorola(Salcomp)	MC-203L
AC Adapter 10 (AU)	Motorola(Salcomp)	MC-205L
AC Adapter 11 (AR)	Motorola(Salcomp)	MC-206L
AC Adapter 12 (BR)	Motorola(Salcomp)	MC-207L
AC Adapter 14 (CHILE)	Motorola(Salcomp)	MC-209L
AC Adapter 15 (BR)	Motorola(Chenyang)	MC-207L
AC Adapter 16 (BR)	Motorola(Cliptech)	MC-207L

AC Adapter 17 (IN)	Motorola(XIHI)	MC-204
Battery 1	Motorola(ATL)	QF50
Battery 2	Motorola (SCUD)	QF50
Battery 3	Motorola (Sunwoda)	QF50
USB Cable 1	Saibao	SZN-A026A
USB Cable 2	JuWei	JWUB1606-ZN01H
USB Cable 3	HeXin	HX-ZN-19

4. Test Configuration of Equipment Under Test

4.1. Test Mode Configuration

Test Case	5G NR	SCS		Bandwidth	Modulation					Channel			RB	
		15KHz	30KHz		PI/2BPSK	QPSK	16QAM	64QAM	256QAM	LCH	MCH	HCH	1	Full
Effective Isotropic Radiated Power	N2 (1850-1910)	●	○	All Supported BW	●	●	●	●	●	●	●	●	●	●
	N5 (824-849)	●	○	All Supported BW	●	●	●	●	●	●	●	●	●	●
	N7 (2500-2570)	●	○	All Supported BW	●	●	●	●	●	●	●	●	●	●
	N26 (814-824)	●	○	All Supported BW	●	●	●	●	●	●	●	●	●	●
	N26 (824-849)	●	○	All Supported BW	●	●	●	●	●	●	●	●	●	●
	N38 (2570-2620)	○	●	All Supported BW	●	●	●	●	●	●	●	●	●	●
	N41 (2496-2690)	○	●	All Supported BW	●	●	●	●	●	●	●	●	●	●
	N66 (1710-1780)	●	○	All Supported BW	●	●	●	●	●	●	●	●	●	●
Peak-Average Ratio	N2 (1850-1910)	●	○	Highest BW	●	●	○	○	○	●	●	●	○	●
	N5 (824-849)	●	○	Highest BW	●	●	○	○	○	●	●	●	○	●
	N7 (2500-2570)	●	○	Highest BW	●	●	○	○	○	●	●	●	○	●
	N26 (814-824)	●	○	Highest BW	●	●	○	○	○	●	●	●	○	●
	N26 (824-849)	●	○	Highest BW	●	●	○	○	○	●	●	●	○	●
	N38 (2570-2620)	○	●	Highest BW	●	●	○	○	○	●	●	●	○	●
	N41 (2496-2690)	○	●	Highest BW	●	●	○	○	○	●	●	●	○	●
	N66 (1710-1780)	●	○	Highest BW	●	●	○	○	○	●	●	●	○	●
Modulation Characteristics	N2 (1850-1910)	●	○	Highest BW	●	●	●	●	●	○	●	○	○	●
	N5 (824-849)	●	○	Highest BW	●	●	●	●	●	○	●	○	○	●
	N7 (2500-2570)	●	○	Highest BW	●	●	●	●	●	○	●	○	○	●
	N26 (814-824)	●	○	Highest BW	●	●	●	●	●	○	●	○	○	●
	N26 (824-849)	●	○	Highest BW	●	●	●	●	●	○	●	○	○	●
	N38 (2570-2620)	○	●	Highest BW	●	●	●	●	●	○	●	○	○	●
	N41 (2496-2690)	○	●	Highest BW	●	●	●	●	●	○	●	○	○	●
	N66 (1710-1780)	●	○	Highest BW	●	●	●	●	●	○	●	○	○	●
Occupied Bandwidth & 26dB Emission	N2 (1850-1910)	●	○	All Supported BW	●	●	●	●	●	○	●	○	○	●
	N5 (824-849)	●	○	All Supported BW	●	●	●	●	●	○	●	○	○	●
	N7 (2500-2570)	●	○	All Supported BW	●	●	●	●	●	○	●	○	○	●

Bandwidth	N26 (814-824)	●	○	All Supported BW	●	●	●	●	●	○	●	○	○	●
	N26 (824-849)	●	○	All Supported BW	●	●	●	●	●	○	●	○	○	●
	N38 (2570-2620)	○	●	All Supported BW	●	●	●	●	●	○	●	○	○	●
	N41 (2496-2690)	○	●	All Supported BW	●	●	●	●	●	○	●	○	○	●
	N66 (1710-1780)	●	○	All Supported BW	●	●	●	●	●	○	●	○	○	●
	N78(3450-3550)	○	●	All Supported BW	●	●	●	●	●	○	●	○	○	●
Conducted Band Edges	N2 (1850-1910)	●	○	All Supported BW	●	●	○	○	○	●	○	●	●	●
	N5 (824-849)	●	○	All Supported BW	●	●	○	○	○	●	○	●	●	●
	N7 (2500-2570)	●	○	All Supported BW	●	●	○	○	○	●	○	●	●	●
	N26 (814-824)	●	○	All Supported BW	●	●	○	○	○	●	○	●	●	●
	N26 (824-849)	●	○	All Supported BW	●	●	○	○	○	●	○	●	●	●
	N38 (2570-2620)	○	●	All Supported BW	●	●	○	○	○	●	○	●	●	●
	N41 (2496-2690)	○	●	All Supported BW	●	●	○	○	○	●	○	●	●	●
	N66 (1710-1780)	●	○	All Supported BW	●	●	○	○	○	●	○	●	●	●
Conducted Spurious Emission	N2 (1850-1910)	●	○	All Supported BW	●	●	○	○	○	●	●	●	●	○
	N5 (824-849)	●	○	All Supported BW	●	●	○	○	○	●	●	●	●	○
	N7 (2500-2570)	●	○	All Supported BW	●	●	○	○	○	●	●	●	●	○
	N26 (814-824)	●	○	All Supported BW	●	●	○	○	○	●	●	●	●	○
	N26 (824-849)	●	○	All Supported BW	●	●	○	○	○	●	●	●	●	○
	N38 (2570-2620)	○	●	All Supported BW	●	●	○	○	○	●	●	●	●	○
	N41 (2496-2690)	○	●	All Supported BW	●	●	○	○	○	●	●	●	●	○
	N66 (1710-1780)	●	○	All Supported BW	●	●	○	○	○	●	●	●	●	○
Frequency Stability	N2 (1850-1910)	●	○	Highest BW	○	●	○	○	○	○	●	○	○	●
	N5 (824-849)	●	○	Highest BW	○	●	○	○	○	○	●	○	○	●
	N7 (2500-2570)	●	○	Highest BW	○	●	○	○	○	○	●	○	○	●
	N26 (814-824)	●	○	Highest BW	○	●	○	○	○	○	●	○	○	●
	N26 (824-849)	●	○	Highest BW	○	●	○	○	○	○	●	○	○	●
	N38 (2570-2620)	○	●	Highest BW	○	●	○	○	○	○	●	○	○	●
	N41 (2496-2690)	○	●	Highest BW	○	●	○	○	○	○	●	○	○	●
	N66 (1710-1780)	●	○	Highest BW	○	●	○	○	○	○	●	○	○	●
	N78(3450-3550)	○	●	Highest BW	○	●	○	○	○	○	●	○	○	●

Remark:

1, the mark “●” means this configuration was chosen for testing, mark “○” means not selected, and the mark “✘” means not applicable.

2, All Supported BW means all supported bandwidth for selected SCS configuration.

4.2. Test Frequencies

4.2.1. 5G NR System

4.2.1.1. NR Band n2 (1850-1910)

4.2.1.1.1. SCS=15KHz

Bandwidth	LCH		MCH		HCH	
	Arfcn	Freq	Arfcn	Freq	Arfcn	Freq
5MHz	370500	1852.5	376000	1880.0	381500	1907.5
10MHz	371000	1855.0	376000	1880.0	381000	1905.0
15MHZ	371500	1857.5	376000	1880.0	380500	1902.5
20MHz	372000	1860.0	376000	1880.0	380000	1900.0

4.2.1.2. NR Band n5 (824-849)

4.2.1.2.1. SCS=15KHz

Bandwidth	LCH		MCH		HCH	
	Arfcn	Freq	Arfcn	Freq	Arfcn	Freq
5MHz	165300	826.5	167300	836.5	169300	846.5
10MHz	165800	829.0	167300	836.5	168800	844.0
15MHZ	166300	831.5	167300	836.5	168300	841.5
20MHz	166800	834.0	167300	836.5	167800	839.0

4.2.1.3. NR Band n7 (2500-2570)

4.2.1.3.1. SCS=15KHz

Bandwidth	LCH		MCH		HCH	
	Arfcn	Freq	Arfcn	Freq	Arfcn	Freq
5MHz	500500	2502.5	507000	2535.0	513500	2567.5
10MHz	501000	2505.0	507000	2535.0	513000	2565.0
15MHZ	501500	2507.5	507000	2535.0	512500	2562.5
20MHz	502000	2510.0	507000	2535.0	512000	2560.0
25MHz	502500	2512.5	507000	2535.0	511500	2557.5
30MHz	503000	2515.0	507000	2535.0	511000	2555.0
40MHz	504000	2520.0	507000	2535.0	510000	2550.0

4.2.1.4. NR Band n26 (814-824)

4.2.1.4.1. SCS=15KHz

Bandwidth	LCH		MCH		HCH	
	Arfcn	Freq	Arfcn	Freq	Arfcn	Freq
5MHz	163300	816.5	163800	819.0	164300	821.5
10MHz	163800	819.0	163800	819.0	163800	819.0

4.2.1.4.2. Cross-rule Channel

Bandwidth	LCH		MCH		HCH	
	Arfcn	Freq	Arfcn	Freq	Arfcn	Freq
5MHz	-	-	164800	824.0	-	-
10MHz	-	-	164800	824.0	-	-
15MHz	-	-	164800	824.0	-	-

4.2.1.5. NR Band n26 (824-849)**4.2.1.5.1. SCS=15KHz**

Bandwidth	LCH		MCH		HCH	
	Arfcn	Freq	Arfcn	Freq	Arfcn	Freq
5MHz	165300	826.5	167300	836.5	169300	846.5
10MHz	165800	829.0	167300	836.5	168800	844.0
15MHz	166300	831.5	167300	836.5	168300	841.5
20MHz	166800	834.0	167300	836.5	167800	839.0

4.2.1.6. NR Band n38 (2570-2620)**4.2.1.6.1. SCS=30KHz**

Bandwidth	LCH		MCH		HCH	
	Arfcn	Freq	Arfcn	Freq	Arfcn	Freq
20MHz	516000	2580.0	519000	2595.0	522000	2610.0
30MHz	517000	2585.0	519000	2595.0	521000	2605.0
40MHz	518000	2590.0	519000	2595.0	520000	2600.0

4.2.1.7. NR Band n41 (2496-2690)**4.2.1.7.1. SCS=30KHz**

Bandwidth	LCH		MCH		HCH	
	Arfcn	Freq	Arfcn	Freq	Arfcn	Freq
20MHz	501204	2506.02	518598	2592.99	535998	2679.99
30MHz	502200	2511.00	518598	2592.99	534996	2674.98
40MHz	503202	2516.01	518598	2592.99	534000	2670.00
50MHz	504204	2521.02	518598	2592.99	532998	2664.99
60MHz	505200	2526.00	518598	2592.99	531996	2659.98
70MHz	506202	2531.01	518598	2592.99	531000	2655.00
80MHz	507204	2536.02	518598	2592.99	529998	2649.99
90MHz	508200	2541.00	518598	2592.99	528996	2644.98
100MHz	509202	2546.01	518598	2592.99	528000	2640.00

4.2.1.8. NR Band n66 (1710-1780)**4.2.1.8.1. SCS=15KHz**

Bandwidth	LCH		MCH		HCH	
	Arfcn	Freq	Arfcn	Freq	Arfcn	Freq
5MHz	342500	1712.5	349000	1745.0	355500	1777.5
10MHz	343000	1715.0	349000	1745.0	355000	1775.0
15MHz	343500	1717.5	349000	1745.0	354500	1772.5
20MHz	344000	1720.0	349000	1745.0	354000	1770.0
30MHz	345000	1725.0	349000	1745.0	353000	1765.0
40MHz	346000	1730.0	349000	1745.0	352000	1760.0

4.2.1.9. NR Band N78 (3450-3550)

4.2.1.9.1. SCS=30KHz

Bandwidth	LCH		MCH		HCH	
	Arfcn	Freq	Arfcn	Freq	Arfcn	Freq
20MHz	630668	3460.02	633334	3500.01	636000	3540.00
30MHz	631000	3465.00	633334	3500.01	635666	3534.99
40MHz	631334	3470.01	633334	3500.01	635332	3529.98
50MHz	631668	3475.02	633334	3500.01	635000	3525.00
60MHz	632000	3480.00	633334	3500.01	634666	3519.99
70MHz	632334	3485.01	633334	3500.01	634332	3514.98
80MHz	632668	3490.02	633334	3500.01	634000	3510.00
90MHz	633000	3495.00	633334	3500.01	633666	3504.99
100MHz	633334	3500.01	633334	3500.01	633334	3500.01

5. Description of Tests

5.1. Conducted Output Power Measurement

5.1.1. Description of Conducted Output Power Measurement

A base station simulator was used to establish communication with the EUT, Its parameters were set to transmit the maximum power on the EUT. The measured power in the radio frequency on the transmitter output terminals shall be reported.

5.1.2. Test Procedures

- 1, The testing follows ANSI C63.26 Section 5.2.
- 2, The transmitter output port was connected to the system simulator.
- 3, Set EUT at maximum power through the system simulator.
- 4, Select lowest, Middle, Highest channels for each band and each modulation.
- 5, Record the reading power from the system simulator.

5.2. Effective (Isotropic) Radiated Power

Measurement Procedure: ANSI C63.26

Calculate power in dBm by the following formula:

ERP (dBm) = Conducted Power (dBm) + antenna gain (dBd)

EIRP (dBm) = Conducted Power (dBm) + antenna gain (dBi)

EIRP=ERP+2.15dB

5.3. Peak-to-Average Ratio Measurement

5.3.1. Description of PAR Measurement

Power Complementary Cumulative Distribution Function (CCDF) curves provide a means for characterizing the power peaks of a digitally modulated signal on a statistical basis, A CCDF curve depicts the probability of peak signal amplitude exceeding the average power level. Most contemporary measurement instrumentation include the capability to produce CCDF curves for an input signal provided that the instrument’s resolution bandwidth can be set wide enough to accommodate the entire input signal bandwidth. In measuring transmissions in this band using an average power technique, the peak-to-average ratio (PAR) of the transmission may not exceed 13dB.

5.3.2. Test Procedures

- 1, The testing follows ANSI C63.26 Section 5.2.3.4(CCDF)
- 2, Refer to instrument's analyser instruction manual for details on how to use the power statistics/CCDF function.
- 3, Centre Frequency = Carrier centre frequency.
- 4, Set resolution bandwidth \geq signal's occupied bandwidth.
- 5, Set the number of counts to a value that stabilizes the measured CCDF curve.
- 6, Set the measurement interval as follows:
 - 1) for continuous transmissions (>98% duty cycle), set to 1ms.
 - 2) for burst transmissions, employ an external trigger that is synchronized with the EUT burst timing sequence, or use the internal burst trigger with a trigger level that allows the burst to stabilize and set the measurement interval to a time that is less than or equal to the burst duration.
- 7, Record the maximum PAR level associated with a probability of 0.1%.

5.3.3. Alternate procedure for PAR

Measurement Procedure: 5.2.6 of ANSI C63.26

Some regulatory requirements specify a PAR limit when the output power limits are specified in terms of average power. If it becomes necessary to provide measurement data to demonstrate compliance to a PAR limit, then the appropriate procedure from those provided in 5.2.3 shall be utilized to determine the peak power (or peak PSD) and the appropriate procedure from those provided in 5.2.4 shall be used to determine the average power (or average PSD). The data from these measurements is then used in Equation (2) to determine the PAR of a narrowband CW-like signal. See 5.2.3.4 for guidance on determining the PAR of a broadband noise-like signal.

$$\text{PAR (dB)} = P_{\text{Pk}} (\text{dBm or dBW}) - P_{\text{Avg}} (\text{dBm or dBW})$$

where

PAR peak-to-average power ratio, in dB

P_{Pk} measured peak power or peak PSD level, in dBm or dBW

P_{Avg} measured average power or average PSD level, in dBm or dBW

5.4. 99% Occupied Bandwidth & 26dB Emission Bandwidth

5.4.1. Description of 99% Occupied Bandwidth & 26dB Emission Bandwidth Measurement

The occupied bandwidth, that is the frequency bandwidth such that, below its lower and above its upper frequency limits, the mean powers radiated are each equal to 0.5 percent of the total mean power radiated by a given emission shall be measured. The transmitter output was connected to a calibrated coaxial cable, attenuator and Spectrum analyser, the other end of which was connected to a Base Station Simulator. The Base Station Simulator was set to force the EUT to its maximum power setting. The tests were performed at three frequencies (low channel, middle channel and high channel). The span of the analyser shall be set to capture all products of the modulation process, including the emission skirts. The resolution bandwidth shall be set to as close to 1 percent of the selected span as is possible without being below 1 percent. The video bandwidth shall be set to 3 times the resolution bandwidth. Video averaging is not permitted. Where practical, a sampling detector shall be used since a peak or, peak hold, may produce a wider bandwidth than actual. The trace data points are recovered and are directly summed in linear terms. The recovered amplitude data points, beginning at the lowest frequency, are placed in a running sum until 0.5 percent of the total is reached and that frequency recorded. The process is repeated for the highest frequency data points. This frequency is recorded. The span between the two recorded frequencies is the occupied bandwidth.

5.4.2. Test Procedures

- 1, The testing follows ANSI C63.26 Section 5.4
- 2, The signal analyzer's automatic measurement capability was used to perform the 99% occupied bandwidth and the 26dB emission bandwidth. The bandwidth measurement was not influenced by any intermediate power nulls in the fundamental emission.
- 3, $RBW \geq 1\% - 5\%$ of the expected OBW.
- 4, $VBW \geq 3 * RBW$
- 5, Detector=Peak
- 6, Trace Mode= MaxHold.
- 7, Sweep Time=Auto
- 8, The trace was allowed to stabilize.
- 9, If necessary, steps 2-7 were repeated after changing the RBW such that it would be within 1%-5% of the 99% occupied bandwidth observed in step 7.

5.5. Conducted Band Edge Measurement

5.5.1. Description of Conducted Band Edge Measurement

The transmitter output was connected to a calibrated coaxial cable, attenuator and spectrum analyser, the other end of which was connected to a Base Station Simulator. The Base Station Simulator was set to force the EUT to its maximum power setting. The tests were performed at two frequencies (low channel and high channel).in the 1MHz bands immediately outside and adjacent to the frequency block a resolution bandwidth of 100kHz or 1% of the emission bandwidth of the fundamental emission of the transmitter may be employed. The EUT emission bandwidth is measured as the width of the signal between two points, outside of which all emissions are attenuated at least 26dB below the transmitter power. The video bandwidth of the spectrum analyser was set at thrice the resolution bandwidth. Detector Mode was set to peak or peak hold power.

5.5.2. Test Procedures

- 1, The testing follows ANSI C63.26 Section 5.7
- 2, Start and stop frequency were set such that the band edge would be placed in the center of the spectrum analyzer screen.
- 3, Span was set large enough to capture all out of band emissions near the band edge.
- 4, $RBW \geq 1\%$ of the emission bandwidth (2% of the emission bandwidth for n7/n38/n41 except when 1MHz band is 2495-2496MHz);
- 5, $VBW \geq 3 * RBW$
- 6, Detector=RMS
- 7, Trace Mode=Trace Average for continuous emissions, Max Hold for pulse emissions.
- 8, Sweep Points $\geq 2 * Span/RBW$
- 9, Sweep Time = Auto
- 10, The trace was allowed to stabilize.

5.6. Conducted Spurious Emission Measurement

5.6.1. Description of Conducted Spurious Emission Measurement

The transmitter output was connected to a calibrated coaxial cable, attenuator and Spectrum analyser, the other end of which was connected to a Base Station Simulator. The Base Station Simulator was set to force the EUT to its maximum power setting. The tests were performed at three frequencies (low channel and high channel). The level of the carrier and the various conducted spurious and harmonic frequencies is

measured by means of a calibrated spectrum analyser. The spectrum is scanned from 9KHz up to a frequency including its 10th harmonic or 40GHz, which is lower.

5.6.2. Test Procedures

- 1, The testing follows ANSI C63.26 Section 5.7
- 2, RBW \geq 100KHz for emissions below 1GHz, 1MHz for emissions above 1GHz.
- 3, VBW \geq 3 * RBW
- 4, Detector = RMS
- 5, Trace Mode = Average.
- 6, Sweep Points \geq 2 * Span/RBW
- 7, Sweep Time = Auto
- 8, The trace was allowed to stabilize.

5.7. Frequency Stability Measurement

5.7.1. Description of Frequency Stability Measurement

The Frequency Stability should be measured by variation of ambient temperature and variation of primary supply voltage to ensure that the fundamental emissions stays within the authorized frequency block.

5.7.2. Measurement Procedure for Temperature Variation

- 1, The testing follows ANSI C63.26 section 5.6.4.
- 2, The EUT was set up in the thermal chamber and connected with the system simulator.
- 3, With power off, the temperature was decreased to -30°C and the EUT was stabilized before testing. Power was applied and the maximum change in frequency was recorded within one minute.
- 4, With power off, the temperature was raised in 10°C step up to 50°C. The EUT was stabilized at each step for at least half an hour. Power was applied and the maximum change in frequency was recorded within one minute.

5.7.3. Measurement Procedure for Voltage Variation

- 1, The testing follows ANSI C63.26 section 5.6.5.
- 2, The EUT was placed in a thermal chamber at 20±5°C and connected with the system simulator.
- 3, The power supply voltage to the EUT was varied from 85% to 115% of the nominal value for other than hand carried battery equipment.
- 4, For hand carried, battery powered equipment, reduce the primary ac or dc supply voltage to the battery operating end point, which shall be specified by the manufacturer.
- 5, The variation in frequency was measured for the worst case.

6. List of Measuring Equipment

Equipment	Model	Manufacture	Device No.	Cal Date	Cal Due
Radio Communication Analyzer	MT8000A	Anritsu	6272478367	2023-09-03	2024-09-02
	MT8821C	Anritsu	6272498303	2023-09-03	2024-09-02
Spectrum Analyzer (50Hz-40GHz)	FSV	R&S	101046	2022-12-24	2023-12-23
Power Supply	2036	Keithley	4058748	2022-12-27	2023-12-26
Temperature Chamber	C/64/40/3	Weiss	56246017780020	2023-04-07	2024-04-06
Power Divider	-	WOKEN	0120A04051801O	NCR	
Power Divider	-	WOKEN	0120A02056002D	NCR	

Remark:

- 1, For equipment listed above that has a calibration date or calibration due date that falls within the test date range, and the equipment was used after calibrate date and before calibrate due date.
- 2, "NCR" means no calibration required.

7. Measurement Uncertainty

The measurement uncertainties shown below were calculated in accordance with the requirements of ANSI 63.26. All the measurement uncertainties value were shown with a coverage K=2 to indicate 95% level of confidence. The measurement data show herein meets or exceeds the CISPR measurement uncertainty values specified in CISPR 16-4-2 and can be directly to specified limit to determine compliance.

7.1. Uncertainty of Conducted Measurement

Contribution	Expanded Uncertainty
Conducted Power	± 0.77
Conducted Emission	± 0.76
Channel Bandwidth	± 0.08%

8. Appendixes

1	Appendix B.1 for n2A(1850-1910)
2	Appendix B.2 for n5A(824-849)
3	Appendix B.3 for DC_4A_n7A(2500-2570)
4	Appendix B.4 for n26A(814-824)
5	Appendix B.5 for n26A(824-849)
6	Appendix B.6 for DC_2A_n38A(2570-2620)
7	Appendix B.7 for DC_66A_n41A(2496-2690)
8	Appendix B.8 for n66A(1710-1780)
9	Appendix B.9 for DC_38A_n78A(3450-3550)
10	Appendix B.10 for DC_66A_n2A(1850-1910)_Other PA
11	Appendix B.11 for DC_7A_n66A(1710-1780)_Other PA

The End