



MOTOROLA

Cellular Infrastructure Group

FCC ID: IHET6AP1

SECTION A

Summary of RF Measurements 4812ETL 1.9GHz


Summary of Radiated RF Measurements

Worst Case Radiated RF Spur Levels for SC4812ETL @ 1.9GHz

<i>Radiated Data</i>			<i>Substituted Power</i>				<i>Spec</i>	<i>Result</i>
TX Channel	Spurious Frequency (MHz)	Antenna Polarity	Measured Radiated Field Strength (dBuV/M)	Measured Radiated Field Strength (dBm) (Note 1)	TX Antenna Terminal Voltage (dBm) (Note 2)	EDRP (dBm) (Note 3)	FCC Part 24 MAX LIMIT (dBm)	Pass/Fail
25	3862.144	H	59.08	-36.15	-47.8	-42.25	-13	Pass

Notes:

1. Converting dBuV/M to dBm at 3 meters
 $(\text{dBuV/M}) + 9.542 - 104.77 \text{dB} = \text{dBm}$
 Converting dBuV/M to dBm at 10 meters
 $(\text{dBuV/M}) + 20 - 104.77 \text{dB} = \text{dBm}$
2. The same horn antenna and measurement system was used for EUT scan and during substitution method. After maximizing the receive antenna and adjusting signal generator power level to measure the same emission level with the spectrum analyzer as with the EUT. Signal generator output level was recorded for each of the spurious frequencies. Test cable was then disconnected from the transmit horn and was connected to the input of the S/A measuring the voltage at the terminals of the antenna.
3. This value was obtained by converting the Equivalent Isotropic Radiated Power (EIRP) to ideal half-wave dipole reference power - (Equivalent Di-Pole Radiated Power - EDRP) per (TIA-603, 2.2.12.2(i)(m))



Radiated Engineer

Date 12/4/00



MOTOROLA

Cellular Infrastructure Group

FCC ID: IHET6AP1

SECTION C

Spurious & Harmonic Emissions Radiated

Radiated RF Measurements

Worst Case Radiated RF Spur Levels for SC4812ETL @ 1.9GHz

<i>Radiated Data</i>			<i>Substituted Power</i>				<i>Spec</i>	<i>Result</i>
TX Channel	Spurious Frequency (MHz)	Antenna Polarity	Measured Radiated Field Strength (dBuV/M)	Measured Radiated Field Strength (dBm) (Note 1)	TX Antenna Terminal Voltage (dBm) (Note 2)	EDRP (dBm) (Note 3)	FCC Part 24 MAX LIMIT (dBm)	Pass/Fail
25	3862.144	H	59.08	-36.15	-47.8	-42.25	- 13	Pass
25	5791.965	H	53.31	-41.85	-53.1	-46.45	- 13	Pass
1175	3978.33	H	56.27	-38.96	-51.3	-45.85	- 13	Pass
1175	3918.82	H	52.17	-43.06	-55.6	-50.15	- 13	Pass
25	3862.144	V	55.7	-39.53	-50.1	-44.55	- 13	Pass
25	5791.96	V	48.57	-46.66	-59.19	-52.54	- 13	Pass

Notes:

1. Converting dBuV/M to dBm at 3 meters
 $(\text{dBuV/M}) + 9.542 - 104.77 \text{dB} = \text{dBm}$
 Converting dBuV/M to dBm at 10 meters
 $(\text{dBuV/M}) + 20 - 104.77 \text{dB} = \text{dBm}$
2. The same horn antenna and measurement system was used for EUT scan and during substitution method. After maximizing the receive antenna and adjusting signal generator power level to measure the same emission level with the spectrum analyzer as with the EUT. Signal generator output level was recorded for each of the spurious frequencies. Test cable was then disconnected from the transmit horn and was connected to the input of the S/A measuring the voltage at the terminals of the antenna.
3. This value was obtained by converting the Equivalent Isotropic Radiated Power (EIRP) to ideal half-wave dipole reference power - (Equivalent Di-Pole Radiated Power - EDRP) per (TIA-603, 2.2.12.2(i)(m))



Radiated Engineer

 12/04/00
 Date