

## RF Exposure / MPE Calculation

No. : 14027963S-A-R1  
Applicant : JVCKENWOOD Corporation  
Type of Equipment : Monitor with Receiver  
Model No. : DMX958XR  
FCC ID : IOMJ5268

JVCKENWOOD Corporation declares that Model: DMX958XR complies with FCC radiation exposure requirement specified in the FCC Rule 2.1091 (for mobile).

### **RF Exposure Calculations:**

The following information provides the minimum separation distance for the highest gain antenna provided with the “DMX958XR“ as calculated from (B) Limits for General Population / Uncontrolled Exposure of TABLE 1- LIMITS FOR MAXIMUM PERMISSIBLE EXPOSURE (MPE) of §1.1310 Radiofrequency radiation exposure limits.

This calculation is based on the highest EIRP possible from the system, considering maximum power and antenna gain, and considering a 1mW/cm<sup>2</sup> uncontrolled exposure limit. The Friis formula used was:

$$S = \frac{P \times G}{4 \times \pi \times r^2}$$

Where

$P =$  29.92 mW (Maximum average output power)  
 Time average was used for the above value in consideration of 6-minutes time-averaging  
 Burst power average was used for the above value in consideration of worst condition.  
 $G =$  0.170 Numerical Antenna gain; equal to -7.7dBi  
 $r =$  20 cm (Separation distance)

**Power Density Result  $S = 0.00101 \text{ mW/cm}^2$**

Even taking into account the tolerance, this device can be satisfied with the limits.

---

**UL Japan, Inc.**

**Shonan EMC Lab.**

1-22-3 Megumigaoka, Hiratsuka-shi, Kanagawa-ken, 259-1220 JAPAN

Telephone : +81 463 50 6400

Facsimile : +81 463 50 6401