

Calibration Laboratory of
Schmid & Partner
Engineering AG
Zeughausstrasse 43, 8004 Zurich, Switzerland



S Schweizerischer Kalibrierdienst
C Service suisse d'étalonnage
C Servizio svizzero di taratura
S Swiss Calibration Service

Accredited by the Swiss Accreditation Service (SAS)

The Swiss Accreditation Service is one of the signatories to the EA
 Multilateral Agreement for the recognition of calibration certificates

Accreditation No.: **SCS 108**

Client **CCS (Auden)**

Certificate No: **DAE4-558_Jul09**

CALIBRATION CERTIFICATE

Object	DAE4 - SD 000 D04 BJ - SN: 558																		
Calibration procedure(s)	QA CAL-06.v20 Calibration procedure for the data acquisition electronics (DAE)																		
Calibration date:	July 17, 2009																		
Condition of the calibrated item	In Tolerance																		
<p>This calibration certificate documents the traceability to national standards, which realize the physical units of measurements (SI). The measurements and the uncertainties with confidence probability are given on the following pages and are part of the certificate.</p> <p>All calibrations have been conducted in the closed laboratory facility: environment temperature (22 ± 3)°C and humidity < 70%.</p> <p>Calibration Equipment used (M&TE critical for calibration)</p> <table border="1"> <thead> <tr> <th>Primary Standards</th> <th>ID #</th> <th>Cal Date (Certificate No.)</th> <th>Scheduled Calibration</th> </tr> </thead> <tbody> <tr> <td>Keithley Multimeter Type 2001</td> <td>SN: 0810278</td> <td>30-Sep-08 (No: 7670)</td> <td>Sep-09</td> </tr> <tr> <th>Secondary Standards</th> <th>ID #</th> <th>Check Date (in house)</th> <th>Scheduled Check</th> </tr> <tr> <td>Calibrator Box V1.1</td> <td>SE UMS 006 AB 1004</td> <td>05-Jun-09 (in house check)</td> <td>In house check: Jun-10</td> </tr> </tbody> </table>				Primary Standards	ID #	Cal Date (Certificate No.)	Scheduled Calibration	Keithley Multimeter Type 2001	SN: 0810278	30-Sep-08 (No: 7670)	Sep-09	Secondary Standards	ID #	Check Date (in house)	Scheduled Check	Calibrator Box V1.1	SE UMS 006 AB 1004	05-Jun-09 (in house check)	In house check: Jun-10
Primary Standards	ID #	Cal Date (Certificate No.)	Scheduled Calibration																
Keithley Multimeter Type 2001	SN: 0810278	30-Sep-08 (No: 7670)	Sep-09																
Secondary Standards	ID #	Check Date (in house)	Scheduled Check																
Calibrator Box V1.1	SE UMS 006 AB 1004	05-Jun-09 (in house check)	In house check: Jun-10																
Calibrated by:	Name Daniel Hess	Function Technician	Signature 																
Approved by:	Fin Bomholt	R&D Director																	
<p>Issued: July 17, 2009</p> <p>This calibration certificate shall not be reproduced except in full without written approval of the laboratory.</p>																			

Calibration Laboratory of

Schmid & Partner

Engineering AG

Zeughausstrasse 43, 8004 Zurich, Switzerland



S	Schweizerischer Kalibrierdienst
C	Service suisse d'étalonnage
S	Servizio svizzero di taratura
S	Swiss Calibration Service

Accredited by the Swiss Accreditation Service (SAS)

The Swiss Accreditation Service is one of the signatories to the EA

Multilateral Agreement for the recognition of calibration certificates

Accreditation No.: SCS 108

Glossary

DAE	data acquisition electronics
Connector angle	information used in DASY system to align probe sensor X to the robot coordinate system.

Methods Applied and Interpretation of Parameters

- *DC Voltage Measurement*: Calibration Factor assessed for use in DASY system by comparison with a calibrated instrument traceable to national standards. The figure given corresponds to the full scale range of the voltmeter in the respective range.
- *Connector angle*: The angle of the connector is assessed measuring the angle mechanically by a tool inserted. Uncertainty is not required.
- The following parameters as documented in the Appendix contain technical information as a result from the performance test and require no uncertainty.
 - *DC Voltage Measurement Linearity*: Verification of the Linearity at +10% and -10% of the nominal calibration voltage. Influence of offset voltage is included in this measurement.
 - *Common mode sensitivity*: Influence of a positive or negative common mode voltage on the differential measurement.
 - *Channel separation*: Influence of a voltage on the neighbor channels not subject to an input voltage.
 - *AD Converter Values with inputs shorted*: Values on the internal AD converter corresponding to zero input voltage
 - *Input Offset Measurement*: Output voltage and statistical results over a large number of zero voltage measurements.
 - *Input Offset Current*: Typical value for information; Maximum channel input offset current, not considering the input resistance.
 - *Input resistance*: DAE input resistance at the connector, during internal auto-zeroing and during measurement.
 - *Low Battery Alarm Voltage*: Typical value for information. Below this voltage, a battery alarm signal is generated.
 - *Power consumption*: Typical value for information. Supply currents in various operating modes.

DC Voltage Measurement

A/D - Converter Resolution nominal

High Range: 1LSB = $6.1\mu V$, full range = -100...+300 mV

Low Range: 1LSB = $61nV$, full range = -1.....+3mV

DASY measurement parameters: Auto Zero Time: 3 sec; Measuring time: 3 sec

Calibration Factors	X	Y	Z
High Range	$404.888 \pm 0.1\% (k=2)$	$404.772 \pm 0.1\% (k=2)$	$404.946 \pm 0.1\% (k=2)$
Low Range	$3.96642 \pm 0.7\% (k=2)$	$3.97253 \pm 0.7\% (k=2)$	$3.99249 \pm 0.7\% (k=2)$

Connector Angle

Connector Angle to be used in DASY system	$230.0^\circ \pm 1^\circ$
---	---------------------------

Appendix

1. DC Voltage Linearity

High Range		Reading (μ V)	Difference (μ V)	Error (%)
Channel X	+ Input	200007.2	4.82	0.00
Channel X	+ Input	20003.95	4.25	0.02
Channel X	- Input	-19995.70	4.00	-0.02
Channel Y	+ Input	200002.8	0.98	0.00
Channel Y	+ Input	20002.40	2.70	0.01
Channel Y	- Input	-19996.81	2.69	-0.01
Channel Z	+ Input	200011.8	1.35	0.00
Channel Z	+ Input	19996.56	-2.94	-0.01
Channel Z	- Input	-20000.08	0.00	0.00

Low Range		Reading (μ V)	Difference (μ V)	Error (%)
Channel X	+ Input	1999.9	-0.04	-0.00
Channel X	+ Input	199.46	-0.64	-0.32
Channel X	- Input	-201.63	-1.83	0.92
Channel Y	+ Input	2000.0	0.04	0.00
Channel Y	+ Input	198.33	-1.77	-0.89
Channel Y	- Input	-202.89	-2.69	1.34
Channel Z	+ Input	2000.2	0.08	0.00
Channel Z	+ Input	197.46	-2.44	-1.22
Channel Z	- Input	-203.16	-2.96	1.48

2. Common mode sensitivity

DASY measurement parameters: Auto Zero Time: 3 sec; Measuring time: 3 sec

	Common mode Input Voltage (mV)	High Range Average Reading (μ V)	Low Range Average Reading (μ V)
Channel X	200	1.79	-0.26
	-200	1.55	-0.33
Channel Y	200	8.52	8.25
	-200	-9.42	-9.67
Channel Z	200	3.33	3.32
	-200	-4.87	-5.02

3. Channel separation

DASY measurement parameters: Auto Zero Time: 3 sec; Measuring time: 3 sec

	Input Voltage (mV)	Channel X (μ V)	Channel Y (μ V)	Channel Z (μ V)
Channel X	200	-	0.99	-0.47
Channel Y	200	2.54	-	2.51
Channel Z	200	0.98	-0.60	-

4. AD-Converter Values with inputs shorted

DASY measurement parameters: Auto Zero Time: 3 sec; Measuring time: 3 sec

	High Range (LSB)	Low Range (LSB)
Channel X	16233	15954
Channel Y	15699	16320
Channel Z	16048	16043

5. Input Offset Measurement

DASY measurement parameters: Auto Zero Time: 3 sec; Measuring time: 3 sec

Input $10M\Omega$

	Average (μV)	min. Offset (μV)	max. Offset (μV)	Std. Deviation (μV)
Channel X	0.32	-1.37	2.50	0.54
Channel Y	-0.78	-2.09	1.43	0.44
Channel Z	-1.30	-3.70	-0.05	0.43

6. Input Offset Current

Nominal Input circuitry offset current on all channels: <25fA

7. Input Resistance

	Zeroing (MOhm)	Measuring (MOhm)
Channel X	0.2000	202.9
Channel Y	0.1999	203.4
Channel Z	0.1999	201.0

8. Low Battery Alarm Voltage (verified during pre test)

Typical values	Alarm Level (VDC)
Supply (+ Vcc)	+7.9
Supply (- Vcc)	-7.6

9. Power Consumption (verified during pre test)

Typical values	Switched off (mA)	Stand by (mA)	Transmitting (mA)
Supply (+ Vcc)	+0.0	+6	+14
Supply (- Vcc)	-0.01	-8	-9