

4-Button Rolling Code Wireless Transmitter

Model: WL 132KF1

EN

Installation Instructions



EN

1 General Description

The keyfob is a 4-button rolling code wireless transmitter with four transmitting channels, which allows you to arm, partial arm and disarm your alarm system as well as send a panic alarm. The keyfobs can be mounted on a key chain or worn as a pendant on a nylon cord.

To operate the keyfob, press the required button for 1 second. The LED lights up after each press, indicating a successful signal transmission.

2 Replacing the Battery


Remove the screw on the back of the keyfob and carefully separate the two sides of the keyfob's plastic casing. Remove the old battery from the metal clips and place a new one instead. To close reattach the two sides of the keyfob's plastic casing.

3 Quick Device Allocation at the Control Panel


The keyFob is automatically programmed to your control panel during the on-line installation wizard setup. If you later purchase an extra keyfob you can enroll it as follows:


To quickly allocate a keyfob at the control panel:


If the control panel is not already in Learn mode, press the

 button on the control panel for 5 seconds; the unit beeps once as it enters Learn mode (all the LEDs also light up, one after the other).

Make sure batteries are installed in each keyfob before allocating them.

Send a signal transmission from the keyfob by pressing  and

 simultaneously for at least 2 seconds; the control panel beeps once to accept or beeps three times to reject. Once accepted, the system announces the device type and its zone (for example, "Keyfob, zone 1").

When the keyfobs have been enrolled, short-press the control panel button  to exit Learn mode; the unit beeps once and the LEDs stop flashing.

Note: For future use, it is recommended to write down the keyfob description, zone number, and installation location of each allocated keyfob.

4 Technical Specifications

Operates up to	650 feet (200m) range (LOS)
Frequency	915MHz
Temperature range	0° – 50°C (32° – 122°F)
Battery type	CR2430, 3V lithium battery
Battery life	3 years (10 button press a day)
Current consumption	1µA stand by

RISCO Group Limited Warranty

RISCO Group and its subsidiaries and affiliates ("Seller") warrants its products to be free from defects in materials and workmanship under normal use for 24 months from the date of production. Because Seller does not install or connect the product and because the product may be used in conjunction with products not manufactured by the Seller, Seller can not guarantee the performance of the security system which uses this product. Seller's obligation and liability under this warranty is expressly limited to repairing and replacing, at Seller's option, within a reasonable time after the date of delivery, any product not meeting the specifications. Seller makes no other warranty, expressed or implied, and makes no warranty of merchantability or of fitness for any particular purpose. In no case shall seller be liable for any consequential or incidental damages for breach of this or any other warranty, expressed or implied, or upon any other basis of liability whatsoever. Seller's obligation under this warranty shall not include any transportation charges or costs of installation or any liability for direct, indirect, or not be compromised or circumvented; that the product will prevent any persons: injury or property loss by intruder, robbery, fire or otherwise; or that the product will in all cases provide adequate warning or protection. Buyer understands that a properly installed and maintained alarm may only reduce the risk of intruder, robbery or fire without warning, but is not insurance or a guaranty that such will not occur or that there will be no personal injury or property loss as a result. Consequently seller shall have no liability for any personal injury, property damage or loss based on a claim that the product fails to give warning. However, if seller is held liable, whether directly or indirectly, for any loss or damage arising from under this limited warranty or otherwise, regardless of cause or origin, seller's maximum liability shall not exceed the purchase price of the product, which shall be complete and exclusive remedy against seller. No employee or representative of Seller is authorized to change this warranty in any way or grant any other warranty.

WARNING: This product should be tested at least once a week.

CAUTION: Risk of explosion if battery is replaced by an incorrect type. Dispose of used batteries according to local regulations.

FCC ID: JE4WL132KF1915

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) This device must accept any interference received, including interference that may cause undesired operation.

Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment

FCC Note

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules.

These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment on and off, the user is encouraged to try to correct the interference by one or more of the following measures:

- ◆ Reorient or relocate the receiving antenna.
- ◆ Increase the separation between the equipment and the receiver.
- ◆ Connect the equipment into an outlet on a different circuit from that to which the receiver is connected.
- ◆ Consult the dealer or an experienced radio/TV technician for help.