

Report on the RF Testing of:

KYOCERA Corporation
Mobile Phone, Model: EB1190EM
FCC ID: JOYPC9699



In accordance with FCC Part 22 Subpart H

Prepared for: KYOCERA Corporation
Yokohama Office 2-1-1 Kagahara, Tsuzuki-ku
Yokohama-shi, Kanagawa, Japan
Phone: +81-45-943-6253 Fax: +81-45-943-6314



COMMERCIAL-IN-CONFIDENCE

Document Number: JPD-TR-24113-0

SIGNATURE			
NAME	JOB TITLE	RESPONSIBLE FOR	ISSUE DATE
Hiroaki Suzuki	Deputy Manager of EMC Lab	Approved Signatory	2024.07.01

Signatures in this approval box have checked this document in line with the requirements of TÜV SÜD Japan Ltd. document control rules.

EXECUTIVE SUMMARY – Result: Complied
A sample of this product was tested and the result above was confirmed in accordance with FCC Part 22 Subpart H.

  <p>Certificate #3686.03</p>	<p>DISCLAIMER AND COPYRIGHT</p> <p>The results in this report are applicable only to the equipment tested. This report shall not be re-produced except in full without the written approval of TÜV SÜD Japan Ltd.</p> <p>Client provided data, for which TÜV SÜD Japan Ltd. take no responsibility, which can affect validity of results within this report is clearly identified.</p> <p>ACCREDITATION</p> <p>This test report must not be used by the client to claim product certification, approval, or endorsement by A2LA or any agency of the U.S. Government.</p>
---	---

TÜV SÜD Japan Ltd.
Yonezawa Testing Center
5-4149-7 Hachimanpara,
Yonezawa-shi, Yamagata,
992-1128 Japan

Phone: +81 (0) 238 28 2881
www.tuvsud.com/ja-jp



Contents

1	Summary of Test	3
1.1	Modification history of the test report.....	3
1.2	Standards.....	3
1.3	Test methods.....	3
1.4	Deviation from standards.....	3
1.5	List of applied test(s) of the EUT.....	3
1.6	Test information.....	3
1.7	Test set up.....	3
1.8	Test period.....	3
2	Equipment Under Test	4
2.1	EUT information.....	4
2.2	Modification to the EUT.....	5
2.3	Variation of family model(s).....	5
2.4	Description of test mode.....	6
3	Configuration of Equipment	7
3.1	Equipment used.....	7
3.2	System configuration.....	7
4	Test Result	8
4.1	Effective Radiated Power.....	8
4.2	Occupied Bandwidth.....	13
4.3	Band Edge Spurious and Harmonic at Antenna Terminals.....	22
4.4	Radiated Emissions and Harmonic Emissions.....	46
4.5	Frequency Stability.....	55
5	Measurement Uncertainty	58
6	Laboratory Information	59
	Appendix A. Test Equipment	60

1 Summary of Test

1.1 Modification history of the test report

Document Number	Modification History	Issue Date
JPD-TR-24113-0	First Issue	Refer to the cover page

1.2 Standards

CFR47 FCC Part 22 Subpart H

1.3 Test methods

KDB 971168 D01 Power Meas License Digital Systems v03r01
ANSI/TIA/EIA 603-E-2016
ANSI C63.26-2015

1.4 Deviation from standards

None

1.5 List of applied test(s) of the EUT

Test item section	Test item	Condition	Result	Remark
2.1046	Conducted Output Power	Conducted	PASS	*1
22.913(a)	Effective Radiated Power	Radiated	PASS	-
22.917(a) 2.1049	Occupied Bandwidth	Conducted	PASS	-
22.917(a) 2.1051	Band Edge Spurious and Harmonic at Antenna Terminal	Conducted	PASS	-
22.917(a) 2.1053	Radiated emissions and Harmonic Emissions	Radiated	PASS	-
22.355 2.1055	Frequency Stability	Conducted	PASS	-

*1: Refer to RF Exposure Report (Test Report SAR)

1.6 Test information

None

1.7 Test set up

Table-top

1.8 Test period

19-April-2024 - 26-April-2024

2 Equipment Under Test

All information in this chapter was provided by the applicant.

2.1 EUT information

Applicant	KYOCERA Corporation Yokohama Office 2-1-1 Kagahara, Tsuzuki-ku Yokohama-shi, Kanagawa, Japan Phone: +81-45-943-6253 Fax: +81-45-943-6314
Equipment Under Test (EUT)	Mobile Phone
Model number	EB1190EM
Serial number	353343640000094, 353343640000102, 353343640000110
Trade name	Kyocera
Number of sample(s)	3
EUT condition	Pre-Production
Power rating	Battery: DC 3.87 V
Size	(W) 73.0 mm × (D) 157.0 mm × (H) 11.43 mm
Environment	Indoor and Outdoor use
Terminal limitation	-20°C to 60°C
Hardware version	DMT1
Software version	0.151BX.0025.a
Firmware version	Not applicable
RF Specification	
Frequency of Operation	Up Link GSM850: 824.2-848.8 MHz WCDMA Band V: 826.4-846.6 MHz LTE Band V: 824.7-848.3 MHz Down Link GSM850: 869.2-893.8 MHz WCDMA Band V: 871.4-891.6 MHz LTE Band V: 869.7-893.3 MHz
Modulation type	GSM850: GMSK WCDMA Band V: QPSK LTE Band V: QPSK, 16QAM, 64QAM

Emission designator	GSM850: 248KGXW WCDMA Band V: 4M16F9W LTE Band V: BW 1.4M QPSK: 1M10G7D, 16QAM: 1M10W7D, 64QAM: 1M09W7D BW 3M QPSK: 2M71G7D, 16QAM: 2M70W7D, 64QAM: 2M71W7D BW 5M QPSK: 4M52G7D, 16QAM: 4M50W7D, 64QAM: 4M51W7D BW 10M QPSK: 9M00G7D, 16QAM: 9M00W7D, 64QAM: 9M01W7D
Effective Radiated Power (E.R.P.)	GSM850: 1.000 W (30.0 dBm) WCDMA Band V: 0.141 W (21.5 dBm) LTE Band V: 0.071 W (18.5 dBm)
Antenna type	Internal antenna
Antenna gain	GSM850: -2.6 dBi WCDMA Band V: -2.6 dBi LTE Band V: -2.6dBi

2.2 Modification to the EUT

The table below details modifications made to the EUT during the test project.

Modification State	Description of Modification	Modification fitted by	Date of Modification
Model: EB1190EM, Serial Number: 353343640000094, 353343640000102, 353343640000110			
0	As supplied by the applicant	Not Applicable	Not Applicable

2.3 Variation of family model(s)

2.3.1 List of family model(s)

EUT

Model number	EB1190EM *1	EB1201	EB1190	EB1190NC
Memory	expansion	standard	standard	standard
Camera	with	with	with	without
Fingerprint Sensor	with	with	without	without
NFC	with	with	without	without
size	73.0 x 157.0 x 11.43 [mm]			

*1:Tested model

2.3.2 Reason for selection of EUT

The applicant decided that the differences between the design had no EMC impact and selected EB1190EM with full function.

2.4 Description of test mode

The EUT had been tested under operating condition.
There are three channels have been tested as following:

Band	Modulation	Bandwidth [MHz]	Channel	Frequency [MHz]
GSM850	GMSK	-	128, 190, 251	824.2, 836.6, 848.8
WCDMA Band V	QPSK, 16QAM	-	4132, 4183, 4233	826.4, 836.6, 846.6
LTE Band V	QPSK, 16QAM, 64WAM	1.4	20407, 20525, 20643	824.7, 836.5, 848.3
		3	20415, 20525, 20635	825.5, 836.5, 847.5
		5	20425, 20525, 20625	826.5, 836.5, 846.5
		10	20450, 20525, 20600	829.0, 836.5, 844.0

The field strength of spurious emissions was measured at each position of all three axis X, Y and Z to compare the level, and the maximum noise.

The worst emission was found in X-axis (GSM850, WCDMA Band V), Z-axis (LTE Band V) and the worst case recorded.

Pre-scan has been conducted to determine the worst-case mode from all possible combinations between available modulations, data rates and antenna ports.

3 Configuration of Equipment

Numbers assigned to equipment on the diagram in “3.2 System configuration” correspond to the list in “3.1 Equipment used”.

This test configuration is based on the manufacture’s instruction.

Cabling and setup(s) were taken into consideration and test data was taken under worse case condition.

3.1 Equipment used

No.	Equipment	Company	Model No.	Serial No.	FCC ID/DoC	Comment
1	Mobile Phone	KYOCERA	EB1190EM	353343640000094, 353343640000102, 353343640000110	JOYPC9699	EUT

3.2 System configuration

1. Mobile Phone
(EUT)

4 Test Result

4.1 Effective Radiated Power

4.1.1 Measurement procedure

[FCC 22.913(a)]

<Step 1>

The EUT and support equipment are placed on a 1 meter x 1 meter surface, 0.8 meter height styrene foam table. Radiated emission measurements are performed at 3 meter distance with the broadband antenna (Log periodic antenna). The antenna is positioned both the horizontal and vertical planes of polarization and height is varied 1 to 4 meters and stopped at height producing the maximum emission.

The turntable is rotated by 360 degrees and stopped at azimuth of producing the maximum emission.

<Step 2>

The substitution antenna is replaced by the transmitter antenna (EUT).


The frequency of the signal generator is adjusted to the measurement frequency.

Level of the signal generator is adjusted to the level that is obtained from step 1, and record the emission level of signal generator.

The spectrum analyzer is set to;

- a) Span = 1.5 times the OBW
- b) RBW = 1-5% of the expected OBW, not to exceed 1 MHz
- c) VBW \geq 3 x RBW
- d) Number of sweep points \geq 2 x span / RBW
- e) Sweep time = auto-couple
- f) Detector = RMS (power averaging)
- g) If the EUT can be configured to transmit continuously (i.e., burst duty cycle \geq 98%), then set the trigger to free run.
- h) If the EUT cannot be configured to transmit continuously (i.e., burst duty cycle < 98 %), then use a sweep trigger with the level set to enable triggering only on full power bursts and configure the EUT to transmit at full power for the entire duration of each sweep. Ensure that the sweep time is less than or equal to the transmission burst duration.
- i) Trace average at least 100 traces in power averaging (i.e., RMS) mode.
- j) Compute the power by integrating the spectrum across the OBW of the signal using the instrument's band power measurement function, with the band limits set equal to the OBW band edges. If the instrument does not have a band power function, then sum the spectrum levels (in linear power units) at intervals equal to the RBW extending across the entire OBW of the spectrum.

- Test configuration



4.1.2 Calculation method

Result (ERP) = Ant. Input - Cable loss + Antenna Gain

Margin = Limit – Result (ERP)

Example:

Limit @ 836.6 MHz: 38.45 dBm

Ant. Input = 40.0 dBm Cable loss = 0.8 dB Ant. Gain = -6.7 dBd

Result = $40.0 - 0.8 + (-6.7) = 32.5$ dBm

Margin = $38.45 - 32.5 = 5.95$ dB

4.1.3 Limit

7 W (38.45 dBm)

4.1.4 Test data

Date : 25-April-2024
 Temperature : 22.2 [°C]
 Humidity : 40.9 [%]
 Test place : 3m Semi-anechoic chamber

Test engineer : Chiaki Kanno

[GSM850]

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBd]	Result [dBm]	Result [W]	Limit [dBm]	Margin [dB]
H	824.2	-33.7	37.3	1.0	-6.3	30.0	1.000	38.45	8.5
H	836.6	-35.7	35.9	1.1	-6.3	28.5	0.708	38.45	10.0
H	848.8	-35.9	36.3	1.1	-6.3	28.9	0.776	38.45	9.6

[WCDMA Band V]

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBd]	Result [dBm]	Result [W]	Limit [dBm]	Margin [dB]
H	826.4	-33.2	28.5	1.0	-6.3	21.2	0.132	38.45	17.3
H	836.6	-33.4	28.9	1.1	-6.3	21.5	0.141	38.45	17.0
H	846.6	-34.0	28.9	1.1	-6.3	21.5	0.141	38.45	17.0

[LTE Band V]

QPSK, BW 1.4MHz

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBd]	Result [dBm]	Result [W]	Limit [dBm]	Margin [dB]
H	824.7	-36.9	24.8	1.0	-6.3	17.5	0.056	38.45	21.0
H	836.5	-37.7	24.6	1.1	-6.3	17.2	0.052	38.45	21.3
H	848.3	-39.0	23.9	1.1	-6.3	16.5	0.045	38.45	22.0

[LTE Band V]

16QAM, BW 1.4MHz

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBd]	Result [dBm]	Result [W]	Limit [dBm]	Margin [dB]
H	824.7	-37.9	23.8	1.0	-6.3	16.5	0.045	38.45	22.0
H	836.5	-38.7	23.6	1.1	-6.3	16.2	0.042	38.45	22.3
H	848.3	-40.4	22.5	1.1	-6.3	15.1	0.032	38.45	23.4

[LTE Band V]

64QAM, BW 1.4MHz

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBd]	Result [dBm]	Result [W]	Limit [dBm]	Margin [dB]
H	824.7	-39.0	22.7	1.0	-6.3	15.4	0.035	38.45	23.1
H	836.5	-39.7	22.6	1.1	-6.3	15.2	0.033	38.45	23.3
H	848.3	-41.1	21.8	1.1	-6.3	14.4	0.028	38.45	24.1

**[LTE Band V]
QPSK, BW 3MHz**

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBd]	Result [dBm]	Result [W]	Limit [dBm]	Margin [dB]
H	825.5	-35.8	25.7	1.0	-6.3	18.4	0.069	38.45	20.1
H	836.5	-38.1	24.2	1.1	-6.3	16.8	0.048	38.45	21.7
H	847.5	-38.9	23.8	1.1	-6.3	16.4	0.044	38.45	22.1

**[LTE Band V]
16QAM, BW 3MHz**

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBd]	Result [dBm]	Result [W]	Limit [dBm]	Margin [dB]
H	825.5	-36.9	24.6	1.0	-6.3	17.3	0.054	38.45	21.2
H	836.5	-38.8	23.5	1.1	-6.3	16.1	0.041	38.45	22.4
H	847.5	-39.8	22.9	1.1	-6.3	15.5	0.035	38.45	23.0

**[LTE Band V]
64QAM, BW 3MHz**

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBd]	Result [dBm]	Result [W]	Limit [dBm]	Margin [dB]
H	825.5	-37.8	23.7	1.0	-6.3	16.4	0.044	38.45	22.1
H	836.5	-39.8	22.5	1.1	-6.3	15.1	0.032	38.45	23.4
H	847.5	-41.1	21.6	1.1	-6.3	14.2	0.026	38.45	24.3

**[LTE Band V]
QPSK, BW 5MHz**

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBd]	Result [dBm]	Result [W]	Limit [dBm]	Margin [dB]
H	826.5	-36.8	25.0	1.0	-6.3	17.7	0.059	38.45	20.8
H	836.5	-36.4	25.9	1.1	-6.3	18.5	0.071	38.45	20.0
H	846.5	-38.6	24.0	1.1	-6.3	16.6	0.046	38.45	21.9

**[LTE Band V]
16QAM, BW 5MHz**

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBd]	Result [dBm]	Result [W]	Limit [dBm]	Margin [dB]
H	826.5	-37.9	23.9	1.0	-6.3	16.6	0.046	38.45	21.9
H	836.5	-37.7	24.6	1.1	-6.3	17.2	0.052	38.45	21.3
H	846.5	-39.9	22.7	1.1	-6.3	15.3	0.034	38.45	23.2

**[LTE Band V]
64QAM, BW 5MHz**

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBd]	Result [dBm]	Result [W]	Limit [dBm]	Margin [dB]
H	826.5	-38.8	23.0	1.0	-6.3	15.7	0.037	38.45	22.8
H	836.5	-38.5	23.8	1.1	-6.3	16.4	0.044	38.45	22.1
H	846.5	-40.9	21.7	1.1	-6.3	14.3	0.027	38.45	24.2

**[LTE Band V]
QPSK, BW 10MHz**

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBd]	Result [dBm]	Result [W]	Limit [dBm]	Margin [dB]
H	829.0	-37.0	25.0	1.0	-6.3	17.7	0.059	38.45	20.8
H	836.5	-36.9	25.4	1.1	-6.3	18.0	0.063	38.45	20.5
H	844.0	-38.2	24.4	1.1	-6.3	17.0	0.050	38.45	21.5

**[LTE Band V]
16QAM, BW 10MHz**

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBd]	Result [dBm]	Result [W]	Limit [dBm]	Margin [dB]
H	829.0	-38.0	24.0	1.0	-6.3	16.7	0.047	38.45	21.8
H	836.5	-38.0	24.3	1.1	-6.3	16.9	0.049	38.45	21.6
H	844.0	-39.3	23.3	1.1	-6.3	15.9	0.039	38.45	22.6

**[LTE Band V]
64QAM, BW 10MHz**

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBd]	Result [dBm]	Result [W]	Limit [dBm]	Margin [dB]
H	829.0	-39.1	22.9	1.0	-6.3	15.6	0.036	38.45	22.9
H	836.5	-39.4	22.9	1.1	-6.3	15.5	0.035	38.45	23.0
H	844.0	-40.6	22.0	1.1	-6.3	14.6	0.029	38.45	23.9

All other emissions measured were greater than 20dB below the specification limit.

4.2 Occupied Bandwidth

4.2.1 Measurement procedure


[FCC 22.917(a), 2.1049]

The Occupied bandwidth was measured with a spectrum analyzer connected to the antenna terminal. The spectrum analyzer's automatic bandwidth measurement capability was used to perform the 99% occupied bandwidth and the 26dB bandwidth.

The spectrum analyzer is set to;

- a) RBW = 1-5% of the expected OBW & VBW $\geq 3 \times$ RBW
- b) Detector = Peak
- c) Trace mode = Max hold
- d) Sweep time = auto-couple

- Test configuration



4.2.2 Limit

None



4.2.3 Measurement result

Date : 19-April-2024
 Temperature : 22.9 [°C]
 Humidity : 29.7 [%]
 Test place : Shielded room No.4
 Test engineer : Kazunori Saito

Date : 22-April-2024
 Temperature : 19.9 [°C]
 Humidity : 34.6 [%]
 Test place : Shielded room No.4
 Test engineer : Kazunori Saito

Date : 23-April-2024
 Temperature : 23.0 [°C]
 Humidity : 36.2 [%]
 Test place : Shielded room No.4
 Test engineer : Kazunori Saito

Band	Channel	Frequency (MHz)	Test Result (kHz)
GSM850	128	824.2	248.3810
	190	836.6	245.1606
	251	848.8	246.6514
W-CDMA850	4132	826.4	4149.0
	4183	836.6	4155.8
	4233	846.6	4131.9




LTE Band V

BW	Mode	UL RB Allocation	UL RB Start	Frequency [MHz]	26dB Bandwidth [MHz]	99% OBW [MHz]
1.4MHz	QPSK	1	0	836.5	0.460	0.2846
		1	5		0.450	0.2794
		3	1		0.857	0.6011
		6	0		1.289	1.0956
	16QAM	1	0	836.5	0.456	0.2888
		1	5		0.462	0.2883
		3	1		0.887	0.6148
		6	0		1.308	1.0990
	64QAM	1	0	836.5	0.456	0.2910
		1	5		0.463	0.2995
		3	1		0.859	0.5999
		6	0		1.292	1.0928
3MHz	QPSK	1	0	836.5	0.583	0.3858
		1	14		0.566	0.3772
		8	4		1.958	1.5386
		15	0		2.962	2.7071
	16QAM	1	0	836.5	0.563	0.3748
		1	14		0.546	0.3643
		8	4		1.936	1.5306
		15	0		2.950	2.7028
	64QAM	1	0	836.5	0.559	0.3763
		1	14		0.527	0.3589
		8	4		1.932	1.5221
		15	0		2.961	2.7095
5MHz	QPSK	1	0	836.5	0.828	0.5881
		1	24		0.844	0.5911
		12	7		3.207	2.3588
		25	0		4.981	4.5209
	16QAM	1	0	836.5	0.829	0.5889
		1	24		0.847	0.6107
		12	7		3.166	2.3130
		25	0		4.985	4.4980
	64QAM	1	0	836.5	0.911	0.6153
		1	24		0.859	0.5919
		12	7		3.105	2.2966
		25	0		4.988	4.5062
10MHz	QPSK	1	0	836.5	1.439	0.9894
		1	49		1.361	0.9558
		25	12		5.696	4.6489
		50	0		9.933	8.9979
	16QAM	1	0	836.5	1.363	0.9834
		1	49		1.376	0.9930
		25	12		5.865	4.6500
		50	0		9.785	8.9994
	64QAM	1	0	836.5	1.452	1.0410
		1	49		1.386	0.9890
		25	12		5.860	4.7081
		50	0		9.817	9.0053


4.2.4 Trace data

[GSM850]


Channel: 128




Channel: 190




Channel: 251




[WCDMA Band V]
Channel: 4132



Channel: 4183




Channel: 4233




[LTE Band V]
Channel: 20525

QPSK, BW 1.4MHz

RB3-1




RB6-0




16QAM, BW 1.4MHz

RB3-1




RB6-0




64QAM, BW 1.4MHz

RB3-1




RB6-0




[LTE Band V]
Channel: 20525

QPSK, BW 3MHz

RB8-4




RB15-0




16QAM, BW 3MHz

RB8-4




RB15-0




64QAM, BW 3MHz

RB8-4




RB15-0




[LTE Band V]
Channel: 20525


QPSK, BW 5MHz
RB12-7




RB25-0




16QAM, BW 5MHz
RB12-7




RB25-0



64QAM, BW 5MHz
RB12-7




RB25-0




[LTE Band V]
Channel: 20525

QPSK, BW 10MHz

RB25-12




RB50-0




16QAM, BW 10MHz

RB25-12




RB50-0




64QAM, BW 10MHz

RB25-12



RB50-0



4.3 Band Edge Spurious and Harmonic at Antenna Terminals

4.3.1 Measurement procedure

[FCC 22.917(a), 2.1051]

The band edge spurious and harmonic was measured with a spectrum analyzer connected to the antenna terminal.

The spectrum analyzer is set to;


<Band Edge>

- a) Span was set large enough so as to capture all out of band emissions near the band edge
- b) $RBW \geq 1\%$ of the emission bandwidth or 2% of the emission bandwidth
- c) $VBW \geq 3 \times RBW$
- d) Detector = RMS
- e) Trace mode = Max hold
- f) Sweep time = auto-couple
- g) Number of sweep point $\geq 2 \times \text{span} / RBW$

<Spurious Emissions>

- a) $RBW = 1\text{MHz}$ & $VBW \geq 3 \times RBW$
- b) Detector = Peak
- c) Trace mode = Max hold
- d) Sweep time = auto-couple
- e) Number of sweep point $\geq 2 \times \text{span} / RBW$

- Test configuration



4.3.2 Limit

-13 dBm or less



4.3.3 Measurement result

Date : 19-April-2024
 Temperature : 22.9 [°C]
 Humidity : 29.7 [%]
 Test place : Shielded room No.4
 Test engineer : Kazunori Saito

Date : 22-April-2024
 Temperature : 19.9 [°C]
 Humidity : 34.6 [%]
 Test place : Shielded room No.4
 Test engineer : Kazunori Saito


Date : 23-April-2024
 Temperature : 23.0 [°C]
 Humidity : 36.2 [%]
 Test place : Shielded room No.4
 Test engineer : Kazunori Saito

Band	Channel/BW	Frequency [MHz]	Limit [dBm]	Results	
GSM850	128	824.2	-13.0	See the trace data	PASS
	190	836.6	-13.0	See the trace data	PASS
	251	848.8	-13.0	See the trace data	PASS
WCDMA Band V	4132	826.4	-13.0	See the trace data	PASS
	4183	836.6	-13.0	See the trace data	PASS
	4233	846.6	-13.0	See the trace data	PASS
LTE Band V	1.4MHz	824.7	-13.0	See the trace data	PASS
		836.5	-13.0	See the trace data	PASS
		847.5	-13.0	See the trace data	PASS
	3MHz	825.5	-13.0	See the trace data	PASS
		836.5	-13.0	See the trace data	PASS
		847.5	-13.0	See the trace data	PASS
	5MHz	826.5	-13.0	See the trace data	PASS
		836.6	-13.0	See the trace data	PASS
		846.5	-13.0	See the trace data	PASS
	10MHz	829.0	-13.0	See the trace data	PASS
		836.6	-13.0	See the trace data	PASS
		844.0	-13.0	See the trace data	PASS


4.3.4 Trace data

[GSM850]
(Band Edge)

Channel: 128




Channel: 251




(Spurious Emissions)

Note: Conducted spurious test was measured in the worst case of conducted output power.


**Channel: 128
30MHz-5GHz**




5GHz-10GHz




**Channel: 190
30MHz-5GHz**




5GHz-10GHz



**Channel: 251
30MHz-5GHz**





5GHz-10GHz





[WCDMA Band V]
(Band Edge)

Channel: 4132




Channel: 4233




(Spurious Emissions)

Note: Conducted spurious test was measured in the worst case of conducted output power.


**Channel: 4132
30MHz-5GHz**




5GHz-10GHz




**Channel: 4183
30MHz-5GHz**




5GHz-10GHz



**Channel: 4233
30MHz-5GHz**




5GHz-10GHz




[LTE Band V]
(Band Edge)


QPSK, BW 1.4MHz, RB1-0
Channel: Low




RB1-5
Channel: High



QPSK, BW 1.4MHz, RB6-0
Channel: Low




Channel: High




[LTE Band V]
(Band Edge)


16QAM, BW 1.4MHz, RB1-0
Channel: Low




RB1-5
Channel: High



16QAM, BW 1.4MHz, RB6-0
Channel: Low




Channel: High




[LTE Band V]
(Band Edge)


64QAM, BW 1.4MHz, RB1-0
Channel: Low




RB1-5
Channel: High



64QAM, BW 1.4MHz, RB6-0
Channel: Low




Channel: High




[LTE Band V]
(Band Edge)


QPSK, BW 3MHz, RB1-0
Channel: Low




RB1-14
Channel: High



QPSK, BW 3MHz, RB15-0
Channel: Low




Channel: High




[LTE Band V]
(Band Edge)


16QAM, BW 3MHz, RB1-0
Channel: Low




RB1-14
Channel: High



16QAM, BW 3MHz, RB15-0
Channel: Low




Channel: High




[LTE Band V]
(Band Edge)


64QAM, BW 3MHz, RB1-0
Channel: Low




RB1-14
Channel: High



64QAM, BW 3MHz, RB15-0
Channel: Low




Channel: High




[LTE Band V]
(Band Edge)


QPSK, BW 5MHz, RB1-0
Channel: Low




RB1-24
Channel: High



QPSK, BW 5MHz, RB25-0
Channel: Low




Channel: High




[LTE Band V]
(Band Edge)


16QAM, BW 5MHz, RB1-0
Channel: Low




RB1-24
Channel: High



16QAM, BW 5MHz, RB25-0
Channel: Low




Channel: High




[LTE Band V]
(Band Edge)


64QAM, BW 5MHz, RB1-0
Channel: Low




RB1-24
Channel: High



64QAM, BW 5MHz, RB25-0
Channel: Low




Channel: High




[LTE Band V]
(Band Edge)


QPSK, BW 10MHz, RB1-0
Channel: Low




RB1-49
Channel: High



QPSK, BW 10MHz, RB50-0
Channel: Low




Channel: High




[LTE Band V]
(Band Edge)


16QAM, BW 10MHz, RB1-0
Channel: Low




RB1-49
Channel: High



16QAM, BW 10MHz, RB50-0
Channel: Low




Channel: High




[LTE Band V]
(Band Edge)


64QAM, BW 10MHz, RB1-0
Channel: Low




RB1-49
Channel: High



64QAM, BW 10MHz, RB50-0
Channel: Low



Channel: High




[LTE Band V]
 (Spurious Emissions)

Note: Conducted spurious test was measured in the worst case of Effective Radiated Power.


QPSK, BW 1.4MHz, RB 1-3

Channel: Low

30MHz-5GHz




5GHz-10GHz




Channel: Middle

30MHz-5GHz




5GHz-10GHz




Channel: High

30MHz-5GHz



5GHz-10GHz



4.4 Radiated Emissions and Harmonic Emissions

4.4.1 Measurement procedure

[FCC 22.917(a), 2.1053]

<Step 1>

The EUT and support equipment are placed on a 1 meter x 1 meter surface, 0.8 meter height (Below 1GHz) or 0.6 meter x 0.6 meter surface, 1.5 meter height (Above 1GHz) styrene foam table. Radiated emission measurements are performed at 3 meter distance with the broadband antenna (Biconical antenna, Log periodic antenna and double ridged guide antenna). The antenna is positioned both the horizontal and vertical planes of polarization and height is varied 1 to 4 meters and stopped at height producing the maximum emission.

The bandwidth of the spectrum analyzer is set to 1MHz. The turntable is rotated by 360 degrees and stopped at azimuth of producing the maximum emission. The frequency is investigated up to 20GHz.

<Step 2>

The substitution antenna is replaced by the transmitter antenna (EUT).


The frequency of the signal generator is adjusted to the measurement frequency.

Level of the signal generator is adjusted to the level that is obtained from step 1, and record the emission level of signal generator.

The spectrum analyzer is set to;

- RBW = 100kHz for below 1GHz and 1MHz for above 1GHz / VBW \geq 3 x RBW
- Detector = Peak
- Trace mode = Max hold
- Sweep time = auto-couple

- Test configuration



4.4.2 Calculation method

Result (EIRP) = Ant. Input - Cable loss + Antenna Gain
Margin = Limit – Result (EIRP)

Example:

Limit @ 1673.2 MHz: -13.0 dBm
Ant. Input = -56.4 dBm Cable loss = 1.0 dB Ant. Gain = 6.9 dBi
Result = $-56.4 - 1.0 + 6.9 = -50.5$ dBm
Margin = $-13.0 - (-50.5) = 37.5$ dB

4.4.3 Limit

-13 dBm or less

4.4.4 Test data

Date : 25-April-2024
 Temperature : 22.2 [°C]
 Humidity : 40.9 [%]
 Test place : 3m Semi-anechoic chamber

Test engineer : Chiaki Kanno

Date : 26-April-2024
 Temperature : 21.8 [°C]
 Humidity : 38.8 [%]
 Test place : 3m Semi-anechoic chamber

Test engineer : Tadahiro Seino

[GSM850]

(Channel: 128)

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBi]	Result [dBm]	Limit [dBm]	Margin [dB]
H	1648.8	-58.6	-58.8	1.1	6.2	-53.7	-13.0	40.7

(Channel: 190)

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBi]	Result [dBm]	Limit [dBm]	Margin [dB]
H	1673.2	-57.9	-57.5	1.1	5.9	-52.7	-13.0	39.7

(Channel: 251)

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBi]	Result [dBm]	Limit [dBm]	Margin [dB]
H	1697.6	-58.1	-57.9	1.1	5.6	-53.3	-13.0	40.3

[WCDMA Band V]

(Channel: 4132)

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBi]	Result [dBm]	Limit [dBm]	Margin [dB]
H	1652.8	-58.2	-55.7	1.1	6.1	-50.7	-13.0	37.7

(Channel: 4183)

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBi]	Result [dBm]	Limit [dBm]	Margin [dB]
H	1673.2	-58.5	-56.1	1.1	5.9	-51.3	-13.0	38.3

(Channel: 4233)

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBi]	Result [dBm]	Limit [dBm]	Margin [dB]
H	1693.2	-58.6	-56.0	1.1	5.7	-51.4	-13.0	38.4

**[LTE Band V]
QPSK, BW 1.4MHz
(Channel: 20407)**

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBi]	Result [dBm]	Limit [dBm]	Margin [dB]
H	1649.4	-58.8	-52.8	1.1	6.2	-47.7	-13.0	34.7
H	2474.1	-59.0	-53.5	1.3	5.7	-49.2	-13.0	36.2

(Channel: 20525)

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBi]	Result [dBm]	Limit [dBm]	Margin [dB]
H	1673.0	-59.9	-53.9	1.1	5.9	-49.1	-13.0	36.1
H	2509.5	-59.8	-54.3	1.3	6.0	-49.6	-13.0	36.6

(Channel: 20643)

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBi]	Result [dBm]	Limit [dBm]	Margin [dB]
H	1696.6	-60.0	-54.0	1.1	5.6	-49.4	-13.0	36.4
H	2544.9	-59.1	-53.8	1.3	6.0	-49.2	-13.0	36.2

**[LTE Band V]
16QAM, BW 1.4MHz
(Channel: 20407)**

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBi]	Result [dBm]	Limit [dBm]	Margin [dB]
H	1649.4	-59.5	-53.5	1.1	6.2	-48.4	-13.0	35.4
H	2474.1	-59.3	-53.8	1.3	5.7	-49.5	-13.0	36.5

(Channel: 20525)

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBi]	Result [dBm]	Limit [dBm]	Margin [dB]
H	1673.0	-59.9	-53.9	1.1	5.9	-49.1	-13.0	36.1
H	2509.5	-59.6	-54.1	1.3	6.0	-49.4	-13.0	36.4

(Channel: 20643)

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBi]	Result [dBm]	Limit [dBm]	Margin [dB]
H	1696.6	-60.1	-54.1	1.1	5.6	-49.5	-13.0	36.5
H	2544.9	-59.3	-54.0	1.3	6.0	-49.4	-13.0	36.4

**[LTE Band V]
64QAM, BW 1.4MHz
(Channel: 20407)**

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBi]	Result [dBm]	Limit [dBm]	Margin [dB]
H	1649.4	-59.9	-53.9	1.1	6.2	-48.8	-13.0	35.8
H	2474.1	-59.8	-54.7	1.3	5.7	-50.4	-13.0	37.4

(Channel: 20525)

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBi]	Result [dBm]	Limit [dBm]	Margin [dB]
H	1673.0	-59.8	-53.8	1.1	5.9	-49.0	-13.0	36.0
H	2509.5	-60.0	-54.5	1.3	6.0	-49.8	-13.0	36.8

(Channel: 20643)

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBi]	Result [dBm]	Limit [dBm]	Margin [dB]
H	1696.6	-60.2	-54.2	1.1	5.6	-49.6	-13.0	36.6
H	2544.9	-59.2	-53.9	1.3	6.0	-49.3	-13.0	36.3

**[LTE Band V]
QPSK, BW 3MHz
(Channel: 20415)**

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBi]	Result [dBm]	Limit [dBm]	Margin [dB]
H	1651.0	-59.9	-53.9	1.1	6.1	-48.8	-13.0	35.8
H	2476.5	-59.8	-54.3	1.3	5.7	-49.9	-13.0	36.9

(Channel: 20525)

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBi]	Result [dBm]	Limit [dBm]	Margin [dB]
H	1673.0	-59.3	-53.3	1.1	5.9	-48.5	-13.0	35.5
H	2509.5	-59.6	-54.1	1.3	6.0	-49.4	-13.0	36.4

(Channel: 20635)

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBi]	Result [dBm]	Limit [dBm]	Margin [dB]
H	1695.0	-59.5	-53.5	1.1	5.7	-48.9	-13.0	35.9
H	2542.5	-59.7	-54.2	1.3	6.0	-49.6	-13.0	36.6

**[LTE Band V]
16QAM, BW 3MHz
(Channel: 20415)**

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBi]	Result [dBm]	Limit [dBm]	Margin [dB]
H	1651.0	-59.6	-53.5	1.1	6.1	-48.4	-13.0	35.4
H	2476.5	-59.3	-53.7	1.3	5.7	-49.3	-13.0	36.3

(Channel: 20525)

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBi]	Result [dBm]	Limit [dBm]	Margin [dB]
H	1673.0	-59.7	-54.0	1.1	5.9	-49.2	-13.0	36.2
H	2509.5	-59.4	-54.6	1.3	6.0	-49.9	-13.0	36.9

(Channel: 20635)

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBi]	Result [dBm]	Limit [dBm]	Margin [dB]
H	1695.0	-59.9	-53.9	1.1	5.7	-49.3	-13.0	36.3
H	2542.5	-59.3	-54.0	1.3	6.0	-49.4	-13.0	36.4

**[LTE Band V]
64QAM, BW 3MHz
(Channel: 20415)**

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBi]	Result [dBm]	Limit [dBm]	Margin [dB]
H	1651.0	-59.6	-53.6	1.1	6.1	-48.5	-13.0	35.5
H	2476.5	-59.5	-54.0	1.3	5.7	-49.6	-13.0	36.6

(Channel: 20525)

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBi]	Result [dBm]	Limit [dBm]	Margin [dB]
H	1673.0	-59.8	-53.8	1.1	5.9	-49.0	-13.0	36.0
H	2509.5	-59.8	-54.3	1.3	6.0	-49.6	-13.0	36.6

(Channel: 20635)

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBi]	Result [dBm]	Limit [dBm]	Margin [dB]
H	1695.0	-59.4	-53.4	1.1	5.7	-48.8	-13.0	35.8
H	2542.5	-60.0	-54.6	1.3	6.0	-50.0	-13.0	37.0

**[LTE Band V]
QPSK, BW 5MHz
(Channel: 20425)**

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBi]	Result [dBm]	Limit [dBm]	Margin [dB]
H	1653.0	-59.5	-53.5	1.1	6.1	-48.5	-13.0	35.5
H	2479.5	-59.2	-53.7	1.3	5.7	-49.3	-13.0	36.3

(Channel: 20525)

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBi]	Result [dBm]	Limit [dBm]	Margin [dB]
H	1673.0	-59.2	-53.2	1.1	5.9	-48.4	-13.0	35.4
H	2509.5	-59.2	-53.7	1.3	6.0	-49.0	-13.0	36.0

(Channel: 20625)

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBi]	Result [dBm]	Limit [dBm]	Margin [dB]
H	1693.0	-59.4	-53.4	1.1	5.7	-48.8	-13.0	35.8
H	2539.5	-59.3	-54.0	1.3	6.0	-49.3	-13.0	36.3

**[LTE Band V]
16QAM, BW 5MHz
(Channel: 20425)**

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBi]	Result [dBm]	Limit [dBm]	Margin [dB]
H	1653.0	-59.7	-53.7	1.1	6.1	-48.7	-13.0	35.7
H	2479.5	-59.4	-53.9	1.3	5.7	-49.5	-13.0	36.5

(Channel: 20525)

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBi]	Result [dBm]	Limit [dBm]	Margin [dB]
H	1673.0	-59.4	-53.4	1.1	5.9	-48.6	-13.0	35.6
H	2509.5	-59.6	-54.1	1.3	6.0	-49.4	-13.0	36.4

(Channel: 20625)

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBi]	Result [dBm]	Limit [dBm]	Margin [dB]
H	1693.0	-59.6	-53.6	1.1	5.7	-49.0	-13.0	36.0
H	2539.5	-59.5	-54.2	1.3	6.0	-49.5	-13.0	36.5

**[LTE Band V]
64QAM, BW 5MHz
(Channel: 20425)**

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBi]	Result [dBm]	Limit [dBm]	Margin [dB]
H	1653.0	-59.8	-53.8	1.1	6.1	-48.8	-13.0	35.8
H	2479.5	-59.7	-54.2	1.3	5.7	-49.8	-13.0	36.8

(Channel: 20525)

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBi]	Result [dBm]	Limit [dBm]	Margin [dB]
H	1673.0	-59.7	-53.7	1.1	5.9	-48.9	-13.0	35.9
H	2509.5	-59.9	-54.4	1.3	6.0	-49.7	-13.0	36.7

(Channel: 20625)

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBi]	Result [dBm]	Limit [dBm]	Margin [dB]
H	1693.0	-59.8	-53.8	1.1	5.7	-49.2	-13.0	36.2
H	2539.5	-59.7	-54.4	1.3	6.0	-49.7	-13.0	36.7

**[LTE Band V]
QPSK, BW 10MHz
(Channel: 20450)**

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBi]	Result [dBm]	Limit [dBm]	Margin [dB]
H	1658.0	-59.5	-53.5	1.1	6.1	-48.5	-13.0	35.5
H	2487.0	-59.4	-53.9	1.3	5.8	-49.4	-13.0	36.4

(Channel: 20525)

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBi]	Result [dBm]	Limit [dBm]	Margin [dB]
H	1673.0	-59.4	-53.4	1.1	5.9	-48.6	-13.0	35.6
H	2509.5	-59.5	-54.0	1.3	6.0	-49.3	-13.0	36.3

(Channel: 20600)

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBi]	Result [dBm]	Limit [dBm]	Margin [dB]
H	1688.0	-59.4	-53.4	1.1	5.7	-48.7	-13.0	35.7
H	2532.0	-59.6	-53.3	1.3	6.0	-48.6	-13.0	35.6

**[LTE Band V]
16QAM, BW 10MHz
(Channel: 20450)**

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBi]	Result [dBm]	Limit [dBm]	Margin [dB]
H	1658.0	-59.7	-53.7	1.1	6.1	-48.7	-13.0	35.7
H	2487.0	-59.6	-54.1	1.3	5.8	-49.6	-13.0	36.6

(Channel: 20525)

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBi]	Result [dBm]	Limit [dBm]	Margin [dB]
H	1673.0	-59.7	-53.7	1.1	5.9	-48.9	-13.0	35.9
H	2509.5	-59.7	-54.2	1.3	6.0	-49.5	-13.0	36.5

(Channel: 20600)

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBi]	Result [dBm]	Limit [dBm]	Margin [dB]
H	1688.0	-59.6	-53.6	1.1	5.7	-48.9	-13.0	35.9
H	2532.0	-59.8	-54.5	1.3	6.0	-49.8	-13.0	36.8

**[LTE Band V]
64QAM, BW 10MHz
(Channel: 20450)**

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBi]	Result [dBm]	Limit [dBm]	Margin [dB]
H	1658.0	-59.8	-53.8	1.1	6.1	-48.8	-13.0	35.8
H	2487.0	-59.7	-54.2	1.3	5.8	-49.7	-13.0	36.7

(Channel: 20525)

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBi]	Result [dBm]	Limit [dBm]	Margin [dB]
H	1673.0	-59.8	-53.8	1.1	5.9	-49.0	-13.0	36.0
H	2509.5	-59.8	-54.3	1.3	6.0	-49.6	-13.0	36.6

(Channel: 20600)

H/V	Frequency [MHz]	S.A Reading [dBm]	Ant. Input [dBm]	Cable loss [dB]	Ant.Gain [dBi]	Result [dBm]	Limit [dBm]	Margin [dB]
H	1688.0	-59.8	-53.8	1.1	5.7	-49.1	-13.0	36.1
H	2532.0	-59.9	-54.6	1.3	6.0	-49.9	-13.0	36.9

All other emissions measured were greater than 20dB below the specification limit.


4.5 Frequency Stability

4.5.1 Measurement procedure

[FCC 22.355, 2.1055]

The EUT was placed on the inside of a constant temperature chamber as the temperature in the chamber was varied between -30°C and $+50^{\circ}\text{C}$. The temperature was incremented by 10°C intervals and the unit was allowed to stabilize at each measurement. The frequency drift was measured with the normal Temperature and voltage tolerance and it is presented as the ppm unit.

- Test configuration



4.5.2 Limit

± 2.5 ppm



4.5.3 Measurement result

Date : 25-April-2024
 Temperature : 20.7 [°C]
 Humidity : 48.3 [%]
 Test place : Shielded room No.4
 Test engineer : Kazunori Saito

Date : 26-April-2024
 Temperature : 18.6 [°C]
 Humidity : 45.4 [%]
 Test place : Shielded room No.4
 Test engineer : Kazunori Saito

**[GSM850]
 (Channel: 190)**

Limit: ±0.00025% = ±2.5ppm					
Power Supply	Temperature	Measurements Frequency	Frequency Tolerance	Limit	Result
[V]	[°C]	[Hz]	[ppm]	[ppm]	
3.87	25(Ref.)	836,599,978	0.00000	±2.5	Pass
	50	836,599,970	-0.00992	±2.5	Pass
	40	836,599,970	-0.01011	±2.5	Pass
	30	836,599,977	-0.00189	±2.5	Pass
	20	836,599,974	-0.00436	±2.5	Pass
	10	836,599,976	-0.00194	±2.5	Pass
	0	836,599,980	0.00204	±2.5	Pass
	-10	836,599,982	0.00502	±2.5	Pass
	-20	836,599,987	0.01057	±2.5	Pass
	-30	836,599,984	0.00672	±2.5	Pass
3.48	25	836,599,977	-0.00109	±2.5	Pass
4.26	25	836,599,980	0.00251	±2.5	Pass

**[WCDMA Band V]
 (Channel: 4183)**

Limit: ±0.00025% = ±2.5ppm					
Power Supply	Temperature	Measurements Frequency	Frequency Tolerance	Limit	Result
[V]	[°C]	[Hz]	[ppm]	[ppm]	
3.87	25(Ref.)	836,599,993	0.00000	±2.5	Pass
	50	836,599,993	0.00008	±2.5	Pass
	40	836,599,991	-0.00245	±2.5	Pass
	30	836,599,996	0.00378	±2.5	Pass
	20	836,599,993	0.00006	±2.5	Pass
	10	836,600,004	0.01265	±2.5	Pass
	0	836,600,003	0.01174	±2.5	Pass
	-10	836,600,003	0.01142	±2.5	Pass
	-20	836,600,006	0.01513	±2.5	Pass
	-30	836,600,005	0.01455	±2.5	Pass
3.48	25	836,599,993	0.00022	±2.5	Pass
4.26	25	836,599,994	0.00063	±2.5	Pass

Calculation:

$$\text{Frequency Tolerance (ppm)} = \frac{\text{Measurements Frequency (Hz)} - \text{Reference Frequency (Hz)}}{\text{Reference Frequency (Hz)}} \times 1000000$$

**[LTE Band V]
QPSK, BW 10MHz, RB 50-0
(Channel: 20525)**

Limit: $\pm 0.00025\% = \pm 2.5\text{ppm}$					
Power Supply	Temperature	Measurements Frequency	Frequency Tolerance	Limit	Result
[V]	[°C]	[Hz]	[ppm]	[ppm]	
3.87	25(Ref.)	836,499,991	0.00000	± 2.5	Pass
	50	836,499,991	-0.00042	± 2.5	Pass
	40	836,499,990	-0.00105	± 2.5	Pass
	30	836,499,993	0.00208	± 2.5	Pass
	20	836,499,992	0.00141	± 2.5	Pass
	10	836,499,988	-0.00387	± 2.5	Pass
	0	836,499,982	-0.01026	± 2.5	Pass
	-10	836,499,986	-0.00612	± 2.5	Pass
	-20	836,499,983	-0.00892	± 2.5	Pass
	-30	836,499,988	-0.00408	± 2.5	Pass
3.48	25	836,499,993	0.00213	± 2.5	Pass
4.26	25	836,499,993	0.00218	± 2.5	Pass





Calculation:

Frequency Tolerance (ppm) = Measurements Frequency (Hz) – Reference Frequency (Hz) / Reference Frequency (Hz) x 1000000

5 Measurement Uncertainty

Expanded uncertainties stated are calculated with a coverage Factor k=2.
 Please note that these results are not taken into account when measurement uncertainty considerations contained in ETSI TR 100 028 Parts 1 and 2 determining compliance or non-compliance with test result.

Test item	Measurement uncertainty
Conducted emission, AMN (9 kHz – 150 kHz)	±3.7 dB
Conducted emission, AMN (150 kHz – 30 MHz)	±3.3 dB
Radiated emission (9kHz – 30 MHz)	±3.8 dB
Radiated emission (30 MHz – 1000 MHz)	±5.4 dB
Radiated emission (1 GHz – 6 GHz)	±4.6 dB
Radiated emission (6 GHz – 18 GHz)	±4.7 dB
Radiated emission (18 GHz – 40 GHz)	±6.3 dB
Radio Frequency	±1.3 * 10 ⁻⁸
RF power, conducted	±0.7 dB
Adjacent channel power	±1.5 dB
Temperature	±0.6 °C
Humidity	±1.2 %
Voltage (DC)	±0.4 %
Voltage (AC, <10kHz)	±0.2 %

Judge	Measured value and standard limit value
PASS	<p>Case1</p>  <p>Even if it takes uncertainty into consideration, a standard limit value is fulfilled.</p>
	<p>Case2</p>  <p>Although measured value is in a standard limit value, a limit value won't be fulfilled if uncertainty is taken into consideration.</p>
FAIL	<p>Case3</p>  <p>Although measured value exceeds a standard limit value, a limit value will be fulfilled if uncertainty is taken into consideration.</p>
	<p>Case4</p>  <p>Even if it takes uncertainty into consideration, a standard limit value isn't fulfilled.</p>

6 Laboratory Information

Testing was performed and the report was issued at:

TÜV SÜD Japan Ltd. Yonezawa Testing Center

Address: 5-4149-7 Hachimanpara, Yonezawa-shi, Yamagata, 992-1128 Japan
Phone: +81-238-28-2881

Accreditation and Registration

A2LA

Certificate #3686.03

VLAC

Accreditation No.: VLAC-013

BSMI

Laboratory Code: SL2-IN-E-6018, SL2-A1-E-6018

Innovation, Science and Economic Development Canada

ISED#: 4224A

VCCI Council

Registration number: A-0166

Appendix A. Test Equipment

Antenna port conducted test

Equipment	Company	Model No.	Serial No.	Cal. Due	Cal. Date
Spectrum analyzer	Agilent Technologies	E4440A	US44302655	31-Oct-2024	06-Oct-2023
Attenuator	Weinschel	56-10	J4993	31-Dec-2024	19-Dec-2023
Microwave cable	Junkosha Inc.	MWX221/1m	N/A(S400)	31-Mar-2025	7-Mar-2024
Power divider	Keysight	11636B	MY51359874	30-Sep-2024	20-Sep-2023
Wideband Radio Frequency Tester	ROHDE&SCHWARZ	CMW500	126079	31-Aug-2024	31-Aug-2023
Wideband Radio Frequency Tester	ROHDE&SCHWARZ	CMW500	116338	30-Sep-2024	21-Sep-2024
Temperature and humidity chamber	ESPEC	PL1KP	14007261	30-Jun-2024	30-Jun-2023

Radiated emission

Equipment	Company	Model No.	Serial No.	Cal. Due	Cal. Date
EMI Receiver	ROHDE&SCHWARZ	ESW44	103171	31-Oct-2024	19-Oct-2023
Preamplifier	SONOMA	310	372170	30-Sep-2024	21-Sep-2023
Biconical antenna	Schwarzbeck	VHBB9124/BBA9106	1344	30-Jun-2024	19-Jun-2023
Log periodic antenna	Schwarzbeck	VUSLP9111B	346	31-Dec-2024	22-Dec-2023
Attenuator	TOYO Connector	NA-PJ-6/6dB	N/A(S541)	30-Sep-2024	21-Sep-2023
Attenuator	TAMAGAWA.ELEC	CFA-10/3dB	N/A(S503)	31-Jul-2024	20-Jul-2023
Preamplifier	TSJ	MLA-100M18-B02-40	1929118	31-Dec-2024	19-Dec-2023
Attenuator	AEROFLEX	26A-10	081217-08	31-Dec-2024	19-Dec-2023
Double ridged guide antenna	ETS LINDGREN	3117	00052315	30-Jun-2024	22-Jun-2023
Attenuator	HUBER+SUHNER	6803.17.B	N/A(2340)	31-Dec-2024	20-Dec-2023
Double ridged guide antenna	A.H.Systems Inc.	SAS-574	469	31-Aug-2024	8-Aug-2023
Preamplifier	TSJ	MLA-1840-B03-35	1240332	31-Aug-2024	8-Aug-2023
Notch Filter	Micro-Tronics	BRM50706	003	31-Jul-2024	19-Jul-2023
Signal generator	ROHDE&SCHWARZ	SMB100A	177525	31-Dec-2024	20-Dec-2023
RF power amplifier	R&K	CGA020M602-2633R	B40240	30-Jun-2024	21-Jun-2023
Attenuator	Qualwave Inc.	QFA2620-26.5-20-S	22295089	30-Sep-2024	20-Sep-2023
Microwave cable	HUBER+SUHNER	SUCOFLEX102/2m	31648	31-Mar-2025	7-Mar-2024
Dipole antenna	Schwarzbeck	VHAP	1021	31-Jul-2024	06-Jul-2023
Dipole antenna	Schwarzbeck	UHAP	993	31-Jul-2024	06-Jul-2023
Double ridged guide antenna	ETS LINDGREN	3117	00218815	31-Dec-2024	7-Dec-2023
Wideband Radio Frequency Tester	ROHDE&SCHWARZ	CMW500	126079	31-Aug-2024	31-Aug-2023
Wideband Radio Frequency Tester	ROHDE&SCHWARZ	CMW500	116338	30-Sep-2024	21-Sep-2024
Microwave cable	HUBER+SUHNER	SUCOFLEX104/9m	800690/4	31-Oct-2024	20-Oct-2023
		SUCOFLEX104/1m	my24610/4	31-Dec-2024	20-Dec-2023
		SUCOFLEX104/9m	2001099/4	31-Dec-2024	20-Dec-2023
		SUCOFLEX104/1m	MY32976/4	31-Dec-2024	20-Dec-2023
		SUCOFLEX104/2m	SN MY28404/4	31-Dec-2024	20-Dec-2023
		SUCOFLEX104/7m	41625/6	31-Dec-2024	21-Dec-2023
Software	TOYO Technica	ES10/RE-AJ	Ver.2023.01.001	N/A	N/A
Absorber	RIKEN	PPF30	N/A	N/A	N/A
3m Semi an-echoic Chamber	TOKIN	N/A	N/A(9002-NSA)	31-May-2024	28-May-2023
3m Semi an-echoic Chamber	TOKIN	N/A	N/A(9002-SVSWR)	31-May-2024	29-May-2023

*: The calibrations of the above equipment are traceable to NIST or equivalent standards of the reference organizations.