

## RF Exposure Report

**Report No.:** SABCKS-WTW-P20110426-1

**FCC ID:** K7S-03685

**Test Model:** MX8500

**Series Model:** MX85EC, MX85WH, MX85MS

**Received Date:** Nov. 12, 2020

**Test Date:** Dec. 08, 2020

**Issued Date:** Mar. 02, 2021

**Applicant:** Belkin International, Inc.

**Address:** 12045 East Waterfront Drive, Playa Vista, CA 90094

**Issued By:** Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch  
Hsin Chu Laboratory

**Lab Address:** E-2, No.1, Li Hsin 1st Road, Hsinchu Science Park, Hsinchu City 300,  
Taiwan

**Test Location:** E-2, No.1, Li Hsin 1st Road, Hsinchu Science Park, Hsinchu City 300,  
Taiwan

**FCC Registration /  
Designation Number:** 723255 / TW2022

This report is for your exclusive use. Any copying or replication of this report to or for any other person or entity, or use of our name or trademark, is permitted only with our prior written permission. This report sets forth our findings solely with respect to the test samples identified herein. The results set forth in this report are not indicative or representative of the quality or characteristics of the lot from which a test sample was taken or any similar or identical product unless specifically and expressly noted. Our report includes all of the tests requested by you and the results thereof based upon the information that you provided to us. You have 60 days from date of issuance of this report to notify us of any material error or omission caused by our negligence, provided, however, that such notice shall be in writing and shall specifically address the issue you wish to raise. A failure to raise such issue within the prescribed time shall constitute your unqualified acceptance of the completeness of this report, the tests conducted and the correctness of the report contents. Unless specific mention, the uncertainty of measurement has been explicitly taken into account to declare the compliance or non-compliance to the specification.

## Table of Contents

<b>Release Control Record</b> .....	<b>3</b>
<b>1 Certificate of Conformity</b> .....	<b>4</b>
<b>2 RF Exposure</b> .....	<b>5</b>
2.1 Limits for Maximum Permissible Exposure (MPE) .....	5
2.2 MPE Calculation Formula .....	5
2.3 Classification .....	5
2.4 Antenna Gain .....	6
2.5 Calculation Result .....	8

### Release Control Record

Issue No.	Description	Date Issued
SABCKS-WTW-P20110426-1	Original release.	Mar. 02, 2021

## 1 Certificate of Conformity

**Product:** Linksys Tri-Band 802.11ax Wireless Router

**Brand:** Linksys

**Test Model:** MX8500

**Series Model:** MX85EC, MX85WH, MX85MS

**Sample Status:** Engineering sample

**Applicant:** Belkin International, Inc.

**Test Date:** Dec. 08, 2020

**Standards:** FCC Part 2 (Section 2.1091)

IEEE C95.3 -2002

**References Test Guidance:** KDB 447498 D01 General RF Exposure Guidance v06

The above equipment has been tested by **Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch**, and found compliance with the requirement of the above standards. The test record, data evaluation & Equipment Under Test (EUT) configurations represented herein are true and accurate accounts of the measurements of the sample's EMC characteristics under the conditions specified in this report.

**Prepared by :**  , **Date:** Mar. 02, 2021  
Claire Kuan / Specialist

**Approved by :**  , **Date:** Mar. 02, 2021  
Clark Lin / Technical Manager

## 2 RF Exposure

### 2.1 Limits for Maximum Permissible Exposure (MPE)

Frequency Range (MHz)	Electric Field Strength (V/m)	Magnetic Field Strength (A/m)	Power Density (mW/cm <sup>2</sup> )	Average Time (minutes)
Limits For General Population / Uncontrolled Exposure				
0.3-1.34	614	1.63	(100)*	30
1.34-30	824/f	2.19/f	(180/f <sup>2</sup> )*	30
30-300	27.5	0.073	0.2	30
300-1500	...	...	f/1500	30
1500-100,000	...	...	1.0	30

f = Frequency in MHz ; \*Plane-wave equivalent power density

### 2.2 MPE Calculation Formula

$$Pd = (Pout * G) / (4 * \pi * r^2)$$

where

Pd = power density in mW/cm<sup>2</sup>

Pout = output power to antenna in mW

G = gain of antenna in linear scale

Pi = 3.1416

R = distance between observation point and center of the radiator in cm

### 2.3 Classification

The antenna of this product, under normal use condition, is at least 30 cm away from the body of the user.

So, this device is classified as **Mobile Device**.

## 2.4 Antenna Gain

### For WLAN(2.4 GHz)

Antenna Type	Dipole on PCB
Antenna Connector	i-pex (MHF)
Antenna No.	Gain (dBi)
	2.4~2.4835GHz
Ant1	2.5
Ant2	3.1
Ant3	3.1
Ant4	2.8

The following antenna allocation table was provided to the EUT.

2G Antenna port		2G Antenna port		TX Function	
Degree -45°	2GA1	Degree +45°	2GB1	MIMO	Correlated
Degree -45°	2GA2	Degree +45°	2GB2	MIMO	

### For WLAN(5GHz)

Antenna Type	Dipole on PCB			
Antenna Connector	i-pex (MHF)			
Antenna No.	Gain (dBi)			
	5150~5250MHz	5250~5350MHz	5500~5720MHz	5745~5825MHz
Ant1	4.9	<b>5.7</b>	<b>5.2</b>	5.4
Ant2	5.1	5.1	4.6	4.8
Ant3	4.1	4.8	4.4	5.7
Ant4	3.0	4.1	4.6	5.8

The following antenna allocation table was provided to the EUT.

5G Antenna port		5G Antenna port		TX Function	
Degree -45°	5GC	Degree +45°	5GD	MIMO	Correlated
Degree -45°	5GA	Degree +45°	5GB	MIMO	

### For WLAN(6GHz)

Antenna Type	Dipole on PCB			
Antenna Connector	i-pex (MHF)			
Antenna No.	Gain (dBi)			
	5105MHz~6425MHz	6425MHz~6525MHz	6525MHz~6875MHz	6875MHz~7125MHz
Ant1	5.3	4.3	3.6	4.1
Ant2	4.8	4.1	3.4	4.4
Ant3	5.1	5.1	4.5	4.8
Ant4	3.2	4.5	5.4	5.9

The following antenna allocation table was provided to the EUT.

6G Antenna port		6G Antenna port		TX Function	
Degree -45°	6GD	Degree +45°	6GC	MIMO	Correlated
Degree -45°	6GB	Degree +45°	6GA	MIMO	

**For BT-LE**

Frequency Range (GHz)	Antenna Gain (dBi)	Antenna Type	Antenna Connector
2.4~2.4835	2	PCB	i-pex(MHF)

**Note:**

All antennas are dipole type. Thus antennas are all used the same type, the difference is only in the placement direction. According this condition, 2GA1 / 2GA2 are cross-polarization, 2GB1 / 2GB2 are cross-polarization, 5GA / 5GC are cross-polarization, 5GB / 5GD are cross-polarization, 6GA / 6GC are cross-polarization, 6GB / 6GD are cross-polarization.

\*The above Antenna information is declared by manufacturer and for more detailed features description, please refer to the manufacturer's specifications, the laboratory shall not be held responsible.

## 2.5 Calculation Result

All test data (Except WLAN 5GHz U-NII-2A & WLAN 5GHz U-NII-2C) was copied from the original test report (Report No.: SABCKS-WTW-P20110426)

Operation Mode	Max Power (mW)	Antenna Gain (dBi)	Distance (cm)	Power Density (mW/cm <sup>2</sup> )	Limit (mW/cm <sup>2</sup> )	Pass / Fail
WLAN 2.4GHz	993.158	5.96	30	0.34639	1	Pass
WLAN 5GHz U-NII-1	653.703	8.01	30	0.36553	1	Pass
WLAN 5GHz U-NII-2A	247.816	8.42	30	0.15229	1	Pass
WLAN 5GHz U-NII-2C	157.837	7.92	30	0.08645	1	Pass
WLAN 5GHz U-NII-3	689.979	8.76	30	0.45855	1	Pass
BT-LE	9.354	2	30	0.00131	1	Pass
Operation Mode	Max. EIRP (mW)		Distance (cm)	Power Density (mW/cm <sup>2</sup> )	Limit (mW/cm <sup>2</sup> )	Pass / Fail
WLAN 6GHz U-NII-5	509.33		30	0.04508	1	Pass
WLAN 6GHz U-NII-6	249.459		30	0.02204	1	Pass
WLAN 6GHz U-NII-7	518.8		30	0.04589	1	Pass
WLAN 6GHz U-NII-8	522.396		30	0.04619	1	Pass

- Note: 1. Determining compliance based on the results of the compliance measurement, not taking into account measurement instrumentation uncertainty.
- For WLAN 2.4GHz\_802.11b: Directional gain =  $10 \log[(10^{G_{1/20}} + 10^{G_{3/20}})^2 / 2] = 5.96\text{dBi}$
  - For WLAN 2.4GHz\_802.11g: Directional gain =  $10 \log[(10^{G_{2/20}} + 10^{G_{3/20}})^2 / 2] = 5.96\text{dBi}$
  - For WLAN 2.4GHz\_802.11n (HT20), VHT20, 802.11ax (HE20): Directional gain =  $10 \log[(10^{G_{2/20}} + 10^{G_{3/20}})^2 / 2] = 5.96\text{dBi}$
  - For WLAN 2.4GHz\_802.11n (HT40), VHT40, 802.11ax (HE40): Directional gain =  $10 \log[(10^{G_{2/20}} + 10^{G_{3/20}})^2 / 2] = 5.96\text{dBi}$
  - For WLAN 5GHz U-NII-1: Directional gain =  $10 \log[(10^{G_{0/20}} + 10^{G_{1/20}})^2 / 2] = 8.01\text{dBi}$
  - For WLAN 5GHz U-NII-2A: Directional gain =  $10 \log[(10^{G_{0/20}} + 10^{G_{1/20}})^2 / 2] = 8.42\text{dBi}$
  - For WLAN 5GHz U-NII-2C: Directional gain =  $10 \log[(10^{G_{0/20}} + 10^{G_{1/20}})^2 / 2] = 7.92\text{dBi}$
  - For WLAN 5GHz U-NII-3: Directional gain =  $10 \log[(10^{G_{2/20}} + 10^{G_{3/20}})^2 / 2] = 8.76\text{dBi}$
  - For WLAN 6GHz U-NII-5: Directional gain =  $10 \log[(10^{G_{0/20}} + 10^{G_{1/20}})^2 / 2] = 8.06\text{dBi}$
  - For WLAN 6GHz U-NII-6: Directional gain =  $10 \log[(10^{G_{2/20}} + 10^{G_{3/20}})^2 / 2] = 7.82\text{dBi}$
  - For WLAN 6GHz U-NII-7: Directional gain =  $10 \log[(10^{G_{2/20}} + 10^{G_{3/20}})^2 / 2] = 7.97\text{dBi}$
  - For WLAN 6GHz U-NII-8: Directional gain =  $10 \log[(10^{G_{2/20}} + 10^{G_{3/20}})^2 / 2] = 8.38\text{dBi}$

**Conclusion:**

The formula of calculated the MPE is:

$CPD1 / LPD1 + CPD2 / LPD2 + \dots \text{etc.} < 1$

CPD = Calculation power density

LPD = Limit of power density

WLAN 2.4GHz + WLAN 5GHz + BT-LE + WLAN 6GHz =

$0.34639 / 1 + 0.45855 / 1 + 0.000131 / 1 + 0.4619 / 1 = 0.85244$

**Therefore the maximum calculations of above situations are less than the “1” limit.**

--- END ---