

MANUAL

Programming your transmitter to the receiver

After the receiver and transmitter are installed, the receiver must be programmed to receive the transmitter frequency

1. Check that a red light is visible on the front of the receiver indicating power to the receiver.
2. Connect the battery cables on the motorcycle, positive cable first.
3. Press and hold the Set button on the receiver. The LED blinks continuously while the Set button is pressed.
4. Set the motorcycle ignition switch to ACC. Switch the headlamp-beam switch using one of the these sequences
 - Starting from Low beam, switch High, then Low
 - Starting from High beam, switch Low, then High

When the receiver receives a signal from the transmitter, the LED on the transmitter turns off.

5. Release the Set button on the receiver.

WARNING

Check for proper lighting and switch operation before riding motorcycle. Visibility is a major concern for motorcyclists. Failure to have proper lighting and signal lamp operation could result in death or serious injury.

Clear all obstructions away from between the transmitter and receiver before testing the operation of the garage door opener.

6. Test the garage door opener, high-beam, and low-beam headlamp operation

When the transmitter is activated by toggling the headlamp switch, the red LED on the transmitter illuminates for one second to indicate that the transmitter is functioning correctly

7. Set the motorcycle ignition switch to OFF
8. Install all parts removed for transmitter installation.

Installation the transmitter:

To protect against shock and accidental start-up of vehicle, disconnect the battery cables before proceeding. Inadequate safety precautions could result in death or serious injury.

Warning : Changes or modifications to this unit not expressly approved by the party responsible of compliance could void the user's authority to operate the equipment.

NOTE. This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed

**CAPITAL PROSPECT LTD.**

10

and used in accordance with the instructions, may cause harmful interference to radio communications.

However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.