

RF Exposure Report

Report No.: SA180904C01 R1

FCC ID: L6AITC100-1

Test Model: ITC100-1

Series Model: ITC100-2

Received Date: Sep. 04, 2018

Date of Evaluation: Oct. 12, 2018

Issued Date: Oct. 25, 2018

Applicant: BlackBerry Limited

Address: 2200 University Avenue East Waterloo, Ontario N2K 0A7 Canada

Issued By: Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch

Lab Address: No. 47-2, 14th Ling, Chia Pau Vil., Lin Kou Dist., New Taipei City, Taiwan, R.O.C.

Test Location: No. 19, Hwa Ya 2nd Rd, Wen Hwa Vil, Kwei Shan Dist., Taoyuan City 33383, Taiwan (R.O.C)

**FCC Registration /
Designation Number:** 788550 / TW0003



This report is for your exclusive use. Any copying or replication of this report to or for any other person or entity, or use of our name or trademark, is permitted only with our prior written permission. This report sets forth our findings solely with respect to the test samples identified herein. The results set forth in this report are not indicative or representative of the quality or characteristics of the lot from which a test sample was taken or any similar or identical product unless specifically and expressly noted. Our report includes all of the tests requested by you and the results thereof based upon the information that you provided to us. You have 60 days from date of issuance of this report to notify us of any material error or omission caused by our negligence, provided, however, that such notice shall be in writing and shall specifically address the issue you wish to raise. A failure to raise such issue within the prescribed time shall constitute your unqualified acceptance of the completeness of this report, the tests conducted and the correctness of the report contents. Unless specifically mentioned, the uncertainty of measurement has been explicitly taken into account to declare the compliance or non-compliance to the specification. The report must not be used by the client to claim product certification, approval, or endorsement by TAF or any government agencies.

Table of Contents

Release Control Record	3
1 Certificate of Conformity	4
2 RF Exposure	5
2.1 Limits for Maximum Permissible Exposure (MPE)	5
2.2 MPE Calculation Formula.....	5
2.3 Classification.....	5
2.4 Calculation Result of Maximum Conducted Power	6

Release Control Record

Issue No.	Description	Date Issued
SA180904C01	Original Release	Oct. 16, 2018
SA180904C01 R1	Revise maximum power	Oct. 25, 2018

1 Certificate of Conformity

Product: Asset Tracker

Brand: BlackBerry

Test Model: ITC100-1

Series Model: ITC100-2

Sample Status: Identical Prototype

Applicant: BlackBerry Limited

Date of Evaluation: Oct. 12, 2018


Standards: FCC Part 2 (Section 2.1091)

KDB 447498 D01 General RF Exposure Guidance v06

IEEE C95.1-1992

The above equipment has been tested by **Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch**, and found compliance with the requirement of the above standards. The test record, data evaluation & Equipment Under Test (EUT) configurations represented herein are true and accurate accounts of the measurements of the sample's RF characteristics under the conditions specified in this report.

Prepared by :  , **Date:** Oct. 25, 2018
Rona Chen / Specialist

Approved by :  , **Date:** Oct. 25, 2018
Dylan Chiou / Project Engineer

2 RF Exposure

2.1 Limits for Maximum Permissible Exposure (MPE)

Frequency Range (MHz)	Electric Field Strength (V/m)	Magnetic Field Strength (A/m)	Power Density (mW/cm ²)	Average Time (minutes)
Limits For General Population / Uncontrolled Exposure				
0.3-1.34	614	1.63	(100)*	30
1.34-30	824/f	2.19/f	(180/f ²)*	30
30-300	27.5	0.073	0.2	30
300-1500	f/1500	30
1500-100,000	1.0	30

f = Frequency in MHz ; *Plane-wave equivalent power density

2.2 MPE Calculation Formula

$$P_d = (P_{out} * G) / (4 * \pi * r^2)$$

where

P_d = power density in mW/cm²

P_{out} = output power to antenna in mW

G = gain of antenna in linear scale

π = 3.1416

R = distance between observation point and center of the radiator in cm

2.3 Classification

The antenna of this product, under normal use condition, is at least 20 cm away from the body of the user.

So, this device is classified as **Mobile Device**.

2.4 General Description

Brand	Model	Difference
BlackBerry	ITC100-1	Supports SRD function
	ITC100-2	Disable SRD function via software

2.5 Calculation Result of Maximum Conducted Power

Band	Frequency Band (MHz)	Max Power (dBm)	Antenna Gain (dBi)	Distance (cm)	Power Density (mW/cm ²)	Limit (mW/cm ²)
GSM850	824-849	33.0	-3.1	20	0.194	0.549
PCS1900	1850-1910	30.0	-2.9	20	0.102	1.0
WCDMA II	1850-1910	23.5	-2.9	20	0.023	1.0
WCDMA V	824-849	24.5	-3.1	20	0.027	0.549
LTE 2	1850-1910	23.0	-2.9	20	0.020	1.0
LTE 4	1710-1755	22.0	-3.2	20	0.015	1.0
LTE 5	824-849	22.5	-3.1	20	0.017	0.549
LTE 12	699-716	23.0	-6.3	20	0.009	0.466
SRD	902-928	18.33	-3.6	20	0.006	0.601

Note:

1. Above used Max. Output Power is Max. Tune-up Power.
2. Only SRD use Maximum Conducted Power as Tunp-up Power.

Conclusion:

The formula of calculated the MPE is:

$CPD1 / LPD1 + CPD2 / LPD2 + \dots \text{etc.} < 1$

CPD = Calculation power density

LPD = Limit of power density

$WWAN + SRD = 0.194/0.549 + 0.006/0.601 = 0.363$

Therefore the maximum calculations of above situations are less than the "1" limit.

--- END ---