# ENGINEERING TEST REPORT

## BlackBerry Wireless Handheld Model No.: R1900G-1-4 FCC ID: L6AR1900G-1-4

Applicant: Research In Motion Limited 295 Phillip Street Waterloo, Ontario

Tested in Accordance With

Canada, N2L 3W8

## Federal Communications Commission (FCC) PERSONAL COMMUNICATIONS SERVICES CFR 47, PARTS 2 and 24 (Subpart E)

UltraTech's File No.: RIM15-FTX

This Test report is Issued under the Authority of Tri M. Luu, Professional Engineer, Vice President of Engineering UltraTech Group of Labs

Date: July 24, 2001

Report Prepared by: Tri Luu, P.Eng.

Tested by: Mr. Tri Luu, P.Eng.

Issued Date: July 25, 2001

Test Dates: July 23, 2001

The results in this Test Report apply only to the sample(s) tested, and the sample tested is randomly selected.

## **UltraTech**

3000 Bristol Circle, Oakville, Ontario, Canada, L6H 6G4Telephone (905) 829-1570Facsimile (905) 829-8050

Website: www.ultratech-labs.com Email: vhk.ultratech@sympatico.ca



## TABLE OF CONTENTS

| EXHI        | BIT 1.      | INTRODUCTION   | 1      |
|-------------|-------------|--|--------|
| 1.1.        | SCO         | )PE  | 1      |
| 1.2.        | NO          | RMATIVE REFERENCES   | 1      |
| EXHI        | BIT 2.      | PERFORMANCE ASSESSMENT   | 2      |
| 2.1.        | CLII        | ENT INFORMATION  | 2      |
| 2.2.        | EQU         | IPMENT UNDER TEST (EUT) INFORMATION  | 2      |
| 2.3.        | EU          | T'S TECHNICAL SPECIFICATIONS   | 3      |
| 2.4.        | LIST        | OF EUT'S PORTS   |        |
| 2.5.<br>2.6 | MOI<br>A NO | DIFICATIONS INCORPORATED IN THE EUT FOR COMPLIANCE PURPOSES<br>YILLARY FOLIPMENT | 4<br>4 |
| EXHI        | BIT 3.      | EUT OPERATING CONDITIONS AND CONFIGURATIONS DURING TESTS                         | 5      |
| 3.1.        | CLII        | MATE TEST CONDITIONS   | 5      |
| 3.2.        | OPE         | RATIONAL TEST CONDITIONS & ARRANGEMENT FOR TEST SIGNALS                          | 5      |
| EXHI        | BIT 4.      | SUMMARY OF TEST RESULTS  | 6      |
| 4.1.        | LO          | CATION OF TESTS  | 6      |
| 4.2.        | API         | PLICABILITY & SUMMARY OF EMC EMISSION TEST RESULTS                               | 6      |
| EXHI        | BIT 5.      | MEASUREMENTS, EXAMINATIONS & TEST DATA FOR EMC EMISSIONS                         | 7      |
| 5.1.        | TES         | T PROCEDURES   | 7      |
| 5.2.        | MEA         | SUREMENT UNCERTAINTIES   | 7      |
| 5.3.        | MEA         | SUREMENT EQUIPMENT USED:   | 7      |
| 5.4.        | ESS         | ENTIAL/PRIMARY FUNCTIONS AS DECLARED BY THE MANUACTURER:                         | 7      |
| 5.5.        | EIR         | P @ FCC 2.1046 & 24.232  | 8<br>0 |
| 5           | 5.1.<br>5.2 | Limits   | 0<br>0 |
| 5           | 5.2.<br>5.3 | Test Fauinment I ist   |        |
| 5           | 5.5.<br>5.4 | Test Equipment List  |        |
| 5           | 5.5.4.1     | Test configurations # 1 through 7: Without Cradle and headset                    | 9      |
|             | 5.5.4.2     | Test configuration # 8: With Cradle and headset                                  |        |
| 5           | 5.5.        | Test Data  | 11     |
| EXHI        | BIT 6.      | MEASUREMENT UNCERTAINTY  | 13     |
| 6.1.        | RAD         | DIATED EMISSION MEASUREMENT UNCERTAINTY  | 13     |
| EXHI        | BIT 7.      | MEASUREMENT METHODS  | 14     |
| 7.1.        | EQU         | JIVALENT ISOTROPIC RADIATED POWER (EIRP) MEASUREMENTS                            | 14     |

#### ULTRATECH GROUP OF LABS 3000 Bristol Circle, Oakville, Ontario, Canada L6H 6G4

File #: RIM15-FTX July 24, 2001

Tel. #: 905-829-1570, Fax. #: 905-829-8050, Email: vhk.ultratech@sympatico.ca, Website: http://www.ultratech-labs.com

Assessed by ITI (UK) Competent Body, NVLAP (USA) Accreditation Body & ACA/AUSTEL (Australia), VCCI (Japan)

Recognized/Listed by FCC (USA)

Accredited by Industry Canada (Canada) under ACC-LAB (Europe/Canada MRA and APEC/Canada MRA)

## **EXHIBIT 1. INTRODUCTION**

## 1.1. SCOPE

| Reference:       | FCC Parts 2 and 24 (Subpart E): 1998   |
|------------------|--|
| Title            | Telecommunication - Code of Federal Regulations, CFR 47, Parts 2 & 24  |
| Purpose of Test: | EIRP Measurements for a PCS radio transmitter operating in the frequency band 1850 - 1910 MHz (Broadband PCS) with with diverse accessories.   |
| Test Procedures  | Radiated emissions measurements were conducted in accordance with American<br>National Standards Institute ANSI C63.4 - American National Standard for Methods<br>of Measurement of Radio-Noise Emissions from Low-Voltage Electrical and<br>Electronic Equipment in the Range of 9 kHz to 40 GHz. |

## **1.2. NORMATIVE REFERENCES**

| Publication               | Year         | Title   |
|---------------------------|--------------|---|
| FCC CFR<br>Parts 2 and 24 | 1998         | Code of Federal Regulations – Telecommunication   |
| ANSI C63.4                | 1992         | American National Standard for Methods of Measurement of Radio-Noise<br>Emissions from Low-Voltage Electrical and Electronic Equipment in the Range of 9<br>kHz to 40 GHz |
| CISPR 22 &<br>EN 55022    | 1997<br>1998 | Limits and Methods of Measurements of Radio Disturbance Characteristics of Information Technology Equipment   |
| CISPR 16-1                |              | Specification for Radio Disturbance and Immunity measuring apparatus and methods  |

#### ULTRATECH GROUP OF LABS 3000 Bristol Circle, Oakville, Ontario, Canada L6H 6G4

File #: RIM15-FTX July 24, 2001

Tel. #: 905-829-1570, Fax. #: 905-829-8050, Email: <u>vhk.ultratech@sympatico.ca</u>, Website: http://www.ultratech-labs.com

- Assessed by ITI (UK) Competent Body, NVLAP (USA) Accreditation Body & ACA/AUSTEL (Australia), VCCI (Japan)
- Accredited by Industry Canada (Canada) under ACC-LAB (Europe/Canada MRA and APEC/Canada MRA)

Recognized/Listed by FCC (USA)

## **EXHIBIT 2. PERFORMANCE ASSESSMENT**

## 2.1. CLIENT INFORMATION

| APPLICANT       |   |  |
|-----------------|---|--|
| Name:           | Research In Motion Limited  |  |
| Address:        | 295 Phillip Street<br>Waterloo, Ontario<br>Canada, N2L 3W8  |  |
| Contact Person: | <b>X Person:</b> Mr. Masud Attayi<br>Phone #: (519) 888-7465 x2442<br>Fax #: (519) 888-6906<br>Email Address: mattayi@rim.net |  |

| MANUFACTURER    |  |  |
|-----------------|--|--|
| Name:           | Research In Motion Limited   |  |
| Address:        | 295 Phillip Street<br>Waterloo, Ontario<br>Canada, N2L 3W8   |  |
| Contact Person: | Mr. Masud Attayi<br>Phone #: (519) 888-7465 x2442<br>Fax #: (519) 888-6906<br>Email Address: mattayi@rim.net |  |

## 2.2. EQUIPMENT UNDER TEST (EUT) INFORMATION

The following information (with the exception of the Date of Receipt) has been supplied by the applicant.

| Brand Name:                          | BlackBerry   |
|--------------------------------------|--|
| Product Name:                        | BlackBerry Wireless Handheld                               |
| Model Name or Number:                | R1900G-1-4   |
| Serial Number:                       | Pre-production sample                                      |
| Type of Equipment:                   | Personal Communications Services                           |
| External Power Supply:               | AC charging adaptor and synchronization cradle<br>supplied |
| Transmitting/Receiving Antenna Type: | Integral   |
| Primary User Functions of EUT:       | e-mail, personal digital assistant (PDA)                   |

#### ULTRATECH GROUP OF LABS 3000 Bristol Circle, Oakville, Ontario, Canada L6H 6G4

File #: RIM15-FTX July 24, 2001

Tel. #: 905-829-1570, Fax. #: 905-829-8050, Email: <u>vhk.ultratech@sympatico.ca</u>, Website: http://www.ultratech-labs.com

Assessed by ITI (UK) Competent Body, NVLAP (USA) Accreditation Body & ACA/AUSTEL (Australia), VCCI (Japan)

Recognized/Listed by FCC (USA)

Accredited by Industry Canada (Canada) under ACC-LAB (Europe/Canada MRA and APEC/Canada MRA)

## 2.3. EUT'S TECHNICAL SPECIFICATIONS

|                                   | TRANSMITTER  |
|-----------------------------------|--|
| Equipment Type:                   | Portable   |
| Intended Operating Environment:   | Residential  |
|                                   | <ul> <li>Commercial, light industry &amp; heavy industry</li> </ul>  |
| Power Supply Requirement:         | Internal rechargeable battery – required accessories supplied for<br>charging  |
| RF Output Power Rating:           | 1.38 Watts EIRP  |
| Duty Cycle:                       | PCS network – 1 slot in 8 slot frame – 12.5%   |
| <b>Operating Frequency Range:</b> | 1850 - 1910 MHz (Broadband PCS)  |
| RF Output Impedance:              | Not applicable – antenna is not removable  |
| Channel Spacing:                  | 200 kHz  |
| Occupied Bandwidth (99%):         | 250 kHz  |
| Emission Designation:             | 307KGXW  |
| Digital Oscillator Frequencies:   | 13 MHz   |
| Radio Oscillator Frequencies:     | 1048 MHz IF LO, 1719-1779 MHz variable oscillators   |
| Antenna Connector Type:           | Integral   |
| Antenna Description:              | Manufacturer: RIM<br>Type: Internal modified center fed folded dipole<br>Model: PCB-03092<br>Frequency Range: 1850 - 1990 MHz<br>In/Out Impedance: Not applicable – antenna in not removable |

## 2.4. LIST OF EUT'S PORTS

| Port<br>Number | EUT's Port Description | Number of<br>Identical Ports | Connector Type                | Cable Type<br>(Shielded/Non-shielded) |
|----------------|------------------------|------------------------------|-------------------------------|---------------------------------------|
| 1              | Serial I/O & DC        | 1                            | JAE PCB-to-cable<br>connector | None                                  |
| 2              | Audio                  | 1                            | 2.5mm audio plug              | None                                  |

#### <u>NOTES:</u>

- (1) **Ports of the EUT which in normal operation** were connected to ancillary equipment through interconnecting cables via a representative interconnecting cable to simulate the input/output characteristics.
- (2) Ports which are not connected to cables during normal intended operation (for factory/technical services uses only)

None.

#### ULTRATECH GROUP OF LABS

3000 Bristol Circle, Oakville, Ontario, Canada L6H 6G4

Tel. #: 905-829-1570, Fax. #: 905-829-8050, Email: vhk.ultratech@sympatico.ca, Website: http://www.ultratech-labs.com

File #: RIM15-FTX

Assessed by ITI (UK) Competent Body, NVLAP (USA) Accreditation Body & ACA/AUSTEL (Australia), VCCI (Japan)

Recognized/Listed by FCC (USA)

July 24, 2001

Accredited by Industry Canada (Canada) under ACC-LAB (Europe/Canada MRA and APEC/Canada MRA)

All test results contained in this engineering test report are traceable to National Institute of Standards and Technology (NIST)

## 2.5. MODIFICATIONS INCORPORATED IN THE EUT FOR COMPLIANCE PURPOSES

None

## 2.6. ANCILLARY EQUIPMENT

The EUT was tested while connected to the following representative configuration of ancillary equipment necessary to exercise the ports during tests:

| Ancillary Equipment # 1  |  |  |  |
|--------------------------|--|--|--|
| Description:             | Cradle   |  |  |
| Brand name:              | BlackBerry   |  |  |
| Model Name or Number:    | ASY-02556-111  |  |  |
| Serial Number:           | Pre-production sample  |  |  |
| Cable Length & Type:     | 2m shielded with RS232 termination to plug into computer and DC receptacle |  |  |
| Connected to EUT's Port: | Serial I/O & DC  |  |  |

| Ancillary Equipment # 2  |  |  |  |
|--------------------------|--|--|--|
| Description:             | AC charging adapter  |  |  |
| Brand name:              | BlackBerry   |  |  |
| Model Name or Number:    | PWR-02908-003  |  |  |
| Serial Number:           | Pre-production sample  |  |  |
| Cable Length & Type:     | 2m unshielded with barrel jack   |  |  |
| Connected to EUT's Port: | None – it is plugs into receptacle by RS232 connector on<br>cradle cable |  |  |

| Ancillary Equipment # 3  |               |
|--------------------------|---------------|
| Description:             | Headset       |
| Model Name or Number:    | HDW-03458-001 |
| Serial Number:           | N/A           |
| Cable Length & Type:     | 1.2m          |
| Connected to EUT's Port: | Audio         |

#### ULTRATECH GROUP OF LABS 3000 Bristol Circle, Oakville, Ontario, Canada L6H 6G4

File #: RIM15-FTX July 24, 2001

Tel. #: 905-829-1570, Fax. #: 905-829-8050, Email: <u>vhk.ultratech@sympatico.ca</u>, Website: http://www.ultratech-labs.com

Assessed by ITI (UK) Competent Body, NVLAP (USA) Accreditation Body & ACA/AUSTEL (Australia), VCCI (Japan)

Accredited by Industry Canada (Canada) under ACC-LAB (Europe/Canada MRA and APEC/Canada MRA)

Recognized/Listed by FCC (USA)

## EXHIBIT 3. EUT OPERATING CONDITIONS AND CONFIGURATIONS DURING TESTS

## 3.1. CLIMATE TEST CONDITIONS

The climate conditions of the test environment are as follows:

| Temperature:        | 21°C                          |
|---------------------|-------------------------------|
| Humidity:           | 51%                           |
| Pressure:           | 102 kPa                       |
| Power input source: | Internal rechargeable battery |

## 3.2. OPERATIONAL TEST CONDITIONS & ARRANGEMENT FOR TEST SIGNALS

| Operating Modes:       | The transmitter was operated in a continuous transmission mode with the carrier modulated as specified in the Test Data. |
|------------------------|--|
| Special Test Software: | N/A  |
| Special Hardware Used: | R&S CMU 200  |

| Transmitter Test Signals  |   |
|---|---|
| Frequency Band(s):  | Near lowest, near middle & near highest frequencies each frequency bands that the transmitter covers: |
| <ul> <li>1850 – 1910 MHz</li> </ul>   | <ul> <li>1850.2 MHz, 1880.0 MHz and 1909.8 MHz</li> </ul>   |
| Transmitter Wanted Output Test Signals:   |   |
| <ul> <li>RF Power Output (measured maximum output power):</li> <li>Normal Test Modulation</li> <li>Modulating signal source:</li> </ul> | <ul> <li>1.38 Watts (e.i.r.p.)</li> <li>GXW</li> <li>Internal</li> </ul>                              |

#### ULTRATECH GROUP OF LABS 3000 Bristol Circle, Oakville, Ontario, Canada L6H 6G4

File #: RIM15-FTX July 24, 2001

Tel. #: 905-829-1570, Fax. #: 905-829-8050, Email: vhk.ultratech@sympatico.ca, Website: http://www.ultratech-labs.com

Assessed by ITI (UK) Competent Body, NVLAP (USA) Accreditation Body & ACA/AUSTEL (Australia), VCCI (Japan)

Accredited by Industry Canada (Canada) under ACC-LAB (Europe/Canada MRA and APEC/Canada MRA)

Recognized/Listed by FCC (USA)

## EXHIBIT 4. SUMMARY OF TEST RESULTS

## 4.1. LOCATION OF TESTS

All of the measurements described in this report were performed at Ultratech Group of Labs located in the city of Oakville, Province of Ontario, Canada.

• Radiated Emissions were performed at the Ultratech's 3 Meter Open Field Test Site (OFTS) situated in the Town of Oakville, province of Ontario.

The above site have been calibrated in accordance with ANSI C63.4, and found to be in compliance with the requirements of Sec. 2.948 of the FCC Rules. The descriptions and site measurement data of the Oakville Open Field Test Site has been filed with FCC office (FCC File No.: 31040/SIT 1300B3) and Industry Canada office (Industry Canada File No.: IC2049). Last Date of Site Calibration: Sep. 20, 1999.

## 4.2. APPLICABILITY & SUMMARY OF EMC EMISSION TEST RESULTS

| FCC PARAGRAPH.                      | TEST REQUIREMENTS   | APPLICABILITY<br>(YES/NO) |
|-------------------------------------|---|---------------------------|
| 24.229                              | Frequencies   | No request                |
| 24.232 & 2.1046                     | Equivalent Isotropically Radiated Power (e.i.r.p.) Limits | Yes                       |
| 24.235 & 2.1055                     | Frequency Stability                                       | No Request                |
| 24.238 & 2.1051                     | Emission Limits (Conducted)                               | No Request                |
| 24.236 & 24.238,<br>2.1057 & 2.1053 | Emission Limits (Radiated)                                | No Request                |

#### ULTRATECH GROUP OF LABS 3000 Bristol Circle, Oakville, Ontario, Canada L6H 6G4

File #: RIM15-FTX July 24, 2001

Tel. #: 905-829-1570, Fax. #: 905-829-8050, Email: <u>vhk.ultratech@sympatico.ca</u>, Website: http://www.ultratech-labs.com

Assessed by ITI (UK) Competent Body, NVLAP (USA) Accreditation Body & ACA/AUSTEL (Australia), VCCI (Japan)

Recognized/Listed by FCC (USA)

Accredited by Industry Canada (Canada) under ACC-LAB (Europe/Canada MRA and APEC/Canada MRA)

## EXHIBIT 5. MEASUREMENTS, EXAMINATIONS & TEST DATA FOR EMC EMISSIONS

## 5.1. TEST PROCEDURES

This section contains test results only. Details of test methods and procedures can be found in Exhibit 7 of this report

## 5.2. MEASUREMENT UNCERTAINTIES

The measurement uncertainties stated were calculated in accordance with requirements of UKAS Document NIS 81 with a confidence level of 95%. Please refer to Exhibit 6 for Measurement Uncertainties.

## 5.3. MEASUREMENT EQUIPMENT USED:

The measurement equipment used complied with the requirements of the Standards referenced in the Methods & Procedures ANSI C63.4:1992 and CISPR 16-1.

## 5.4. ESSENTIAL/PRIMARY FUNCTIONS AS DECLARED BY THE MANUACTURER:

The essential function of the EUT is to correctly communicate data to and from radios over RF link.

#### ULTRATECH GROUP OF LABS 3000 Bristol Circle, Oakville, Ontario, Canada L6H 6G4

File #: RIM15-FTX July 24, 2001

Tel. #: 905-829-1570, Fax. #: 905-829-8050, Email: <u>vhk.ultratech@sympatico.ca</u>, Website: http://www.ultratech-labs.com

Recognized/Listed by FCC (USA)

Assessed by ITI (UK) Competent Body, NVLAP (USA) Accreditation Body & ACA/AUSTEL (Australia), VCCI (Japan)

Accredited by Industry Canada (Canada) under ACC-LAB (Europe/Canada MRA and APEC/Canada MRA)

### 5.5. EIRP @ FCC 2.1046 & 24.232

#### 5.5.1. Limits

Mobile/portable stations are limited to 2 watts e.i.r.p. peak power and the equipment must employ means to limit the power to the minimum necessary for successful communications

#### 5.5.2. Method of Measurements

Please refer to Exhibit 7, Section 7.1 for test procedures and test setup.

#### 5.5.3. Test Equipment List

| Test Instruments                   | Manufacturer    | Model No. | Serial No. | Frequency Range                      | Calibration Date   |
|------------------------------------|-----------------|-----------|------------|--------------------------------------|--|
| Spectrum Analyzer/<br>EMI Receiver | Advantest       | R3271     | 15050203   | 100 Hz – 26.5 GHz                    | Nov. 03, 2000  |
| Microwave Amplifier                | Hewlett Packard | HP 83017A | 3116A00661 | 1 GHz to 26.5 GHz                    | Apr. 20, 2001  |
| Horn Antenna                       | ЕМСО            | 3155      | 9701-5061  | 1 GHz – 18 GHz                       | Apr. 27, 2001  |
| Horn Antenna                       | ЕМСО            | 3155      | 9911-5955  | 1 GHz – 18 GHz                       | Apr. 27, 2001  |
| Power Meter                        | Hewlett Packard | 436A      | 1725A02249 | 10 kHz – 50 GHz, sensor<br>dependent | Sep. 08, 2000  |
| Power Sensor                       | Hewlett Packard | 8481A     | 2702A68983 | 10 MHz – 18 GHz                      | Jan.04, 2001   |
| Synthesize Sweeper                 | Hewlett Packard | 83752B    | 3610A00457 | 0.01 – 20 GHz                        | Jan.30, 2001   |
| RF Power Amplifier                 | OPHIR           | GRF5058   | 1009       | 0.8-4.2 GHz, 41 dB gain,<br>13W max. | No calibration is<br>required.<br>The RF output was<br>measured by a<br>calibrated power<br>meter. |

#### ULTRATECH GROUP OF LABS 3000 Bristol Circle, Oakville, Ontario, Canada L6H 6G4

File #: RIM15-FTX July 24, 2001

Tel. #: 905-829-1570, Fax. #: 905-829-8050, Email: vhk.ultratech@sympatico.ca, Website: http://www.ultratech-labs.com

Recognized/Listed by FCC (USA)

Assessed by ITI (UK) Competent Body, NVLAP (USA) Accreditation Body & ACA/AUSTEL (Australia), VCCI (Japan)

Accredited by Industry Canada (Canada) under ACC-LAB (Europe/Canada MRA and APEC/Canada MRA)

All test results contained in this engineering test report are traceable to National Institute of Standards and Technology (NIST)

#### 5.5.4. Test Arrangement

#### 5.5.4.1. Test configurations # 1 through 7: Without Cradle and headset

The EUT was placed at 3 different orthogonal positions (vertical, horizontal and flat down) for searching the highest emission level:



#### ULTRATECH GROUP OF LABS 3000 Bristol Circle, Oakville, Ontario, Canada L6H 6G4

File #: RIM15-FTX July 24, 2001

Tel. #: 905-829-1570, Fax. #: 905-829-8050, Email: vhk.ultratech@sympatico.ca, Website: http://www.ultratech-labs.com

Assessed by ITI (UK) Competent Body, NVLAP (USA) Accreditation Body & ACA/AUSTEL (Australia), VCCI (Japan)

- Recognized/Listed by FCC (USA)
- All test results contained in this engineering test report are traceable to National Institute of Standards and Technology (NIST)

Accredited by Industry Canada (Canada) under ACC-LAB (Europe/Canada MRA and APEC/Canada MRA)

#### 5.5.4.2. Test configuration # 8: With Cradle and headset

The EUT was placed at 1 allowable position (sitting in the cradle) for testing:



#### ULTRATECH GROUP OF LABS 3000 Bristol Circle, Oakville, Ontario, Canada L6H 6G4

File #: RIM15-FTX July 24, 2001

Tel. #: 905-829-1570, Fax. #: 905-829-8050, Email: vhk.ultratech@sympatico.ca, Website: http://www.ultratech-labs.com

Assessed by ITI (UK) Competent Body, NVLAP (USA) Accreditation Body & ACA/AUSTEL (Australia), VCCI (Japan)

Recognized/Listed by FCC (USA)

Accredited by Industry Canada (Canada) under ACC-LAB (Europe/Canada MRA and APEC/Canada MRA)

All test results contained in this engineering test report are traceable to National Institute of Standards and Technology (NIST)

#### 5.5.5. Test Data

#### EIRP MEASUREMENTS – SUBSTITUTION METHOD

The following EIRP measurements were conducted with different configuration to determine the worst case of measurements:

| Test<br>No | Test Configuration                      | Carrier<br>Frequency<br>(MHz) | E-Field Level<br>@3m<br>(dBμV/m) | Transmitting<br>Antenna<br>Polarization for<br>highest E-Field | Receiving<br>Antenna<br>Polarization for<br>highest E-Field |
|------------|---|-------------------------------|----------------------------------|--|---|
| 1          | Radio S/N: 341 with:                    | 1850.2                        | 127.9                            | Vertical   | Vertical  |
|            | <ul> <li>Toshiba battery</li> </ul>     | 1880.0                        | 126.1                            | Vertical   | Vertical  |
|            | <ul> <li>Epson LCD</li> </ul>           | 1909.8                        | 124.5                            | Vertical   | Vertical  |
| 2          | Radio S/N: 341 with:                    | 1850.2                        | 126.4                            | Vertical   | Vertical  |
|            | <ul> <li>GS Melcotec battery</li> </ul> | 1880.0                        | 126.6                            | Vertical   | Vertical  |
|            | <ul> <li>Epson LCD</li> </ul>           | 1909.8                        | 124.5                            | Vertical   | Vertical  |
| 3          | Radio S/N: 341 with:                    | 1850.2                        | 127.9                            | Vertical   | Vertical  |
|            | <ul> <li>GS Melcotec battery</li> </ul> | 1880.0                        | 129.8                            | Vertical   | Vertical  |
|            | <ul> <li>Samsung LCD</li> </ul>         | 1909.8                        | 125.3                            | Vertical   | Vertical  |
| 4          | Radio S/N: 341 with:                    | 1850.2                        | 127.9                            | Vertical   | Vertical  |
|            | <ul> <li>Toshiba battery</li> </ul>     | 1880.0                        | 129.4                            | Vertical   | Vertical  |
|            | <ul> <li>Samsung LCD</li> </ul>         | 1909.8                        | 125.7                            | Vertical   | Vertical  |
| 5          | Radio S/N: 183 with:                    | 1850.2                        | 128.9                            | Vertical   | Vertical  |
|            | <ul> <li>Toshiba battery</li> </ul>     | 1880.0                        | 130.5                            | Vertical   | Vertical  |
|            | <ul> <li>Samsung LCD</li> </ul>         | 1909.8                        | 128.2                            | Vertical   | Vertical  |
| 7          | Radio S/N: 183 with:                    | 1850.2                        | 128.2                            | Vertical   | Vertical  |
|            | <ul> <li>GS Melcotec battery</li> </ul> | 1880.0                        | 130.1                            | Vertical   | Vertical  |
|            | <ul> <li>Samsung LCD</li> </ul>         | 1909.8                        | 128.6                            | Vertical   | Vertical  |

The above E-field in test configuration No. 5 yielded the highest reading; therefore, it was used for final EIRP measurements using substitution method.

#### ULTRATECH GROUP OF LABS 3000 Bristol Circle, Oakville, Ontario, Canada L6H 6G4

File #: RIM15-FTX July 24, 2001

Tel. #: 905-829-1570, Fax. #: 905-829-8050, Email: vhk.ultratech@sympatico.ca, Website: http://www.ultratech-labs.com

Recognized/Listed by FCC (USA)

Assessed by ITI (UK) Competent Body, NVLAP (USA) Accreditation Body & ACA/AUSTEL (Australia), VCCI (Japan)

Accredited by Industry Canada (Canada) under ACC-LAB (Europe/Canada MRA and APEC/Canada MRA)

#### • Test Configuration # 5: Model R1900G-1-4 with Radio S/N: 183, Toshiba battery and Samsung LCD

| Frequency<br>(MHz) | Peak E-Field @ 3m<br>(dBµV/m) | Antenna<br>Polarization<br>(V/H) | Peak Power From<br>Signal Generator<br>(dBm) | Substitution<br>Antenna Gain<br>(dBi) | Measured<br>Peak EIRP<br>(dBm) | Peak<br>EIRP LIMIT<br>(dBm) |
|--------------------|-------------------------------|----------------------------------|--|---------------------------------------|--------------------------------|-----------------------------|
| 1850.2             | 128.9                         | V                                | 21.0   | 9.0                                   | 30.0                           | 33.0                        |
|                    | 127.7                         | Н                                | 19.6   | 9.0                                   | 28.6                           | 33.0                        |
| 1880.0             | 130.5                         | V                                | 22.4   | 9.0                                   | 31.4                           | 33.0                        |
|                    | 127.9                         | Н                                | 19.6   | 9.0                                   | 28.6                           | 33.0                        |
| 1909.8             | 128.2                         | V                                | 21.5   | 9.0                                   | 30.5                           | 33.0                        |
|                    | 128.4                         | Н                                | 20.8   | 9.0                                   | 29.8                           | 33.0                        |

#### • Test Configuration # 8:

## Model R1900G-1-4 with Radio S/N: 183, Toshiba battery and Samsung LCD, Cradle, External power supply and headset

The worst test configuration # 5 was repeated with the charging cradle + external power supply and headset and the results were found as follows:

| Frequency<br>(MHz) | Peak E-Field @ 3m<br>(dBµV/m) | Antenna<br>Polarization<br>(V/H) | Peak Power From<br>Signal Generator<br>(dBm) | Substitution<br>Antenna Gain<br>(dBi) | Measured<br>Peak EIRP<br>(dBm) | Peak<br>EIRP LIMIT<br>(dBm) |
|--------------------|-------------------------------|----------------------------------|--|---------------------------------------|--------------------------------|-----------------------------|
| 1850.2             | 126.6                         | V                                | **   | **                                    | **                             | **                          |
|                    | 121.1                         | Н                                | **   | **                                    | **                             | **                          |
| 1880.0             | 125.7                         | V                                | **   | **                                    | **                             | **                          |
|                    | 124.1                         | Н                                | **   | **                                    | **                             | **                          |
| 1909.8             | 125.6                         | V                                | **   | **                                    | **                             | **                          |
|                    | 124.0                         | Н                                | **   | **                                    | **                             | **                          |

\*\* Since the E-field levels measured above are less than those in Test Configuration #5. The test results in Test Configuration #5 still represents the highest readings. Therefore, the EIRP measurements using substitution method was not necessary to be conducted.

#### ULTRATECH GROUP OF LABS 3000 Bristol Circle, Oakville, Ontario, Canada L6H 6G4

File #: RIM15-FTX July 24, 2001

Tel. #: 905-829-1570, Fax. #: 905-829-8050, Email: <u>vhk.ultratech@sympatico.ca</u>, Website: http://www.ultratech-labs.com

Assessed by ITI (UK) Competent Body, NVLAP (USA) Accreditation Body & ACA/AUSTEL (Australia), VCCI (Japan)

Recognized/Listed by FCC (USA)

Accredited by Industry Canada (Canada) under ACC-LAB (Europe/Canada MRA and APEC/Canada MRA)

## EXHIBIT 6. MEASUREMENT UNCERTAINTY

The measurement uncertainties stated were calculated in accordance with the requirements of NIST Technical Note 1297 and NIS 81 (1994)

## 6.1. RADIATED EMISSION MEASUREMENT UNCERTAINTY

| CONTRIBUTION  | PROBABILITY    | UNCERTAINTY ( <u>+</u> dB) |               |  |
|---|----------------|----------------------------|---------------|--|
| (Radiated Emissions)  | DISTRIBUTION   | 3 m                        | 10 m          |  |
| Antenna Factor Calibration  | Normal (k=2)   | <u>+</u> 1.0               | <u>+</u> 1.0  |  |
| Cable Loss Calibration  | Normal (k=2)   | <u>+</u> 0.3               | <u>+</u> 0.5  |  |
| EMI Receiver specification  | Rectangular    | <u>+</u> 1.5               | <u>+</u> 1.5  |  |
| Antenna Directivity   | Rectangular    | +0.5                       | +0.5          |  |
| Antenna factor variation with height  | Rectangular    | <u>+</u> 2.0               | <u>+</u> 0.5  |  |
| Antenna phase center variation  | Rectangular    | 0.0                        | <u>+</u> 0.2  |  |
| Antenna factor frequency interpolation  | Rectangular    | <u>+</u> 0.25              | <u>+</u> 0.25 |  |
| Measurement distance variation  | Rectangular    | <u>+</u> 0.6               | <u>+</u> 0.4  |  |
| Site imperfections  | Rectangular    | <u>+</u> 2.0               | <u>+</u> 2.0  |  |
| Mismatch: Receiver VRC $\Gamma_1 = 0.2$<br>Antenna VRC $\Gamma_R = 0.67$ (Bi) 0.3 (Lp)<br>Uncertainty limits 20Log(1 $\pm$ $\Gamma_1\Gamma_R$ ) | U-Shaped       | +1.1<br>-1.25              | <u>+</u> 0.5  |  |
| System repeatability  | Std. Deviation | <u>+</u> 0.5               | <u>+</u> 0.5  |  |
| Repeatability of EUT  |                | -                          | -             |  |
| Combined standard uncertainty   | Normal         | +2.19 / -2.21              | +1.74 / -1.72 |  |
| Expanded uncertainty U  | Normal (k=2)   | +4.38 / -4.42              | +3.48 / -3.44 |  |

Calculation for maximum uncertainty when 3m biconical antenna including a factor of k=2 is used:

 $U = 2u_c(y) = 2x(+2.19) = +4.38 \text{ dB}$  And  $U = 2u_c(y) = 2x(-2.21) = -4.42 \text{ dB}$ 

#### ULTRATECH GROUP OF LABS 3000 Bristol Circle, Oakville, Ontario, Canada L6H 6G4

File #: RIM15-FTX July 24, 2001

Tel. #: 905-829-1570, Fax. #: 905-829-8050, Email: vhk.ultratech@sympatico.ca, Website: http://www.ultratech-labs.com

Recognized/Listed by FCC (USA)

Assessed by ITI (UK) Competent Body, NVLAP (USA) Accreditation Body & ACA/AUSTEL (Australia), VCCI (Japan)

Accredited by Industry Canada (Canada) under ACC-LAB (Europe/Canada MRA and APEC/Canada MRA)

## **EXHIBIT 7. MEASUREMENT METHODS**

## 7.1. EQUIVALENT ISOTROPIC RADIATED POWER (EIRP) MEASUREMENTS

- The following shall be applied to the combination(s) of the radio device and its intended antenna(e).
- I f the RF level is user adjustable, all measurements shall be made with the highest power level available to the user for that combination.
- The following method of measurement shall apply to both conducted and radiated measurements.
- The radiated measurements are performed at the Ultratech Calibrated Open Field Test Site.
- The measurement shall be performed using normal operation of the equipment with modulation.

Test procedure shall be as follows:

Step 1: Duty Cycle measurements

- Using a spectrum analyzer with the frequency span set to 0 Hz and the sweep time set at a suitable value to capture the envelope peaks and the duty cycle of the transmitter output signal;
- The duty cycle of the transmitter, x = Tx on / (Tx on + Tx off) with 0<x<1, is measure and recorded in the test report. For the purpose of testing, the equipment shall be operated with a duty cycle that is equal or more than 0.1.</p>

Step 2: Calculation of Average EIRP. See Figure 1

- The average output power of the transmitter shall be determined using a wideband, calibrated RF power meter with the power sensor with an integration period that exceeds the repetition period of the transmitter by a factor 5 or more. The observed value shall be recorded as "A" (in dBm);
- The e.i.r.p. shall be calculated from the above measured power output "A", the observed duty cycle x, and the applicable antenna assembly gain "G" in dBi, according to the formula:

#### EIRP = A + G + 10log(1/x)





#### Step 3: Substitution Method. See Figure 2

- (a) The measurements was performed in the absence of modulation (un-modulated)
- (b) Test was performed at listed 3m open area test site (listed with FCC, IC, ITI, NVLAP, ACA & VCCI).
- (c) The transmitter under test was placed at the specified height on a non-conducting turntable (80 cm height)
- (d) The horn test antenna was used and tuned to the transmitter carrier frequency.
- (e) The spectrum analyzer was tuned to transmitter carrier frequency. The test antenna was lowered or raised from 1 to 4 meters until the maximum signal level was detected.
- (f) The transmitter was rotated through 360° about a vertical axis until a higher maximum signal was received.
- (g) The test antenna was lowered or raised again from 1 to 4 meters until a maximum was obtained. This level was recorded.

#### **ULTRATECH GROUP OF LABS**

3000 Bristol Circle, Oakville, Ontario, Canada L6H 6G4

Tel. #: 905-829-1570, Fax. #: 905-829-8050, Email: vhk.ultratech@sympatico.ca, Website: http://www.ultratech-labs.com

- File #: RIM15-FTX July 24, 2001
- Assessed by ITI (UK) Competent Body, NVLAP (USA) Accreditation Body & ACA/AUSTEL (Australia), VCCI (Japan)

- Recognized/Listed by FCC (USA)
- All test results contained in this engineering test report are traceable to National Institute of Standards and Technology (NIST)

Accredited by Industry Canada (Canada) under ACC-LAB (Europe/Canada MRA and APEC/Canada MRA)

- (h) The substitution horn antenna and the signal generator replaced the transmitter and antenna under test in the same position, and the substitution horn antenna was placed in vertical polarization. The test horn antenna was lowered or raised as necessary to ensure that the maximum signal is still received.
- (i) The input signal to the substitution antenna was adjusted in level until an equal or a known related level to that detected from the transmitter was obtained in the test receiver. The maximum carrier radiated power is equal to the power supply by the generator.
- (j) The substitution antenna gain and cable loss were added to the signal generator level for the corrected ERP level.
- (k) Repeat steps (c) to (j) with the substitution antenna oriented in horizontal polarization.
- (I) Actual gain of the EUT's antenna is the difference of the measured ERP and measured RF power at the RF port. Correct the antenna gain if necessary.
- (m) EIRP = ERP + 2.15

#### Figure 2





#### **ULTRATECH GROUP OF LABS**

3000 Bristol Circle, Oakville, Ontario, Canada L6H 6G4 Tel. #: 905-829-1570, Fax. #: 905-829-8050, Email: <u>vhk.ultratech@sympatico.ca</u>, Website: http://www.ultratech-labs.com File #: RIM15-FTX July 24, 2001

- Assessed by ITI (UK) Competent Body, NVLAP (USA) Accreditation Body & ACA/AUSTEL (Australia), VCCI (Japan)
- Accredited by Industry Canada (Canada) under ACC-LAB (Europe/Canada MRA and APEC/Canada MRA)
- Recognized/Listed by FCC (USA)
- All test results contained in this engineering test report are traceable to National Institute of Standards and Technology (NIST)