

		duct Specification 0 + MAH9011	
Base MAB9030 Specification			
Transmission Frequency:	Channel 1 – 1.762 MHz \pm 2kHz	Channel 2 – 1.784 MHz \pm 2kHz	
Receiving Frequency:	Channel 1 – 403.0 kHz \pm 10kHz	Channel 2 – 413.7 kHz \pm 10kHz	
Audio Frequency Response:	300 Hz to 6kHz		
AM Modulation depth:	≦ 150%		
Fundamental radiation emission level measured @ 30m:	< 10µV		
Operating Voltage:	3.2V to 4.5V		
Operating Range:	\geq 1.5 meter		
Operating Temperature:	0°C to 45°C		
Features			
Selectable channels			
Automatic power On/Standby 3.6V (40mAh) dedicated rechargeable battery pack			
Battery Talk time	≧ 2.5 hours		
Battery Standby time	≥ 150 hours		
Light weight	39g (included belt clip and battery)		
Red LED Power On Indication			
Green LED In Range Indication			
Integrated antennas			
2.5mm stereo plug (compatible with most of the mobile phones by adding connectors)			
Controls			
Power On/Off switch			
Channel Selection switch			
LED indicators for Power On and In Range			



Headset MAH9011 Specification			
Transmission Frequency:	Channel 1 – 403.046 kHz \pm 1kHz	Channel 2 – 413.696 kHz ± 1kHz	
Receiving Frequency:	Channel 1 – 1.762 MHz \pm 10kHz	Channel 2 – 1.784 MHz \pm 10kHz	
Audio Frequency Response:	300 Hz to 6kHz		
AM Modulation depth:	≦ 120%		
Fundamental radiation emission level measured @ 30 meter:	< 10µV		
Audio distortion:	Nominal 5%		
Signal to Noise Ratio @ 1 meter:	\ge 40 dB		
Operating Voltage:	3.2V to 4.5V		
Operating Range:	\geq 1.5 meter		
Operating Temperature:	0°C to 45°C		
Features			
Selectable channels			
Automatic power On/Standby			
3.6V (40mAh) dedicated rechargeable battery			
Battery Talk time	\geq 2.5 hours		
Battery Standby time	\ge 150 hours		
Light weight	26g (included battery)		
Blinking Green LED Standby Indication			
Green LED In Range Indication			
Integrated antennas			
Symmetrical design: suitable for wearing on either left or right ears			
4-level audio output			
Low-Battery Sound Alert			
Noise cancellation Microphone			
Controls			
Power On/Off switch			
Channel Selection switch			
Volume control button			
LED indicator for Power On			



Accessory

6Vdc 100mA UL listed (or CE/TUV) AC adapter

Charging unit with 3 charging cavities

3 pieces of dedicated battery packs