

2/3

A. Number of operating channel on 36248 (ANALOG CORDLESS)

The operating channel between the base and handset is 40 channels.

The reference channel is defined by ID number which is generated automatically by CPU.

That means the first channel to communicate between base and handset is the reference channel.

AUG 11 2000

B. Channel frequency (MHz)

Channel #	Base unit		Handset	
	Transmitter	Receiver	Transmitter	Receiver
1	2400.45	2472.45	2472.45	2400.45
2	2400.60	2472.60	2472.60	2400.60
3	2400.75	2472.75	2472.75	2400.75
4	2400.90	2472.90	2472.90	2400.90
5	2401.05	2473.05	2473.05	2401.05
6	2401.20	2473.20	2473.20	2401.20
7	2401.35	2473.35	2473.35	2401.35
8	2401.50	2473.50	2473.50	2401.50
9	2401.65	2473.65	2473.65	2401.65
10	2401.80	2473.80	2473.80	2401.80
11	2401.95	2473.95	2473.95	2401.95
12	2402.10	2474.10	2474.10	2402.10
13	2402.25	2474.25	2474.25	2402.25
14	2402.40	2474.40	2474.40	2402.40
15	2402.55	2474.55	2474.55	2402.55
16	2402.70	2474.70	2474.70	2402.70
17	2402.85	2474.85	2474.85	2402.85
18	2403.00	2475.00	2475.00	2403.00
19	2403.15	2475.15	2475.15	2403.15
20 (*note)	2403.30	2475.30	2475.30	2403.30
21	2403.45	2475.45	2475.45	2403.45
22	2403.60	2475.60	2475.60	2403.60
23	2403.75	2475.75	2475.75	2403.75
24	2403.90	2475.90	2475.90	2403.90
25	2404.05	2476.05	2476.05	2404.05
26	2404.20	2476.20	2476.20	2404.20
27	2404.35	2476.35	2476.35	2404.35
28	2404.50	2476.50	2476.50	2404.50
29	2404.65	2476.65	2476.65	2404.65
30	2404.80	2476.80	2476.80	2404.80
31	2404.95	2476.95	2476.95	2404.95
32	2405.10	2477.10	2477.10	2405.10
33	2405.25	2477.25	2477.25	2405.25
34	2405.40	2477.40	2477.40	2405.40
35	2405.55	2477.55	2477.55	2405.55
36	2405.70	2477.70	2477.70	2405.70
37	2405.85	2477.85	2477.85	2405.85
38	2406.00	2478.00	2478.00	2406.00
39	2406.15	2478.15	2478.15	2406.15
40	2406.30	2478.30	2478.30	2406.30
41	2406.45	2478.45	2478.45	2406.45

*note: this channel is used only in test mode for factory manufacture.

2/3

1/2