

APPLICANT: MIPRO ELECTRONICS CO. LTD.

FCC ID: M5XMH-801

TABLE OF CONTENTS

TEST REPORT CONTAINING:

PAGE	1.....	TEST EQUIPMENT LIST AND TEST PROCEDURE
PAGE	2.....	TEST PROCEDURE CONTINUED
PAGE	3.....	CIRCUIT DESCRIPTION
PAGE	4.....	RADIATION INTERFERENCE TEST DATA
PAGE	5.....	OCCUPIED BANDWIDTH TEST DATA

EXHIBITS CONTAINING:

EXHIBIT	1.....	POWER OF ATTORNEY LETTER
EXHIBIT	2.....	BLOCK DIAGRAM
EXHIBIT	3.....	SCHEMATICS
EXHIBIT	4.....	FCC ID LABEL SAMPLE
EXHIBIT	5.....	SKETCH OF FCC ID LABEL LOCATION
EXHIBIT	6A.....	EXTERNAL PHOTO FRONT VIEW
EXHIBIT	6B.....	EXTERNAL PHOTO REAR VIEW
EXHIBIT	6C-6D..	INTERNAL PHOTO - SOLDER
EXHIBIT	6E-6F..	INTERNAL PHOTO - COMPONENT
EXHIBIT	7.....	PARTS LIST - 10 PAGES
EXHIBIT	8.....	USER'S MANUAL -11 PAGES
EXHIBIT	9.....	OCCUPIED BANDWIDTH PLOT - NO MODULATION
EXHIBIT	10.....	OCCUPIED BANDWIDTH PLOT - LOUD VOICE
EXHIBIT	11.....	OCCUPIED BANDWIDTH PLOT - MODULATED 2500 Hz
EXHIBIT	12.....	OCCUPIED BANDWIDTH PLOT - NO MODULATION

APPLICANT: MIPRO ELECTRONICS CO. LTD.

FCC ID: M5XMH-801

DATE: 15 July 1999

REPORT #: F:\CUS\M\MIPRO\MIP241T9\MIP241T9RPT.DOC

PAGE: TABLE OF CONTENTS

THE RECEIVER PORTION OF THIS DEVICE, MODEL NO. MR-801 WAS TESTED WITH PASSING RESULTS. A DECLARATION OF CONFORMITY REPORT HAS BEEN ISSUED PER FCC RULES PART 15.109.

TEST EQUIPMENT LIST

1. Spectrum Analyzer: Hewlett Packard 8566B - Opt 462, w/ preselector 85685A, & Quasi-Peak Adapter HP 85650A, & HP 8449B - OPT H02 Cal. 7/6/99
2. Signal Generator, Hewlett Packard 8640B, cal. 10/1/98
3. Signal Generator, HP 8614A Serial No.2015A07428 cal. 5/27/99
4. Eaton Biconnical Antenna Model 94455-1
20-200 MHz Serial No. 0997 Cal. 10/30/98
5. Electro-Metric Dipole Kit, 20-1000 MHz, Model TDA-30 10/31/98
6. Electro-Metric Horn 1-18 GHz, Model RGA-180, Cal. 10/30/98
7. Electro-Metric Antennas Model TDA-30/1-4, Cal. 10/15/98
8. Electro-Metric Line Impedance Stabilization Network Model No. EM-7821, Serial No. 101; 100KHz-30MHz 50uH. Cal.11/19/98
9. Electro-Metric Line Impedance Stabilization Network Model No. EM-7820, Serial No. 2682; 10KHz-30MHz 50uH. Cal. 11/19/98
10. Special low loss cable was used above 1 GHz
11. Tenney Temperature Chamber

TEST PROCEDURE

GENERAL: This report shall NOT be reproduced except in full without the written approval of TIMCO ENGINEERING, INC.

RADIATION INTERFERENCE: The test procedure used was ANSI STANDARD C63.4-1992 using a HEWLETT PACKARD spectrum analyzer with a preselector. The bandwidth of the spectrum analyzer was 100 kHz with an appropriate sweep speed. The analyzer was calibrated in dB above a microvolt at the output of the antenna. The resolution bandwidth was 100KHz and the video bandwidth was 300KHz. The ambient temperature of the UUT was 89oF with a humidity of 80%.

APPLICANT: MIPRO ELECTRONICS CO. LTD.

FCC ID: M5XMH-801

DATE: 15 July 1999

REPORT #: F:\CUS\M\MIPRO\MIP241T9\MIP241T9RPT.DOC

PAGE #: 1

TEST PROCEDURE (CONT)

ANSI STANDARD C63.4-1992 10.1.7 MEASUREMENT PROCEDURES: The UUT was placed on a table 80 cm high and with dimensions of 1m by 1.5m. The UUT was placed flush with the back of the table (1.5m side). The table used for radiated measurements is capable of continuous rotation.

When an emission was found, the table was rotated to produce the maximum signal strength. At this point, the antenna was raised and lowered from 1m to 4m. The antenna was placed in both the horizontal and vertical planes.

The situation was similar for the conducted measurement except that the table did not rotate. The EUT was setup as described in ANSIC63.4-1992 with the EUT 40 cm from the vertical ground wall.

FORMULA OF CONVERSION FACTORS: The Field Strength at 3m was established by adding the meter reading of the spectrum analyzer (which is set to read in units of dBuV) to the antenna correction factor supplied by the antenna manufacturer. The antenna correction factors are stated in terms of dB. The gain of the Preselector was accounted for in the Spectrum Analyzer Meter Reading.

Example:

Freq (MHz)	METER READING + ACF = FS
33	20 dBuV + 10.36 dB = 30.36 dBuV/m @ 3m

POWER LINE CONDUCTED INTERFERENCE: The procedure used was ANSI STANDARD C63.4-1992 using a 50uH LISN. Both lines were observed. The bandwidth of the spectrum analyzer was 10kHz with an appropriate sweep speed. The ambient temperature of the UUT was 89oF with a humidity of 80%.

APPLICANT: MIPRO ELECTRONICS CO. LTD.

FCC ID: M5XMH-801

DATE: 15 July 1999

REPORT #: F:\CUS\M\MIPRO\MIP241T9\MIP241T9RPT.DOC

PAGE #: 2

APPLICANT: MIPRO ELECTRONICS CO. LTD.
FCC ID: M5XMH-801

CIRCUIT DESCRIPTION:

The incoming signal comes in on the antenna and is fed through the duplexer to the LNA, Q500 and then to a SAW bandpass filter, FL501. The frequency range of the base receiver is 926-928MHz. From the bandpass filter the signal is fed to the mixer, Q501 which converts the signal down to 26.05MHz. From Q501 the signal is fed to the IF filter FL502 and then to the integrated circuit U500. In the U500 the signal is converted down to 450KHz and then to the detector for FM signal. From the detector the audio is fed to a low pass filter and to the Channel Detector Indicator. From the low pass filter the audio is fed into another low pass filter and shaper and then to the CPU, U311. From the CPU, U311, the audio is fed to a speaker amplifier and the telephone line depending which is selected. From the CPU the line audio is fed to U305A and then to U305B then to the telephone coupling transformer, T301. The CPU also compares the SECURITY CODES and provides the outgoing SECURITY CODE.

On the transmitting side, when a ring signal is detected the transmitter is turned on by photo coupler integrated circuit U301 and the ring detect signal is fed into the CPU, U306, which in turn triggers the transmitter and send a ring signal to the handset. The base transmit frequency range is 902-904MHz. When the handset answers the base unit connects to the phone line and telephone line audio is fed into the speech network and then to an audio amplifier, Q304. The audio is then fed into the compressor U311. From U311 the audio is fed into the VCO, VT which modulated the outgoing carrier. From the VCO the signal is fed through a series of amplifiers, Q508 & Q509. From Q508 the signal is fed to the antenna.

ANTENNA AND GROUND CIRCUITRY

This unit makes use of a short, antenna. The antenna is inductively coupled. The antenna is self contained, no provision is made for an external antenna.

No ground connection is provided. The unit relies on the ground tract of the printed circuit board.

APPLICANT: MIPRO ELECTRONICS CO. LTD.
FCC ID: M5XMH-801
DATE: 15 July 1999
REPORT #: F:\CUS\M\MIPRO\MIP241T9\MIP241T9RPT.DOC
PAGE #: 3

APPLICANT: MIPRO ELECTRONICS CO. LTD.

FCC ID: M5XMH-801

NAME OF TEST: RADIATION INTERFERENCE

RULES PART NO.: 15.249

REQUIREMENTS: Carrier frequency will not exceed 94.0 dBuV/m

FREQUENCY		LEVEL
_____MHz_____		_____dBuV/M_____
902- 928	MHz:	54.0 dBuV/M
ABOVE 960	MHz:	54.0 dBuV/M

TEST DATA:

EMISSION FREQ. MHz	METER READING @ 3m dBuV	COAX LOSS dB	ACF dB	PEAK FIELD STRNGTH dBuV/m	AVERAGE FIELD STRNGTH dBuV/m	MARGIN dB	ANT.
TEST DATA:							
914.01	65.60	2.90	24.14	92.64	92.64	1.36	V
1828.02	20.30	1.00	27.31	48.62	48.62	5.38	V
2742.02R	17.20	1.14	29.86	48.20	48.20	5.80	H
3656.04R	14.60	1.28	32.14	48.02	48.02	5.98	V
4570.04R	8.90	1.42	33.64	43.96	43.96	10.04	V
5484.06	0.00	1.55	34.67	36.22	36.22	17.78	V
6399.07	-2.30	1.69	35.70	35.09	35.09	18.94	V
927.00	65.80	2.90	24.12	92.82	92.82	1.18	V
1854.00	23.20	1.01	27.42	51.62	51.62	2.38	V
2781.00R	20.60	1.15	29.95	52.70	51.70	2.30	H
3708.00R	14.80	1.29	32.27	48.36	48.36	5.64	V
4635.00R	4.50	1.43	33.71	39.64	39.64	14.36	V
6489.00	-2.60	1.70	35.80	34.90	34.90	19.10	V

SAMPLE CALCULATION: FSdBuV/m = MR(dBuV) + ACFdB.

METHOD OF MEASUREMENT: The procedure used was ANSI STANDARD. Measurements were made at Timco Engineering, Inc. 6051 N.W. 19th Lane, Gainesville, FL 32605.

TEST RESULTS: The unit DOES meet the FCC requirements.

PERFORMED BY: _____ DATE: 15 July 1999

APPLICANT: MIPRO ELECTRONICS CO. LTD.
 FCC ID: M5XMH-801
 DATE: 15 July 1999
 REPORT #: F:\CUS\M\MIPRO\MIP241T9\MIP241T9RPT.DOC
 PAGE #: 4

APPLICANT: MIPRO ELECTRONICS CO. LTD.
FCC ID: M5XMH-801
NAME OF TEST: Occupied Bandwidth
RULES PART NO.: 15.249
REQUIREMENTS: The field strength of any emissions appearing between the band edges and up to 10 kHz above and below the band edges shall be attenuated at least 26 dB below the level of the unmodulated carrier or to the general limits of 15.209, whichever permits the higher emission levels.

THE GRAPHS IN EXHIBITS 9-12 REPRESENT THE EMISSIONS TAKEN FOR THIS DEVICE.

METHOD OF MEASUREMENT: A small sample of the transmitter output was fed into the spectrum analyzer and the above photo was taken. The vertical scale is set to -10 dBm per division. The horizontal scale is set to 5 kHz per division.

TEST RESULTS: The unit DOES meet the FCC requirements.

PERFORMED BY: _____ 15 July 1999

APPLICANT: MIPRO ELECTRONICS CO. LTD.
FCC ID: M5XMH-801
DATE: 15 July 1999
REPORT #: F:\CUS\M\MIPRO\MIP241T9\MIP241T9RPT.DOC
PAGE #: 5