

| Level | Item | SAP code         | Description                              | Quantity |
|-------|------|------------------|------------------------------------------|----------|
| 1     |      | <b>287295676</b> | <b>ass_mobile Runur black</b>            |          |
|       | 10   | 287288098        | RefEPCB RunuR                            | 1        |
|       | 20   | 287295241        | runur-lcd-sup-pre-asm                    | 1        |
|       | 30   | 287290147        | RUNUR keypad FPC                         | 1        |
|       | 40   | 287290134        | RUNUR CAMERA FLEX 3MP+VGA                | 1        |
|       | 50   | 287295275        | runur-proxi-foam                         | 1        |
|       | 60   | 179134039        | LCM 2.8" QVGA 2.05T                      | 1        |
|       | 70   | 287295212        | runur-fla-lg                             | 1        |
|       | 80   | 287294778        | upper housing assy Runur black           | 1        |
|       | 90   | 287295233        | runur-mic-cover                          | 1        |
|       | 100  | 179134229        | touch window 6pin capacitive             | 1        |
|       | 110  | 179135242        | receiver 0711*2.3H spring contact        | 1        |
|       | 120  | 189757970        | VIBRATION MOTOR 3V DIA.9Xt3.0 RoHS       | 1        |
|       | 130  | 287294799        | keypad Runur black                       | 1        |
|       | 140  | 287294843        | camera keypad Runur black                | 1        |
|       | 150  | 287294864        | side key Runur black                     | 1        |
|       | 160  | 287294801        | lower housing assy Runur black           | 1        |
|       | 170  | 189942553        | LOUD SPEAKER 8 OHM 9X18MM                | 1        |
|       | 180  | 287294872        | camera window Runur black                | 1        |
|       | 190  | 287295600        | runur-ant-asm                            | 1        |
|       | 200  | 287294905        | IO cover Runur black                     | 1        |
|       | 210  | 179087040        | screw M1.4*4.5 BX2 RoHS                  | 6        |
|       | 220  | 287294885        | battery cover assy Runur black           | 1        |
|       | 230  | 287295118        | runur-solar-pad-isol-film                | 3        |
|       | 240  | 287295085        | runur-solar-cell-foam                    | 1        |
|       | 250  | 287290155        | RUNUR Solar cell FPC                     | 1        |
|       | 260  | 179135804        | solar cell module LR0GC02 67.5*41.0 RoHS | 1        |
|       | 270  | 287295358        | solar cell window Runur black            | 1        |
|       | 280  | 287300547        | runur keypad metal dome assembly         | 1        |
| 2     |      | <b>287288098</b> | <b>RefEPCB RunuR</b>                     |          |
|       | 10   | 287300430        | MMI board I RunuR V03                    | 1        |
|       |      | <b>287300430</b> | <b>MMI board I RunuR V03</b>             |          |
|       | 10   | 287300443        | PCB board RunuR V03                      | 1        |
|       | 1005 | 179133996        | pogo 3pin 2.5pitch 7.6*2.5*4.2 RoHS      | 1        |
|       | 1010 | 179069969        | N-MOSFET RoHS                            | 2        |
|       | 1015 | 189682925        | TRANS.SMD NMOS 30V 2.9A UFET2x2          | 1        |
|       | 1020 | 179097070        | Dual PMOSFET RoHS                        | 1        |
|       | 1025 | 179132709        | crystal 26MHZ 15pf 3225                  | 1        |
|       | 1030 | 179116664        | MIC Mini Zero Height 4.72*3.76*1.25 RoHS | 1        |
|       | 1035 | 179123630        | SIM connector 6pin 1.5H RoHS             | 1        |
|       | 1040 | 179119769        | MicroSD conn w detect pin 2.65H RoHS     | 1        |
|       | 1045 | 179133975        | micro USB connector socket sink RoHS     | 1        |
|       | 1050 | 179132085        | Batt conn 2pin_4.0H sink 2bump RoHS      | 1        |

|      |           |                                          |    |
|------|-----------|------------------------------------------|----|
| 1055 | 179097773 | FPC Connector FH-26-41S-0.3SHW(05) RoHS  | 2  |
| 1060 | 189843276 | SMD TRANS. NTA7002 NMOS 30V SC75 RoHS    | 2  |
| 1065 | 179068074 | inductor0402 8.2NH ±0.5nH RoHS           | 1  |
| 1070 | 179133714 | resistor 0201 12KΩ ±1% 0.05W RoHS        | 1  |
| 1075 | 179101569 | resistor0201 470KΩ ±5% 0.05W RoHS        | 14 |
| 1080 | 179121454 | resistor0402 30KΩ 1% 0.063W RoHS         | 1  |
| 1085 | 179101486 | resistor0201 100KΩ ±1% 0.05W RoHS        | 16 |
| 1090 | 179105012 | resistor0201 39KΩ ±5% 0.05W RoHS         | 1  |
| 1095 | 187960280 | SMD RES 0201 100KOHM 5% 50MW 250PPM      | 12 |
| 1100 | 179068368 | resistor0402 220KΩ ±5% 0.063W RoHS       | 1  |
| 1105 | 179101361 | resistor0201 1KΩ ±5% 0.05W RoHS          | 5  |
| 1110 | 188126829 | SMD RES.0201 1MOHM 5% 50MW 250PPM Ro     | 5  |
| 1115 | 179074816 | resistor0201 0Ω ±1% 0.05W RoHS           | 44 |
| 1120 | 179136794 | MCP 2G+1G+128Mb 1.8V 0.65p Bgt(133Mhz) F | 1  |
| 1125 | 189393156 | SMD IC LM3208CONVERT.DC/DC S.D.UBGA8     | 1  |
| 1130 | 179132288 | 2input logic IC SC70                     | 1  |
| 1135 | 179132340 | LDO 300mA 2.8V DFN(PLP)1820-6            | 1  |
| 1140 | 189124689 | SMD REG.IC R1116 LDO 2V8 SON1612-6 RoH   | 1  |
| 1145 | 189977027 | SMD.IC AAT3171A CHARGE PUMP TDFN12 R     | 1  |
| 1150 | 189368679 | REG.SMD.IC R1163 LDO 2V75 PLP1616-6 RoH  | 1  |
| 1155 | 179125741 | current limit IC FPF2165                 | 1  |
| 1160 | 179132192 | baseband controller AB3100 μBGA7*7 RoHS  | 1  |
| 1165 | 179099115 | class D audio amplifier D607 RoHS        | 1  |
| 1170 | 189758456 | IC.SMD SKY77181 PAM WCDMA/HSDPA RoH      | 1  |
| 1175 | 179136327 | IC WCDMA/HSDPA band I PA BA01271         | 1  |
| 1180 | 179133615 | 3-axis Electronic Compass AK8973B RoHS   | 1  |
| 1185 | 189434499 | SMD LOG IC 74LVC1G125 DSBGA5 RoHS        | 1  |
| 1190 | 179128875 | Motion sensor MMA7660 DFN10              | 1  |
| 1195 | 189829581 | SMD IC BCM4750 AGPS RECEIVER WLCSP47     | 1  |
| 1200 | 188648359 | SMD LOG.IC SN74LVC1G126 DSBGA-5 RoHS     | 1  |
| 1205 | 179132171 | baseband controller DB3350 14*14POP RoHS | 1  |
| 1210 | 189739972 | SMD IC 2593 BLUETOOTH TRANSC.BGA100      | 1  |
| 1215 | 188696970 | SMD LOG.IC 74LVC1G32 DSBGA-5 RoHS        | 2  |
| 1220 | 189512909 | SMD IC BGA615L7 L.N.AMPLI.RF TSLP7-1RoH  | 1  |
| 1225 | 188694786 | SMD REG.IC R1115Z LDO 2V85 WLCSP4P4 R    | 2  |
| 1230 | 189131499 | SMD REG.IC R1116 LDO 1V8 SON1612-6 RoH   | 1  |
| 1235 | 179132741 | Level shifter ST6G3238BE uTFBGA25        | 1  |
| 1240 | 179068186 | resistor0402 10Ω ±5% 0.063W RoHS         | 1  |
| 1245 | 188127206 | SMD RES.0201 4.7KOHM 5% 50MW 250PPM F    | 2  |
| 1250 | 188127102 | SMD RES.0201 3.3KOHM 5% 50MW 250PPM F    | 3  |
| 1255 | 189732353 | SMD RES.0201 1.1KOHM 1% 50MW 250PPM F    | 2  |
| 1260 | 179101382 | resistor0201 2.2KΩ ±5% 0.05W RoHS        | 1  |
| 1265 | 188126952 | SMD RES.0201 1.8KOHM 5% 50MW 250PPM F    | 1  |
| 1270 | 179101548 | resistor0201 220KΩ ±5% 0.05W RoHS        | 1  |

|      |           |                                                     |   |
|------|-----------|-----------------------------------------------------|---|
| 1275 | 179082607 | resistor0402 24K $\Omega$ $\pm$ 1% 0.063W RoHS      | 1 |
| 1280 | 188127334 | SMD RES.0201 680KOHM 5% 50MW 250PPM                 | 1 |
| 1285 | 179101308 | resistor0201 100 $\Omega$ $\pm$ 5% 0.05W RoHS       | 1 |
| 1290 | 188126923 | SMD RES.0201 150KOHM 5% 50MW 250PPM                 | 2 |
| 1295 | 179101423 | resistor0201 10K $\Omega$ $\pm$ 5% 0.05W RoHS       | 4 |
| 1300 | 179055879 | array res. RoHS 0402*4 100 $\Omega$ $\pm$ 5% 0.063W | 5 |
| 1305 | 189796360 | WCDMA band VIII Coupler 1*0.5*0.4 RoHS              | 1 |
| 1310 | 189781773 | SMD ISOLATOR WCDMA BANDE8 RoHS                      | 1 |
| 1315 | 179132382 | WCDMA band I Coupler 1*0.5*0.4                      | 1 |
| 1320 | 179132361 | WCDMA band I Isolator 2020                          | 1 |
| 1325 | 179132308 | power detector LMH2100TMX 6Bump RoHS                | 1 |
| 1330 | 189816906 | SMD IC SKY77521 FEM QUAD BAND MCM30                 | 1 |
| 1335 | 179069906 | NTC Resistor0402 10k $\Omega$ $\pm$ 1%              | 1 |
| 1340 | 179086345 | varistor(for USB ESD protection) RoHS               | 3 |
| 1345 | 189648238 | SMD CRYSTAL UNIT 32.768KZ 20/-40+85 RoH             | 1 |
| 1350 | 179123049 | OSC 26MHz 2520 2.8V                                 | 1 |
| 1355 | 179132139 | WCDMA transceiver RF3300 HVQFN56 RoHS               | 1 |
| 1360 | 188127058 | SMD RES 0201 2.7KOHM 5% 50MW 250PPM                 | 1 |
| 1365 | 179082628 | resistor0402 27 $\Omega$ $\pm$ 5% 0.063W RoHS       | 2 |
| 1370 | 179086556 | resistor0402 270 $\Omega$ $\pm$ 5% 0.063W RoHS      | 4 |
| 1375 | 179134089 | resistor 0603 0.1 $\Omega$ $\pm$ 1% 0.1W RoHS       | 1 |
| 1380 | 379026325 | resistor0402 180K $\Omega$ $\pm$ 1% 0.063W RoHS     | 1 |
| 1385 | 179068334 | resistor0402 4.7K $\Omega$ $\pm$ 5% 0.063W RoHS     | 1 |
| 1390 | 179137217 | resistor 0402 0.1 $\Omega$ $\pm$ 1% 0.125W          | 5 |
| 1395 | 188126709 | SMD RES.0201 10 OHM 5% 50MW 250PPM Ro               | 2 |
| 1400 | 179106415 | resistor0201 56 $\Omega$ $\pm$ 5% 0.05W RoHS        | 3 |
| 1405 | 179105033 | resistor0201 330 $\Omega$ $\pm$ 5% 0.05W RoHS       | 1 |
| 1410 | 189741279 | SMD RES.0201 470KOHM 1% 50MW 250PPM                 | 2 |
| 1415 | 179104177 | resistor0201 47 $\Omega$ $\pm$ 5% 0.05W RoHS        | 3 |
| 1420 | 189407877 | SMD THMS.CTN 0402 4.7KOHM 5% 150MW R                | 2 |
| 1425 | 179101329 | resistor0201 470 $\Omega$ $\pm$ 5% 0.05W RoHS       | 1 |
| 1430 | 188454179 | SMD CAPA.0402COG 6.8pf +-0.25pF 50V RoH             | 1 |
| 1435 | 188126994 | RES.0201 RC41 220 OHM 5% 50MW 250PPM                | 1 |
| 1440 | 179101444 | resistor0201 15K $\Omega$ $\pm$ 5% 0.05W RoHS       | 1 |
| 1445 | 179101465 | resistor0201 47K $\Omega$ $\pm$ 5% 0.05W RoHS       | 3 |
| 1450 | 179068199 | resistor0402 100 $\Omega$ $\pm$ 5% 0.063W RoHS      | 1 |
| 1455 | 379025779 | resistor0402 10k $\Omega$ $\pm$ 1% 0.063W RoHS      | 1 |
| 1460 | 188127016 | SMD RES 0201 22KOHM 5% 50MW 250PPM R                | 1 |
| 1465 | 188126986 | SMD RES.0201 22 OHM 5% 50MW 250PPM Ro               | 2 |
| 1470 | 179073814 | resistor 0402 220 $\Omega$ $\pm$ 5% 0.063W RoHS     | 1 |
| 1475 | 179074618 | resistor 0402 75 $\Omega$ $\pm$ 1% 0.063W RoHS      | 1 |
| 1480 | 179074014 | capacitor 0402 33NF $\pm$ 10% DC16V RoHS            | 2 |
| 1485 | 188609464 | SMD CAPA.0603 X5R 1UF 10% 25V RoHS                  | 1 |
| 1490 | 179112992 | capacitor0402 100NF 10% X5R DC25V RoHS              | 1 |

|      |           |                                         |    |
|------|-----------|-----------------------------------------|----|
| 1495 | 188580916 | SMD CAPA.0402 COG 4.7PF +-0.1PF 50V RoH | 2  |
| 1500 | 179068165 | capacitor0402 56PF ±5% DC50V RoHS       | 1  |
| 1505 | 179068420 | capacitor0402 220NF ±10%DC6.3V RoHS     | 3  |
| 1510 | 179068157 | capacitor0402 47PF ±5% DC50V RoHS       | 1  |
| 1515 | 179068136 | capacitor0402 22PF ±5% DC50V RoHS       | 8  |
| 1520 | 179075566 | capacitor 0402 33PF ±5% DC50V RoHS      | 1  |
| 1525 | 379132701 | capacitor0402 2.2PF ±0.1pF DC50V RoHS   | 1  |
| 1530 | 179066244 | capacitor0402 X5R 1NF 5% DC50V RoHS     | 2  |
| 1535 | 179101085 | C 0201 47PF 5% COG DC25V RoHS           | 1  |
| 1540 | 188605643 | SMD CAPA 0603 X5R 2.2UF 10% 16V RoHS    | 2  |
| 1545 | 179101064 | C 0201 33PF 5% COG DC25V RoHS           | 4  |
| 1550 | 179101209 | C 0201 47nF 10% X5R DC6.3V RoHS         | 1  |
| 1555 | 185639027 | SMD CAPA.0402 CERA.X7R 3.3NF5% 50V      | 1  |
| 1560 | 188127470 | COND.CMS 0201 X5R 2.2NF 10% 16V RoHS    | 1  |
| 1565 | 189172304 | SMD.TA.CAPA. 33UF 20% 10V CASE A RoHS   | 1  |
| 1570 | 179068115 | capacitor0402 15PF ±5% DC50V RoHS       | 1  |
| 1575 | 179100989 | C 0201 10PF 5% COG DC25V RoHS           | 3  |
| 1580 | 179101001 | C 0201 12PF 5% COG DC25V RoHS           | 1  |
| 1585 | 179068397 | capacitor0402 10NF ±10% DC16V RoHS      | 3  |
| 1590 | 189649136 | SMD CAP.0201COG 8.2PF +/-0.5PF 25V RoHS | 1  |
| 1595 | 179063628 | C 0603 10UF 20% X5R DC6.3V RoHS         | 9  |
| 1600 | 179101105 | C 0201 100PF 5% COG DC25V RoHS          | 5  |
| 1605 | 179134480 | C 0402 1uF±10% X5R DC10V RoHS           | 15 |
| 1610 | 189329086 | COND.CMS 0402 X5R 2.2UF 20% 6.3V RoHS   | 10 |
| 1615 | 179002745 | tan capacitor2.05*1.35*1.5 10UF±20% 10V | 1  |
| 1620 | 179068462 | C 0603 4.7uF 10% X5R DC6.3V RoHS        | 9  |
| 1625 | 179104094 | Capacitor0201 1nF ±10% DC16V RoHS       | 6  |
| 1630 | 287287252 | RF shielding frame Runur                | 1  |
| 1635 | 287287202 | BB shielding frame Runur                | 1  |
| 1640 | 287295262 | runur-mic-shielding                     | 1  |
| 1645 | 179101043 | C 0201 22PF 5% COG DC25V RoHS           | 53 |
| 1650 | 179101220 | C 0201 100nF 10% X5R DC6.3V RoHS        | 72 |
| 1655 | 179068095 | capacitor0402 100NF ±10% DC10V RoHS     | 8  |
| 1660 | 189973991 | CAP.TA.SMD 4.7UF 20% 10V BOIT.R RoHS    | 4  |
| 1665 | 179074118 | Capacitor RoHS 0402 3.9PF ±0.25PF DC50V | 2  |
| 1670 | 179046453 | capacitor0402 3.3PF ±0.1pF DC50V RoHS   | 1  |
| 1675 | 179001321 | capacitor0402 5PF ±0.25pF DC50V RoHS    | 1  |
| 1680 | 179074564 | capacitor 0402 8.2PF ±0.5pF DC50V RoHS  | 1  |
| 1685 | 179133298 | Tan cap 47UF ±20% 4V 2.0*1.25*1.0       | 2  |
| 1690 | 179068082 | capacitor0402 10PF ±0.5pF DC50V RoHS    | 2  |
| 1695 | 179080265 | capacitor 0402 1UF ±10% DC6.3V RoHS     | 24 |
| 1700 | 179001730 | capacitor0402 15NF ±10% RoHS            | 1  |
| 1705 | 179101189 | Capacitor0201 10nF ±10% DC10V RoHS      | 8  |
| 1710 | 179074671 | capacitor 0603 1UF ±10% DC16V RoHS      | 2  |

|      |           |                                          |    |
|------|-----------|------------------------------------------|----|
| 1715 | 179068285 | resistor0402 0Ω ±5% 0.063W RoHS          | 12 |
| 1720 | 179039507 | INDUCTOR0402 7.5nH ±5%                   | 1  |
| 1725 | 179081910 | Inductor0402 15NH ±5% RoHS               | 1  |
| 1730 | 188180208 | SMD INDUCTOR 0402 27NH 5% RoHS           | 1  |
| 1735 | 179076336 | inductor0402 1.5NH ±0.3nH RoHS           | 1  |
| 1740 | 179074069 | Inductor 0402 100NH ±5% RoHS             | 2  |
| 1745 | 179084086 | inductor0402 2.7NH ±0.3nH RoHS           | 3  |
| 1750 | 189683071 | EMI SUPPRESS. FILTER 0402 120 OHM RoHS   | 2  |
| 1755 | 179135002 | Inductor3015 4.7uH 20% 1020mA 0.12ohm    | 1  |
| 1760 | 179135044 | Inductor2016 4.7uH 20% 300mA 0.8ohm      | 1  |
| 1765 | 179074056 | inductor 0402 6.8NH ±0.5nH               | 1  |
| 1770 | 179066111 | inductor0402 8.2NH ±0.25nH RoHS          | 1  |
| 1775 | 189555058 | SMD INDUCTOR 3012 3.3UH 20% 910MA RoH    | 1  |
| 1780 | 179137374 | Charger IC ISL6298 QFN16 4*4 RoHS        | 1  |
| 1785 | 179078129 | Single 2-input AND gate RoHS             | 1  |
| 1790 | 189390689 | IC.LOG.SMD NC7WZ04DUAL INVERT. UPAK6     | 2  |
| 1795 | 179132655 | Analog Switch dual SP3T ISL54217 UTQFN   | 1  |
| 1800 | 179133079 | High speed USB transceiver ISP1704AET R  | 1  |
| 1805 | 189244712 | SMD FILTER EMI 0805 300MHZ 25V RoHS      | 3  |
| 1810 | 179074709 | Filter EXC24CP121U RoHS                  | 1  |
| 1815 | 179132267 | FB 0603 120Ω 100MHZ 400mA RoHS           | 2  |
| 1820 | 179077268 | inductor RoHS 0402 5.6NH ±0.3nH 200mA    | 1  |
| 1825 | 179073760 | inductor RoHS 0402 3.3NH ±0.3nH          | 1  |
| 1830 | 188973244 | SMD INDUCTOR 0603 120NH 5% 300MA RoH     | 1  |
| 1835 | 179045906 | high-Q inductor0603 180NH ±2% RoHS       | 1  |
| 1840 | 179076170 | diode Schot RB520G-30FJT2R RoHS          | 2  |
| 1845 | 179133699 | WCDMA band VIII Duplexer 3025            | 1  |
| 1850 | 189485524 | SMD SAW FILTER DUPLEXER1900/2100MHZ      | 1  |
| 1855 | 179080327 | ESD protection chip RoHS                 | 2  |
| 1860 | 179095972 | TVS 12V SOD523 RoHS                      | 3  |
| 1865 | 179059608 | schottky Diode 1.6*0.8*0.6 RoHS          | 1  |
| 1870 | 179106986 | C 0201 27PF 5% COG DC25V RoHS            | 1  |
| 1875 | 179083894 | capacitor0402 10NF ±10% DC25V RoHS       | 3  |
| 1880 | 179101022 | C 0201 15PF 5% COG DC25V RoHS            | 3  |
| 1885 | 179100512 | Schotty Diode NSR0320MW2T1G RoHS         | 1  |
| 1890 | 179070574 | diode SCHOT. RB751S-40TE61 RoHS          | 1  |
| 1895 | 179113379 | single TVS 5V SOD-923 RoHS               | 4  |
| 1900 | 189825541 | SMD BAND PASS FILTER BLUETOOTH RoHS      | 1  |
| 1905 | 189492206 | SMD LOW-LOSS FILTER 1575.42MHZ B9415F    | 1  |
| 1910 | 189882244 | SMD SAW FILTER FOR GPS 1575.5MHZ RoH     | 1  |
| 1915 | 188650007 | SMDCOAX.CONN.1CT.50 OHM WITH SWITCH      | 1  |
| 1920 | 179092236 | filte DLM11GN601SZ2D RoHS                | 2  |
| 1925 | 189788371 | SMD SAW FILTER TX WCDMA 800MHZ RoHS      | 1  |
| 1930 | 179133678 | ESD protect4channe dual voltage TDFN-8 R | 1  |

|      |           |                                       |   |
|------|-----------|---------------------------------------|---|
| 1935 | 188620413 | ESD PROTECTION DIODE RSA1.6J4 EMD5 R  | 2 |
| 1940 | 189774596 | SMD DUAL SAW FILTER 800/900MHZ RoHS   | 1 |
| 1945 | 189788433 | SMD DUAL SAW FILTER 1800/1900MHZ RoHS | 1 |
| 1950 | 189433517 | SMD SAW FILTER 1950MHZ RoHS           | 1 |
| 1955 | 179076419 | high-Q inductor0402 9.1nH ±0.3nH RoHS | 1 |
| 1960 | 179053643 | resistor0402 2KΩ ±1% RoHS             | 1 |
| 1965 | 189757897 | IC SMD NCP347 PROTECT TENSION WDFN    | 1 |
| 1970 | 287287265 | RF shielding cover Runur              | 1 |
| 1980 | 287287231 | BB shielding cover Runur              | 1 |