

RF Exposure Report

Report No.: SABEEO-WTW-P21020573B

FCC ID: MADG2021-49-01B

Test Model: G2021-49-01B

Received Date: Sep. 13, 2021

Test Date: Sep. 14 ~ Sep. 28, 2021

Issued Date: Oct. 26, 2021

Applicant: Microelectronics Technology Inc.

Address: No. 1, Innovation Road II, Hsinchu Science Park, Hsinchu 300, Taiwan,
R.O.C.

Issued By: Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan
Branch
Lin Kou Laboratories

Lab Address: No. 47-2, 14th Ling, Chia Pau Vil., Lin Kou Dist., New Taipei City,
Taiwan

Test Location: No. 19, Hwa Ya 2nd Rd., Wen Hwa Vil., Kwei Shan Dist., Taoyuan City
33383, Taiwan

**FCC Registration /
Designation Number:** 788550 / TW0003



This report is for your exclusive use. Any copying or replication of this report to or for any other person or entity, or use of our name or trademark, is permitted only with our prior written permission. This report sets forth our findings solely with respect to the test samples identified herein. The results set forth in this report are not indicative or representative of the quality or characteristics of the lot from which a test sample was taken or any similar or identical product unless specifically and expressly noted. Our report includes all of the tests requested by you and the results thereof based upon the information that you provided to us. You have 60 days from date of issuance of this report to notify us of any material error or omission caused by our negligence, provided, however, that such notice shall be in writing and shall specifically address the issue you wish to raise. A failure to raise such issue within the prescribed time shall constitute your unqualified acceptance of the completeness of this report, the tests conducted and the correctness of the report contents. Unless specifically mentioned, the uncertainty of measurement has been explicitly taken into account to declare the compliance or non-compliance to the specification.

Table of Contents

Release Control Record	3
1 Certificate of Conformity	4
2 RF Exposure	5
2.1 Limits for Maximum Permissible Exposure (MPE).....	5
2.2 MPE Calculation Formula	5
2.3 Classification	5
3 General Description of Antenna Gain	6
4 Calculation Result of Maximum Conducted Power	6

Release Control Record

Issue No.	Description	Date Issued
SABEOO-WTW-P21020573B	Original release	Oct. 26, 2021

1 Certificate of Conformity

Product: Dual Mid Band RU

Brand: MTI

Test Model: G2021-49-01B

Sample Status: Engineering sample

Applicant: Microelectronics Technology Inc.

Test Date: Sep. 14 ~ Sep. 28, 2021

Standards: FCC Part 2 (Section 2.1091)

References Test Guidance: KDB 447498 D01 General RF Exposure Guidance v06

The above equipment has been tested by **Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch**, and found compliance with the requirement of the above standards. The test record, data evaluation & Equipment Under Test (EUT) configurations represented herein are true and accurate accounts of the measurements of the sample's RF characteristics under the conditions specified in this report.

Prepared by : Pettie Chen , **Date:** Oct. 26, 2021
Pettie Chen / Senior Specialist

Approved by : Bruce Chen , **Date:** Oct. 26, 2021
Bruce Chen / Senior Engineer

2 RF Exposure

2.1 Limits for Maximum Permissible Exposure (MPE)

Frequency Range (MHz)	Electric Field Strength (V/m)	Magnetic Field Strength (A/m)	Power Density (mW/cm ²)	Average Time (minutes)
Limits For General Population / Uncontrolled Exposure				
0.3-1.34	614	1.63	(100)*	30
1.34-30	824/f	2.19/f	(180/f ²)*	30
30-300	27.5	0.073	0.2	30
300-1500	f/1500	30
1500-100,000	1.0	30

f = Frequency in MHz; *Plane-wave equivalent power density

2.2 MPE Calculation Formula

$$Pd = (Pout * G) / (4 * pi * r^2)$$

where

Pd = power density in mW/cm²

Pout = output power to antenna in mW

G = gain of antenna in linear scale

pi = 3.1416

r = distance between observation point and center of the radiator in cm

2.3 Classification

The antenna of this product, under normal use condition, is at least 487cm away from the body of the user. So, this device is classified as fixed station and installations by professional service personnel device.

3 General Description of Antenna Gain

The antennas provided to the EUT, please refer to the following table:

Antenna Type	Directional Cross-Polarized Sector antenna with : Band n66 Gain = 15 dBi Band n70 Gain = 17 dBi
Antenna Connector	4x4.3-10 Female

Note:

1. The above EUT information is declared by manufacturer and for more detailed features description, please refer to the manufacturer's specifications or user's manual.
2. Based on the maximum RF power (conducted & EIRP) listed in this report, considerations pertaining to the maximum allowed EIRP (conducted power level), signal type and antenna gain should be considered for each installation.

4 Calculation Result of Maximum Conducted Power

For 5G NR Band n66

5MHz (Single Carrier): 16QAM

Frequency Band (MHz)	Conducted Average Power - Per Chain (dBm/MHz)				Max Conducted Average Power - Total (dBm/MHz)	Directional Gain (dBi)	Max EIRP Power (dBm/MHz)	Max EIRP Power (mW/MHz)	Distance (cm)	Power Density (mW/cm ²)	Limit (mW/cm ²)
	ANT0	ANT1	ANT2	ANT3							
2155	40.68	40.62	40.68	40.63	46.67	15	61.67	1470005.098	487	0.493	1

For 5G NR Band n70

5MHz (Single Carrier): 16QAM

Frequency Band (MHz)	Conducted Average Power - Per Chain (dBm/MHz)				Max Conducted Average Power - Total (dBm/MHz)	Directional Gain (dBi)	Max EIRP Power (dBm/MHz)	Max EIRP Power (mW/MHz)	Distance (cm)	Power Density (mW/cm ²)	Limit (mW/cm ²)
	ANT0	ANT1	ANT2	ANT3							
2007.5	38.80	38.83	38.66	38.70	44.77	17	61.77	1638110.088	487	0.504	1

Note:

1. EIRP Power = Conducted Power+ Antenna gain
2. Determining compliance based on the results of the compliance measurement, not taking into account measurement instrumentation uncertainty.

Conclusion:

The formula of calculated the MPE is:

$CPD1 / LPD1 + CPD2 / LPD2 + \dots \text{etc.} < 1$

CPD = Calculation power density

LPD = Limit of power density

Band n66 + Band n70 = $0.493/1 + 0.504/1 = 0.997$

Therefore the maximum calculations of above situations are less than the “1” limit.

--- END ---