



# RF EXPOSURE REPORT

**REPORT NO.:** SA140515E03B

**MODEL NO.:** J20H086

**FCC ID:** MCLJ20H086

**RECEIVED:** May 16, 2014

**TESTED:** May 16, 2014 to June 11, 2015

**ISSUED:** July 24, 2015

**APPLICANT:** HON HAI PRECISION IND.CO.,LTD

**ADDRESS:** 5F-1, Hsin-An Road, Hsinchu, Science  
Industrial Park, Taiwan, R.O.C.

**ISSUED BY:** Bureau Veritas Consumer Products Services  
(H.K.) Ltd., Taoyuan Branch Hsin Chu Laboratory

**LAB ADDRESS :** No. 81-1, Lu Liao Keng, 9th Ling, Wu Lung Tsuen,  
Chiung Lin Hsiang, Hsin Chu Hsien 307, Taiwan,  
R.O.C.

**TEST LOCATION (1):** No. 81-1, Lu Liao Keng, 9th Ling, Wu Lung Tsuen,  
Chiung Lin Hsiang, Hsin Chu Hsien 307, Taiwan,  
R.O.C.

**TEST LOCATION (2):** No. 49, Ln. 206, Wende Rd., Shangshan Tsuen,  
Chiung Lin Hsiang, Hsin Chu Hsien 307, Taiwan,  
R.O.C.

This report should not be used by the client to claim product certification, approval, or endorsement by any government agencies.

This report is for your exclusive use. Any copying or replication of this report to or for any other person or entity, or use of our name or trademark, is permitted only with our prior written permission. This report sets forth our findings solely with respect to the test samples identified herein. The results set forth in this report are not indicative or representative of the quality or characteristics of the lot from which a test sample was taken or any similar or identical product unless specifically and expressly noted. Our report includes all of the tests requested by you and the results thereof based upon the information that you provided to us. You have 60 days from date of issuance of this report to notify us of any material error or omission caused by our negligence, provided, however, that such notice shall be in writing and shall specifically address the issue you wish to raise. A failure to raise such issue within the prescribed time shall constitute your unqualified acceptance of the completeness of this report, the tests conducted and the correctness of the report contents. Unless specific mention, the uncertainty of measurement has been explicitly taken into account to declare the compliance or non-compliance to the specification



## TABLE OF CONTENTS

RELEASE CONTROL RECORD.....	3
1. CERTIFICATION.....	4
2. RF EXPOSURE LIMIT .....	5
3. MPE CALCULATION FORMULA.....	5
4. CLASSIFICATION.....	5
5. ANTENNA GAIN .....	6
6. CALCULATION RESULT OF MAXIMUM CONDUCTED POWER .....	12



## RELEASE CONTROL RECORD

ISSUE NO.	REASON FOR CHANGE	DATE ISSUED
SA140515E03B	Original release	July 24, 2015



A D T

## 1. CERTIFICATION

**PRODUCT:** WLAN Module  
**BRAND NAME:** FOXCONN  
**MODEL NO.:** J20H086  
**TEST SAMPLE:** ENGINEERING SAMPLE  
**APPLICANT:** HON HAI PRECISION IND.CO.,LTD  
**TESTED DATE:** May 16, 2014 to June 11, 2015  
**STANDARDS:** FCC Part 2 (Section 2.1091)  
KDB 447498 D03  
IEEE C95.1

The above equipment (Model: J20H086) has been tested by **Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch**, and found compliance with the requirement of the above standards. The test record, data evaluation & Equipment Under Test (EUT) configurations represented herein are true and accurate accounts of the measurements of the sample's EMC characteristics under the conditions specified in this report.

**Prepared by :** Phoenix Huang , **Date:** July 24, 2015  
( Phoenix Huang, Specialist )

**Approved by :** May Chen , **Date:** July 24, 2015  
( May Chen, Manager )

## 2. RF EXPOSURE LIMIT

### LIMITS FOR MAXIMUM PERMISSIBLE EXPOSURE (MPE)

FREQUENCY RANGE (MHz)	ELECTRIC FIELD STRENGTH (V/m)	MAGNETIC FIELD STRENGTH (A/m)	POWER DENSITY (mW/cm <sup>2</sup> )	AVERAGE TIME (minutes)
<b>LIMITS FOR GENERAL POPULATION / UNCONTROLLED EXPOSURE</b>				
300-1500	...	...	F/1500	30
1500-100,000	...	...	1.0	30

F = Frequency in MHz

### 3. MPE CALCULATION FORMULA

$$P_d = (P_{out} * G) / (4 * \pi * r^2)$$

where

$P_d$  = power density in mW/cm<sup>2</sup>

$P_{out}$  = output power to antenna in mW

G = gain of antenna in linear scale

$\pi$  = 3.1416

r = distance between observation point and center of the radiator in cm

### 4. CLASSIFICATION

The antenna of this product, under normal use condition, is at least 20cm away from the body of the user. So, this device is classified as **Mobile Device**.

## 5. ANTENNA GAIN

The antennas provided to the EUT, please refer to the following table:

For WLAN								
Ant. No.	Transmitter Circuit	Brand	Ant. Model	Ant. Gain(dBi) <Including cable loss>	Freq. range (GHz)	Ant. Type	Connector Type	Cable Length (mm)
1	Chain (0)	Foxconn WiFi	J20H086	2.81	2.4	PCB printing	NA	NA
				3.03	2.45			
				3.40	2.5			
				3.47	5.15			
				3.2	5.45			
				3.79	5.85			
2	Chain (1)	Foxconn WiFi	J20H086	2.93	2.4	PCB printing	NA	NA
				2.91	2.45			
				2.76	2.5			
				2.96	5.15			
				2.57	5.45			
				2.82	5.85			
For Bluetooth								
Ant. No.	Brand	Ant. Model	Ant. Gain(dBi) <Excluding cable loss>	Freq. range (GHz)	Ant. Type	Connector Type	Cable Loss (dB)	Cable Length (mm)
3	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	0.86	220 (Model No.: 822EKQ2200000001H1)
				2.45			0.89	
				2.5			0.89	
4	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	0.89	230 (Model No.: 822EKQ2300000001H1)
				2.45			0.92	
				2.5			0.92	
5	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	0.92	240 (Model No.: 822EKQ2400000001H1)
				2.45			0.95	
				2.5			0.95	

Ant. No.	Brand	Ant. Model	Ant. Gain(dBi) <Excluding cable loss>	Freq. range (GHz)	Ant. Type	Connector Type	Cable Loss (dB)	Cable Length (mm)
6	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	0.95	250 (Model No.: 822EKQ2500000001H1)
				2.45			0.98	
				2.5			0.98	
7	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	0.98	260 (Model No.: 822EKQ2600000001H1)
				2.45			1.00	
				2.5			1.01	
8	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	1.01	270 (Model No.: 822EKQ2700000001H1)
				2.45			1.03	
				2.5			1.04	
9	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	1.04	280 (Model No.: 822EKQ2800000001H1)
				2.45			1.06	
				2.5			1.06	
10	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	1.07	290 (Model No.: 822EKQ2900000001H1)
				2.45			1.09	
				2.5			1.09	
11	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	1.10	300 (Model No.: 822EKQ3000000001H1)
				2.45			1.12	
				2.5			1.12	
12	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	1.13	310 (Model No.: 822EKQ3100000001H1)
				2.45			1.15	
				2.5			1.15	
13	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	1.16	320 (Model No.: 822EKQ3200000001H1)
				2.45			1.18	
				2.5			1.18	
14	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	1.19	330 (Model No.: 822EKQ3300000001H1)
				2.45			1.21	
				2.5			1.21	
15	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	1.21	340 (Model No.: 822EKQ3400000001H1)
				2.45			1.23	
				2.5			1.24	

Ant. No.	Brand	Ant. Model	Ant. Gain(dBi) <Excluding cable loss>	Freq. range (GHz)	Ant. Type	Connector Type	Cable Loss (dB)	Cable Length (mm)
16	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	1.24	350 (Model No.: 822EKQ3500000001H1)
				2.45			1.26	
				2.5			1.27	
17	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	1.27	360 (Model No.: 822EKQ3600000001H1)
				2.45			1.29	
				2.5			1.30	
18	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	1.30	370 (Model No.: 822EKQ3700000001H1)
				2.45			1.32	
				2.5			1.33	
19	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	1.33	380 (Model No.: 822EKQ3800000001H1)
				2.45			1.35	
				2.5			1.36	
20	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	1.36	390 (Model No.: 822EKQ3900000001H1)
				2.45			1.38	
				2.5			1.39	
21	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	1.39	400 (Model No.: 822EKQ4000000001H1)
				2.45			1.41	
				2.5			1.41	
22	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	1.42	410 (Model No.: 822EKQ4100000001H1)
				2.45			1.44	
				2.5			1.44	
23	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	1.45	420 (Model No.: 822EKQ4200000001H1)
				2.45			1.46	
				2.5			1.47	
24	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	1.48	430 (Model No.: 822EKQ4300000001H1)
				2.45			1.49	
				2.5			1.50	
25	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	1.51	440 (Model No.: 822EKQ4400000001H1)
				2.45			1.52	
				2.5			1.53	





Ant. No.	Brand	Ant. Model	Ant. Gain(dBi) <Excluding cable loss>	Freq. range (GHz)	Ant. Type	Connector Type	Cable Loss (dB)	Cable Length (mm)
26	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	1.54	450 (Model No.: 822EKQ4500000001H1)
				2.45			1.55	
				2.5			1.56	
27	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	0.88	220 (Model No.: 822MN82200000001H1)
				2.45			0.93	
				2.5			0.93	
28	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	0.91	230 (Model No.: 822MN82300000001H1)
				2.45			0.95	
				2.5			0.96	
29	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	0.94	240 (Model No.: 822MN82400000001H1)
				2.45			0.98	
				2.5			0.99	
30	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	0.97	250 (Model No.: 822MN82500000001H1)
				2.45			1.01	
				2.5			1.02	
31	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	1.00	260 (Model No.: 822MN82600000001H1)
				2.45			1.04	
				2.5			1.05	
32	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	1.03	270 (Model No.: 822MN82700000001H1)
				2.45			1.07	
				2.5			1.08	
33	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	1.07	280 (Model No.: 822MN82800000001H1)
				2.45			1.10	
				2.5			1.11	
34	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	1.10	290 (Model No.: 822MN82900000001H1)
				2.45			1.13	
				2.5			1.14	
35	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	1.13	300 (Model No.: 822MN83000000001H1)
				2.45			1.16	
				2.5			1.17	



A D T

Ant. No.	Brand	Ant. Model	Ant. Gain(dBi) <Excluding cable loss>	Freq. range (GHz)	Ant. Type	Connector Type	Cable Loss (dB)	Cable Length (mm)
36	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	1.16	310 (Model No.: 822MN83100000001H1)
				2.45			1.19	
				2.5			1.20	
37	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	1.19	320 (Model No.: 822MN83200000001H1)
				2.45			1.22	
				2.5			1.23	
38	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	1.22	330 (Model No.: 822MN83300000001H1)
				2.45			1.25	
				2.5			1.26	
39	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	1.25	340 (Model No.: 822MN83400000001H1)
				2.45			1.29	
				2.5			1.30	
40	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	1.28	350 (Model No.: 822MN83500000001H1)
				2.45			1.32	
				2.5			1.33	
41	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	1.31	360 (Model No.: 822MN83600000001H1)
				2.45			1.35	
				2.5			1.36	
42	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	1.34	370 (Model No.: 822MN83700000001H1)
				2.45			1.38	
				2.5			1.39	
43	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	1.37	380 (Model No.: 822MN83800000001H1)
				2.45			1.41	
				2.5			1.42	
44	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	1.40	390 (Model No.: 822MN83900000001H1)
				2.45			1.44	
				2.5			1.45	
45	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	1.44	400 (Model No.: 822MN84000000001H1)
				2.45			1.47	
				2.5			1.48	



A D T

Ant. No.	Brand	Ant. Model	Ant. Gain(dBi) <Excluding cable loss>	Freq. range (GHz)	Ant. Type	Connector Type	Cable Loss (dB)	Cable Length (mm)
46	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	1.47	410 (Model No.: 822MN8410000001H1)
				2.45			1.50	
				2.5			1.51	
47	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	1.50	420 (Model No.: 822MN8420000001H1)
				2.45			1.53	
				2.5			1.54	
48	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	1.53	430 (Model No.: 822MN8430000001H1)
				2.45			1.56	
				2.5			1.57	
49	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	1.56	440 (Model No.: 822MN8440000001H1)
				2.45			1.59	
				2.5			1.60	
50	SONY	BT-1504 (1-980-185-11)	1.71	2.4	PCB	MHF	1.59	450 (Model No.: 822MN8450000001H1)
				2.45			1.62	
				2.5			1.63	

Note: From the above antennas for BT used, the **Ant. No.: 3** (BT max antenna gain: 0.85dBi) was selected as representative value for the test and its data was recorded in this report.

## 6. CALCULATION RESULT OF MAXIMUM CONDUCTED POWER

For WLAN: 15.247(2.4GHz)

### 802.11b

FREQUENCY (MHz)	CONDUCTED POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/cm <sup>2</sup> )	LIMIT (mW/cm <sup>2</sup> )
2412 - 2462	325.835	6.18	20	0.26898	1.00

NOTE: Directional gain =  $10 \log[(10^{G1/20} + 10^{G2/20})^2 / 2] = 6.18\text{dBi}$ .

### 802.11g

FREQUENCY (MHz)	CONDUCTED POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/cm <sup>2</sup> )	LIMIT (mW/cm <sup>2</sup> )
2412 - 2462	709.261	6.18	20	0.58551	1.00

NOTE: Directional gain =  $10 \log[(10^{G1/20} + 10^{G2/20})^2 / 2] = 6.18\text{dBi}$ .

### 802.11n (HT20)

FREQUENCY BAND (MHz)	CONDUCTED POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/cm <sup>2</sup> )	LIMIT (mW/cm <sup>2</sup> )
2412 - 2462	700.427	6.18	20	0.57822	1.00

NOTE: Directional gain =  $10 \log[(10^{G1/20} + 10^{G2/20})^2 / 2] = 6.18\text{dBi}$ .

**For WLAN: 15.407(5GHz)**

**802.11a**

FREQUENCY (MHz)	CONDUCTED POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/cm <sup>2</sup> )	LIMIT (mW/cm <sup>2</sup> )
5180 - 5240, 5260 - 5320, 5500 - 5700 & 5745 - 5825	233.91	6.33	20	0.19988	1.00

**NOTE:** Directional gain =  $10 \log[(10^{G1/20} + 10^{G2/20})^2 / 2] = 6.33\text{dBi}$ .

**802.11n (HT20)**

FREQUENCY (MHz)	CONDUCTED POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/cm <sup>2</sup> )	LIMIT (mW/cm <sup>2</sup> )
5180 - 5240, 5260 - 5320, 5500 - 5700 & 5745 - 5825	328.794	6.33	20	0.28097	1.00

**NOTE:** Directional gain =  $10 \log[(10^{G1/20} + 10^{G2/20})^2 / 2] = 6.33\text{dBi}$ .

**802.11n (HT40)**

FREQUENCY (MHz)	CONDUCTED POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/cm <sup>2</sup> )	LIMIT (mW/cm <sup>2</sup> )
5190 - 5230, 5270 - 5310, 5510 - 5670 & 5755 - 5795	145.631	6.33	20	0.12445	1.00

**NOTE:** Directional gain =  $10 \log[(10^{G1/20} + 10^{G2/20})^2 / 2] = 6.33\text{dBi}$ .

**For Bluetooth:**

**BT-EDR (GFSK)**

FREQUENCY (MHz)	CONDUCTED POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/ cm <sup>2</sup> )	LIMIT (mW/cm <sup>2</sup> )
2402-2480	6.714	0.85	20	0.00162	1.00

**BT-EDR (8DPSK)**

FREQUENCY (MHz)	CONDUCTED POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/ cm <sup>2</sup> )	LIMIT (mW/cm <sup>2</sup> )
2402-2480	7.907	0.85	20	0.00191	1.00

**BT-LE (GFSK)**

FREQUENCY (MHz)	CONDUCTED POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/ cm <sup>2</sup> )	LIMIT (mW/cm <sup>2</sup> )
2402 - 2480	12.05	0.85	20	0.00292	1.00

**CONCLUSION:**

Both of the Bluetooth and WLAN can transmit simultaneously, the formula of calculated the MPE is:

$$CPD_1 / LPD_1 + CPD_2 / LPD_2 + \dots \text{etc.} < 1$$

**CPD = Calculation power density**

**LPD = Limit of power density**

**For WLAN (2.4G) and Bluetooth:**

Therefore, the worst-case situation is  $0.58551 / 1 + 0.00292 / 1 = 0.588$ , which is less than "1". This confirmed that the device comply with FCC 1.1310 MPE limit.

**For WLAN (5G) and Bluetooth:**

Therefore, the worst-case situation is  $0.28097 / 1 + 0.00292 / 1 = 0.284$ , which is less than "1". This confirmed that the device comply with FCC 1.1310 MPE limit.

--- END ---