

Mode	TX channel 1413	Frequency Range	Below 1000 MHz
------	-----------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	91.77	33.73	-58.18	-1.04	-59.23	-13	-46.23
2	237.13	34.95	-60.41	3.84	-56.57	-13	-43.57
3	287.14	32.78	-62.69	3.78	-58.90	-13	-45.90
4	345.23	32.66	-65.03	3.61	-61.42	-13	-48.42
5	471.25	35.27	-61.91	2.84	-59.07	-13	-46.07
6	738.29	29.72	-66.65	1.02	-65.62	-13	-52.62

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	69.43	31.28	-56.35	-4.91	-61.26	-13	-48.26
2	94.39	33.21	-58.59	-1.00	-59.60	-13	-46.60
3	128.6	27.30	-64.05	-1.23	-65.29	-13	-52.29
4	238.71	30.96	-64.40	3.82	-60.58	-13	-47.58
5	510.39	33.50	-61.89	2.81	-59.08	-13	-46.08
6	609.07	33.51	-61.18	1.78	-59.40	-13	-46.40

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 1513	Frequency Range	Below 1000 MHz
------	-----------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	89.56	33.05	-58.86	-1.04	-59.91	-13	-46.91
2	236.53	33.15	-62.21	3.84	-58.37	-13	-45.37
3	285.96	31.29	-64.18	3.78	-60.39	-13	-47.39
4	347.69	30.90	-66.79	3.61	-63.18	-13	-50.18
5	471.6	33.83	-63.35	2.84	-60.51	-13	-47.51
6	739.48	28.20	-68.17	1.02	-67.14	-13	-54.14

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	67.95	29.82	-57.81	-4.91	-62.72	-13	-49.72
2	94.97	31.76	-60.04	-1.00	-61.05	-13	-48.05
3	130.5	25.39	-65.96	-1.23	-67.20	-13	-54.20
4	239.71	29.82	-65.54	3.82	-61.72	-13	-48.72
5	510.97	31.35	-64.04	2.81	-61.23	-13	-48.23
6	608.6	32.67	-62.02	1.78	-60.24	-13	-47.24

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 4: 1.4MHz

Mode	TX channel 19957	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	85.1	33.40	-58.51	-1.04	-59.56	-13	-46.56
2	137.56	34.07	-61.29	3.84	-57.45	-13	-44.45
3	289.38	32.91	-62.56	3.78	-58.77	-13	-45.77
4	344.85	30.81	-66.88	3.61	-63.27	-13	-50.27
5	470.74	33.04	-64.14	2.84	-61.30	-13	-48.30
6	737.34	27.25	-69.12	1.02	-68.09	-13	-55.09

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	43.14	28.52	-59.11	-4.91	-64.02	-13	-51.02
2	93.52	31.23	-60.57	-1.00	-61.58	-13	-48.58
3	128.83	24.23	-67.12	-1.23	-68.36	-13	-55.36
4	239.37	27.41	-67.95	3.82	-64.13	-13	-51.13
5	509.99	31.16	-64.23	2.81	-61.42	-13	-48.42
6	610.31	31.45	-63.24	1.78	-61.46	-13	-48.46

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 20175	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	86.35	33.37	-58.54	-1.04	-59.59	-13	-46.59
2	137.66	34.30	-61.06	3.84	-57.22	-13	-44.22
3	289.77	33.94	-61.53	3.78	-57.74	-13	-44.74
4	346.28	31.04	-66.65	3.61	-63.04	-13	-50.04
5	470.93	33.78	-63.40	2.84	-60.56	-13	-47.56
6	738.31	27.68	-68.69	1.02	-67.66	-13	-54.66

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	43.4	27.73	-59.90	-4.91	-64.81	-13	-51.81
2	93.13	31.77	-60.03	-1.00	-61.04	-13	-48.04
3	129.19	23.53	-67.82	-1.23	-69.06	-13	-56.06
4	238.68	28.27	-67.09	3.82	-63.27	-13	-50.27
5	509.86	31.52	-63.87	2.81	-61.06	-13	-48.06
6	610.33	31.52	-63.17	1.78	-61.39	-13	-48.39

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 20393	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	85.88	32.79	-59.12	-1.04	-60.17	-13	-47.17
2	137.38	33.55	-61.81	3.84	-57.97	-13	-44.97
3	290.48	33.25	-62.22	3.78	-58.43	-13	-45.43
4	345.57	30.31	-67.38	3.61	-63.77	-13	-50.77
5	471.39	33.24	-63.94	2.84	-61.10	-13	-48.10
6	737.75	28.26	-68.11	1.02	-67.08	-13	-54.08

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	44.05	28.43	-59.20	-4.91	-64.11	-13	-51.11
2	91.82	32.06	-59.74	-1.00	-60.75	-13	-47.75
3	127.73	23.83	-67.52	-1.23	-68.76	-13	-55.76
4	239.72	27.04	-68.32	3.82	-64.50	-13	-51.50
5	510.49	30.68	-64.71	2.81	-61.90	-13	-48.90
6	610.06	31.13	-63.56	1.78	-61.78	-13	-48.78

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 4: 3MHz

Mode	TX channel 19965	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	86.3	33.43	-58.48	-1.04	-59.53	-13	-46.53
2	137.86	34.33	-61.03	3.84	-57.19	-13	-44.19
3	289.6	33.36	-62.11	3.78	-58.32	-13	-45.32
4	344.78	31.01	-66.68	3.61	-63.07	-13	-50.07
5	471.35	33.48	-63.70	2.84	-60.86	-13	-47.86
6	738.34	27.46	-68.91	1.02	-67.88	-13	-54.88

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	44.48	28.21	-59.42	-4.91	-64.33	-13	-51.33
2	91.92	31.33	-60.47	-1.00	-61.48	-13	-48.48
3	128.07	24.34	-67.01	-1.23	-68.25	-13	-55.25
4	238.66	27.52	-67.84	3.82	-64.02	-13	-51.02
5	508.71	30.70	-64.69	2.81	-61.88	-13	-48.88
6	610.91	32.29	-62.40	1.78	-60.62	-13	-47.62

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 20175	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	86.76	33.09	-58.82	-1.04	-59.87	-13	-46.87
2	137.08	33.72	-61.64	3.84	-57.80	-13	-44.80
3	289.99	33.23	-62.24	3.78	-58.45	-13	-45.45
4	344.97	30.03	-67.66	3.61	-64.05	-13	-51.05
5	470.38	34.18	-63.00	2.84	-60.16	-13	-47.16
6	738.96	28.60	-67.77	1.02	-66.74	-13	-53.74

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	43.38	28.43	-59.20	-4.91	-64.11	-13	-51.11
2	92.58	31.10	-60.70	-1.00	-61.71	-13	-48.71
3	128.29	24.64	-66.71	-1.23	-67.95	-13	-54.95
4	238.21	28.30	-67.06	3.82	-63.24	-13	-50.24
5	510.15	31.06	-64.33	2.81	-61.52	-13	-48.52
6	609.81	31.71	-62.98	1.78	-61.20	-13	-48.20

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 20385	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	85.67	33.20	-58.71	-1.04	-59.76	-13	-46.76
2	136.63	34.05	-61.31	3.84	-57.47	-13	-44.47
3	289.63	32.99	-62.48	3.78	-58.69	-13	-45.69
4	346.02	30.84	-66.85	3.61	-63.24	-13	-50.24
5	470.34	33.92	-63.26	2.84	-60.42	-13	-47.42
6	737.9	28.14	-68.23	1.02	-67.20	-13	-54.20

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	43.46	29.02	-58.61	-4.91	-63.52	-13	-50.52
2	91.77	30.89	-60.91	-1.00	-61.92	-13	-48.92
3	127.83	24.25	-67.10	-1.23	-68.34	-13	-55.34
4	238.37	28.15	-67.21	3.82	-63.39	-13	-50.39
5	510.36	32.09	-63.30	2.81	-60.49	-13	-47.49
6	610.53	31.81	-62.88	1.78	-61.10	-13	-48.10

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 4: 5MHz

Mode	TX channel 19975	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	86.52	32.98	-58.93	-1.04	-59.98	-13	-46.98
2	137.26	34.30	-61.06	3.84	-57.22	-13	-44.22
3	290.1	33.87	-61.60	3.78	-57.81	-13	-44.81
4	345.21	29.70	-67.99	3.61	-64.38	-13	-51.38
5	470.35	33.43	-63.75	2.84	-60.91	-13	-47.91
6	737.54	27.62	-68.75	1.02	-67.72	-13	-54.72

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	43.19	28.14	-59.49	-4.91	-64.40	-13	-51.40
2	93.6	31.06	-60.74	-1.00	-61.75	-13	-48.75
3	127.96	24.66	-66.69	-1.23	-67.93	-13	-54.93
4	238.87	27.31	-68.05	3.82	-64.23	-13	-51.23
5	509.1	31.60	-63.79	2.81	-60.98	-13	-47.98
6	611.13	32.14	-62.55	1.78	-60.77	-13	-47.77

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 20175	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	86.82	33.09	-58.82	-1.04	-59.87	-13	-46.87
2	137.36	33.83	-61.53	3.84	-57.69	-13	-44.69
3	289.05	32.92	-62.55	3.78	-58.76	-13	-45.76
4	345.79	30.45	-67.24	3.61	-63.63	-13	-50.63
5	470.19	33.85	-63.33	2.84	-60.49	-13	-47.49
6	738.73	28.03	-68.34	1.02	-67.31	-13	-54.31

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	43.62	27.90	-59.73	-4.91	-64.64	-13	-51.64
2	93.41	31.40	-60.40	-1.00	-61.41	-13	-48.41
3	128.67	23.89	-67.46	-1.23	-68.70	-13	-55.70
4	238.92	27.68	-67.68	3.82	-63.86	-13	-50.86
5	508.83	31.41	-63.98	2.81	-61.17	-13	-48.17
6	610.54	31.00	-63.69	1.78	-61.91	-13	-48.91

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 20375	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	86.78	33.60	-58.31	-1.04	-59.36	-13	-46.36
2	136.2	34.79	-60.57	3.84	-56.73	-13	-43.73
3	288.91	32.89	-62.58	3.78	-58.79	-13	-45.79
4	345.32	30.60	-67.09	3.61	-63.48	-13	-50.48
5	470.17	33.88	-63.30	2.84	-60.46	-13	-47.46
6	738.74	27.62	-68.75	1.02	-67.72	-13	-54.72

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	42.71	28.74	-58.89	-4.91	-63.80	-13	-50.80
2	92.07	31.94	-59.86	-1.00	-60.87	-13	-47.87
3	129.16	23.70	-67.65	-1.23	-68.89	-13	-55.89
4	238.44	27.70	-67.66	3.82	-63.84	-13	-50.84
5	509.76	31.72	-63.67	2.81	-60.86	-13	-47.86
6	610.06	32.29	-62.40	1.78	-60.62	-13	-47.62

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 4: 10MHz

Mode	TX channel 20000	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	85.91	32.72	-59.19	-1.04	-60.24	-13	-47.24
2	136.28	34.34	-61.02	3.84	-57.18	-13	-44.18
3	288.89	33.73	-61.74	3.78	-57.95	-13	-44.95
4	345.57	30.47	-67.22	3.61	-63.61	-13	-50.61
5	470.46	33.24	-63.94	2.84	-61.10	-13	-48.10
6	736.98	27.99	-68.38	1.02	-67.35	-13	-54.35

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	43.91	28.12	-59.51	-4.91	-64.42	-13	-51.42
2	91.92	31.76	-60.04	-1.00	-61.05	-13	-48.05
3	127.97	24.24	-67.11	-1.23	-68.35	-13	-55.35
4	239	26.99	-68.37	3.82	-64.55	-13	-51.55
5	508.63	31.27	-64.12	2.81	-61.31	-13	-48.31
6	610.1	32.31	-62.38	1.78	-60.60	-13	-47.60

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 20175	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	85.06	33.62	-58.29	-1.04	-59.34	-13	-46.34
2	137.45	34.90	-60.46	3.84	-56.62	-13	-43.62
3	289.85	33.68	-61.79	3.78	-58.00	-13	-45.00
4	344.5	30.40	-67.29	3.61	-63.68	-13	-50.68
5	470.53	34.13	-63.05	2.84	-60.21	-13	-47.21
6	738.97	27.55	-68.82	1.02	-67.79	-13	-54.79

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	44.17	27.80	-59.83	-4.91	-64.74	-13	-51.74
2	93.1	31.43	-60.37	-1.00	-61.38	-13	-48.38
3	129.47	24.67	-66.68	-1.23	-67.92	-13	-54.92
4	238.58	27.18	-68.18	3.82	-64.36	-13	-51.36
5	509.69	31.53	-63.86	2.81	-61.05	-13	-48.05
6	609.98	31.32	-63.37	1.78	-61.59	-13	-48.59

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 20350	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	86.1	32.73	-59.18	-1.04	-60.23	-13	-47.23
2	137.8	33.58	-61.78	3.84	-57.94	-13	-44.94
3	290.13	32.77	-62.70	3.78	-58.91	-13	-45.91
4	345.14	30.43	-67.26	3.61	-63.65	-13	-50.65
5	470.65	33.19	-63.99	2.84	-61.15	-13	-48.15
6	737.83	27.34	-69.03	1.02	-68.00	-13	-55.00

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	43.72	27.77	-59.86	-4.91	-64.77	-13	-51.77
2	92.89	32.05	-59.75	-1.00	-60.76	-13	-47.76
3	127.67	24.39	-66.96	-1.23	-68.20	-13	-55.20
4	239.6	27.02	-68.34	3.82	-64.52	-13	-51.52
5	510.43	31.00	-64.39	2.81	-61.58	-13	-48.58
6	611.31	31.29	-63.40	1.78	-61.62	-13	-48.62

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 4: 15MHz

Mode	TX channel 20025	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	86.2	33.52	-58.39	-1.04	-59.44	-13	-46.44
2	136.48	34.54	-60.82	3.84	-56.98	-13	-43.98
3	290.57	32.67	-62.80	3.78	-59.01	-13	-46.01
4	344.91	30.61	-67.08	3.61	-63.47	-13	-50.47
5	470.24	33.82	-63.36	2.84	-60.52	-13	-47.52
6	737.71	28.30	-68.07	1.02	-67.04	-13	-54.04

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	42.99	28.60	-59.03	-4.91	-63.94	-13	-50.94
2	92.81	31.23	-60.57	-1.00	-61.58	-13	-48.58
3	129.36	23.96	-67.39	-1.23	-68.63	-13	-55.63
4	238.37	27.94	-67.42	3.82	-63.60	-13	-50.60
5	510.56	31.93	-63.46	2.81	-60.65	-13	-47.65
6	610.07	32.16	-62.53	1.78	-60.75	-13	-47.75

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 20175	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	86.36	32.67	-59.24	-1.04	-60.29	-13	-47.29
2	137.67	33.47	-61.89	3.84	-58.05	-13	-45.05
3	290.74	32.73	-62.74	3.78	-58.95	-13	-45.95
4	345.25	30.90	-66.79	3.61	-63.18	-13	-50.18
5	469.83	33.19	-63.99	2.84	-61.15	-13	-48.15
6	738.84	28.02	-68.35	1.02	-67.32	-13	-54.32

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	42.99	28.07	-59.56	-4.91	-64.47	-13	-51.47
2	93.57	30.87	-60.93	-1.00	-61.94	-13	-48.94
3	129.26	24.61	-66.74	-1.23	-67.98	-13	-54.98
4	238.39	27.68	-67.68	3.82	-63.86	-13	-50.86
5	509.96	31.29	-64.10	2.81	-61.29	-13	-48.29
6	610.73	31.52	-63.17	1.78	-61.39	-13	-48.39

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 20325	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	85.85	32.78	-59.13	-1.04	-60.18	-13	-47.18
2	137.56	33.52	-61.84	3.84	-58.00	-13	-45.00
3	290.62	33.44	-62.03	3.78	-58.24	-13	-45.24
4	345.3	30.17	-67.52	3.61	-63.91	-13	-50.91
5	471.21	33.15	-64.03	2.84	-61.19	-13	-48.19
6	738.41	27.61	-68.76	1.02	-67.73	-13	-54.73

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	42.7	28.08	-59.55	-4.91	-64.46	-13	-51.46
2	93.04	31.36	-60.44	-1.00	-61.45	-13	-48.45
3	127.6	24.73	-66.62	-1.23	-67.86	-13	-54.86
4	239.51	27.69	-67.67	3.82	-63.85	-13	-50.85
5	509.2	31.48	-63.91	2.81	-61.10	-13	-48.10
6	611.06	30.93	-63.76	1.78	-61.98	-13	-48.98

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 4: 20MHz

Mode	TX channel 20050	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	85.72	33.71	-58.20	-1.04	-59.25	-13	-46.25
2	137	34.41	-60.95	3.84	-57.11	-13	-44.11
3	290.61	33.19	-62.28	3.78	-58.49	-13	-45.49
4	346.23	30.03	-67.66	3.61	-64.05	-13	-51.05
5	470.57	33.81	-63.37	2.84	-60.53	-13	-47.53
6	738.49	27.94	-68.43	1.02	-67.40	-13	-54.40

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	44.37	28.56	-59.07	-4.91	-63.98	-13	-50.98
2	92	32.07	-59.73	-1.00	-60.74	-13	-47.74
3	129.2	24.09	-67.26	-1.23	-68.50	-13	-55.50
4	239.68	28.14	-67.22	3.82	-63.40	-13	-50.40
5	509.6	30.69	-64.70	2.81	-61.89	-13	-48.89
6	611.03	32.04	-62.65	1.78	-60.87	-13	-47.87

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 20175	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	86.01	33.01	-58.90	-1.04	-59.95	-13	-46.95
2	136.72	34.39	-60.97	3.84	-57.13	-13	-44.13
3	289.22	33.50	-61.97	3.78	-58.18	-13	-45.18
4	345.46	30.79	-66.90	3.61	-63.29	-13	-50.29
5	471.23	33.64	-63.54	2.84	-60.70	-13	-47.70
6	738.58	27.58	-68.79	1.02	-67.76	-13	-54.76

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	44.2	28.92	-58.71	-4.91	-63.62	-13	-50.62
2	93	31.80	-60.00	-1.00	-61.01	-13	-48.01
3	128.58	24.38	-66.97	-1.23	-68.21	-13	-55.21
4	239.21	27.04	-68.32	3.82	-64.50	-13	-51.50
5	509.1	30.67	-64.72	2.81	-61.91	-13	-48.91
6	611.52	31.88	-62.81	1.78	-61.03	-13	-48.03

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 20300	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	84.85	33.46	-58.45	-1.04	-59.50	-13	-46.50
2	136.88	34.38	-60.98	3.84	-57.14	-13	-44.14
3	289.31	33.19	-62.28	3.78	-58.49	-13	-45.49
4	344.79	30.92	-66.77	3.61	-63.16	-13	-50.16
5	470.01	34.02	-63.16	2.84	-60.32	-13	-47.32
6	737.13	28.52	-67.85	1.02	-66.82	-13	-53.82

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	43.78	27.82	-59.81	-4.91	-64.72	-13	-51.72
2	92.59	30.88	-60.92	-1.00	-61.93	-13	-48.93
3	127.84	23.99	-67.36	-1.23	-68.60	-13	-55.60
4	238.58	28.12	-67.24	3.82	-63.42	-13	-50.42
5	509.38	31.44	-63.95	2.81	-61.14	-13	-48.14
6	609.61	31.24	-63.45	1.78	-61.67	-13	-48.67

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 7: 5MHz

Mode	TX channel 20775	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	85.8	23.97	-67.94	-1.04	-68.99	-25	-43.99
2	137.12	23.88	-71.48	3.84	-67.64	-25	-42.64
3	289.18	25.72	-69.75	3.78	-65.96	-25	-40.96
4	342.35	20.99	-76.70	3.61	-73.09	-25	-48.09
5	472.14	24.33	-72.85	2.84	-70.01	-25	-45.01
6	737.45	21.34	-75.03	1.02	-74.00	-25	-49.00

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	43.37	-0.46	-88.09	-4.91	-93.00	-25	-68.00
2	96.85	9.98	-81.82	-1.00	-82.83	-25	-57.83
3	123.52	4.34	-87.01	-1.23	-88.25	-25	-63.25
4	240.17	6.50	-88.86	3.82	-85.04	-25	-60.04
5	512.78	7.63	-87.76	2.81	-84.95	-25	-59.95
6	614.4	10.22	-84.47	1.78	-82.69	-25	-57.69

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 21100	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	85.69	26.53	-65.38	-1.04	-66.43	-25	-41.43
2	140.23	26.33	-69.03	3.84	-65.19	-25	-40.19
3	292.9	26.32	-69.15	3.78	-65.36	-25	-40.36
4	345.27	23.93	-73.76	3.61	-70.15	-25	-45.15
5	472.78	23.90	-73.28	2.84	-70.44	-25	-45.44
6	741.26	21.50	-74.87	1.02	-73.84	-25	-48.84

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	40.42	3.80	-83.83	-4.91	-88.74	-25	-63.74
2	97.22	9.81	-81.99	-1.00	-83.00	-25	-58.00
3	123.15	4.04	-87.31	-1.23	-88.55	-25	-63.55
4	235.46	6.62	-88.74	3.82	-84.92	-25	-59.92
5	512.68	9.47	-85.92	2.81	-83.11	-25	-58.11
6	613.96	14.21	-80.48	1.78	-78.70	-25	-53.70

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 21425	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	86.35	24.04	-67.87	-1.04	-68.92	-25	-43.92
2	140.71	25.05	-70.31	3.84	-66.47	-25	-41.47
3	289.9	26.94	-68.53	3.78	-64.74	-25	-39.74
4	345.8	24.38	-73.31	3.61	-69.70	-25	-44.70
5	471.07	22.64	-74.54	2.84	-71.70	-25	-46.70
6	738.46	20.91	-75.46	1.02	-74.43	-25	-49.43

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	42.89	3.00	-84.63	-4.91	-89.54	-25	-64.54
2	96.28	9.05	-82.75	-1.00	-83.76	-25	-58.76
3	120.36	4.14	-87.21	-1.23	-88.45	-25	-63.45
4	237.07	6.03	-89.33	3.82	-85.51	-25	-60.51
5	511.04	11.35	-84.04	2.81	-81.23	-25	-56.23
6	618.21	11.57	-83.12	1.78	-81.34	-25	-56.34

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 7: 10MHz

Mode	TX channel 20800	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	85.06	12.69	-79.22	-1.04	-80.27	-25	-55.27
2	139.94	13.85	-81.51	3.84	-77.67	-25	-52.67
3	289.09	14.97	-80.50	3.78	-76.71	-25	-51.71
4	348.06	8.00	-89.69	3.61	-86.08	-25	-61.08
5	470.44	15.34	-81.84	2.84	-79.00	-25	-54.00
6	737.19	6.35	-90.02	1.02	-88.99	-25	-63.99

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	42.41	4.37	-83.26	-4.91	-88.17	-25	-63.17
2	96.67	8.75	-83.05	-1.00	-84.06	-25	-59.06
3	123.54	3.23	-88.12	-1.23	-89.36	-25	-64.36
4	241.75	5.85	-89.51	3.82	-85.69	-25	-60.69
5	511.67	10.17	-85.22	2.81	-82.41	-25	-57.41
6	617.69	10.44	-84.25	1.78	-82.47	-25	-57.47

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 21100	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	87.12	15.65	-76.26	-1.04	-77.31	-25	-52.31
2	141.05	13.13	-82.23	3.84	-78.39	-25	-53.39
3	286.08	13.08	-82.39	3.78	-78.60	-25	-53.60
4	346.36	9.61	-88.08	3.61	-84.47	-25	-59.47
5	473.41	16.01	-81.17	2.84	-78.33	-25	-53.33
6	737.91	10.06	-86.31	1.02	-85.28	-25	-60.28

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	38.89	1.54	-86.09	-4.91	-91.00	-25	-66.00
2	95.61	8.04	-83.76	-1.00	-84.77	-25	-59.77
3	123.4	5.07	-86.28	-1.23	-87.52	-25	-62.52
4	238.41	7.71	-87.65	3.82	-83.83	-25	-58.83
5	508.83	8.74	-86.65	2.81	-83.84	-25	-58.84
6	614.68	13.47	-81.22	1.78	-79.44	-25	-54.44

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 21400	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	89.31	12.37	-79.54	-1.04	-80.59	-25	-55.59
2	136.85	11.04	-84.32	3.84	-80.48	-25	-55.48
3	290.2	13.00	-82.47	3.78	-78.68	-25	-53.68
4	347.6	9.24	-88.45	3.61	-84.84	-25	-59.84
5	468.9	13.07	-84.11	2.84	-81.27	-25	-56.27
6	734.57	6.21	-90.16	1.02	-89.13	-25	-64.13

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	39.92	3.21	-84.42	-4.91	-89.33	-25	-64.33
2	99.98	8.33	-83.47	-1.00	-84.48	-25	-59.48
3	121.73	3.77	-87.58	-1.23	-88.82	-25	-63.82
4	240.29	7.63	-87.73	3.82	-83.91	-25	-58.91
5	512.07	6.36	-89.03	2.81	-86.22	-25	-61.22
6	617.06	8.88	-85.81	1.78	-84.03	-25	-59.03

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 7: 15MHz

Mode	TX channel 20825	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	85.65	24.12	-67.79	-1.04	-68.84	-25	-43.84
2	137.95	27.75	-67.61	3.84	-63.77	-25	-38.77
3	288.86	25.59	-69.88	3.78	-66.09	-25	-41.09
4	346.05	23.62	-74.07	3.61	-70.46	-25	-45.46
5	469.28	28.74	-68.44	2.84	-65.60	-25	-40.60
6	737.37	22.06	-74.31	1.02	-73.28	-25	-48.28

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	43.72	19.35	-68.28	-4.91	-73.19	-25	-48.19
2	91.7	21.57	-70.23	-1.00	-71.24	-25	-46.24
3	124.34	12.80	-78.55	-1.23	-79.79	-25	-54.79
4	242.17	20.47	-74.89	3.82	-71.07	-25	-46.07
5	508.17	24.53	-70.86	2.81	-68.05	-25	-43.05
6	609.67	27.01	-67.68	1.78	-65.90	-25	-40.90

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 21100	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	89.24	23.86	-68.05	-1.04	-69.10	-25	-44.10
2	138.74	28.30	-67.06	3.84	-63.22	-25	-38.22
3	290.74	25.56	-69.91	3.78	-66.12	-25	-41.12
4	344.57	23.25	-74.44	3.61	-70.83	-25	-45.83
5	469.61	24.49	-72.69	2.84	-69.85	-25	-44.85
6	738.22	20.80	-75.57	1.02	-74.54	-25	-49.54

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	42.6	21.02	-66.61	-4.91	-71.52	-25	-46.52
2	91.71	23.18	-68.62	-1.00	-69.63	-25	-44.63
3	129.01	15.98	-75.37	-1.23	-76.61	-25	-51.61
4	239.06	18.88	-76.48	3.82	-72.66	-25	-47.66
5	508.47	23.87	-71.52	2.81	-68.71	-25	-43.71
6	608.98	24.39	-70.30	1.78	-68.52	-25	-43.52

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 21375	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	85.36	25.35	-66.56	-1.04	-67.61	-25	-42.61
2	139.7	25.70	-69.66	3.84	-65.82	-25	-40.82
3	294.45	27.57	-67.90	3.78	-64.11	-25	-39.11
4	345.49	22.79	-74.90	3.61	-71.29	-25	-46.29
5	468.34	27.90	-69.28	2.84	-66.44	-25	-41.44
6	740.02	19.38	-76.99	1.02	-75.96	-25	-50.96

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	39.47	20.72	-66.91	-4.91	-71.82	-25	-46.82
2	93.71	21.45	-70.35	-1.00	-71.36	-25	-46.36
3	128.91	15.59	-75.76	-1.23	-77.00	-25	-52.00
4	238.34	19.62	-75.74	3.82	-71.92	-25	-46.92
5	508.69	23.56	-71.83	2.81	-69.02	-25	-44.02
6	610.25	23.67	-71.02	1.78	-69.24	-25	-44.24

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 7: 20MHz

Mode	TX channel 20850	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	85.71	25.44	-66.47	-1.04	-67.52	-25	-42.52
2	140.99	27.16	-68.20	3.84	-64.36	-25	-39.36
3	289.19	26.05	-69.42	3.78	-65.63	-25	-40.63
4	346.39	22.21	-75.48	3.61	-71.87	-25	-46.87
5	469.98	26.22	-70.96	2.84	-68.12	-25	-43.12
6	741.21	20.41	-75.96	1.02	-74.93	-25	-49.93

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	44.55	19.28	-68.35	-4.91	-73.26	-25	-48.26
2	93.01	22.94	-68.86	-1.00	-69.87	-25	-44.87
3	130.14	13.88	-77.47	-1.23	-78.71	-25	-53.71
4	239.93	21.35	-74.01	3.82	-70.19	-25	-45.19
5	512.51	22.78	-72.61	2.81	-69.80	-25	-44.80
6	612.2	22.44	-72.25	1.78	-70.47	-25	-45.47

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 21100	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	85.09	26.46	-65.45	-1.04	-66.50	-25	-41.50
2	132.51	27.96	-67.40	3.84	-63.56	-25	-38.56
3	288.52	25.39	-70.08	3.78	-66.29	-25	-41.29
4	346.73	22.19	-75.50	3.61	-71.89	-25	-46.89
5	471.87	25.38	-71.80	2.84	-68.96	-25	-43.96
6	739.39	21.75	-74.62	1.02	-73.59	-25	-48.59

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	44.53	19.70	-67.93	-4.91	-72.84	-25	-47.84
2	91.47	23.35	-68.45	-1.00	-69.46	-25	-44.46
3	128.03	16.14	-75.21	-1.23	-76.45	-25	-51.45
4	237.53	18.12	-77.24	3.82	-73.42	-25	-48.42
5	507.12	22.99	-72.40	2.81	-69.59	-25	-44.59
6	607.87	23.04	-71.65	1.78	-69.87	-25	-44.87

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 21350	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	85.9	23.86	-68.05	-1.04	-69.10	-25	-44.10
2	137.05	26.93	-68.43	3.84	-64.59	-25	-39.59
3	286.77	26.80	-68.67	3.78	-64.88	-25	-39.88
4	347.88	25.57	-72.12	3.61	-68.51	-25	-43.51
5	470.02	24.32	-72.86	2.84	-70.02	-25	-45.02
6	737.59	22.49	-73.88	1.02	-72.85	-25	-47.85

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	44.4	20.01	-67.62	-4.91	-72.53	-25	-47.53
2	93.19	22.48	-69.32	-1.00	-70.33	-25	-45.33
3	128.92	14.83	-76.52	-1.23	-77.76	-25	-52.76
4	241.14	20.71	-74.65	3.82	-70.83	-25	-45.83
5	509.69	22.60	-72.79	2.81	-69.98	-25	-44.98
6	610.75	21.58	-73.11	1.78	-71.33	-25	-46.33

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE CA_7C (15MHz+20MHz)

Mode	TX channel 21100+21271	Frequency Range	Below 1000 MHz
------	------------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	85.65	30.42	-61.49	-1.04	-62.54	-25	-37.54
2	138.8	28.07	-67.29	3.84	-63.45	-25	-38.45
3	288.63	32.69	-62.78	3.78	-58.99	-25	-33.99
4	344.82	35.06	-62.63	3.61	-59.02	-25	-34.02
5	472.08	35.14	-62.04	2.84	-59.20	-25	-34.20
6	736.57	38.30	-58.07	1.02	-57.04	-25	-32.04

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	65.17	33.17	-54.46	-4.91	-59.37	-25	-34.37
2	94.65	31.56	-60.24	-1.00	-61.25	-25	-36.25
3	131.91	36.14	-55.21	-1.23	-56.45	-25	-31.45
4	239.06	38.21	-57.15	3.82	-53.33	-25	-28.33
5	512.6	36.53	-58.86	2.81	-56.05	-25	-31.05
6	604.07	39.59	-55.10	1.78	-53.32	-25	-28.32

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 12: 1.4MHz

Mode	TX channel 23017	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	83.17	27.32	-64.59	-1.04	-65.64	-13	-52.64
2	138.2	26.90	-68.46	3.84	-64.62	-13	-51.62
3	286.9	25.84	-69.63	3.78	-65.84	-13	-52.84
4	344.99	24.99	-72.70	3.61	-69.09	-13	-56.09
5	470.51	26.73	-70.45	2.84	-67.61	-13	-54.61
6	737.06	20.52	-75.85	1.02	-74.82	-13	-61.82

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	62.01	17.30	-70.33	-4.91	-75.24	-13	-62.24
2	88.9	21.32	-70.48	-1.00	-71.49	-13	-58.49
3	131.91	14.75	-76.60	-1.23	-77.84	-13	-64.84
4	235.7	16.65	-78.71	3.82	-74.89	-13	-61.89
5	510.39	18.42	-76.97	2.81	-74.16	-13	-61.16
6	612.89	17.07	-77.62	1.78	-75.84	-13	-62.84

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 23095	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	87.2	25.13	-66.78	-1.04	-67.83	-13	-54.83
2	139.96	25.00	-70.36	3.84	-66.52	-13	-53.52
3	285.17	25.42	-70.05	3.78	-66.26	-13	-53.26
4	348.24	22.28	-75.41	3.61	-71.80	-13	-58.80
5	470.33	25.37	-71.81	2.84	-68.97	-13	-55.97
6	738.47	20.76	-75.61	1.02	-74.58	-13	-61.58

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	43.73	20.85	-66.78	-4.91	-71.69	-13	-58.69
2	91.37	21.64	-70.16	-1.00	-71.17	-13	-58.17
3	133.48	13.76	-77.59	-1.23	-78.83	-13	-65.83
4	237.62	19.69	-75.67	3.82	-71.85	-13	-58.85
5	509.72	22.65	-72.74	2.81	-69.93	-13	-56.93
6	611.73	22.55	-72.14	1.78	-70.36	-13	-57.36

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 23173	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	82.64	24.10	-67.81	-1.04	-68.86	-13	-55.86
2	140.02	26.98	-68.38	3.84	-64.54	-13	-51.54
3	294.77	25.56	-69.91	3.78	-66.12	-13	-53.12
4	345.74	21.39	-76.30	3.61	-72.69	-13	-59.69
5	473.25	22.83	-74.35	2.84	-71.51	-13	-58.51
6	739.04	20.82	-75.55	1.02	-74.52	-13	-61.52

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	46.36	17.19	-70.44	-4.91	-75.35	-13	-62.35
2	92.52	21.98	-69.82	-1.00	-70.83	-13	-57.83
3	128.89	15.51	-75.84	-1.23	-77.08	-13	-64.08
4	240.14	16.44	-78.92	3.82	-75.10	-13	-62.10
5	509.26	18.20	-77.19	2.81	-74.38	-13	-61.38
6	609.73	20.97	-73.72	1.78	-71.94	-13	-58.94

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 12: 3MHz

Mode	TX channel 23025	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	86.35	25.13	-66.78	-1.04	-67.83	-13	-54.83
2	137.42	23.32	-72.04	3.84	-68.20	-13	-55.20
3	287.56	25.60	-69.87	3.78	-66.08	-13	-53.08
4	344.88	25.26	-72.43	3.61	-68.82	-13	-55.82
5	471.51	25.48	-71.70	2.84	-68.86	-13	-55.86
6	736.08	19.87	-76.50	1.02	-75.47	-13	-62.47

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	46.47	17.33	-70.30	-4.91	-75.21	-13	-62.21
2	94.09	23.56	-68.24	-1.00	-69.25	-13	-56.25
3	123.42	13.17	-78.18	-1.23	-79.42	-13	-66.42
4	239.42	17.62	-77.74	3.82	-73.92	-13	-60.92
5	510.26	20.14	-75.25	2.81	-72.44	-13	-59.44
6	610.9	23.01	-71.68	1.78	-69.90	-13	-56.90

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 23095	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	89.2	24.48	-67.43	-1.04	-68.48	-13	-55.48
2	138.94	26.02	-69.34	3.84	-65.50	-13	-52.50
3	293.7	25.88	-69.59	3.78	-65.80	-13	-52.80
4	347.8	21.16	-76.53	3.61	-72.92	-13	-59.92
5	472.53	27.25	-69.93	2.84	-67.09	-13	-54.09
6	740.17	18.34	-78.03	1.02	-77.00	-13	-64.00

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	43.73	18.22	-69.41	-4.91	-74.32	-13	-61.32
2	87.99	21.27	-70.53	-1.00	-71.54	-13	-58.54
3	126.81	12.20	-79.15	-1.23	-80.39	-13	-67.39
4	236.85	14.87	-80.49	3.82	-76.67	-13	-63.67
5	511	20.84	-74.55	2.81	-71.74	-13	-58.74
6	609.67	25.38	-69.31	1.78	-67.53	-13	-54.53

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 23165	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	86.56	24.86	-67.05	-1.04	-68.10	-13	-55.10
2	138.67	27.36	-68.00	3.84	-64.16	-13	-51.16
3	288.3	25.80	-69.67	3.78	-65.88	-13	-52.88
4	349.95	20.60	-77.09	3.61	-73.48	-13	-60.48
5	468.96	27.17	-70.01	2.84	-67.17	-13	-54.17
6	736.4	21.29	-75.08	1.02	-74.05	-13	-61.05

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	41.6	21.25	-66.38	-4.91	-71.29	-13	-58.29
2	94.93	21.29	-70.51	-1.00	-71.52	-13	-58.52
3	133.09	11.30	-80.05	-1.23	-81.29	-13	-68.29
4	240.71	18.46	-76.90	3.82	-73.08	-13	-60.08
5	513.15	22.47	-72.92	2.81	-70.11	-13	-57.11
6	609.44	21.18	-73.51	1.78	-71.73	-13	-58.73

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 12: 5MHz

Mode	TX channel 23035	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	89.87	23.10	-68.81	-1.04	-69.86	-13	-56.86
2	136.94	24.88	-70.48	3.84	-66.64	-13	-53.64
3	286.98	26.26	-69.21	3.78	-65.42	-13	-52.42
4	344.08	20.72	-76.97	3.61	-73.36	-13	-60.36
5	470.76	26.80	-70.38	2.84	-67.54	-13	-54.54
6	737.16	17.60	-78.77	1.02	-77.74	-13	-64.74

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	41.08	13.82	-73.81	-4.91	-78.72	-13	-65.72
2	97.41	20.28	-71.52	-1.00	-72.53	-13	-59.53
3	124.91	15.13	-76.22	-1.23	-77.46	-13	-64.46
4	239.01	18.02	-77.34	3.82	-73.52	-13	-60.52
5	511.09	21.56	-73.83	2.81	-71.02	-13	-58.02
6	617.89	22.10	-72.59	1.78	-70.81	-13	-57.81

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 23095	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	87.51	24.57	-67.34	-1.04	-68.39	-13	-55.39
2	138.26	26.33	-69.03	3.84	-65.19	-13	-52.19
3	286.13	25.09	-70.38	3.78	-66.59	-13	-53.59
4	346.58	21.70	-75.99	3.61	-72.38	-13	-59.38
5	471.18	24.00	-73.18	2.84	-70.34	-13	-57.34
6	738.66	19.81	-76.56	1.02	-75.53	-13	-62.53

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	41.55	18.20	-69.43	-4.91	-74.34	-13	-61.34
2	92.84	25.19	-66.61	-1.00	-67.62	-13	-54.62
3	127.37	13.81	-77.54	-1.23	-78.78	-13	-65.78
4	238.05	19.08	-76.28	3.82	-72.46	-13	-59.46
5	506.67	24.37	-71.02	2.81	-68.21	-13	-55.21
6	611.24	20.50	-74.19	1.78	-72.41	-13	-59.41

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 23155	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	87.6	26.14	-65.77	-1.04	-66.82	-13	-53.82
2	136.96	25.98	-69.38	3.84	-65.54	-13	-52.54
3	288.95	26.76	-68.71	3.78	-64.92	-13	-51.92
4	345.8	21.03	-76.66	3.61	-73.05	-13	-60.05
5	469.46	21.81	-75.37	2.84	-72.53	-13	-59.53
6	743.51	16.62	-79.75	1.02	-78.72	-13	-65.72

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	43.14	17.90	-69.73	-4.91	-74.64	-13	-61.64
2	90.83	20.97	-70.83	-1.00	-71.84	-13	-58.84
3	126.87	12.49	-78.86	-1.23	-80.10	-13	-67.10
4	239.31	19.52	-75.84	3.82	-72.02	-13	-59.02
5	511.26	21.88	-73.51	2.81	-70.70	-13	-57.70
6	612.36	23.51	-71.18	1.78	-69.40	-13	-56.40

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 12: 10MHz

Mode	TX channel 23060	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	86.07	24.52	-67.39	-1.04	-68.44	-13	-55.44
2	135.62	23.99	-71.37	3.84	-67.53	-13	-54.53
3	289.86	27.44	-68.03	3.78	-64.24	-13	-51.24
4	342.13	21.71	-75.98	3.61	-72.37	-13	-59.37
5	469.84	23.34	-73.84	2.84	-71.00	-13	-58.00
6	739.56	20.11	-76.26	1.02	-75.23	-13	-62.23

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	42.77	17.80	-69.83	-4.91	-74.74	-13	-61.74
2	94.59	23.10	-68.70	-1.00	-69.71	-13	-56.71
3	127.57	14.04	-77.31	-1.23	-78.55	-13	-65.55
4	239.97	16.04	-79.32	3.82	-75.50	-13	-62.50
5	507.67	22.40	-72.99	2.81	-70.18	-13	-57.18
6	607.1	23.41	-71.28	1.78	-69.50	-13	-56.50

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 23095	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	83.62	24.65	-67.26	-1.04	-68.31	-13	-55.31
2	139.03	26.67	-68.69	3.84	-64.85	-13	-51.85
3	290.06	26.02	-69.45	3.78	-65.66	-13	-52.66
4	345.45	21.69	-76.00	3.61	-72.39	-13	-59.39
5	468.93	26.20	-70.98	2.84	-68.14	-13	-55.14
6	740.3	17.39	-78.98	1.02	-77.95	-13	-64.95

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	42.97	18.00	-69.63	-4.91	-74.54	-13	-61.54
2	94.73	22.85	-68.95	-1.00	-69.96	-13	-56.96
3	129.92	14.41	-76.94	-1.23	-78.18	-13	-65.18
4	240.05	19.84	-75.52	3.82	-71.70	-13	-58.70
5	514.8	22.50	-72.89	2.81	-70.08	-13	-57.08
6	606.69	18.62	-76.07	1.78	-74.29	-13	-61.29

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 23130	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	87	24.90	-67.01	-1.04	-68.06	-13	-55.06
2	137.15	25.22	-70.14	3.84	-66.30	-13	-53.30
3	288.17	25.50	-69.97	3.78	-66.18	-13	-53.18
4	347.55	21.09	-76.60	3.61	-72.99	-13	-59.99
5	471.34	26.27	-70.91	2.84	-68.07	-13	-55.07
6	736.48	19.63	-76.74	1.02	-75.71	-13	-62.71

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	49.38	19.28	-68.35	-4.91	-73.26	-13	-60.26
2	95.93	23.16	-68.64	-1.00	-69.65	-13	-56.65
3	125.5	17.52	-73.83	-1.23	-75.07	-13	-62.07
4	240.08	17.87	-77.49	3.82	-73.67	-13	-60.67
5	513.62	22.66	-72.73	2.81	-69.92	-13	-56.92
6	611.01	23.36	-71.33	1.78	-69.55	-13	-56.55

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 13: 5MHz

Mode	TX channel 23205	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	85.22	13.80	-78.11	-1.04	-79.16	-13	-66.16
2	131.98	15.86	-79.50	3.84	-75.66	-13	-62.66
3	291.03	12.52	-82.95	3.78	-79.16	-13	-66.16
4	346.35	18.91	-78.78	3.61	-75.17	-13	-62.17
5	471.07	15.18	-82.00	2.84	-79.16	-13	-66.16
6	736.17	13.86	-82.51	1.02	-81.48	-13	-68.48

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	52.59	1.51	-86.12	-4.91	-91.03	-13	-78.03
2	90.6	1.12	-90.68	-1.00	-91.69	-13	-78.69
3	127.7	-14.12	-105.47	-1.23	-106.71	-13	-93.71
4	241.35	1.24	-94.12	3.82	-90.30	-13	-77.30
5	509.65	2.89	-92.50	2.81	-89.69	-13	-76.69
6	614.28	4.36	-90.33	1.78	-88.55	-13	-75.55

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 23230	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	84.67	14.68	-77.23	-1.04	-78.28	-13	-65.28
2	137.13	15.60	-79.76	3.84	-75.92	-13	-62.92
3	289.95	12.28	-83.19	3.78	-79.40	-13	-66.40
4	346	13.43	-84.26	3.61	-80.65	-13	-67.65
5	470.24	14.00	-83.18	2.84	-80.34	-13	-67.34
6	738.34	11.57	-84.80	1.02	-83.77	-13	-70.77

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	39.8	-4.03	-91.66	-4.91	-96.57	-13	-83.57
2	91.04	2.41	-89.39	-1.00	-90.40	-13	-77.40
3	124.8	-2.04	-93.39	-1.23	-94.63	-13	-81.63
4	238.13	-0.57	-95.93	3.82	-92.11	-13	-79.11
5	509.04	-1.58	-96.97	2.81	-94.16	-13	-81.16
6	608.21	5.88	-88.81	1.78	-87.03	-13	-74.03

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 23255	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	84.06	18.70	-73.21	-1.04	-74.26	-13	-61.26
2	135.32	21.52	-73.84	3.84	-70.00	-13	-57.00
3	282.54	11.85	-83.62	3.78	-79.83	-13	-66.83
4	340.12	11.26	-86.43	3.61	-82.82	-13	-69.82
5	475.05	15.80	-81.38	2.84	-78.54	-13	-65.54
6	733.88	11.70	-84.67	1.02	-83.64	-13	-70.64

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	40.21	-2.60	-90.23	-4.91	-95.14	-13	-82.14
2	89.57	-0.39	-92.19	-1.00	-93.20	-13	-80.20
3	129.5	-11.86	-103.21	-1.23	-104.45	-13	-91.45
4	234.74	1.39	-93.97	3.82	-90.15	-13	-77.15
5	513.04	-4.12	-99.51	2.81	-96.70	-13	-83.70
6	617.4	2.40	-92.29	1.78	-90.51	-13	-77.51

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 13: 10MHz

Mode	TX channel 23230	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	88.13	18.43	-73.48	-1.04	-74.53	-13	-61.53
2	138.45	17.75	-77.61	3.84	-73.77	-13	-60.77
3	287.74	13.51	-81.96	3.78	-78.17	-13	-65.17
4	340.03	15.48	-82.21	3.61	-78.60	-13	-65.60
5	475.79	18.53	-78.65	2.84	-75.81	-13	-62.81
6	728.69	9.29	-87.08	1.02	-86.05	-13	-73.05

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	39.84	-4.90	-92.53	-4.91	-97.44	-13	-84.44
2	92.14	2.31	-89.49	-1.00	-90.50	-13	-77.50
3	128.82	-5.75	-97.10	-1.23	-98.34	-13	-85.34
4	233.71	-4.84	-100.20	3.82	-96.38	-13	-83.38
5	508.76	-3.14	-98.53	2.81	-95.72	-13	-82.72
6	611.86	0.81	-93.88	1.78	-92.10	-13	-79.10

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 17: 5MHz

Mode	TX channel 23755	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	88.55	22.04	-69.87	-1.04	-70.92	-13	-57.92
2	138.51	21.70	-73.66	3.84	-69.82	-13	-56.82
3	287.74	21.73	-73.74	3.78	-69.95	-13	-56.95
4	345.25	18.04	-79.65	3.61	-76.04	-13	-63.04
5	472.65	22.77	-74.41	2.84	-71.57	-13	-58.57
6	736.52	16.52	-79.85	1.02	-78.82	-13	-65.82

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	41.33	11.78	-75.85	-4.91	-80.76	-13	-67.76
2	96.99	18.14	-73.66	-1.00	-74.67	-13	-61.67
3	123.84	12.42	-78.93	-1.23	-80.17	-13	-67.17
4	238.96	15.81	-79.55	3.82	-75.73	-13	-62.73
5	511.56	18.26	-77.13	2.81	-74.32	-13	-61.32
6	616.24	20.84	-73.85	1.78	-72.07	-13	-59.07

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 23790	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	88.76	22.06	-69.85	-1.04	-70.90	-13	-57.90
2	137.64	21.99	-73.37	3.84	-69.53	-13	-56.53
3	287.35	21.24	-74.23	3.78	-70.44	-13	-57.44
4	346.15	17.85	-79.84	3.61	-76.23	-13	-63.23
5	472.17	22.34	-74.84	2.84	-72.00	-13	-59.00
6	736.36	15.76	-80.61	1.02	-79.58	-13	-66.58

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	41.53	11.65	-75.98	-4.91	-80.89	-13	-67.89
2	96.14	17.35	-74.45	-1.00	-75.46	-13	-62.46
3	123.92	11.83	-79.52	-1.23	-80.76	-13	-67.76
4	238.22	15.22	-80.14	3.82	-76.32	-13	-63.32
5	512.52	17.94	-77.45	2.81	-74.64	-13	-61.64
6	616.09	19.87	-74.82	1.78	-73.04	-13	-60.04

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 23825	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	87.66	21.59	-70.32	-1.04	-71.37	-13	-58.37
2	137.67	21.80	-73.56	3.84	-69.72	-13	-56.72
3	287.8	21.92	-73.55	3.78	-69.76	-13	-56.76
4	345.51	17.26	-80.43	3.61	-76.82	-13	-63.82
5	471.94	23.10	-74.08	2.84	-71.24	-13	-58.24
6	737.28	15.93	-80.44	1.02	-79.41	-13	-66.41

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	42.08	10.79	-76.84	-4.91	-81.75	-13	-68.75
2	95.99	17.63	-74.17	-1.00	-75.18	-13	-62.18
3	122.94	12.00	-79.35	-1.23	-80.59	-13	-67.59
4	239.12	15.61	-79.75	3.82	-75.93	-13	-62.93
5	511.5	18.01	-77.38	2.81	-74.57	-13	-61.57
6	616.78	19.37	-75.32	1.78	-73.54	-13	-60.54

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 17: 10MHz

Mode	TX channel 23780	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	87.38	21.18	-70.73	-1.04	-71.78	-13	-58.78
2	138.73	21.36	-74.00	3.84	-70.16	-13	-57.16
3	286.63	21.30	-74.17	3.78	-70.38	-13	-57.38
4	346.17	16.68	-81.01	3.61	-77.40	-13	-64.40
5	471.6	23.75	-73.43	2.84	-70.59	-13	-57.59
6	736.26	15.12	-81.25	1.02	-80.22	-13	-67.22

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	41.08	10.71	-76.92	-4.91	-81.83	-13	-68.83
2	96.99	17.37	-74.43	-1.00	-75.44	-13	-62.44
3	123.62	12.14	-79.21	-1.23	-80.45	-13	-67.45
4	239.31	15.07	-80.29	3.82	-76.47	-13	-63.47
5	511.98	17.45	-77.94	2.81	-75.13	-13	-62.13
6	615.91	19.43	-75.26	1.78	-73.48	-13	-60.48

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 23790	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	88.83	21.54	-70.37	-1.04	-71.42	-13	-58.42
2	138.21	21.46	-73.90	3.84	-70.06	-13	-57.06
3	286.74	21.74	-73.73	3.78	-69.94	-13	-56.94
4	346.3	16.60	-81.09	3.61	-77.48	-13	-64.48
5	472.48	23.57	-73.61	2.84	-70.77	-13	-57.77
6	736.23	16.18	-80.19	1.02	-79.16	-13	-66.16

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	40.86	11.17	-76.46	-4.91	-81.37	-13	-68.37
2	96.08	17.06	-74.74	-1.00	-75.75	-13	-62.75
3	124.08	12.26	-79.09	-1.23	-80.33	-13	-67.33
4	238.66	14.67	-80.69	3.82	-76.87	-13	-63.87
5	511.21	18.20	-77.19	2.81	-74.38	-13	-61.38
6	615.31	20.74	-73.95	1.78	-72.17	-13	-59.17

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 23800	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	88.07	19.32	-72.59	-1.04	-73.64	-13	-60.64
2	136.05	19.99	-75.37	3.84	-71.53	-13	-58.53
3	288.66	21.45	-74.02	3.78	-70.23	-13	-57.23
4	346.04	15.33	-82.36	3.61	-78.75	-13	-65.75
5	472.3	22.45	-74.73	2.84	-71.89	-13	-58.89
6	736.83	12.96	-83.41	1.02	-82.38	-13	-69.38

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	42.18	10.97	-76.66	-4.91	-81.57	-13	-68.57
2	96.58	17.73	-74.07	-1.00	-75.08	-13	-62.08
3	124.58	11.82	-79.53	-1.23	-80.77	-13	-67.77
4	238.71	15.79	-79.57	3.82	-75.75	-13	-62.75
5	511.62	17.10	-78.29	2.81	-75.48	-13	-62.48
6	615.97	19.51	-75.18	1.78	-73.40	-13	-60.40

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 30: 5MHz

Mode	TX channel 27685	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	85.24	30.26	-61.65	-1.04	-62.70	-40	-22.70
2	137.96	30.55	-64.81	3.84	-60.97	-40	-20.97
3	287.4	30.32	-65.15	3.78	-61.36	-40	-21.36
4	346.61	27.46	-70.23	3.61	-66.62	-40	-26.62
5	470.62	30.39	-66.79	2.84	-63.95	-40	-23.95
6	738.2	24.88	-71.49	1.02	-70.46	-40	-30.46

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	41.43	25.69	-61.94	-4.91	-66.85	-40	-26.85
2	94.36	28.28	-63.52	-1.00	-64.53	-40	-24.53
3	127.86	19.67	-71.68	-1.23	-72.92	-40	-32.92
4	236.56	26.11	-69.25	3.82	-65.43	-40	-25.43
5	510.11	27.36	-68.03	2.81	-65.22	-40	-25.22
6	611.64	28.75	-65.94	1.78	-64.16	-40	-24.16

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 27710	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	85.51	29.61	-62.30	-1.04	-63.35	-40	-23.35
2	138.06	29.50	-65.86	3.84	-62.02	-40	-22.02
3	287.99	29.27	-66.20	3.78	-62.41	-40	-22.41
4	347.54	27.23	-70.46	3.61	-66.85	-40	-26.85
5	471.05	29.08	-68.10	2.84	-65.26	-40	-25.26
6	738.9	24.22	-72.15	1.02	-71.12	-40	-31.12

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	40.47	25.26	-62.37	-4.91	-67.28	-40	-27.28
2	94.16	27.01	-64.79	-1.00	-65.80	-40	-25.80
3	126.87	18.44	-72.91	-1.23	-74.15	-40	-34.15
4	235.7	24.84	-70.52	3.82	-66.70	-40	-26.70
5	510.54	26.61	-68.78	2.81	-65.97	-40	-25.97
6	611.99	28.02	-66.67	1.78	-64.89	-40	-24.89

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 27735	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	85.74	30.18	-61.73	-1.04	-62.78	-40	-22.78
2	137.7	30.24	-65.12	3.84	-61.28	-40	-21.28
3	288.12	28.98	-66.49	3.78	-62.70	-40	-22.70
4	346.83	26.98	-70.71	3.61	-67.10	-40	-27.10
5	470.29	29.09	-68.09	2.84	-65.25	-40	-25.25
6	737.42	24.60	-71.77	1.02	-70.74	-40	-30.74

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	40.94	24.88	-62.75	-4.91	-67.66	-40	-27.66
2	93.66	28.07	-63.73	-1.00	-64.74	-40	-24.74
3	127.03	18.43	-72.92	-1.23	-74.16	-40	-34.16
4	237.47	25.55	-69.81	3.82	-65.99	-40	-25.99
5	509.71	25.99	-69.40	2.81	-66.59	-40	-26.59
6	611.49	28.37	-66.32	1.78	-64.54	-40	-24.54

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 30: 10MHz

Mode	TX channel 27710	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	84.38	29.19	-62.72	-1.04	-63.77	-40	-23.77
2	138.07	29.48	-65.88	3.84	-62.04	-40	-22.04
3	286.72	29.42	-66.05	3.78	-62.26	-40	-22.26
4	346.14	26.21	-71.48	3.61	-67.87	-40	-27.87
5	470.26	29.10	-68.08	2.84	-65.24	-40	-25.24
6	739.13	23.86	-72.51	1.02	-71.48	-40	-31.48

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	40.92	24.94	-62.69	-4.91	-67.60	-40	-27.60
2	94.78	26.88	-64.92	-1.00	-65.93	-40	-25.93
3	128.25	18.95	-72.40	-1.23	-73.64	-40	-33.64
4	236.52	25.09	-70.27	3.82	-66.45	-40	-26.45
5	510.69	27.30	-68.09	2.81	-65.28	-40	-25.28
6	611.92	27.98	-66.71	1.78	-64.93	-40	-24.93

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 38: 5MHz

Mode	TX channel 37775	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	86.19	28.22	-63.69	-1.04	-64.74	-25	-39.74
2	134.41	27.04	-68.32	3.84	-64.48	-25	-39.48
3	286.73	27.23	-68.24	3.78	-64.45	-25	-39.45
4	344.31	23.38	-74.31	3.61	-70.70	-25	-45.70
5	470.73	26.40	-70.78	2.84	-67.94	-25	-42.94
6	738.22	19.51	-76.86	1.02	-75.83	-25	-50.83

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	45.25	23.25	-64.38	-4.91	-69.29	-25	-44.29
2	94.04	21.35	-70.45	-1.00	-71.46	-25	-46.46
3	123.34	16.47	-74.88	-1.23	-76.12	-25	-51.12
4	237.66	19.63	-75.73	3.82	-71.91	-25	-46.91
5	509.06	21.12	-74.27	2.81	-71.46	-25	-46.46
6	612.93	22.00	-72.69	1.78	-70.91	-25	-45.91

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 38000	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	84.15	25.06	-66.85	-1.04	-67.90	-25	-42.90
2	135.76	27.22	-68.14	3.84	-64.30	-25	-39.30
3	290	28.24	-67.23	3.78	-63.44	-25	-38.44
4	344.81	23.40	-74.29	3.61	-70.68	-25	-45.68
5	469.5	24.24	-72.94	2.84	-70.10	-25	-45.10
6	737.03	21.99	-74.38	1.02	-73.35	-25	-48.35

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	41.66	17.55	-70.08	-4.91	-74.99	-25	-49.99
2	91.46	24.20	-67.60	-1.00	-68.61	-25	-43.61
3	130.48	15.36	-75.99	-1.23	-77.23	-25	-52.23
4	236.13	16.48	-78.88	3.82	-75.06	-25	-50.06
5	507.52	21.82	-73.57	2.81	-70.76	-25	-45.76
6	607.11	20.91	-73.78	1.78	-72.00	-25	-47.00

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 38225	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	84.5	25.51	-66.40	-1.04	-67.45	-25	-42.45
2	135.91	29.23	-66.13	3.84	-62.29	-25	-37.29
3	286.1	26.63	-68.84	3.78	-65.05	-25	-40.05
4	345.06	23.46	-74.23	3.61	-70.62	-25	-45.62
5	472.04	27.81	-69.37	2.84	-66.53	-25	-41.53
6	737.41	21.17	-75.20	1.02	-74.17	-25	-49.17

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	43.44	19.08	-68.55	-4.91	-73.46	-25	-48.46
2	92.71	21.46	-70.34	-1.00	-71.35	-25	-46.35
3	126.22	14.51	-76.84	-1.23	-78.08	-25	-53.08
4	237.11	17.22	-78.14	3.82	-74.32	-25	-49.32
5	509.06	23.80	-71.59	2.81	-68.78	-25	-43.78
6	608.45	25.30	-69.39	1.78	-67.61	-25	-42.61

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 38: 10MHz

Mode	TX channel 37800	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	85.67	24.67	-67.24	-1.04	-68.29	-25	-43.29
2	137.58	27.99	-67.37	3.84	-63.53	-25	-38.53
3	287.65	24.67	-70.80	3.78	-67.01	-25	-42.01
4	345.11	25.12	-72.57	3.61	-68.96	-25	-43.96
5	471.59	28.42	-68.76	2.84	-65.92	-25	-40.92
6	737.62	20.11	-76.26	1.02	-75.23	-25	-50.23

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	43.92	19.48	-68.15	-4.91	-73.06	-25	-48.06
2	91.44	22.57	-69.23	-1.00	-70.24	-25	-45.24
3	130.28	16.47	-74.88	-1.23	-76.12	-25	-51.12
4	239.18	19.45	-75.91	3.82	-72.09	-25	-47.09
5	505.86	23.33	-72.06	2.81	-69.25	-25	-44.25
6	612.98	24.94	-69.75	1.78	-67.97	-25	-42.97

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 38000	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	83.64	25.85	-66.06	-1.04	-67.11	-25	-42.11
2	134.73	29.41	-65.95	3.84	-62.11	-25	-37.11
3	288.37	27.98	-67.49	3.78	-63.70	-25	-38.70
4	345.75	22.23	-75.46	3.61	-71.85	-25	-46.85
5	470.09	27.07	-70.11	2.84	-67.27	-25	-42.27
6	741.1	22.02	-74.35	1.02	-73.32	-25	-48.32

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	48.12	18.26	-69.37	-4.91	-74.28	-25	-49.28
2	96.9	23.05	-68.75	-1.00	-69.76	-25	-44.76
3	129.6	16.26	-75.09	-1.23	-76.33	-25	-51.33
4	239.03	16.30	-79.06	3.82	-75.24	-25	-50.24
5	505.04	22.11	-73.28	2.81	-70.47	-25	-45.47
6	612.35	22.75	-71.94	1.78	-70.16	-25	-45.16

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 38200	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	85.77	26.11	-65.80	-1.04	-66.85	-25	-41.85
2	136.43	26.57	-68.79	3.84	-64.95	-25	-39.95
3	288.59	25.20	-70.27	3.78	-66.48	-25	-41.48
4	346.23	25.26	-72.43	3.61	-68.82	-25	-43.82
5	469.25	26.48	-70.70	2.84	-67.86	-25	-42.86
6	739.22	20.51	-75.86	1.02	-74.83	-25	-49.83

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	44.49	17.98	-69.65	-4.91	-74.56	-25	-49.56
2	90.98	20.66	-71.14	-1.00	-72.15	-25	-47.15
3	129.88	14.96	-76.39	-1.23	-77.63	-25	-52.63
4	237.38	17.09	-78.27	3.82	-74.45	-25	-49.45
5	512.32	21.23	-74.16	2.81	-71.35	-25	-46.35
6	609.64	20.50	-74.19	1.78	-72.41	-25	-47.41

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 38: 15MHz

Mode	TX channel 37825	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	85.25	28.74	-63.17	-1.04	-64.22	-25	-39.22
2	133.95	26.08	-69.28	3.84	-65.44	-25	-40.44
3	290.3	25.38	-70.09	3.78	-66.30	-25	-41.30
4	348.39	22.82	-74.87	3.61	-71.26	-25	-46.26
5	470.02	26.39	-70.79	2.84	-67.95	-25	-42.95
6	738.4	18.78	-77.59	1.02	-76.56	-25	-51.56

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	43.53	20.24	-67.39	-4.91	-72.30	-25	-47.30
2	91.43	20.78	-71.02	-1.00	-72.03	-25	-47.03
3	128.46	16.05	-75.30	-1.23	-76.54	-25	-51.54
4	242.07	18.29	-77.07	3.82	-73.25	-25	-48.25
5	510.03	24.24	-71.15	2.81	-68.34	-25	-43.34
6	605.48	20.57	-74.12	1.78	-72.34	-25	-47.34

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 38000	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	85.44	26.12	-65.79	-1.04	-66.84	-25	-41.84
2	139.88	29.19	-66.17	3.84	-62.33	-25	-37.33
3	290.84	27.78	-67.69	3.78	-63.90	-25	-38.90
4	342.55	24.13	-73.56	3.61	-69.95	-25	-44.95
5	471.41	27.90	-69.28	2.84	-66.44	-25	-41.44
6	740.06	20.85	-75.52	1.02	-74.49	-25	-49.49

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	48.28	19.08	-68.55	-4.91	-73.46	-25	-48.46
2	94.48	23.59	-68.21	-1.00	-69.22	-25	-44.22
3	129.79	16.17	-75.18	-1.23	-76.42	-25	-51.42
4	239.88	20.44	-74.92	3.82	-71.10	-25	-46.10
5	507.9	23.61	-71.78	2.81	-68.97	-25	-43.97
6	609.33	23.17	-71.52	1.78	-69.74	-25	-44.74

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 38175	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	87.73	27.21	-64.70	-1.04	-65.75	-25	-40.75
2	134.17	28.72	-66.64	3.84	-62.80	-25	-37.80
3	288.37	27.13	-68.34	3.78	-64.55	-25	-39.55
4	345.58	22.74	-74.95	3.61	-71.34	-25	-46.34
5	472.6	25.03	-72.15	2.84	-69.31	-25	-44.31
6	739.39	19.63	-76.74	1.02	-75.71	-25	-50.71

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	38.77	19.87	-67.76	-4.91	-72.67	-25	-47.67
2	90.13	20.40	-71.40	-1.00	-72.41	-25	-47.41
3	122.59	16.46	-74.89	-1.23	-76.13	-25	-51.13
4	240.99	18.87	-76.49	3.82	-72.67	-25	-47.67
5	508.71	22.51	-72.88	2.81	-70.07	-25	-45.07
6	613.54	20.79	-73.90	1.78	-72.12	-25	-47.12

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 38: 20MHz

Mode	TX channel 37805	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	85.36	26.16	-65.75	-1.04	-66.80	-25	-41.80
2	138.61	28.81	-66.55	3.84	-62.71	-25	-37.71
3	291.61	27.66	-67.81	3.78	-64.02	-25	-39.02
4	345.21	23.20	-74.49	3.61	-70.88	-25	-45.88
5	466.77	26.02	-71.16	2.84	-68.32	-25	-43.32
6	739.58	21.13	-75.24	1.02	-74.21	-25	-49.21

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	45.53	18.02	-69.61	-4.91	-74.52	-25	-49.52
2	93.37	23.02	-68.78	-1.00	-69.79	-25	-44.79
3	126.86	14.55	-76.80	-1.23	-78.04	-25	-53.04
4	242.44	20.06	-75.30	3.82	-71.48	-25	-46.48
5	508.67	19.80	-75.59	2.81	-72.78	-25	-47.78
6	608.88	20.68	-74.01	1.78	-72.23	-25	-47.23

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 38000	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	86.47	26.96	-64.95	-1.04	-66.00	-25	-41.00
2	138.03	29.29	-66.07	3.84	-62.23	-25	-37.23
3	285.96	28.04	-67.43	3.78	-63.64	-25	-38.64
4	348.19	23.49	-74.20	3.61	-70.59	-25	-45.59
5	472.2	26.99	-70.19	2.84	-67.35	-25	-42.35
6	735.48	19.84	-76.53	1.02	-75.50	-25	-50.50

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	43.82	20.58	-67.05	-4.91	-71.96	-25	-46.96
2	90.45	22.44	-69.36	-1.00	-70.37	-25	-45.37
3	128.49	16.63	-74.72	-1.23	-75.96	-25	-50.96
4	236.25	16.01	-79.35	3.82	-75.53	-25	-50.53
5	510.65	22.31	-73.08	2.81	-70.27	-25	-45.27
6	612.44	20.34	-74.35	1.78	-72.57	-25	-47.57

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 38150	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	85.3	28.71	-63.20	-1.04	-64.25	-25	-39.25
2	137.14	28.06	-67.30	3.84	-63.46	-25	-38.46
3	287.45	25.48	-69.99	3.78	-66.20	-25	-41.20
4	347.23	24.73	-72.96	3.61	-69.35	-25	-44.35
5	471.38	28.93	-68.25	2.84	-65.41	-25	-40.41
6	735.58	23.45	-72.92	1.02	-71.89	-25	-46.89

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	43.14	17.31	-70.32	-4.91	-75.23	-25	-50.23
2	89.94	22.08	-69.72	-1.00	-70.73	-25	-45.73
3	131.17	15.46	-75.89	-1.23	-77.13	-25	-52.13
4	238.31	22.87	-72.49	3.82	-68.67	-25	-43.67
5	512.54	21.98	-73.41	2.81	-70.60	-25	-45.60
6	609.67	23.52	-71.17	1.78	-69.39	-25	-44.39

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE CA_38C (15MHz+15MHz)

Mode	TX channel 38000+38150	Frequency Range	Below 1000 MHz
------	------------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	84.96	28.39	-63.52	-1.04	-64.57	-25	-39.57
2	138.34	25.37	-69.99	3.84	-66.15	-25	-41.15
3	288.68	30.54	-64.93	3.78	-61.14	-25	-36.14
4	344.39	34.17	-63.52	3.61	-59.91	-25	-34.91
5	472.54	33.01	-64.17	2.84	-61.33	-25	-36.33
6	737.04	36.48	-59.89	1.02	-58.86	-25	-33.86

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	65.84	29.80	-57.83	-4.91	-62.74	-25	-37.74
2	93.08	28.38	-63.42	-1.00	-64.43	-25	-39.43
3	130.53	33.46	-57.89	-1.23	-59.13	-25	-34.13
4	239.73	33.85	-61.51	3.82	-57.69	-25	-32.69
5	513.92	32.13	-63.26	2.81	-60.45	-25	-35.45
6	605.82	37.13	-57.56	1.78	-55.78	-25	-30.78

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 41: 5MHz

Mode	TX channel 39715	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	86.49	25.71	-66.20	-1.04	-67.25	-25	-42.25
2	135.42	24.38	-70.98	3.84	-67.14	-25	-42.14
3	286.8	25.35	-70.12	3.78	-66.33	-25	-41.33
4	344.13	21.13	-76.56	3.61	-72.95	-25	-47.95
5	471.45	24.39	-72.79	2.84	-69.95	-25	-44.95
6	735.88	16.46	-79.91	1.02	-78.88	-25	-53.88

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	43.87	14.76	-72.87	-4.91	-77.78	-25	-52.78
2	90.87	15.79	-76.01	-1.00	-77.02	-25	-52.02
3	122	9.07	-82.28	-1.23	-83.52	-25	-58.52
4	236.27	13.76	-81.60	3.82	-77.78	-25	-52.78
5	508.51	15.90	-79.49	2.81	-76.68	-25	-51.68
6	613.7	15.54	-79.15	1.78	-77.37	-25	-52.37

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 40620	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	83.56	23.83	-68.08	-1.04	-69.13	-25	-44.13
2	137.24	23.71	-71.65	3.84	-67.81	-25	-42.81
3	290.32	26.50	-68.97	3.78	-65.18	-25	-40.18
4	347.36	22.69	-75.00	3.61	-71.39	-25	-46.39
5	469.65	21.03	-76.15	2.84	-73.31	-25	-48.31
6	735.53	18.50	-77.87	1.02	-76.84	-25	-51.84

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	44.41	10.83	-76.80	-4.91	-81.71	-25	-56.71
2	89.61	18.80	-73.00	-1.00	-74.01	-25	-49.01
3	130.34	10.07	-81.28	-1.23	-82.52	-25	-57.52
4	236.32	10.90	-84.46	3.82	-80.64	-25	-55.64
5	506.95	15.80	-79.59	2.81	-76.78	-25	-51.78
6	608.51	16.09	-78.60	1.78	-76.82	-25	-51.82

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 41565	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	84.37	22.98	-68.93	-1.04	-69.98	-25	-44.98
2	137.72	26.89	-68.47	3.84	-64.63	-25	-39.63
3	287.52	24.46	-71.01	3.78	-67.22	-25	-42.22
4	345.02	22.78	-74.91	3.61	-71.30	-25	-46.30
5	472.26	25.43	-71.75	2.84	-68.91	-25	-43.91
6	737.74	19.81	-76.56	1.02	-75.53	-25	-50.53

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	43.09	13.77	-73.86	-4.91	-78.77	-25	-53.77
2	89.95	13.64	-78.16	-1.00	-79.17	-25	-54.17
3	125.58	10.46	-80.89	-1.23	-82.13	-25	-57.13
4	239.9	8.87	-86.49	3.82	-82.67	-25	-57.67
5	510.46	19.91	-75.48	2.81	-72.67	-25	-47.67
6	610.12	18.23	-76.46	1.78	-74.68	-25	-49.68

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 41: 10MHz

Mode	TX channel 39700	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	85.98	22.02	-69.89	-1.04	-70.94	-25	-45.94
2	138.18	26.46	-68.90	3.84	-65.06	-25	-40.06
3	288.19	21.29	-74.18	3.78	-70.39	-25	-45.39
4	345.39	23.77	-73.92	3.61	-70.31	-25	-45.31
5	471.54	26.42	-70.76	2.84	-67.92	-25	-42.92
6	738.67	18.62	-77.75	1.02	-76.72	-25	-51.72

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	45.13	12.65	-74.98	-4.91	-79.89	-25	-54.89
2	88.98	15.90	-75.90	-1.00	-76.91	-25	-51.91
3	127.58	9.91	-81.44	-1.23	-82.68	-25	-57.68
4	241.28	16.52	-78.84	3.82	-75.02	-25	-50.02
5	507.69	17.31	-78.08	2.81	-75.27	-25	-50.27
6	613.79	18.74	-75.95	1.78	-74.17	-25	-49.17

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 40620	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	84.15	23.22	-68.69	-1.04	-69.74	-25	-44.74
2	135.09	27.31	-68.05	3.84	-64.21	-25	-39.21
3	289.08	26.74	-68.73	3.78	-64.94	-25	-39.94
4	346.19	20.14	-77.55	3.61	-73.94	-25	-48.94
5	470.83	23.74	-73.44	2.84	-70.60	-25	-45.60
6	741.79	19.55	-76.82	1.02	-75.79	-25	-50.79

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	46.12	11.53	-76.10	-4.91	-81.01	-25	-56.01
2	99.31	19.15	-72.65	-1.00	-73.66	-25	-48.66
3	129.91	10.37	-80.98	-1.23	-82.22	-25	-57.22
4	238.92	11.16	-84.20	3.82	-80.38	-25	-55.38
5	504.44	16.61	-78.78	2.81	-75.97	-25	-50.97
6	616.3	15.99	-78.70	1.78	-76.92	-25	-51.92

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 41540	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	85.61	23.81	-68.10	-1.04	-69.15	-25	-44.15
2	136.95	23.38	-71.98	3.84	-68.14	-25	-43.14
3	288.22	23.33	-72.14	3.78	-68.35	-25	-43.35
4	346.72	23.20	-74.49	3.61	-70.88	-25	-45.88
5	468.74	24.84	-72.34	2.84	-69.50	-25	-44.50
6	738.97	17.71	-78.66	1.02	-77.63	-25	-52.63

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	45.92	11.43	-76.20	-4.91	-81.11	-25	-56.11
2	90.5	14.60	-77.20	-1.00	-78.21	-25	-53.21
3	130.29	9.06	-82.29	-1.23	-83.53	-25	-58.53
4	235.18	11.20	-84.16	3.82	-80.34	-25	-55.34
5	513.94	14.89	-80.50	2.81	-77.69	-25	-52.69
6	608.97	13.60	-81.09	1.78	-79.31	-25	-54.31

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 41: 15MHz

Mode	TX channel 39725	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	84.2	27.12	-64.79	-1.04	-65.84	-25	-40.84
2	134.19	24.25	-71.11	3.84	-67.27	-25	-42.27
3	289.28	22.83	-72.64	3.78	-68.85	-25	-43.85
4	348.5	20.82	-76.87	3.61	-73.26	-25	-48.26
5	469.37	22.72	-74.46	2.84	-71.62	-25	-46.62
6	738.9	16.61	-79.76	1.02	-78.73	-25	-53.73

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	43.64	14.13	-73.50	-4.91	-78.41	-25	-53.41
2	92.86	15.01	-76.79	-1.00	-77.80	-25	-52.80
3	125.55	9.06	-82.29	-1.23	-83.53	-25	-58.53
4	241.31	13.15	-82.21	3.82	-78.39	-25	-53.39
5	511.14	16.74	-78.65	2.81	-75.84	-25	-50.84
6	607.17	13.80	-80.89	1.78	-79.11	-25	-54.11

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 40620	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	85.85	24.32	-67.59	-1.04	-68.64	-25	-43.64
2	138.45	27.22	-68.14	3.84	-64.30	-25	-39.30
3	289.74	23.97	-71.50	3.78	-67.71	-25	-42.71
4	341.7	22.96	-74.73	3.61	-71.12	-25	-46.12
5	471.63	27.21	-69.97	2.84	-67.13	-25	-42.13
6	740.04	17.74	-78.63	1.02	-77.60	-25	-52.60

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	45.61	11.70	-75.93	-4.91	-80.84	-25	-55.84
2	95.07	15.97	-75.83	-1.00	-76.84	-25	-51.84
3	131.84	12.60	-78.75	-1.23	-79.99	-25	-54.99
4	239.55	13.80	-81.56	3.82	-77.74	-25	-52.74
5	505.81	16.78	-78.61	2.81	-75.80	-25	-50.80
6	607.76	16.21	-78.48	1.78	-76.70	-25	-51.70

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 41515	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	89.28	25.03	-66.88	-1.04	-67.93	-25	-42.93
2	134.37	27.71	-67.65	3.84	-63.81	-25	-38.81
3	287.66	24.47	-71.00	3.78	-67.21	-25	-42.21
4	346.37	20.06	-77.63	3.61	-74.02	-25	-49.02
5	472	22.82	-74.36	2.84	-71.52	-25	-46.52
6	739.07	16.79	-79.58	1.02	-78.55	-25	-53.55

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	41.23	15.42	-72.21	-4.91	-77.12	-25	-52.12
2	88.56	15.68	-76.12	-1.00	-77.13	-25	-52.13
3	117.84	11.14	-80.21	-1.23	-81.45	-25	-56.45
4	242.84	12.21	-83.15	3.82	-79.33	-25	-54.33
5	508.2	15.89	-79.50	2.81	-76.69	-25	-51.69
6	615.57	14.96	-79.73	1.78	-77.95	-25	-52.95

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 41: 20MHz

Mode	TX channel 39750	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	84.47	24.68	-67.23	-1.04	-68.28	-25	-43.28
2	140.38	26.51	-68.85	3.84	-65.01	-25	-40.01
3	292.52	25.12	-70.35	3.78	-66.56	-25	-41.56
4	344.99	21.94	-75.75	3.61	-72.14	-25	-47.14
5	465.83	23.10	-74.08	2.84	-71.24	-25	-46.24
6	740.42	18.82	-77.55	1.02	-76.52	-25	-51.52

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	48.92	12.15	-75.48	-4.91	-80.39	-25	-55.39
2	95.46	18.95	-72.85	-1.00	-73.86	-25	-48.86
3	125.76	8.77	-82.58	-1.23	-83.82	-25	-58.82
4	240.38	16.33	-79.03	3.82	-75.21	-25	-50.21
5	506.66	13.22	-82.17	2.81	-79.36	-25	-54.36
6	609.49	14.80	-79.89	1.78	-78.11	-25	-53.11

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 40620	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	87.49	26.07	-65.84	-1.04	-66.89	-25	-41.89
2	136.5	27.97	-67.39	3.84	-63.55	-25	-38.55
3	285.46	25.19	-70.28	3.78	-66.49	-25	-41.49
4	348.82	22.11	-75.58	3.61	-71.97	-25	-46.97
5	471.01	24.57	-72.61	2.84	-69.77	-25	-44.77
6	735.28	18.20	-78.17	1.02	-77.14	-25	-52.14

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	45.69	16.37	-71.26	-4.91	-76.17	-25	-51.17
2	90.06	17.79	-74.01	-1.00	-75.02	-25	-50.02
3	129.71	8.86	-82.49	-1.23	-83.73	-25	-58.73
4	233.64	12.28	-83.08	3.82	-79.26	-25	-54.26
5	508.89	18.44	-76.95	2.81	-74.14	-25	-49.14
6	610.78	12.51	-82.18	1.78	-80.40	-25	-55.40

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 41490	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	85.7	26.59	-65.32	-1.04	-66.37	-25	-41.37
2	138.09	25.57	-69.79	3.84	-65.95	-25	-40.95
3	288.91	23.67	-71.80	3.78	-68.01	-25	-43.01
4	346.87	22.05	-75.64	3.61	-72.03	-25	-47.03
5	470.09	26.03	-71.15	2.84	-68.31	-25	-43.31
6	733.84	21.75	-74.62	1.02	-73.59	-25	-48.59

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	40.29	9.80	-77.83	-4.91	-82.74	-25	-57.74
2	90	16.19	-75.61	-1.00	-76.62	-25	-51.62
3	129.09	10.20	-81.15	-1.23	-82.39	-25	-57.39
4	238.71	15.25	-80.11	3.82	-76.29	-25	-51.29
5	512.53	15.87	-79.52	2.81	-76.71	-25	-51.71
6	607.37	18.10	-76.59	1.78	-74.81	-25	-49.81

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE CA_41C (10MHz+5MHz)

Mode	TX channel 40620+40692	Frequency Range	Below 1000 MHz
------	------------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	85.18	25.02	-66.89	-1.04	-67.94	-25	-42.94
2	138.13	23.92	-71.44	3.84	-67.60	-25	-42.60
3	289.94	29.38	-66.09	3.78	-62.30	-25	-37.30
4	343.6	32.29	-65.40	3.61	-61.79	-25	-36.79
5	470.07	31.75	-65.43	2.84	-62.59	-25	-37.59
6	736.42	33.02	-63.35	1.02	-62.32	-25	-37.32

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	65.22	25.55	-62.08	-4.91	-66.99	-25	-41.99
2	92.18	24.55	-67.25	-1.00	-68.26	-25	-43.26
3	131.68	31.54	-59.81	-1.23	-61.05	-25	-36.05
4	238.28	29.51	-65.85	3.82	-62.03	-25	-37.03
5	514.6	26.95	-68.44	2.81	-65.63	-25	-40.63
6	608.73	33.38	-61.31	1.78	-59.53	-25	-34.53

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 66: 1.4MHz

Mode	TX channel 131979	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	82.83	25.64	-66.27	-1.04	-67.32	-13	-54.32
2	133.27	26.10	-69.26	3.84	-65.42	-13	-52.42
3	288.82	19.54	-75.93	3.78	-72.14	-13	-59.14
4	343.17	20.69	-77.00	3.61	-73.39	-13	-60.39
5	470.17	21.67	-75.51	2.84	-72.67	-13	-59.67
6	738.79	18.83	-77.54	1.02	-76.51	-13	-63.51

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	42.1	8.00	-79.63	-4.91	-84.54	-13	-71.54
2	89.85	11.99	-79.81	-1.00	-80.82	-13	-67.82
3	127.2	4.38	-86.97	-1.23	-88.21	-13	-75.21
4	236.57	6.75	-88.61	3.82	-84.79	-13	-71.79
5	510.12	7.30	-88.09	2.81	-85.28	-13	-72.28
6	611.03	12.14	-82.55	1.78	-80.77	-13	-67.77

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 132322	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	85.66	26.13	-65.78	-1.04	-66.83	-13	-53.83
2	134.25	24.28	-71.08	3.84	-67.24	-13	-54.24
3	290.08	21.89	-73.58	3.78	-69.79	-13	-56.79
4	343.39	22.46	-75.23	3.61	-71.62	-13	-58.62
5	470.77	25.50	-71.68	2.84	-68.84	-13	-55.84
6	738.01	18.20	-78.17	1.02	-77.14	-13	-64.14

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	46.83	7.37	-80.26	-4.91	-85.17	-13	-72.17
2	92.24	11.44	-80.36	-1.00	-81.37	-13	-68.37
3	131.6	1.23	-90.12	-1.23	-91.36	-13	-78.36
4	236.41	6.41	-88.95	3.82	-85.13	-13	-72.13
5	505.41	7.69	-87.70	2.81	-84.89	-13	-71.89
6	608	17.65	-77.04	1.78	-75.26	-13	-62.26

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 132665	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	82.84	22.98	-68.93	-1.04	-69.98	-13	-56.98
2	136.23	24.42	-70.94	3.84	-67.10	-13	-54.10
3	288.42	22.38	-73.09	3.78	-69.30	-13	-56.30
4	344.55	22.11	-75.58	3.61	-71.97	-13	-58.97
5	470.44	21.67	-75.51	2.84	-72.67	-13	-59.67
6	733.36	18.47	-77.90	1.02	-76.87	-13	-63.87

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	41.68	7.87	-79.76	-4.91	-84.67	-13	-71.67
2	89.9	11.00	-80.80	-1.00	-81.81	-13	-68.81
3	126.45	3.11	-88.24	-1.23	-89.48	-13	-76.48
4	237.43	6.59	-88.77	3.82	-84.95	-13	-71.95
5	510.11	6.46	-88.93	2.81	-86.12	-13	-73.12
6	611.81	12.03	-82.66	1.78	-80.88	-13	-67.88

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 66: 3MHz

Mode	TX channel 131987	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	79.92	23.94	-67.97	-1.04	-69.02	-13	-56.02
2	135.83	28.34	-67.02	3.84	-63.18	-13	-50.18
3	290.46	18.34	-77.13	3.78	-73.34	-13	-60.34
4	342.24	22.35	-75.34	3.61	-71.73	-13	-58.73
5	469.27	23.78	-73.40	2.84	-70.56	-13	-57.56
6	735.62	19.35	-77.02	1.02	-75.99	-13	-62.99

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	43.62	7.10	-80.53	-4.91	-85.44	-13	-72.44
2	92.67	11.13	-80.67	-1.00	-81.68	-13	-68.68
3	126.82	6.68	-84.67	-1.23	-85.91	-13	-72.91
4	237.05	6.56	-88.80	3.82	-84.98	-13	-71.98
5	502.95	8.12	-87.27	2.81	-84.46	-13	-71.46
6	609.8	8.72	-85.97	1.78	-84.19	-13	-71.19

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 132322	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	85.38	26.72	-65.19	-1.04	-66.24	-13	-53.24
2	134.78	26.51	-68.85	3.84	-65.01	-13	-52.01
3	287.13	27.46	-68.01	3.78	-64.22	-13	-51.22
4	341.86	23.40	-74.29	3.61	-70.68	-13	-57.68
5	473.45	25.04	-72.14	2.84	-69.30	-13	-56.30
6	736.56	16.97	-79.40	1.02	-78.37	-13	-65.37

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	46.67	6.95	-80.68	-4.91	-85.59	-13	-72.59
2	98.56	10.32	-81.48	-1.00	-82.49	-13	-69.49
3	127.39	3.58	-87.77	-1.23	-89.01	-13	-76.01
4	237.92	10.28	-85.08	3.82	-81.26	-13	-68.26
5	510.75	8.88	-86.51	2.81	-83.70	-13	-70.70
6	614.78	11.24	-83.45	1.78	-81.67	-13	-68.67

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 132657	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	85.5	26.51	-65.40	-1.04	-66.45	-13	-53.45
2	140.65	24.84	-70.52	3.84	-66.68	-13	-53.68
3	286.26	22.74	-72.73	3.78	-68.94	-13	-55.94
4	343.87	23.02	-74.67	3.61	-71.06	-13	-58.06
5	471.47	21.36	-75.82	2.84	-72.98	-13	-59.98
6	733.15	19.05	-77.32	1.02	-76.29	-13	-63.29

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	42.72	6.00	-81.63	-4.91	-86.54	-13	-73.54
2	92.79	8.31	-83.49	-1.00	-84.50	-13	-71.50
3	126.85	2.44	-88.91	-1.23	-90.15	-13	-77.15
4	239.97	7.40	-87.96	3.82	-84.14	-13	-71.14
5	509.1	8.49	-86.90	2.81	-84.09	-13	-71.09
6	609.94	12.61	-82.08	1.78	-80.30	-13	-67.30

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 66: 5MHz

Mode	TX channel 131997	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	86.08	24.75	-67.16	-1.04	-68.21	-13	-55.21
2	134.81	27.45	-67.91	3.84	-64.07	-13	-51.07
3	288.08	23.30	-72.17	3.78	-68.38	-13	-55.38
4	345.46	26.51	-71.18	3.61	-67.57	-13	-54.57
5	471.26	23.79	-73.39	2.84	-70.55	-13	-57.55
6	736.15	20.37	-76.00	1.02	-74.97	-13	-61.97

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	49.03	10.25	-77.38	-4.91	-82.29	-13	-69.29
2	89.72	13.05	-78.75	-1.00	-79.76	-13	-66.76
3	129.28	-2.33	-93.68	-1.23	-94.92	-13	-81.92
4	241.45	12.32	-83.04	3.82	-79.22	-13	-66.22
5	509.45	12.23	-83.16	2.81	-80.35	-13	-67.35
6	613.17	13.37	-81.32	1.78	-79.54	-13	-66.54

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 132322	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	81.17	24.41	-67.50	-1.04	-68.55	-13	-55.55
2	136.03	24.89	-70.47	3.84	-66.63	-13	-53.63
3	286.62	20.30	-75.17	3.78	-71.38	-13	-58.38
4	345.7	21.72	-75.97	3.61	-72.36	-13	-59.36
5	470.16	21.72	-75.46	2.84	-72.62	-13	-59.62
6	737.99	19.47	-76.90	1.02	-75.87	-13	-62.87

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	40.33	6.17	-81.46	-4.91	-86.37	-13	-73.37
2	88.91	11.90	-79.90	-1.00	-80.91	-13	-67.91
3	124.13	8.57	-82.78	-1.23	-84.02	-13	-71.02
4	238.26	5.74	-89.62	3.82	-85.80	-13	-72.80
5	509.17	10.02	-85.37	2.81	-82.56	-13	-69.56
6	610.84	13.43	-81.26	1.78	-79.48	-13	-66.48

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 132647	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	81.53	26.82	-65.09	-1.04	-66.14	-13	-53.14
2	136.53	29.48	-65.88	3.84	-62.04	-13	-49.04
3	284.82	21.20	-74.27	3.78	-70.48	-13	-57.48
4	344.52	20.64	-77.05	3.61	-73.44	-13	-60.44
5	473.57	24.00	-73.18	2.84	-70.34	-13	-57.34
6	735	21.17	-75.20	1.02	-74.17	-13	-61.17

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	38.71	8.55	-79.08	-4.91	-83.99	-13	-70.99
2	91.66	10.28	-81.52	-1.00	-82.53	-13	-69.53
3	130.24	-2.46	-93.81	-1.23	-95.05	-13	-82.05
4	237.64	8.44	-86.92	3.82	-83.10	-13	-70.10
5	510.8	6.87	-88.52	2.81	-85.71	-13	-72.71
6	614.82	11.07	-83.62	1.78	-81.84	-13	-68.84

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 66: 10MHz

Mode	TX channel 132022	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	84.92	23.78	-68.13	-1.04	-69.18	-13	-56.18
2	133.61	26.32	-69.04	3.84	-65.20	-13	-52.20
3	288.6	22.28	-73.19	3.78	-69.40	-13	-56.40
4	344.88	24.19	-73.50	3.61	-69.89	-13	-56.89
5	469.83	23.66	-73.52	2.84	-70.68	-13	-57.68
6	739.63	21.50	-74.87	1.02	-73.84	-13	-60.84

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	41.63	11.36	-76.27	-4.91	-81.18	-13	-68.18
2	88.95	11.75	-80.05	-1.00	-81.06	-13	-68.06
3	133.29	1.35	-90.00	-1.23	-91.24	-13	-78.24
4	240.13	6.62	-88.74	3.82	-84.92	-13	-71.92
5	507.58	13.15	-82.24	2.81	-79.43	-13	-66.43
6	611.56	15.85	-78.84	1.78	-77.06	-13	-64.06

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 132322	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	86.86	25.24	-66.67	-1.04	-67.72	-13	-54.72
2	136.13	25.02	-70.34	3.84	-66.50	-13	-53.50
3	287.73	22.30	-73.17	3.78	-69.38	-13	-56.38
4	342.39	23.61	-74.08	3.61	-70.47	-13	-57.47
5	472.81	24.79	-72.39	2.84	-69.55	-13	-56.55
6	730.37	15.68	-80.69	1.02	-79.66	-13	-66.66

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	43.06	6.74	-80.89	-4.91	-85.80	-13	-72.80
2	89.88	11.09	-80.71	-1.00	-81.72	-13	-68.72
3	127.16	3.56	-87.79	-1.23	-89.03	-13	-76.03
4	235.9	6.73	-88.63	3.82	-84.81	-13	-71.81
5	510.16	6.63	-88.76	2.81	-85.95	-13	-72.95
6	610.1	11.34	-83.35	1.78	-81.57	-13	-68.57

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 132622	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	84.95	25.61	-66.30	-1.04	-67.35	-13	-54.35
2	133.08	25.88	-69.48	3.84	-65.64	-13	-52.64
3	285.79	24.11	-71.36	3.78	-67.57	-13	-54.57
4	346.11	24.17	-73.52	3.61	-69.91	-13	-56.91
5	471.63	22.41	-74.77	2.84	-71.93	-13	-58.93
6	731.21	18.30	-78.07	1.02	-77.04	-13	-64.04

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	37.89	6.41	-81.22	-4.91	-86.13	-13	-73.13
2	94.79	11.24	-80.56	-1.00	-81.57	-13	-68.57
3	127.93	4.50	-86.85	-1.23	-88.09	-13	-75.09
4	235.84	4.15	-91.21	3.82	-87.39	-13	-74.39
5	513.14	13.83	-81.56	2.81	-78.75	-13	-65.75
6	606.25	10.20	-84.49	1.78	-82.71	-13	-69.71

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 66: 15MHz

Mode	TX channel 132047	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	84.05	26.04	-65.87	-1.04	-66.92	-13	-53.92
2	133.99	25.28	-70.08	3.84	-66.24	-13	-53.24
3	291.49	22.62	-72.85	3.78	-69.06	-13	-56.06
4	344.64	22.65	-75.04	3.61	-71.43	-13	-58.43
5	466.49	24.41	-72.77	2.84	-69.93	-13	-56.93
6	735.76	19.43	-76.94	1.02	-75.91	-13	-62.91

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	40.33	5.24	-82.39	-4.91	-87.30	-13	-74.30
2	94.04	15.23	-76.57	-1.00	-77.58	-13	-64.58
3	126.09	6.27	-85.08	-1.23	-86.32	-13	-73.32
4	244	7.28	-88.08	3.82	-84.26	-13	-71.26
5	513.91	12.08	-83.31	2.81	-80.50	-13	-67.50
6	612.17	10.16	-84.53	1.78	-82.75	-13	-69.75

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 132322	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	84.63	25.65	-67.62	-1.50	-69.12	-13	-56.12
2	132.09	26.16	-69.55	5.18	-64.37	-13	-51.37
3	286.08	25.42	-70.00	3.79	-66.21	-13	-53.21
4	344.57	24.07	-73.61	3.61	-70.00	-13	-57.00
5	467.67	20.07	-77.11	2.84	-74.27	-13	-61.27
6	737.47	21.33	-75.04	1.01	-74.02	-13	-61.02

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	44.85	5.27	-81.29	-5.43	-86.72	-13	-73.72
2	87.46	12.74	-79.20	-1.05	-80.25	-13	-67.25
3	128.16	4.18	-87.61	-1.25	-88.86	-13	-75.86
4	237.92	3.07	-92.29	3.83	-88.46	-13	-75.46
5	507.91	12.39	-83.02	2.82	-80.20	-13	-67.20
6	616.66	16.17	-78.53	1.78	-76.74	-13	-63.74

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 132597	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	83.54	26.94	-64.97	-1.04	-66.02	-13	-53.02
2	134.46	27.33	-68.03	3.84	-64.19	-13	-51.19
3	291.42	20.67	-74.80	3.78	-71.01	-13	-58.01
4	347.06	26.56	-71.13	3.61	-67.52	-13	-54.52
5	468.82	23.40	-73.78	2.84	-70.94	-13	-57.94
6	738.52	19.95	-76.42	1.02	-75.39	-13	-62.39

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	42.04	7.89	-79.74	-4.91	-84.65	-13	-71.65
2	97.01	10.46	-81.34	-1.00	-82.35	-13	-69.35
3	130.34	0.60	-90.75	-1.23	-91.99	-13	-78.99
4	245.6	6.67	-88.69	3.82	-84.87	-13	-71.87
5	509.06	10.42	-84.97	2.81	-82.16	-13	-69.16
6	607.21	11.71	-82.98	1.78	-81.20	-13	-68.20

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 66: 20MHz

Mode	TX channel 132072	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	83.31	25.57	-66.34	-1.04	-67.39	-13	-54.39
2	136.31	25.74	-69.62	3.84	-65.78	-13	-52.78
3	286.33	24.21	-71.26	3.78	-67.47	-13	-54.47
4	344.84	24.10	-73.59	3.61	-69.98	-13	-56.98
5	469	22.89	-74.29	2.84	-71.45	-13	-58.45
6	733.34	17.34	-79.03	1.02	-78.00	-13	-65.00

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	48.04	7.11	-80.52	-4.91	-85.43	-13	-72.43
2	89.12	10.84	-80.96	-1.00	-81.97	-13	-68.97
3	131	3.79	-87.56	-1.23	-88.80	-13	-75.80
4	239.13	5.26	-90.10	3.82	-86.28	-13	-73.28
5	516.04	17.11	-78.28	2.81	-75.47	-13	-62.47
6	613.34	9.97	-84.72	1.78	-82.94	-13	-69.94

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 132322	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	82.66	25.07	-68.07	-1.45	-69.53	-13	-56.53
2	136.67	28.06	-67.65	5.18	-62.47	-13	-49.47
3	289.86	21.27	-74.18	3.79	-70.39	-13	-57.39
4	345.68	26.71	-70.99	3.60	-67.38	-13	-54.38
5	471.92	21.96	-75.21	2.84	-72.37	-13	-59.37
6	739.08	16.65	-79.72	1.01	-78.70	-13	-65.70

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	47.4	10.34	-76.17	-5.46	-81.63	-13	-68.63
2	89.15	8.64	-83.33	-1.06	-84.39	-13	-71.39
3	129.75	-3.93	-95.50	-1.24	-96.74	-13	-83.74
4	243.46	7.73	-87.63	3.85	-83.79	-13	-70.79
5	511.67	8.52	-86.90	2.82	-84.07	-13	-71.07
6	609.18	13.79	-80.91	1.78	-79.13	-13	-66.13

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 132572	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	83.74	26.32	-65.59	-1.04	-66.64	-13	-53.64
2	135.5	25.85	-69.51	3.84	-65.67	-13	-52.67
3	289.62	24.31	-71.16	3.78	-67.37	-13	-54.37
4	345.5	23.83	-73.86	3.61	-70.25	-13	-57.25
5	472.56	23.44	-73.74	2.84	-70.90	-13	-57.90
6	734.31	21.24	-75.13	1.02	-74.10	-13	-61.10

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	43.47	11.08	-76.55	-4.91	-81.46	-13	-68.46
2	97.96	11.29	-80.51	-1.00	-81.52	-13	-68.52
3	123.16	2.72	-88.63	-1.23	-89.87	-13	-76.87
4	237.79	8.39	-86.97	3.82	-83.15	-13	-70.15
5	506.88	8.70	-86.69	2.81	-83.88	-13	-70.88
6	612.41	12.99	-81.70	1.78	-79.92	-13	-66.92

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

ABOVE 1GHz

WCDMA:

Mode	TX channel 1312	Frequency Range	Above 1000 MHz
------	-----------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3424.8	38.20	-65.95	7.68	-58.27	-13	-45.27
2	5137.2	42.80	-61.94	7.02	-54.92	-13	-41.92
3	6849.6	45.70	-56.92	4.53	-52.39	-13	-39.39
4	8562	48.5	-53.37	4.21	-49.17	-13	-36.17
5	10274.4	49.2	-52.29	3.48	-48.81	-13	-35.81
6	11986.8	49.6	-51.01	4.06	-46.94	-13	-33.94
7	13699.2	51.4	-45.95	3.70	-42.25	-13	-29.25
8	15411.6	51.9	-45.45	3.70	-41.75	-13	-28.75
9	17124	52.5	-44.85	3.70	-41.15	-13	-28.15

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3424.8	38.9	-65.47	7.90	-57.57	-13	-44.57
2	5137.2	45.3	-59.80	7.37	-52.42	-13	-39.42
3	6849.6	45.5	-57.69	5.10	-52.59	-13	-39.59
4	8562	47.7	-54.33	4.36	-49.97	-13	-36.97
5	10274.4	49.5	-50.59	2.08	-48.51	-13	-35.51
6	11986.8	49.9	-50.87	4.23	-46.64	-13	-33.64
7	13699.2	53.5	-41.94	1.79	-40.15	-13	-27.15
8	15411.6	51.8	-45.55	3.70	-41.85	-13	-28.85
9	17124	52.3	-45.05	3.70	-41.35	-13	-28.35

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 1413	Frequency Range	Above 1000 MHz
------	-----------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3465.2	38.31	-65.84	7.68	-58.16	-13	-45.16
2	5197.8	43.63	-61.11	7.02	-54.09	-13	-41.09
3	6930.4	44.99	-57.63	4.53	-53.10	-13	-40.10
4	8663	49.29	-52.58	4.21	-48.38	-13	-35.38
5	10395.6	48.55	-52.94	3.48	-49.46	-13	-36.46
6	12128.2	48.63	-51.98	4.06	-47.91	-13	-34.91
7	13860.8	51.4	-45.95	3.70	-42.25	-13	-29.25
8	15593.4	51.42	-45.93	3.70	-42.23	-13	-29.23
9	17326	52.64	-44.71	3.70	-41.01	-13	-28.01

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3465.2	38.39	-65.95	7.87	-58.08	-13	-45.08
2	5197.8	45.93	-59.12	7.33	-51.79	-13	-38.79
3	6930.4	45.69	-57.43	5.03	-52.40	-13	-39.40
4	8663	48.01	-54.00	4.34	-49.66	-13	-36.66
5	10395.6	50	-50.26	2.24	-48.01	-13	-35.01
6	12128.2	49.22	-51.58	4.26	-47.32	-13	-34.32
7	13860.8	52.54	-43.13	2.03	-41.11	-13	-28.11
8	15593.4	52.42	-44.93	3.70	-41.23	-13	-28.23
9	17326	53.13	-44.22	3.70	-40.52	-13	-27.52

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 1513	Frequency Range	Above 1000 MHz
------	-----------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3505.2	38.20	-65.95	7.68	-58.27	-13	-45.27
2	5257.8	42.09	-62.65	7.02	-55.63	-13	-42.63
3	7010.4	46.55	-56.07	4.53	-51.54	-13	-38.54
4	8763	48.79	-53.08	4.21	-48.88	-13	-35.88
5	10515.6	50.19	-51.30	3.48	-47.82	-13	-34.82
6	12268.2	50.13	-50.48	4.06	-46.41	-13	-33.41
7	14020.8	51.02	-46.33	3.70	-42.63	-13	-29.63
8	15773.4	51.08	-46.27	3.70	-42.57	-13	-29.57
9	17526	52.69	-44.66	3.70	-40.96	-13	-27.96

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3505.2	38.94	-65.38	7.84	-57.53	-13	-44.53
2	5257.8	46.37	-58.64	7.29	-51.35	-13	-38.35
3	7010.4	45.76	-57.29	4.96	-52.33	-13	-39.33
4	8763	48.27	-53.72	4.32	-49.40	-13	-36.40
5	10515.6	50.06	-50.36	2.41	-47.95	-13	-34.95
6	12268.2	48.59	-52.24	4.29	-47.95	-13	-34.95
7	14020.8	51.99	-43.92	2.26	-41.66	-13	-28.66
8	15773.4	53.32	-44.03	3.70	-40.33	-13	-27.33
9	17526	54.04	-43.31	3.70	-39.61	-13	-26.61

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 4: 1.4MHz

Mode	TX channel 19957	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3421.4	35.19	-67.88	7.87	-60.01	-13	-47.01
2	5132.1	44.65	-59.88	7.05	-52.82	-13	-39.82
3	6842.8	49.80	-52.14	5.03	-47.11	-13	-34.11
4	8553.5	48.84	-53.87	4.23	-49.64	-13	-36.64
5	10264.2	51.50	-50.17	2.24	-47.93	-13	-34.93
6	11974.9	49.77	-51.71	4.38	-47.33	-13	-34.33
7	13685.6	54.33	-45.52	1.93	-43.58	-13	-30.58
8	15396.3	53.80	-43.55	3.70	-39.85	-13	-26.85
9	17107	45.06	-53.96	3.77	-50.19	-13	-37.19

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3421.4	40.49	-62.58	7.87	-54.71	-13	-41.71
2	5132.1	45.68	-58.85	7.05	-51.79	-13	-38.79
3	6842.8	48.18	-53.76	5.03	-48.73	-13	-35.73
4	8553.5	49.81	-52.90	4.23	-48.67	-13	-35.67
5	10264.2	54.37	-47.30	2.24	-45.06	-13	-32.06
6	11974.9	51.45	-50.03	4.38	-45.65	-13	-32.65
7	13685.6	58.79	-41.06	1.93	-39.12	-13	-26.12
8	15396.3	53.34	-44.01	3.70	-40.31	-13	-27.31
9	17107	51.50	-47.52	3.77	-43.75	-13	-30.75

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 20175	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3465	45.41	-57.66	7.87	-49.79	-13	-36.79
2	5197.5	42.69	-62.80	7.33	-55.47	-13	-42.47
3	6930	46.57	-56.05	5.03	-51.02	-13	-38.02
4	8662.5	52.35	-51.40	4.34	-47.05	-13	-34.05
5	10395	46.99	-54.68	2.24	-52.44	-13	-39.44
6	12127.5	44.28	-57.89	4.26	-53.64	-13	-40.64
7	13860	58.27	-40.84	2.03	-38.81	-13	-25.81
8	15592.5	48.95	-48.40	3.70	-44.70	-13	-31.70
9	17325	46.25	-51.10	3.70	-47.40	-13	-34.40

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3465	41.58	-61.49	7.87	-53.62	-13	-40.62
2	5197.5	45.50	-59.99	7.33	-52.66	-13	-39.66
3	6930	47.97	-54.65	5.03	-49.62	-13	-36.62
4	8662.5	49.03	-54.72	4.34	-50.37	-13	-37.37
5	10395	54.24	-47.43	2.24	-45.19	-13	-32.19
6	12127.5	49.79	-52.38	4.26	-48.13	-13	-35.13
7	13860	59.48	-39.63	2.03	-37.60	-13	-24.60
8	15592.5	52.85	-44.50	3.70	-40.80	-13	-27.80
9	17325	51.89	-45.46	3.70	-41.76	-13	-28.76

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 20393	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3508.6	39.40	-63.83	7.84	-55.99	-13	-42.99
2	5262.9	40.32	-65.06	7.29	-57.77	-13	-44.77
3	7017.2	51.00	-51.62	4.43	-47.19	-13	-34.19
4	8771.5	51.49	-50.12	4.18	-45.95	-13	-32.95
5	10525.8	49.91	-51.73	2.43	-49.31	-13	-36.31
6	12280.1	43.21	-57.11	3.57	-53.54	-13	-40.54
7	14034.4	56.95	-40.40	3.70	-36.70	-13	-23.70
8	15788.7	50.28	-47.07	3.70	-43.37	-13	-30.37
9	17543	48.54	-48.81	3.70	-45.11	-13	-32.11

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3508.6	39.87	-63.36	7.84	-55.52	-13	-42.52
2	5262.9	46.58	-58.80	7.29	-51.51	-13	-38.51
3	7017.2	47.78	-54.84	4.43	-50.41	-13	-37.41
4	8771.5	49.95	-51.66	4.18	-47.49	-13	-34.49
5	10525.8	52.61	-49.03	2.43	-46.61	-13	-33.61
6	12280.1	50.84	-49.48	3.57	-45.91	-13	-32.91
7	14034.4	58.60	-38.75	3.70	-35.05	-13	-22.05
8	15788.7	52.92	-44.43	3.70	-40.73	-13	-27.73
9	17543	52.42	-44.93	3.70	-41.23	-13	-28.23

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 4: 3MHz

Mode	TX channel 19965	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3423	47.97	-54.95	7.90	-47.05	-13	-34.05
2	5134.5	38.52	-67.07	7.38	-59.70	-13	-46.70
3	6846	46.66	-55.18	5.10	-50.07	-13	-37.07
4	8557.5	47.14	-56.87	4.36	-52.51	-13	-39.51
5	10269	52.36	-49.34	2.07	-47.27	-13	-34.27
6	11980.5	50.81	-51.59	4.22	-47.37	-13	-34.37
7	13692	59.30	-40.06	1.78	-38.29	-13	-25.29
8	15403.5	52.16	-45.19	3.70	-41.49	-13	-28.49
9	17115	43.63	-53.72	3.70	-50.02	-13	-37.02

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3423	38.96	-63.96	7.90	-56.06	-13	-43.06
2	5134.5	44.98	-60.61	7.38	-53.24	-13	-40.24
3	6846	49.29	-52.55	5.10	-47.44	-13	-34.44
4	8557.5	48.69	-55.32	4.36	-50.96	-13	-37.96
5	10269	53.44	-48.26	2.07	-46.19	-13	-33.19
6	11980.5	51.72	-50.68	4.22	-46.46	-13	-33.46
7	13692	58.74	-40.62	1.78	-38.85	-13	-25.85
8	15403.5	53.51	-43.84	3.70	-40.14	-13	-27.14
9	17115	53.02	-44.33	3.70	-40.63	-13	-27.63

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 20175	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3465	41.54	-61.53	7.87	-53.66	-13	-40.66
2	5197.5	40.56	-64.93	7.33	-57.60	-13	-44.60
3	6930	45.41	-57.21	5.03	-52.18	-13	-39.18
4	8662.5	52.77	-50.98	4.34	-46.63	-13	-33.63
5	10395	52.56	-49.11	2.24	-46.87	-13	-33.87
6	12127.5	58.75	-43.42	4.26	-39.17	-13	-26.17
7	13860	58.17	-40.94	2.03	-38.91	-13	-25.91
8	15592.5	47.21	-50.14	3.70	-46.44	-13	-33.44
9	17325	48.93	-48.42	3.70	-44.72	-13	-31.72

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3465	41.24	-61.83	7.87	-53.96	-13	-40.96
2	5197.5	44.83	-60.66	7.33	-53.33	-13	-40.33
3	6930	48.09	-54.53	5.03	-49.50	-13	-36.50
4	8662.5	49.79	-53.96	4.34	-49.61	-13	-36.61
5	10395	53.37	-48.30	2.24	-46.06	-13	-33.06
6	12127.5	49.74	-52.43	4.26	-48.18	-13	-35.18
7	13860	59.50	-39.61	2.03	-37.58	-13	-24.58
8	15592.5	53.05	-44.30	3.70	-40.60	-13	-27.60
9	17325	51.37	-45.98	3.70	-42.28	-13	-29.28

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 20385	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3507	47.13	-56.10	7.84	-48.25	-13	-35.25
2	5260.5	46.49	-58.89	7.29	-51.60	-13	-38.60
3	7014	38.04	-64.58	4.43	-60.15	-13	-47.15
4	8767.5	45.61	-56.00	4.18	-51.83	-13	-38.83
5	10521	52.69	-48.96	2.42	-46.54	-13	-33.54
6	12274.5	47.52	-52.80	3.57	-49.23	-13	-36.23
7	14028	58.71	-38.64	3.70	-34.94	-13	-21.94
8	15781.5	50.14	-47.21	3.70	-43.51	-13	-30.51
9	17535	47.72	-49.63	3.70	-45.93	-13	-32.93

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3507	40.16	-63.07	7.84	-55.22	-13	-42.22
2	5260.5	46.26	-59.12	7.29	-51.83	-13	-38.83
3	7014	48.55	-54.07	4.43	-49.64	-13	-36.64
4	8767.5	49.99	-51.62	4.18	-47.45	-13	-34.45
5	10521	54.54	-47.11	2.42	-44.69	-13	-31.69
6	12274.5	51.14	-49.18	3.57	-45.61	-13	-32.61
7	14028	59.64	-37.71	3.70	-34.01	-13	-21.01
8	15781.5	53.43	-43.92	3.70	-40.22	-13	-27.22
9	17535	51.27	-46.08	3.70	-42.38	-13	-29.38

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 4: 5MHz

Mode	TX channel 19957	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3425	40.84	-62.09	7.90	-54.19	-13	-41.19
2	5137.5	40.62	-64.97	7.37	-57.60	-13	-44.60
3	6850	47.35	-54.49	5.10	-49.39	-13	-36.39
4	8562.5	52.68	-51.32	4.36	-46.96	-13	-33.96
5	10275	48.07	-53.63	2.08	-51.55	-13	-38.55
6	11987.5	47.43	-54.96	4.23	-50.73	-13	-37.73
7	13700	55.09	-44.26	1.79	-42.47	-13	-29.47
8	15412.5	53.58	-43.77	3.70	-40.07	-13	-27.07
9	17125	49.34	-48.01	3.70	-44.31	-13	-31.31

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3425	41.19	-61.74	7.90	-53.84	-13	-40.84
2	5137.5	45.61	-59.98	7.37	-52.61	-13	-39.61
3	6850	48.76	-53.08	5.10	-47.98	-13	-34.98
4	8562.5	49.85	-54.15	4.36	-49.79	-13	-36.79
5	10275	53.05	-48.65	2.08	-46.57	-13	-33.57
6	11987.5	50.88	-51.51	4.23	-47.28	-13	-34.28
7	13700	59.48	-39.87	1.79	-38.08	-13	-25.08
8	15412.5	53.83	-43.52	3.70	-39.82	-13	-26.82
9	17125	52.08	-45.27	3.70	-41.57	-13	-28.57

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 20175	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3465	38.51	-64.56	7.87	-56.69	-13	-43.69
2	5197.5	43.69	-61.80	7.33	-54.47	-13	-41.47
3	6930	40.02	-62.60	5.03	-57.57	-13	-44.57
4	8662.5	47.36	-56.39	4.34	-52.04	-13	-39.04
5	10395	63.09	-38.58	2.24	-36.34	-13	-23.34
6	12127.5	51.29	-50.88	4.26	-46.63	-13	-33.63
7	13860	60.94	-38.17	2.03	-36.14	-13	-23.14
8	15592.5	57.58	-39.77	3.70	-36.07	-13	-23.07
9	17325	46.85	-50.50	3.70	-46.80	-13	-33.80

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3465	38.94	-64.13	7.87	-56.26	-13	-43.26
2	5197.5	46.34	-59.15	7.33	-51.82	-13	-38.82
3	6930	48.61	-54.01	5.03	-48.98	-13	-35.98
4	8662.5	50.17	-53.58	4.34	-49.23	-13	-36.23
5	10395	54.85	-46.82	2.24	-44.58	-13	-31.58
6	12127.5	50.48	-51.69	4.26	-47.44	-13	-34.44
7	13860	57.65	-41.46	2.03	-39.43	-13	-26.43
8	15592.5	52.97	-44.38	3.70	-40.68	-13	-27.68
9	17325	52.22	-45.13	3.70	-41.43	-13	-28.43

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 20375	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3505	39.99	-63.23	7.84	-55.38	-13	-42.38
2	5257.5	44.57	-60.82	7.29	-53.53	-13	-40.53
3	7010	48.66	-53.96	4.43	-49.53	-13	-36.53
4	8762.5	49.90	-51.71	4.18	-47.54	-13	-34.54
5	10515	49.88	-51.77	2.41	-49.35	-13	-36.35
6	12267.5	54.85	-45.47	3.57	-41.90	-13	-28.90
7	14020	58.36	-38.99	3.70	-35.29	-13	-22.29
8	15772.5	52.79	-44.56	3.70	-40.86	-13	-27.86
9	17525	49.47	-47.88	3.70	-44.18	-13	-31.18

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3505	40.07	-63.15	7.84	-55.30	-13	-42.30
2	5257.5	44.81	-60.58	7.29	-53.29	-13	-40.29
3	7010	48.47	-54.15	4.43	-49.72	-13	-36.72
4	8762.5	50.18	-51.43	4.18	-47.26	-13	-34.26
5	10515	52.96	-48.69	2.41	-46.27	-13	-33.27
6	12267.5	50.58	-49.74	3.57	-46.17	-13	-33.17
7	14020	59.90	-37.45	3.70	-33.75	-13	-20.75
8	15772.5	52.39	-44.96	3.70	-41.26	-13	-28.26
9	17525	52.64	-44.71	3.70	-41.01	-13	-28.01

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 4: 10MHz

Mode	TX channel 20000	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3430	43.34	-59.60	7.89	-51.71	-13	-38.71
2	5145	42.20	-63.38	7.37	-56.01	-13	-43.01
3	6860	52.05	-49.80	5.09	-44.71	-13	-31.71
4	8575	49.65	-54.32	4.36	-49.96	-13	-36.96
5	10290	52.53	-49.16	2.10	-47.06	-13	-34.06
6	12005	49.30	-53.06	4.23	-48.83	-13	-35.83
7	13720	59.53	-39.79	1.82	-37.97	-13	-24.97
8	15435	48.82	-48.53	3.70	-44.83	-13	-31.83
9	17150	50.94	-46.41	3.70	-42.71	-13	-29.71

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3430	39.54	-63.40	7.89	-55.51	-13	-42.51
2	5145	43.79	-61.79	7.37	-54.42	-13	-41.42
3	6860	49.14	-52.71	5.09	-47.62	-13	-34.62
4	8575	50.03	-53.94	4.36	-49.58	-13	-36.58
5	10290	54.32	-47.37	2.10	-45.27	-13	-32.27
6	12005	50.95	-51.41	4.23	-47.18	-13	-34.18
7	13720	59.04	-40.28	1.82	-38.46	-13	-25.46
8	15435	52.15	-45.20	3.70	-41.50	-13	-28.50
9	17150	51.86	-45.49	3.70	-41.79	-13	-28.79

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 20175	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3465	46.12	-56.95	7.87	-49.08	-13	-36.08
2	5197.5	46.53	-58.96	7.33	-51.63	-13	-38.63
3	6930	41.95	-60.67	5.03	-55.64	-13	-42.64
4	8662.5	46.75	-57.00	4.34	-52.65	-13	-39.65
5	10395	50.53	-51.14	2.24	-48.90	-13	-35.90
6	12127.5	53.50	-48.67	4.26	-44.42	-13	-31.42
7	13860	57.21	-41.90	2.03	-39.87	-13	-26.87
8	15592.5	51.06	-46.29	3.70	-42.59	-13	-29.59
9	17325	44.16	-53.19	3.70	-49.49	-13	-36.49

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3465	38.91	-64.16	7.87	-56.29	-13	-43.29
2	5197.5	45.43	-60.06	7.33	-52.73	-13	-39.73
3	6930	48.39	-54.23	5.03	-49.20	-13	-36.20
4	8662.5	49.25	-54.50	4.34	-50.15	-13	-37.15
5	10395	53.58	-48.09	2.24	-45.85	-13	-32.85
6	12127.5	50.44	-51.73	4.26	-47.48	-13	-34.48
7	13860	58.37	-40.74	2.03	-38.71	-13	-25.71
8	15592.5	53.29	-44.06	3.70	-40.36	-13	-27.36
9	17325	51.84	-45.51	3.70	-41.81	-13	-28.81

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 20350	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3500	37.69	-65.51	7.85	-57.66	-13	-44.66
2	5250	47.85	-57.55	7.29	-50.26	-13	-37.26
3	7000	52.71	-49.91	4.43	-45.48	-13	-32.48
4	8750	51.57	-50.04	4.18	-45.87	-13	-32.87
5	10500	54.83	-46.82	2.39	-44.43	-13	-31.43
6	12250	46.19	-54.13	3.57	-50.56	-13	-37.56
7	14000	60.77	-36.58	3.70	-32.88	-13	-19.88
8	15750	48.41	-48.94	3.70	-45.24	-13	-32.24
9	17500	43.26	-54.09	3.70	-50.39	-13	-37.39

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3500	39.63	-63.57	7.85	-55.72	-13	-42.72
2	5250	47.18	-58.22	7.29	-50.93	-13	-37.93
3	7000	48.18	-54.44	4.43	-50.01	-13	-37.01
4	8750	50.38	-51.23	4.18	-47.06	-13	-34.06
5	10500	53.26	-48.39	2.39	-46.00	-13	-33.00
6	12250	49.52	-50.80	3.57	-47.23	-13	-34.23
7	14000	58.63	-38.72	3.70	-35.02	-13	-22.02
8	15750	53.56	-43.79	3.70	-40.09	-13	-27.09
9	17500	51.12	-46.23	3.70	-42.53	-13	-29.53

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 4: 15MHz

Mode	TX channel 20025	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3435	42.93	-60.03	7.89	-52.14	-13	-39.14
2	5152.5	42.43	-63.13	7.36	-55.77	-13	-42.77
3	6870	45.38	-56.48	5.08	-51.40	-13	-38.40
4	8587.5	49.70	-54.24	4.36	-49.88	-13	-36.88
5	10305	54.67	-47.02	2.12	-44.90	-13	-31.90
6	12022.5	53.51	-48.83	4.23	-44.59	-13	-31.59
7	13740	55.98	-43.31	1.85	-41.46	-13	-28.46
8	15457.5	53.10	-44.25	3.70	-40.55	-13	-27.55
9	17175	50.21	-47.14	3.70	-43.44	-13	-30.44

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3435	39.81	-63.15	7.89	-55.26	-13	-42.26
2	5152.5	45.93	-59.63	7.36	-52.27	-13	-39.27
3	6870	48.10	-53.76	5.08	-48.68	-13	-35.68
4	8587.5	50.47	-53.47	4.36	-49.11	-13	-36.11
5	10305	54.51	-47.18	2.12	-45.06	-13	-32.06
6	12022.5	51.81	-50.53	4.23	-46.29	-13	-33.29
7	13740	59.79	-39.50	1.85	-37.65	-13	-24.65
8	15457.5	53.71	-43.64	3.70	-39.94	-13	-26.94
9	17175	52.52	-44.83	3.70	-41.13	-13	-28.13

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 20175	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3465	41.92	-61.15	7.87	-53.28	-13	-40.28
2	5197.5	45.61	-59.88	7.33	-52.55	-13	-39.55
3	6930	48.56	-54.06	5.03	-49.03	-13	-36.03
4	8662.5	45.49	-58.26	4.34	-53.91	-13	-40.91
5	10395	53.80	-47.87	2.24	-45.63	-13	-32.63
6	12127.5	47.18	-54.99	4.26	-50.74	-13	-37.74
7	13860	60.17	-38.94	2.03	-36.91	-13	-23.91
8	15592.5	53.34	-44.01	3.70	-40.31	-13	-27.31
9	17325	46.93	-50.42	3.70	-46.72	-13	-33.72

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3465	38.82	-64.25	7.87	-56.38	-13	-43.38
2	5197.5	45.99	-59.50	7.33	-52.17	-13	-39.17
3	6930	48.69	-53.93	5.03	-48.90	-13	-35.90
4	8662.5	51.35	-52.40	4.34	-48.05	-13	-35.05
5	10395	54.74	-46.93	2.24	-44.69	-13	-31.69
6	12127.5	51.15	-51.02	4.26	-46.77	-13	-33.77
7	13860	58.94	-40.17	2.03	-38.14	-13	-25.14
8	15592.5	54.17	-43.18	3.70	-39.48	-13	-26.48
9	17325	52.18	-45.17	3.70	-41.47	-13	-28.47

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 20325	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3495	42.21	-60.97	7.85	-53.12	-13	-40.12
2	5242.5	47.73	-57.68	7.30	-50.38	-13	-37.38
3	6990	49.79	-52.83	4.43	-48.40	-13	-35.40
4	8737.5	44.01	-57.60	4.18	-53.43	-13	-40.43
5	10485	54.17	-47.48	2.37	-45.11	-13	-32.11
6	12232.5	45.07	-55.25	3.57	-51.68	-13	-38.68
7	13980	59.46	-37.89	3.70	-34.19	-13	-21.19
8	15727.5	50.57	-46.78	3.70	-43.08	-13	-30.08
9	17475	47.49	-49.86	3.70	-46.16	-13	-33.16

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3495	39.55	-63.63	7.85	-55.78	-13	-42.78
2	5242.5	46.89	-58.52	7.30	-51.22	-13	-38.22
3	6990	48.75	-53.87	4.43	-49.44	-13	-36.44
4	8737.5	49.84	-51.77	4.18	-47.60	-13	-34.60
5	10485	55.26	-46.39	2.37	-44.02	-13	-31.02
6	12232.5	50.84	-49.48	3.57	-45.91	-13	-32.91
7	13980	59.88	-37.47	3.70	-33.77	-13	-20.77
8	15727.5	54.46	-42.89	3.70	-39.19	-13	-26.19
9	17475	52.25	-45.10	3.70	-41.40	-13	-28.40

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 4: 20MHz

Mode	TX channel 20050	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3440	46.77	-56.21	7.89	-48.32	-13	-35.32
2	5160	42.12	-63.43	7.36	-56.07	-13	-43.07
3	6880	44.03	-57.85	5.07	-52.77	-13	-39.77
4	8600	52.28	-51.63	4.35	-47.27	-13	-34.27
5	10320	48.06	-53.63	2.14	-51.49	-13	-38.49
6	12040	43.65	-58.66	4.24	-54.42	-13	-41.42
7	13760	58.32	-40.94	1.88	-39.06	-13	-26.06
8	15480	51.47	-45.88	3.70	-42.18	-13	-29.18
9	17200	48.76	-48.59	3.70	-44.89	-13	-31.89

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3440	41.55	-61.43	7.89	-53.54	-13	-40.54
2	5160	46.57	-58.98	7.36	-51.62	-13	-38.62
3	6880	49.58	-52.30	5.07	-47.22	-13	-34.22
4	8600	50.72	-53.19	4.35	-48.83	-13	-35.83
5	10320	53.41	-48.28	2.14	-46.14	-13	-33.14
6	12040	51.18	-51.13	4.24	-46.89	-13	-33.89
7	13760	58.22	-41.04	1.88	-39.16	-13	-26.16
8	15480	53.61	-43.74	3.70	-40.04	-13	-27.04
9	17200	51.41	-45.94	3.70	-42.24	-13	-29.24

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 20175	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3465	34.58	-68.49	7.87	-60.62	-13	-47.62
2	5197.5	44.50	-60.99	7.33	-53.66	-13	-40.66
3	6930	49.80	-52.82	5.03	-47.79	-13	-34.79
4	8662.5	48.39	-55.36	4.34	-51.01	-13	-38.01
5	10395	50.89	-50.78	2.24	-48.54	-13	-35.54
6	12127.5	49.34	-52.83	4.26	-48.58	-13	-35.58
7	13860	53.84	-45.27	2.03	-43.24	-13	-30.24
8	15592.5	54.31	-43.04	3.70	-39.34	-13	-26.34
9	17325	45.49	-51.86	3.70	-48.16	-13	-35.16

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3465	40.18	-62.89	7.87	-55.02	-13	-42.02
2	5197.5	45.28	-60.21	7.33	-52.88	-13	-39.88
3	6930	48.73	-53.89	5.03	-48.86	-13	-35.86
4	8662.5	51.58	-52.17	4.34	-47.82	-13	-34.82
5	10395	53.50	-48.17	2.24	-45.93	-13	-32.93
6	12127.5	51.38	-50.79	4.26	-46.54	-13	-33.54
7	13860	59.84	-39.27	2.03	-37.24	-13	-24.24
8	15592.5	53.72	-43.63	3.70	-39.93	-13	-26.93
9	17325	52.80	-44.55	3.70	-40.85	-13	-27.85

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 20300	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3490	37.96	-65.20	7.85	-57.35	-13	-44.35
2	5235	41.63	-63.80	7.31	-56.49	-13	-43.49
3	6980	49.62	-53.00	4.43	-48.57	-13	-35.57
4	8725	44.30	-57.31	4.18	-53.14	-13	-40.14
5	10470	50.08	-51.58	2.35	-49.23	-13	-36.23
6	12215	48.76	-51.56	3.57	-47.99	-13	-34.99
7	13960	56.11	-41.24	3.70	-37.54	-13	-24.54
8	15705	50.03	-47.32	3.70	-43.62	-13	-30.62
9	17450	45.21	-52.14	3.70	-48.44	-13	-35.44

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3490	39.18	-63.98	7.85	-56.13	-13	-43.13
2	5235	44.60	-60.83	7.31	-53.52	-13	-40.52
3	6980	48.63	-53.99	4.43	-49.56	-13	-36.56
4	8725	51.29	-50.32	4.18	-46.15	-13	-33.15
5	10470	53.39	-48.27	2.35	-45.92	-13	-32.92
6	12215	50.33	-49.99	3.57	-46.42	-13	-33.42
7	13960	57.58	-39.77	3.70	-36.07	-13	-23.07
8	15705	53.13	-44.22	3.70	-40.52	-13	-27.52
9	17450	52.33	-45.02	3.70	-41.32	-13	-28.32

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 7: 5MHz

Mode	TX channel 20775	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5005	34.49	-69.75	7.01	-62.74	-25	-37.74
2	7507.5	48.70	-53.92	4.54	-49.38	-25	-24.38
3	10010	55.08	-46.49	4.03	-42.46	-25	-17.46
4	12512.5	51.12	-50.46	4.34	-46.12	-25	-21.12
5	15015	53.81	-43.54	3.70	-39.84	-25	-14.84
6	17517.5	47.95	-49.40	3.70	-45.70	-25	-20.70
7	20020	47.60	-49.75	3.70	-46.05	-25	-21.05
8	22522.5	48.67	-48.68	3.70	-44.98	-25	-19.98
9	25025	44.21	-53.14	3.70	-49.44	-25	-24.44

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5005	40.60	-63.64	7.01	-56.63	-25	-31.63
2	7507.5	46.09	-56.53	4.54	-51.99	-25	-26.99
3	10010	46.49	-55.08	4.03	-51.05	-25	-26.05
4	12512.5	49.74	-51.84	4.34	-47.50	-25	-22.50
5	15015	49.36	-47.99	3.70	-44.29	-25	-19.29
6	17517.5	56.95	-40.40	3.70	-36.70	-25	-11.70
7	20020	51.80	-45.55	3.70	-41.85	-25	-16.85
8	22522.5	51.60	-45.75	3.70	-42.05	-25	-17.05
9	25025	54.03	-43.32	3.70	-39.62	-25	-14.62

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 21100	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5070	35.02	-69.22	7.01	-62.21	-25	-37.21
2	7605	48.33	-54.29	4.54	-49.75	-25	-24.75
3	10140	54.10	-47.47	4.03	-43.44	-25	-18.44
4	12675	50.56	-51.02	4.34	-46.68	-25	-21.68
5	15210	53.41	-43.94	3.70	-40.24	-25	-15.24
6	17745	48.38	-48.97	3.70	-45.27	-25	-20.27
7	20280	47.06	-50.29	3.70	-46.59	-25	-21.59
8	22815	48.28	-49.07	3.70	-45.37	-25	-20.37
9	25350	43.75	-53.60	3.70	-49.90	-25	-24.90

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5070	40.45	-63.79	7.01	-56.78	-25	-31.78
2	7605	45.55	-57.07	4.54	-52.53	-25	-27.53
3	10140	46.50	-55.07	4.03	-51.04	-25	-26.04
4	12675	51.20	-50.38	4.34	-46.04	-25	-21.04
5	15210	49.47	-47.88	3.70	-44.18	-25	-19.18
6	17745	55.57	-41.78	3.70	-38.08	-25	-13.08
7	20280	51.54	-45.81	3.70	-42.11	-25	-17.11
8	22815	52.58	-44.77	3.70	-41.07	-25	-16.07
9	25350	53.54	-43.81	3.70	-40.11	-25	-15.11

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 21425	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5135	34.58	-69.66	7.01	-62.65	-25	-37.65
2	7702.5	47.89	-54.73	4.54	-50.19	-25	-25.19
3	10270	54.17	-47.40	4.03	-43.37	-25	-18.37
4	12837.5	50.84	-50.74	4.34	-46.40	-25	-21.40
5	15405	53.87	-43.48	3.70	-39.78	-25	-14.78
6	17972.5	48.43	-48.92	3.70	-45.22	-25	-20.22
7	20540	48.10	-49.25	3.70	-45.55	-25	-20.55
8	23107.5	49.44	-47.91	3.70	-44.21	-25	-19.21
9	25675	43.91	-53.44	3.70	-49.74	-25	-24.74

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5135	39.59	-64.65	7.01	-57.64	-25	-32.64
2	7702.5	45.49	-57.13	4.54	-52.59	-25	-27.59
3	10270	46.34	-55.23	4.03	-51.20	-25	-26.20
4	12837.5	52.12	-49.46	4.34	-45.12	-25	-20.12
5	15405	49.98	-47.37	3.70	-43.67	-25	-18.67
6	17972.5	56.37	-40.98	3.70	-37.28	-25	-12.28
7	20540	51.70	-45.65	3.70	-41.95	-25	-16.95
8	23107.5	52.62	-44.73	3.70	-41.03	-25	-16.03
9	25675	53.51	-43.84	3.70	-40.14	-25	-15.14

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 7: 10MHz

Mode	TX channel 20800	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5010	34.43	-69.81	7.01	-62.80	-25	-37.80
2	7515	49.22	-53.40	4.54	-48.86	-25	-23.86
3	10020	55.67	-45.90	4.03	-41.87	-25	-16.87
4	12525	51.52	-50.06	4.34	-45.72	-25	-20.72
5	15030	54.51	-42.84	3.70	-39.14	-25	-14.14
6	17535	48.31	-49.04	3.70	-45.34	-25	-20.34
7	20040	47.75	-49.60	3.70	-45.90	-25	-20.90
8	22545	48.96	-48.39	3.70	-44.69	-25	-19.69
9	25050	44.35	-53.00	3.70	-49.30	-25	-24.30

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5010	40.99	-63.25	7.01	-56.24	-25	-31.24
2	7515	44.91	-57.71	4.54	-53.17	-25	-28.17
3	10020	46.27	-55.30	4.03	-51.27	-25	-26.27
4	12525	51.08	-50.50	4.34	-46.16	-25	-21.16
5	15030	50.18	-47.17	3.70	-43.47	-25	-18.47
6	17535	55.97	-41.38	3.70	-37.68	-25	-12.68
7	20040	52.44	-44.91	3.70	-41.21	-25	-16.21
8	22545	53.00	-44.35	3.70	-40.65	-25	-15.65
9	25050	54.06	-43.29	3.70	-39.59	-25	-14.59

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 21100	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5070	34.96	-69.28	7.01	-62.27	-25	-37.27
2	7605	48.54	-54.08	4.54	-49.54	-25	-24.54
3	10140	54.70	-46.87	4.03	-42.84	-25	-17.84
4	12675	50.88	-50.70	4.34	-46.36	-25	-21.36
5	15210	53.56	-43.79	3.70	-40.09	-25	-15.09
6	17745	47.39	-49.96	3.70	-46.26	-25	-21.26
7	20280	46.70	-50.65	3.70	-46.95	-25	-21.95
8	22815	47.94	-49.41	3.70	-45.71	-25	-20.71
9	25350	43.83	-53.52	3.70	-49.82	-25	-24.82

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5070	41.24	-63.00	7.01	-55.99	-25	-30.99
2	7605	45.86	-56.76	4.54	-52.22	-25	-27.22
3	10140	46.95	-54.62	4.03	-50.59	-25	-25.59
4	12675	51.06	-50.52	4.34	-46.18	-25	-21.18
5	15210	48.57	-48.78	3.70	-45.08	-25	-20.08
6	17745	55.32	-42.03	3.70	-38.33	-25	-13.33
7	20280	51.98	-45.37	3.70	-41.67	-25	-16.67
8	22815	52.95	-44.40	3.70	-40.70	-25	-15.70
9	25350	53.64	-43.71	3.70	-40.01	-25	-15.01

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 21400	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5130	35.14	-69.10	7.01	-62.09	-25	-37.09
2	7695	47.87	-54.75	4.54	-50.21	-25	-25.21
3	10260	54.94	-46.63	4.03	-42.60	-25	-17.60
4	12825	50.44	-51.14	4.34	-46.80	-25	-21.80
5	15390	54.11	-43.24	3.70	-39.54	-25	-14.54
6	17955	48.02	-49.33	3.70	-45.63	-25	-20.63
7	20520	48.45	-48.90	3.70	-45.20	-25	-20.20
8	23085	48.39	-48.96	3.70	-45.26	-25	-20.26
9	25650	43.23	-54.12	3.70	-50.42	-25	-25.42

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5130	40.12	-64.12	7.01	-57.11	-25	-32.11
2	7695	44.83	-57.79	4.54	-53.25	-25	-28.25
3	10260	46.13	-55.44	4.03	-51.41	-25	-26.41
4	12825	50.47	-51.11	4.34	-46.77	-25	-21.77
5	15390	49.77	-47.58	3.70	-43.88	-25	-18.88
6	17955	55.84	-41.51	3.70	-37.81	-25	-12.81
7	20520	50.94	-46.41	3.70	-42.71	-25	-17.71
8	23085	51.72	-45.63	3.70	-41.93	-25	-16.93
9	25650	54.13	-43.22	3.70	-39.52	-25	-14.52

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 7: 15MHz

Mode	TX channel 20825	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5015	33.50	-70.74	7.01	-63.73	-25	-38.73
2	7522.5	49.00	-53.62	4.54	-49.08	-25	-24.08
3	10030	55.53	-46.04	4.03	-42.01	-25	-17.01
4	12537.5	50.28	-51.30	4.34	-46.96	-25	-21.96
5	15045	54.14	-43.21	3.70	-39.51	-25	-14.51
6	17552.5	47.48	-49.87	3.70	-46.17	-25	-21.17
7	20060	48.46	-48.89	3.70	-45.19	-25	-20.19
8	22567.5	48.88	-48.47	3.70	-44.77	-25	-19.77
9	25075	44.11	-53.24	3.70	-49.54	-25	-24.54

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5015	40.95	-63.29	7.01	-56.28	-25	-31.28
2	7522.5	45.10	-57.52	4.54	-52.98	-25	-27.98
3	10030	47.10	-54.47	4.03	-50.44	-25	-25.44
4	12537.5	51.90	-49.68	4.34	-45.34	-25	-20.34
5	15045	48.75	-48.60	3.70	-44.90	-25	-19.90
6	17552.5	55.62	-41.73	3.70	-38.03	-25	-13.03
7	20060	52.40	-44.95	3.70	-41.25	-25	-16.25
8	22567.5	52.29	-45.06	3.70	-41.36	-25	-16.36
9	25075	53.32	-44.03	3.70	-40.33	-25	-15.33

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).