

| | | | |
|------|------------------|-----------------|----------------|
| Mode | TX channel 19193 | Frequency Range | Above 1000 MHz |
|------|------------------|-----------------|----------------|

Antenna Polarity & Test Distance: Horizontal at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3818.6 | 40.79 | -63.36 | 7.68 | -55.68 | -13 | -42.68 |
| 2 | 5727.9 | 43.21 | -61.53 | 7.02 | -54.51 | -13 | -41.51 |
| 3 | 7637.2 | 46.99 | -55.63 | 4.53 | -51.10 | -13 | -38.10 |
| 4 | 9546.5 | 47.92 | -53.69 | 4.18 | -49.52 | -13 | -36.52 |
| 5 | 11455.8 | 51.12 | -50.37 | 3.48 | -46.89 | -13 | -33.89 |
| 6 | 13365.1 | 51.35 | -49.23 | 4.48 | -44.75 | -13 | -31.75 |
| 7 | 15274.4 | 57.25 | -40.10 | 3.70 | -36.40 | -13 | -23.40 |
| 8 | 17183.7 | 52.25 | -45.10 | 3.70 | -41.40 | -13 | -28.40 |

Antenna Polarity & Test Distance: Vertical at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3818.6 | 39.56 | -64.59 | 7.68 | -56.91 | -13 | -43.91 |
| 2 | 5727.9 | 44.34 | -60.40 | 7.02 | -53.38 | -13 | -40.38 |
| 3 | 7637.2 | 48.29 | -54.33 | 4.53 | -49.80 | -13 | -36.80 |
| 4 | 9546.5 | 50.13 | -51.48 | 4.18 | -47.31 | -13 | -34.31 |
| 5 | 11455.8 | 53.77 | -47.72 | 3.48 | -44.24 | -13 | -31.24 |
| 6 | 13365.1 | 51.64 | -48.94 | 4.48 | -44.46 | -13 | -31.46 |
| 7 | 15274.4 | 59.05 | -38.30 | 3.70 | -34.60 | -13 | -21.60 |
| 8 | 17183.7 | 51.93 | -45.42 | 3.70 | -41.72 | -13 | -28.72 |

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 2: 3 MHz

| | | | |
|------|------------------|-----------------|----------------|
| Mode | TX channel 18615 | Frequency Range | Above 1000 MHz |
|------|------------------|-----------------|----------------|

Antenna Polarity & Test Distance: Horizontal at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3703 | 40.36 | -63.58 | 7.72 | -55.87 | -13 | -42.87 |
| 2 | 5554.5 | 42.50 | -62.39 | 7.08 | -55.31 | -13 | -42.31 |
| 3 | 7406 | 46.17 | -56.34 | 4.63 | -51.71 | -13 | -38.71 |
| 4 | 9257.5 | 47.99 | -53.66 | 4.26 | -49.40 | -13 | -36.40 |
| 5 | 11109 | 52.39 | -49.14 | 3.24 | -45.89 | -13 | -32.89 |
| 6 | 12960.5 | 49.93 | -50.96 | 4.44 | -46.52 | -13 | -33.52 |
| 7 | 14812 | 56.96 | -40.39 | 3.70 | -36.69 | -13 | -23.69 |
| 8 | 16663.5 | 52.99 | -44.36 | 3.70 | -40.66 | -13 | -27.66 |

Antenna Polarity & Test Distance: Vertical at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3703 | 40.01 | -63.93 | 7.72 | -56.22 | -13 | -43.22 |
| 2 | 5554.5 | 45.28 | -59.61 | 7.08 | -52.53 | -13 | -39.53 |
| 3 | 7406 | 49.69 | -52.82 | 4.63 | -48.19 | -13 | -35.19 |
| 4 | 9257.5 | 49.19 | -52.46 | 4.26 | -48.20 | -13 | -35.20 |
| 5 | 11109 | 53.91 | -47.62 | 3.24 | -44.37 | -13 | -31.37 |
| 6 | 12960.5 | 51.40 | -49.49 | 4.44 | -45.05 | -13 | -32.05 |
| 7 | 14812 | 59.18 | -38.17 | 3.70 | -34.47 | -13 | -21.47 |
| 8 | 16663.5 | 53.56 | -43.79 | 3.70 | -40.09 | -13 | -27.09 |

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

| | | | |
|------|------------------|-----------------|----------------|
| Mode | TX channel 18900 | Frequency Range | Above 1000 MHz |
|------|------------------|-----------------|----------------|

Antenna Polarity & Test Distance: Horizontal at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3760 | 40.20 | -65.07 | 7.63 | -57.45 | -13 | -44.45 |
| 2 | 5640 | 43.51 | -61.23 | 7.02 | -54.21 | -13 | -41.21 |
| 3 | 7520 | 46.75 | -55.87 | 4.53 | -51.34 | -13 | -38.34 |
| 4 | 9400 | 49.73 | -51.90 | 4.22 | -47.68 | -13 | -34.68 |
| 5 | 11280 | 50.91 | -50.58 | 3.48 | -47.10 | -13 | -34.10 |
| 6 | 13160 | 50.11 | -50.50 | 4.06 | -46.43 | -13 | -33.43 |
| 7 | 15040 | 56.58 | -40.77 | 3.70 | -37.07 | -13 | -24.07 |
| 8 | 16920 | 51.67 | -45.68 | 3.70 | -41.98 | -13 | -28.98 |

Antenna Polarity & Test Distance: Vertical at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3760 | 40.08 | -65.19 | 7.63 | -57.57 | -13 | -44.57 |
| 2 | 5640 | 44.68 | -60.06 | 7.02 | -53.04 | -13 | -40.04 |
| 3 | 7520 | 50.47 | -52.15 | 4.53 | -47.62 | -13 | -34.62 |
| 4 | 9400 | 49.31 | -52.32 | 4.22 | -48.10 | -13 | -35.10 |
| 5 | 11280 | 54.18 | -47.31 | 3.48 | -43.83 | -13 | -30.83 |
| 6 | 13160 | 51.60 | -49.01 | 4.06 | -44.94 | -13 | -31.94 |
| 7 | 15040 | 58.90 | -38.45 | 3.70 | -34.75 | -13 | -21.75 |
| 8 | 16920 | 53.60 | -43.75 | 3.70 | -40.05 | -13 | -27.05 |

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

| | | | |
|------|------------------|-----------------|----------------|
| Mode | TX channel 19185 | Frequency Range | Above 1000 MHz |
|------|------------------|-----------------|----------------|

Antenna Polarity & Test Distance: Horizontal at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3817 | 40.37 | -63.99 | 7.64 | -56.35 | -13 | -43.35 |
| 2 | 5725.5 | 43.67 | -60.93 | 6.96 | -53.97 | -13 | -40.97 |
| 3 | 7634 | 47.19 | -55.43 | 4.43 | -51.00 | -13 | -38.00 |
| 4 | 9542.5 | 49.10 | -52.51 | 4.18 | -48.34 | -13 | -35.34 |
| 5 | 11451 | 51.57 | -49.88 | 3.73 | -46.15 | -13 | -33.15 |
| 6 | 13359.5 | 50.04 | -50.28 | 3.57 | -46.71 | -13 | -33.71 |
| 7 | 15268 | 58.01 | -39.34 | 3.70 | -35.64 | -13 | -22.64 |
| 8 | 17176.5 | 53.40 | -43.95 | 3.70 | -40.25 | -13 | -27.25 |

Antenna Polarity & Test Distance: Vertical at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3817 | 39.63 | -64.73 | 7.64 | -57.09 | -13 | -44.09 |
| 2 | 5725.5 | 44.94 | -59.66 | 6.96 | -52.70 | -13 | -39.70 |
| 3 | 7634 | 49.92 | -52.70 | 4.43 | -48.27 | -13 | -35.27 |
| 4 | 9542.5 | 49.94 | -51.67 | 4.18 | -47.50 | -13 | -34.50 |
| 5 | 11451 | 54.71 | -46.74 | 3.73 | -43.01 | -13 | -30.01 |
| 6 | 13359.5 | 50.90 | -49.42 | 3.57 | -45.85 | -13 | -32.85 |
| 7 | 15268 | 59.42 | -37.93 | 3.70 | -34.23 | -13 | -21.23 |
| 8 | 17176.5 | 52.90 | -44.45 | 3.70 | -40.75 | -13 | -27.75 |

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 2: 5 MHz

| | | | |
|------|------------------|-----------------|----------------|
| Mode | TX channel 18625 | Frequency Range | Above 1000 MHz |
|------|------------------|-----------------|----------------|

Antenna Polarity & Test Distance: Horizontal at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3705 | 41.38 | -62.57 | 7.71 | -54.86 | -13 | -41.86 |
| 2 | 5557.5 | 42.45 | -62.43 | 7.08 | -55.35 | -13 | -42.35 |
| 3 | 7410 | 46.04 | -56.58 | 4.62 | -51.96 | -13 | -38.96 |
| 4 | 9262.5 | 48.30 | -53.92 | 4.23 | -49.69 | -13 | -36.69 |
| 5 | 11115 | 52.55 | -48.98 | 3.25 | -45.73 | -13 | -32.73 |
| 6 | 12967.5 | 50.28 | -50.60 | 4.52 | -46.07 | -13 | -33.07 |
| 7 | 14820 | 57.10 | -40.25 | 3.70 | -36.55 | -13 | -23.55 |
| 8 | 16672.5 | 53.30 | -44.05 | 3.70 | -40.35 | -13 | -27.35 |

Antenna Polarity & Test Distance: Vertical at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3705 | 39.47 | -64.48 | 7.71 | -56.77 | -13 | -43.77 |
| 2 | 5557.5 | 45.13 | -59.75 | 7.08 | -52.67 | -13 | -39.67 |
| 3 | 7410 | 50.58 | -52.04 | 4.62 | -47.42 | -13 | -34.42 |
| 4 | 9262.5 | 50.37 | -51.85 | 4.23 | -47.62 | -13 | -34.62 |
| 5 | 11115 | 55.46 | -46.07 | 3.25 | -42.82 | -13 | -29.82 |
| 6 | 12967.5 | 50.32 | -50.56 | 4.52 | -46.03 | -13 | -33.03 |
| 7 | 14820 | 60.25 | -37.10 | 3.70 | -33.40 | -13 | -20.40 |
| 8 | 16672.5 | 51.94 | -45.41 | 3.70 | -41.71 | -13 | -28.71 |

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

| | | | |
|------|------------------|-----------------|----------------|
| Mode | TX channel 18900 | Frequency Range | Above 1000 MHz |
|------|------------------|-----------------|----------------|

Antenna Polarity & Test Distance: Horizontal at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3760 | 41.05 | -64.22 | 7.63 | -56.60 | -13 | -43.60 |
| 2 | 5640 | 44.05 | -60.69 | 7.02 | -53.67 | -13 | -40.67 |
| 3 | 7520 | 47.41 | -55.21 | 4.53 | -50.68 | -13 | -37.68 |
| 4 | 9400 | 49.04 | -52.59 | 4.22 | -48.37 | -13 | -35.37 |
| 5 | 11280 | 52.48 | -49.01 | 3.48 | -45.53 | -13 | -32.53 |
| 6 | 13160 | 49.91 | -50.70 | 4.06 | -46.63 | -13 | -33.63 |
| 7 | 15040 | 57.52 | -39.83 | 3.70 | -36.13 | -13 | -23.13 |
| 8 | 16920 | 53.14 | -44.21 | 3.70 | -40.51 | -13 | -27.51 |

Antenna Polarity & Test Distance: Vertical at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3760 | 38.85 | -66.42 | 7.63 | -58.80 | -13 | -45.80 |
| 2 | 5640 | 44.14 | -60.60 | 7.02 | -53.58 | -13 | -40.58 |
| 3 | 7520 | 50.89 | -51.73 | 4.53 | -47.20 | -13 | -34.20 |
| 4 | 9400 | 49.41 | -52.22 | 4.22 | -48.00 | -13 | -35.00 |
| 5 | 11280 | 54.38 | -47.11 | 3.48 | -43.63 | -13 | -30.63 |
| 6 | 13160 | 50.28 | -50.33 | 4.06 | -46.26 | -13 | -33.26 |
| 7 | 15040 | 60.02 | -37.33 | 3.70 | -33.63 | -13 | -20.63 |
| 8 | 16920 | 52.93 | -44.42 | 3.70 | -40.72 | -13 | -27.72 |

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

| | | | |
|------|------------------|-----------------|----------------|
| Mode | TX channel 19175 | Frequency Range | Above 1000 MHz |
|------|------------------|-----------------|----------------|

Antenna Polarity & Test Distance: Horizontal at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3815 | 40.46 | -64.76 | 7.60 | -57.16 | -13 | -44.16 |
| 2 | 5722.5 | 43.45 | -60.69 | 7.24 | -53.45 | -13 | -40.45 |
| 3 | 7630 | 46.21 | -56.41 | 4.43 | -51.98 | -13 | -38.98 |
| 4 | 9537.5 | 49.64 | -51.98 | 4.18 | -47.80 | -13 | -34.80 |
| 5 | 11445 | 52.30 | -49.16 | 3.71 | -45.45 | -13 | -32.45 |
| 6 | 13352.5 | 50.13 | -50.19 | 3.57 | -46.62 | -13 | -33.62 |
| 7 | 15260 | 56.18 | -41.17 | 3.70 | -37.47 | -13 | -24.47 |
| 8 | 17167.5 | 52.09 | -45.26 | 3.70 | -41.56 | -13 | -28.56 |

Antenna Polarity & Test Distance: Vertical at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3815 | 39.44 | -65.78 | 7.60 | -58.18 | -13 | -45.18 |
| 2 | 5722.5 | 44.12 | -60.02 | 7.24 | -52.78 | -13 | -39.78 |
| 3 | 7630 | 50.74 | -51.88 | 4.43 | -47.45 | -13 | -34.45 |
| 4 | 9537.5 | 49.08 | -52.54 | 4.18 | -48.36 | -13 | -35.36 |
| 5 | 11445 | 54.74 | -46.72 | 3.71 | -43.01 | -13 | -30.01 |
| 6 | 13352.5 | 50.58 | -49.74 | 3.57 | -46.17 | -13 | -33.17 |
| 7 | 15260 | 58.70 | -38.65 | 3.70 | -34.95 | -13 | -21.95 |
| 8 | 17167.5 | 52.25 | -45.10 | 3.70 | -41.40 | -13 | -28.40 |

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 2: 10 MHz

| | | | |
|------|------------------|-----------------|----------------|
| Mode | TX channel 18650 | Frequency Range | Above 1000 MHz |
|------|------------------|-----------------|----------------|

Antenna Polarity & Test Distance: Horizontal at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3710 | 40.98 | -62.99 | 7.71 | -55.28 | -13 | -42.28 |
| 2 | 5565 | 44.27 | -60.60 | 7.07 | -53.53 | -13 | -40.53 |
| 3 | 7420 | 47.66 | -54.96 | 4.61 | -50.35 | -13 | -37.35 |
| 4 | 9275 | 49.32 | -52.87 | 4.23 | -48.64 | -13 | -35.64 |
| 5 | 11130 | 52.39 | -49.13 | 3.27 | -45.86 | -13 | -32.86 |
| 6 | 12985 | 49.79 | -51.06 | 4.48 | -46.58 | -13 | -33.58 |
| 7 | 14840 | 57.22 | -40.13 | 3.70 | -36.43 | -13 | -23.43 |
| 8 | 16695 | 52.18 | -45.17 | 3.70 | -41.47 | -13 | -28.47 |

Antenna Polarity & Test Distance: Vertical at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3710 | 40.30 | -63.67 | 7.71 | -55.96 | -13 | -42.96 |
| 2 | 5565 | 45.35 | -59.52 | 7.07 | -52.45 | -13 | -39.45 |
| 3 | 7420 | 50.00 | -52.62 | 4.61 | -48.01 | -13 | -35.01 |
| 4 | 9275 | 50.38 | -51.81 | 4.23 | -47.58 | -13 | -34.58 |
| 5 | 11130 | 55.56 | -45.96 | 3.27 | -42.69 | -13 | -29.69 |
| 6 | 12985 | 50.82 | -50.03 | 4.48 | -45.55 | -13 | -32.55 |
| 7 | 14840 | 59.09 | -38.26 | 3.70 | -34.56 | -13 | -21.56 |
| 8 | 16695 | 53.87 | -43.48 | 3.70 | -39.78 | -13 | -26.78 |

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

| | | | |
|------|------------------|-----------------|----------------|
| Mode | TX channel 18900 | Frequency Range | Above 1000 MHz |
|------|------------------|-----------------|----------------|

Antenna Polarity & Test Distance: Horizontal at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3760 | 41.95 | -63.32 | 7.63 | -55.70 | -13 | -42.70 |
| 2 | 5640 | 43.68 | -61.06 | 7.02 | -54.04 | -13 | -41.04 |
| 3 | 7520 | 48.03 | -54.59 | 4.53 | -50.06 | -13 | -37.06 |
| 4 | 9400 | 50.18 | -51.45 | 4.22 | -47.23 | -13 | -34.23 |
| 5 | 11280 | 52.91 | -48.58 | 3.48 | -45.10 | -13 | -32.10 |
| 6 | 13160 | 50.65 | -49.96 | 4.06 | -45.89 | -13 | -32.89 |
| 7 | 15040 | 57.39 | -39.96 | 3.70 | -36.26 | -13 | -23.26 |
| 8 | 16920 | 51.97 | -45.38 | 3.70 | -41.68 | -13 | -28.68 |

Antenna Polarity & Test Distance: Vertical at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3760 | 39.64 | -65.63 | 7.63 | -58.01 | -13 | -45.01 |
| 2 | 5640 | 43.94 | -60.80 | 7.02 | -53.78 | -13 | -40.78 |
| 3 | 7520 | 49.95 | -52.67 | 4.53 | -48.14 | -13 | -35.14 |
| 4 | 9400 | 49.61 | -52.02 | 4.22 | -47.80 | -13 | -34.80 |
| 5 | 11280 | 55.16 | -46.33 | 3.48 | -42.85 | -13 | -29.85 |
| 6 | 13160 | 51.38 | -49.23 | 4.06 | -45.16 | -13 | -32.16 |
| 7 | 15040 | 60.15 | -37.20 | 3.70 | -33.50 | -13 | -20.50 |
| 8 | 16920 | 53.70 | -43.65 | 3.70 | -39.95 | -13 | -26.95 |

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

| | | | |
|------|------------------|-----------------|----------------|
| Mode | TX channel 19150 | Frequency Range | Above 1000 MHz |
|------|------------------|-----------------|----------------|

Antenna Polarity & Test Distance: Horizontal at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3810 | 41.67 | -63.55 | 7.60 | -55.95 | -13 | -42.95 |
| 2 | 5715 | 43.77 | -60.85 | 6.97 | -53.88 | -13 | -40.88 |
| 3 | 7620 | 47.41 | -55.21 | 4.43 | -50.78 | -13 | -37.78 |
| 4 | 9525 | 48.57 | -53.04 | 4.18 | -48.87 | -13 | -35.87 |
| 5 | 11430 | 51.55 | -49.91 | 3.69 | -46.22 | -13 | -33.22 |
| 6 | 13335 | 51.44 | -48.92 | 3.65 | -45.28 | -13 | -32.28 |
| 7 | 15240 | 56.22 | -41.13 | 3.70 | -37.43 | -13 | -24.43 |
| 8 | 17145 | 52.07 | -45.28 | 3.70 | -41.58 | -13 | -28.58 |

Antenna Polarity & Test Distance: Vertical at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3810 | 39.27 | -65.95 | 7.60 | -58.35 | -13 | -45.35 |
| 2 | 5715 | 45.14 | -59.48 | 6.97 | -52.51 | -13 | -39.51 |
| 3 | 7620 | 50.01 | -52.61 | 4.43 | -48.18 | -13 | -35.18 |
| 4 | 9525 | 50.79 | -50.82 | 4.18 | -46.65 | -13 | -33.65 |
| 5 | 11430 | 55.33 | -46.13 | 3.69 | -42.44 | -13 | -29.44 |
| 6 | 13335 | 51.76 | -48.60 | 3.65 | -44.96 | -13 | -31.96 |
| 7 | 15240 | 59.88 | -37.47 | 3.70 | -33.77 | -13 | -20.77 |
| 8 | 17145 | 53.89 | -43.46 | 3.70 | -39.76 | -13 | -26.76 |

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 2: 15 MHz

| | | | |
|------|------------------|-----------------|----------------|
| Mode | TX channel 18675 | Frequency Range | Above 1000 MHz |
|------|------------------|-----------------|----------------|

Antenna Polarity & Test Distance: Horizontal at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3715 | 41.00 | -64.32 | 7.65 | -56.68 | -13 | -43.68 |
| 2 | 5572.5 | 44.29 | -60.57 | 7.07 | -53.50 | -13 | -40.50 |
| 3 | 7430 | 46.78 | -55.84 | 4.61 | -51.23 | -13 | -38.23 |
| 4 | 9287.5 | 49.62 | -52.54 | 4.23 | -48.31 | -13 | -35.31 |
| 5 | 11145 | 50.94 | -50.58 | 3.29 | -47.29 | -13 | -34.29 |
| 6 | 13002.5 | 50.77 | -50.06 | 4.44 | -45.62 | -13 | -32.62 |
| 7 | 14860 | 58.11 | -39.46 | 3.50 | -35.96 | -13 | -22.96 |
| 8 | 16717.5 | 51.92 | -45.43 | 3.70 | -41.73 | -13 | -28.73 |

Antenna Polarity & Test Distance: Vertical at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3715 | 40.45 | -64.87 | 7.65 | -57.23 | -13 | -44.23 |
| 2 | 5572.5 | 45.34 | -59.52 | 7.07 | -52.45 | -13 | -39.45 |
| 3 | 7430 | 49.98 | -52.64 | 4.61 | -48.03 | -13 | -35.03 |
| 4 | 9287.5 | 50.70 | -51.46 | 4.23 | -47.23 | -13 | -34.23 |
| 5 | 11145 | 54.92 | -46.60 | 3.29 | -43.31 | -13 | -30.31 |
| 6 | 13002.5 | 51.32 | -49.51 | 4.44 | -45.07 | -13 | -32.07 |
| 7 | 14860 | 59.63 | -37.94 | 3.50 | -34.44 | -13 | -21.44 |
| 8 | 16717.5 | 52.71 | -44.64 | 3.70 | -40.94 | -13 | -27.94 |

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

| | | | |
|------|------------------|-----------------|----------------|
| Mode | TX channel 18900 | Frequency Range | Above 1000 MHz |
|------|------------------|-----------------|----------------|

Antenna Polarity & Test Distance: Horizontal at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3760 | 40.97 | -64.30 | 7.63 | -56.68 | -13 | -43.68 |
| 2 | 5640 | 43.30 | -61.44 | 7.02 | -54.42 | -13 | -41.42 |
| 3 | 7520 | 46.51 | -56.11 | 4.53 | -51.58 | -13 | -38.58 |
| 4 | 9400 | 48.16 | -53.47 | 4.22 | -49.25 | -13 | -36.25 |
| 5 | 11280 | 51.33 | -50.16 | 3.48 | -46.68 | -13 | -33.68 |
| 6 | 13160 | 51.02 | -49.59 | 4.06 | -45.52 | -13 | -32.52 |
| 7 | 15040 | 56.46 | -40.89 | 3.70 | -37.19 | -13 | -24.19 |
| 8 | 16920 | 53.44 | -43.91 | 3.70 | -40.21 | -13 | -27.21 |

Antenna Polarity & Test Distance: Vertical at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3760 | 39.85 | -65.42 | 7.63 | -57.80 | -13 | -44.80 |
| 2 | 5640 | 44.67 | -60.07 | 7.02 | -53.05 | -13 | -40.05 |
| 3 | 7520 | 50.82 | -51.80 | 4.53 | -47.27 | -13 | -34.27 |
| 4 | 9400 | 50.33 | -51.30 | 4.22 | -47.08 | -13 | -34.08 |
| 5 | 11280 | 55.43 | -46.06 | 3.48 | -42.58 | -13 | -29.58 |
| 6 | 13160 | 50.37 | -50.24 | 4.06 | -46.17 | -13 | -33.17 |
| 7 | 15040 | 59.25 | -38.10 | 3.70 | -34.40 | -13 | -21.40 |
| 8 | 16920 | 52.45 | -44.90 | 3.70 | -41.20 | -13 | -28.20 |

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

| | | | |
|------|------------------|-----------------|----------------|
| Mode | TX channel 19125 | Frequency Range | Above 1000 MHz |
|------|------------------|-----------------|----------------|

Antenna Polarity & Test Distance: Horizontal at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3805 | 40.47 | -64.76 | 7.61 | -57.15 | -13 | -44.15 |
| 2 | 5707.5 | 44.09 | -60.54 | 6.97 | -53.57 | -13 | -40.57 |
| 3 | 7610 | 47.83 | -54.79 | 4.43 | -50.36 | -13 | -37.36 |
| 4 | 9512.5 | 49.29 | -52.33 | 4.19 | -48.14 | -13 | -35.14 |
| 5 | 11415 | 51.07 | -50.40 | 3.67 | -46.73 | -13 | -33.73 |
| 6 | 13317.5 | 51.19 | -49.18 | 3.65 | -45.53 | -13 | -32.53 |
| 7 | 15220 | 56.37 | -40.98 | 3.70 | -37.28 | -13 | -24.28 |
| 8 | 17122.5 | 51.89 | -45.46 | 3.70 | -41.76 | -13 | -28.76 |

Antenna Polarity & Test Distance: Vertical at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3805 | 40.12 | -65.11 | 7.61 | -57.50 | -13 | -44.50 |
| 2 | 5707.5 | 44.63 | -60.00 | 6.97 | -53.03 | -13 | -40.03 |
| 3 | 7610 | 49.67 | -52.95 | 4.43 | -48.52 | -13 | -35.52 |
| 4 | 9512.5 | 50.17 | -51.45 | 4.19 | -47.26 | -13 | -34.26 |
| 5 | 11415 | 55.68 | -45.79 | 3.67 | -42.12 | -13 | -29.12 |
| 6 | 13317.5 | 50.51 | -49.86 | 3.65 | -46.21 | -13 | -33.21 |
| 7 | 15220 | 59.06 | -38.29 | 3.70 | -34.59 | -13 | -21.59 |
| 8 | 17122.5 | 53.75 | -43.60 | 3.70 | -39.90 | -13 | -26.90 |

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 2: 20 MHz

| | | | |
|------|------------------|-----------------|----------------|
| Mode | TX channel 18700 | Frequency Range | Above 1000 MHz |
|------|------------------|-----------------|----------------|

Antenna Polarity & Test Distance: Horizontal at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3720 | 40.97 | -63.04 | 7.70 | -55.33 | -13 | -42.33 |
| 2 | 5580 | 42.64 | -62.21 | 7.06 | -55.14 | -13 | -42.14 |
| 3 | 7440 | 47.12 | -55.43 | 4.60 | -50.83 | -13 | -37.83 |
| 4 | 9300 | 49.72 | -52.41 | 4.23 | -48.18 | -13 | -35.18 |
| 5 | 11160 | 51.89 | -49.63 | 3.31 | -46.31 | -13 | -33.31 |
| 6 | 13020 | 51.57 | -49.23 | 4.40 | -44.83 | -13 | -31.83 |
| 7 | 14880 | 57.83 | -39.52 | 3.70 | -35.82 | -13 | -22.82 |
| 8 | 16740 | 52.65 | -44.70 | 3.70 | -41.00 | -13 | -28.00 |

Antenna Polarity & Test Distance: Vertical at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3720 | 39.47 | -64.54 | 7.70 | -56.83 | -13 | -43.83 |
| 2 | 5580 | 44.91 | -59.94 | 7.06 | -52.87 | -13 | -39.87 |
| 3 | 7440 | 50.44 | -52.11 | 4.60 | -47.51 | -13 | -34.51 |
| 4 | 9300 | 49.91 | -52.22 | 4.23 | -47.99 | -13 | -34.99 |
| 5 | 11160 | 54.97 | -46.55 | 3.31 | -43.23 | -13 | -30.23 |
| 6 | 13020 | 51.51 | -49.29 | 4.40 | -44.89 | -13 | -31.89 |
| 7 | 14880 | 58.72 | -38.63 | 3.70 | -34.93 | -13 | -21.93 |
| 8 | 16740 | 53.39 | -43.96 | 3.70 | -40.26 | -13 | -27.26 |

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

| | | | |
|------|------------------|-----------------|----------------|
| Mode | TX channel 18900 | Frequency Range | Above 1000 MHz |
|------|------------------|-----------------|----------------|

Antenna Polarity & Test Distance: Horizontal at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3760 | 40.42 | -64.85 | 7.63 | -57.23 | -13 | -44.23 |
| 2 | 5640 | 42.80 | -61.94 | 7.02 | -54.92 | -13 | -41.92 |
| 3 | 7520 | 47.25 | -55.37 | 4.53 | -50.84 | -13 | -37.84 |
| 4 | 9400 | 49.63 | -52.00 | 4.22 | -47.78 | -13 | -34.78 |
| 5 | 11280 | 52.33 | -49.19 | 3.29 | -45.90 | -13 | -32.90 |
| 6 | 13160 | 51.41 | -50.08 | 3.48 | -46.60 | -13 | -33.60 |
| 7 | 15040 | 57.04 | -40.31 | 3.70 | -36.61 | -13 | -23.61 |
| 8 | 16920 | 52.78 | -44.57 | 3.70 | -40.87 | -13 | -27.87 |

Antenna Polarity & Test Distance: Vertical at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3760 | 39.76 | -65.51 | 7.63 | -57.89 | -13 | -44.89 |
| 2 | 5640 | 45.19 | -59.55 | 7.02 | -52.53 | -13 | -39.53 |
| 3 | 7520 | 50.03 | -52.59 | 4.53 | -48.06 | -13 | -35.06 |
| 4 | 9400 | 49.34 | -52.29 | 4.22 | -48.07 | -13 | -35.07 |
| 5 | 11280 | 53.83 | -47.69 | 3.29 | -44.40 | -13 | -31.40 |
| 6 | 13160 | 51.61 | -49.88 | 3.48 | -46.40 | -13 | -33.40 |
| 7 | 15040 | 59.47 | -37.88 | 3.70 | -34.18 | -13 | -21.18 |
| 8 | 16920 | 52.41 | -44.94 | 3.70 | -41.24 | -13 | -28.24 |

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

| | | | |
|------|------------------|-----------------|----------------|
| Mode | TX channel 19100 | Frequency Range | Above 1000 MHz |
|------|------------------|-----------------|----------------|

Antenna Polarity & Test Distance: Horizontal at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3800 | 39.82 | -65.41 | 7.61 | -57.81 | -13 | -44.81 |
| 2 | 5700 | 43.16 | -60.98 | 7.28 | -53.70 | -13 | -40.70 |
| 3 | 7600 | 46.22 | -56.40 | 4.43 | -51.97 | -13 | -38.97 |
| 4 | 9500 | 49.02 | -52.59 | 4.18 | -48.42 | -13 | -35.42 |
| 5 | 11400 | 52.19 | -49.28 | 3.65 | -45.63 | -13 | -32.63 |
| 6 | 13300 | 50.04 | -50.28 | 3.57 | -46.71 | -13 | -33.71 |
| 7 | 15200 | 57.17 | -40.40 | 3.50 | -36.90 | -13 | -23.90 |
| 8 | 17100 | 53.43 | -43.92 | 3.70 | -40.22 | -13 | -27.22 |

Antenna Polarity & Test Distance: Vertical at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3800 | 40.00 | -65.23 | 7.61 | -57.63 | -13 | -44.63 |
| 2 | 5700 | 46.07 | -58.07 | 7.28 | -50.79 | -13 | -37.79 |
| 3 | 7600 | 50.35 | -52.27 | 4.43 | -47.84 | -13 | -34.84 |
| 4 | 9500 | 49.81 | -51.80 | 4.18 | -47.63 | -13 | -34.63 |
| 5 | 11400 | 54.49 | -46.98 | 3.65 | -43.33 | -13 | -30.33 |
| 6 | 13300 | 52.05 | -48.27 | 3.57 | -44.70 | -13 | -31.70 |
| 7 | 15200 | 59.72 | -37.85 | 3.50 | -34.35 | -13 | -21.35 |
| 8 | 17100 | 51.60 | -45.75 | 3.70 | -42.05 | -13 | -29.05 |

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 25: 1.4 MHz

| | | | |
|------|------------------|-----------------|----------------|
| Mode | TX channel 26047 | Frequency Range | Above 1000 MHz |
|------|------------------|-----------------|----------------|

Antenna Polarity & Test Distance: Horizontal at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3701.4 | 41.00 | -62.94 | 7.72 | -55.22 | -13 | -42.22 |
| 2 | 5552.1 | 42.70 | -62.19 | 7.08 | -55.11 | -13 | -42.11 |
| 3 | 7402.8 | 47.04 | -55.58 | 4.63 | -50.95 | -13 | -37.95 |
| 4 | 9253.5 | 49.37 | -52.88 | 4.23 | -48.64 | -13 | -35.64 |
| 5 | 11104.2 | 50.77 | -50.76 | 3.24 | -47.52 | -13 | -34.52 |
| 6 | 12954.9 | 51.02 | -49.88 | 4.44 | -45.44 | -13 | -32.44 |
| 7 | 14805.6 | 56.89 | -40.76 | 3.42 | -37.34 | -13 | -24.34 |
| 8 | 16656.3 | 52.29 | -45.06 | 3.70 | -41.36 | -13 | -28.36 |

Antenna Polarity & Test Distance: Vertical at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3701.4 | 39.83 | -64.11 | 7.72 | -56.39 | -13 | -43.39 |
| 2 | 5552.1 | 44.84 | -60.05 | 7.08 | -52.97 | -13 | -39.97 |
| 3 | 7402.8 | 48.82 | -53.80 | 4.63 | -49.17 | -13 | -36.17 |
| 4 | 9253.5 | 50.06 | -52.19 | 4.23 | -47.95 | -13 | -34.95 |
| 5 | 11104.2 | 53.32 | -48.21 | 3.24 | -44.97 | -13 | -31.97 |
| 6 | 12954.9 | 50.50 | -50.40 | 4.44 | -45.96 | -13 | -32.96 |
| 7 | 14805.6 | 58.16 | -39.49 | 3.42 | -36.07 | -13 | -23.07 |
| 8 | 16656.3 | 52.60 | -44.75 | 3.70 | -41.05 | -13 | -28.05 |

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

| | | | |
|------|------------------|-----------------|----------------|
| Mode | TX channel 26365 | Frequency Range | Above 1000 MHz |
|------|------------------|-----------------|----------------|

Antenna Polarity & Test Distance: Horizontal at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3765 | 41.00 | -63.17 | 7.68 | -55.49 | -13 | -42.49 |
| 2 | 5647.5 | 42.59 | -62.14 | 7.02 | -55.13 | -13 | -42.13 |
| 3 | 7530 | 46.31 | -56.31 | 4.52 | -51.79 | -13 | -38.79 |
| 4 | 9412.5 | 49.31 | -52.32 | 4.22 | -48.10 | -13 | -35.10 |
| 5 | 11295 | 51.02 | -50.47 | 3.50 | -46.97 | -13 | -33.97 |
| 6 | 13177.5 | 50.15 | -50.41 | 4.48 | -45.92 | -13 | -32.92 |
| 7 | 15060 | 57.54 | -39.81 | 3.70 | -36.11 | -13 | -23.11 |
| 8 | 16942.5 | 51.50 | -45.85 | 3.70 | -42.15 | -13 | -29.15 |

Antenna Polarity & Test Distance: Vertical at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3765 | 40.08 | -64.09 | 7.68 | -56.41 | -13 | -43.41 |
| 2 | 5647.5 | 45.26 | -59.47 | 7.02 | -52.46 | -13 | -39.46 |
| 3 | 7530 | 48.96 | -53.66 | 4.52 | -49.14 | -13 | -36.14 |
| 4 | 9412.5 | 50.97 | -50.66 | 4.22 | -46.44 | -13 | -33.44 |
| 5 | 11295 | 53.82 | -47.67 | 3.50 | -44.17 | -13 | -31.17 |
| 6 | 13177.5 | 49.84 | -50.72 | 4.48 | -46.23 | -13 | -33.23 |
| 7 | 15060 | 58.53 | -38.82 | 3.70 | -35.12 | -13 | -22.12 |
| 8 | 16942.5 | 52.23 | -45.12 | 3.70 | -41.42 | -13 | -28.42 |

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

| | | | |
|------|------------------|-----------------|----------------|
| Mode | TX channel 26683 | Frequency Range | Above 1000 MHz |
|------|------------------|-----------------|----------------|

Antenna Polarity & Test Distance: Horizontal at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3828.6 | 40.14 | -64.01 | 7.68 | -56.33 | -13 | -43.33 |
| 2 | 5742.9 | 43.10 | -61.64 | 7.02 | -54.62 | -13 | -41.62 |
| 3 | 7657.2 | 46.92 | -55.70 | 4.53 | -51.17 | -13 | -38.17 |
| 4 | 9571.5 | 50.03 | -51.58 | 4.18 | -47.41 | -13 | -34.41 |
| 5 | 11485.8 | 50.67 | -50.82 | 3.48 | -47.34 | -13 | -34.34 |
| 6 | 13400.1 | 51.66 | -48.92 | 4.48 | -44.44 | -13 | -31.44 |
| 7 | 15314.4 | 56.43 | -40.92 | 3.70 | -37.22 | -13 | -24.22 |
| 8 | 17228.7 | 52.60 | -44.75 | 3.70 | -41.05 | -13 | -28.05 |

Antenna Polarity & Test Distance: Vertical at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3828.6 | 39.23 | -64.92 | 7.68 | -57.24 | -13 | -44.24 |
| 2 | 5742.9 | 44.46 | -60.28 | 7.02 | -53.26 | -13 | -40.26 |
| 3 | 7657.2 | 49.68 | -52.94 | 4.53 | -48.41 | -13 | -35.41 |
| 4 | 9571.5 | 50.52 | -51.09 | 4.18 | -46.92 | -13 | -33.92 |
| 5 | 11485.8 | 53.03 | -48.46 | 3.48 | -44.98 | -13 | -31.98 |
| 6 | 13400.1 | 51.11 | -49.47 | 4.48 | -44.99 | -13 | -31.99 |
| 7 | 15314.4 | 59.00 | -38.35 | 3.70 | -34.65 | -13 | -21.65 |
| 8 | 17228.7 | 53.08 | -44.27 | 3.70 | -40.57 | -13 | -27.57 |

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 25: 3 MHz

| | | | |
|------|------------------|-----------------|----------------|
| Mode | TX channel 26055 | Frequency Range | Above 1000 MHz |
|------|------------------|-----------------|----------------|

Antenna Polarity & Test Distance: Horizontal at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3703 | 41.72 | -62.22 | 7.72 | -54.51 | -13 | -41.51 |
| 2 | 5554.5 | 42.14 | -62.75 | 7.08 | -55.67 | -13 | -42.67 |
| 3 | 7406 | 47.12 | -55.39 | 4.63 | -50.76 | -13 | -37.76 |
| 4 | 9257.5 | 50.15 | -51.50 | 4.26 | -47.24 | -13 | -34.24 |
| 5 | 11109 | 50.12 | -51.41 | 3.24 | -48.16 | -13 | -35.16 |
| 6 | 12960.5 | 51.03 | -49.86 | 4.44 | -45.42 | -13 | -32.42 |
| 7 | 14812 | 56.07 | -41.28 | 3.70 | -37.58 | -13 | -24.58 |
| 8 | 16663.5 | 51.49 | -45.86 | 3.70 | -42.16 | -13 | -29.16 |

Antenna Polarity & Test Distance: Vertical at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3703 | 39.46 | -64.48 | 7.72 | -56.77 | -13 | -43.77 |
| 2 | 5554.5 | 44.49 | -60.40 | 7.08 | -53.32 | -13 | -40.32 |
| 3 | 7406 | 48.42 | -54.09 | 4.63 | -49.46 | -13 | -36.46 |
| 4 | 9257.5 | 50.44 | -51.21 | 4.26 | -46.95 | -13 | -33.95 |
| 5 | 11109 | 52.85 | -48.68 | 3.24 | -45.43 | -13 | -32.43 |
| 6 | 12960.5 | 49.81 | -51.08 | 4.44 | -46.64 | -13 | -33.64 |
| 7 | 14812 | 58.24 | -39.11 | 3.70 | -35.41 | -13 | -22.41 |
| 8 | 16663.5 | 52.72 | -44.63 | 3.70 | -40.93 | -13 | -27.93 |

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

| | | | |
|------|------------------|-----------------|----------------|
| Mode | TX channel 26365 | Frequency Range | Above 1000 MHz |
|------|------------------|-----------------|----------------|

Antenna Polarity & Test Distance: Horizontal at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3765 | 40.46 | -64.81 | 7.63 | -57.19 | -13 | -44.19 |
| 2 | 5647.5 | 42.95 | -61.79 | 7.02 | -54.77 | -13 | -41.77 |
| 3 | 7530 | 47.10 | -55.52 | 4.53 | -50.99 | -13 | -37.99 |
| 4 | 9412.5 | 49.32 | -52.31 | 4.22 | -48.09 | -13 | -35.09 |
| 5 | 11295 | 50.13 | -51.36 | 3.48 | -47.88 | -13 | -34.88 |
| 6 | 13177.5 | 51.89 | -48.72 | 4.06 | -44.65 | -13 | -31.65 |
| 7 | 15060 | 57.79 | -39.56 | 3.70 | -35.86 | -13 | -22.86 |
| 8 | 16942.5 | 51.93 | -45.42 | 3.70 | -41.72 | -13 | -28.72 |

Antenna Polarity & Test Distance: Vertical at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3765 | 40.80 | -64.47 | 7.63 | -56.85 | -13 | -43.85 |
| 2 | 5647.5 | 45.54 | -59.19 | 7.02 | -52.18 | -13 | -39.18 |
| 3 | 7530 | 47.87 | -54.75 | 4.52 | -50.23 | -13 | -37.23 |
| 4 | 9412.5 | 50.59 | -51.04 | 4.22 | -46.82 | -13 | -33.82 |
| 5 | 11295 | 54.18 | -47.31 | 3.50 | -43.81 | -13 | -30.81 |
| 6 | 13177.5 | 51.14 | -49.47 | 4.06 | -45.40 | -13 | -32.40 |
| 7 | 15060 | 58.99 | -38.36 | 3.70 | -34.66 | -13 | -21.66 |
| 8 | 16942.5 | 51.78 | -45.57 | 3.70 | -41.87 | -13 | -28.87 |

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

| | | | |
|------|------------------|-----------------|----------------|
| Mode | TX channel 26675 | Frequency Range | Above 1000 MHz |
|------|------------------|-----------------|----------------|

Antenna Polarity & Test Distance: Horizontal at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3827 | 40.64 | -63.72 | 7.64 | -56.08 | -13 | -43.08 |
| 2 | 5740.5 | 43.05 | -61.55 | 6.96 | -54.59 | -13 | -41.59 |
| 3 | 7654 | 47.32 | -55.30 | 4.43 | -50.87 | -13 | -37.87 |
| 4 | 9567.5 | 48.73 | -52.88 | 4.18 | -48.71 | -13 | -35.71 |
| 5 | 11481 | 51.26 | -50.19 | 3.73 | -46.46 | -13 | -33.46 |
| 6 | 13394.5 | 50.44 | -49.88 | 3.57 | -46.31 | -13 | -33.31 |
| 7 | 15308 | 57.48 | -39.87 | 3.70 | -36.17 | -13 | -23.17 |
| 8 | 17221.5 | 51.74 | -45.61 | 3.70 | -41.91 | -13 | -28.91 |

Antenna Polarity & Test Distance: Vertical at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3827 | 39.02 | -65.38 | 7.63 | -57.74 | -13 | -44.74 |
| 2 | 5740.5 | 45.26 | -59.32 | 6.95 | -52.36 | -13 | -39.36 |
| 3 | 7654 | 49.33 | -53.29 | 4.43 | -48.86 | -13 | -35.86 |
| 4 | 9567.5 | 49.72 | -51.89 | 4.18 | -47.72 | -13 | -34.72 |
| 5 | 11481 | 52.69 | -48.76 | 3.73 | -45.03 | -13 | -32.03 |
| 6 | 13394.5 | 50.68 | -49.64 | 3.57 | -46.07 | -13 | -33.07 |
| 7 | 15308 | 58.96 | -38.39 | 3.70 | -34.69 | -13 | -21.69 |
| 8 | 17221.5 | 51.67 | -45.68 | 3.70 | -41.98 | -13 | -28.98 |

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 25: 5 MHz

| | | | |
|------|------------------|-----------------|----------------|
| Mode | TX channel 26065 | Frequency Range | Above 1000 MHz |
|------|------------------|-----------------|----------------|

Antenna Polarity & Test Distance: Horizontal at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3705 | 40.50 | -63.45 | 7.71 | -55.74 | -13 | -42.74 |
| 2 | 5557.5 | 42.65 | -62.23 | 7.08 | -55.15 | -13 | -42.15 |
| 3 | 7410 | 46.44 | -56.18 | 4.62 | -51.56 | -13 | -38.56 |
| 4 | 9262.5 | 49.63 | -52.59 | 4.23 | -48.36 | -13 | -35.36 |
| 5 | 11115 | 50.70 | -50.83 | 3.25 | -47.58 | -13 | -34.58 |
| 6 | 12967.5 | 51.42 | -49.46 | 4.52 | -44.93 | -13 | -31.93 |
| 7 | 14820 | 56.97 | -40.38 | 3.70 | -36.68 | -13 | -23.68 |
| 8 | 16672.5 | 52.57 | -44.78 | 3.70 | -41.08 | -13 | -28.08 |

Antenna Polarity & Test Distance: Vertical at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3705 | 40.82 | -63.13 | 7.71 | -55.42 | -13 | -42.42 |
| 2 | 5557.5 | 44.46 | -60.42 | 7.08 | -53.34 | -13 | -40.34 |
| 3 | 7410 | 48.16 | -54.46 | 4.62 | -49.84 | -13 | -36.84 |
| 4 | 9262.5 | 50.44 | -51.78 | 4.23 | -47.55 | -13 | -34.55 |
| 5 | 11115 | 54.30 | -47.23 | 3.25 | -43.98 | -13 | -30.98 |
| 6 | 12967.5 | 51.40 | -49.48 | 4.52 | -44.95 | -13 | -31.95 |
| 7 | 14820 | 57.30 | -40.05 | 3.70 | -36.35 | -13 | -23.35 |
| 8 | 16672.5 | 52.25 | -45.10 | 3.70 | -41.40 | -13 | -28.40 |

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

| | | | |
|------|------------------|-----------------|----------------|
| Mode | TX channel 26365 | Frequency Range | Above 1000 MHz |
|------|------------------|-----------------|----------------|

Antenna Polarity & Test Distance: Horizontal at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3765 | 41.24 | -64.03 | 7.63 | -56.41 | -13 | -43.41 |
| 2 | 5647.5 | 42.59 | -62.15 | 7.02 | -55.13 | -13 | -42.13 |
| 3 | 7530 | 46.50 | -56.12 | 4.53 | -51.59 | -13 | -38.59 |
| 4 | 9412.5 | 50.33 | -51.30 | 4.22 | -47.08 | -13 | -34.08 |
| 5 | 11295 | 51.47 | -50.02 | 3.48 | -46.54 | -13 | -33.54 |
| 6 | 13177.5 | 50.75 | -49.86 | 4.06 | -45.79 | -13 | -32.79 |
| 7 | 15060 | 57.11 | -40.24 | 3.70 | -36.54 | -13 | -23.54 |
| 8 | 16942.5 | 52.46 | -44.89 | 3.70 | -41.19 | -13 | -28.19 |

Antenna Polarity & Test Distance: Vertical at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3765 | 38.95 | -66.32 | 7.63 | -58.70 | -13 | -45.70 |
| 2 | 5647.5 | 44.20 | -60.54 | 7.02 | -53.52 | -13 | -40.52 |
| 3 | 7530 | 49.77 | -52.85 | 4.53 | -48.32 | -13 | -35.32 |
| 4 | 9412.5 | 49.90 | -51.73 | 4.22 | -47.51 | -13 | -34.51 |
| 5 | 11295 | 53.08 | -48.41 | 3.48 | -44.93 | -13 | -31.93 |
| 6 | 13177.5 | 49.75 | -50.86 | 4.06 | -46.79 | -13 | -33.79 |
| 7 | 15060 | 59.02 | -38.33 | 3.70 | -34.63 | -13 | -21.63 |
| 8 | 16942.5 | 53.42 | -43.93 | 3.70 | -40.23 | -13 | -27.23 |

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

| | | | |
|------|------------------|-----------------|----------------|
| Mode | TX channel 26665 | Frequency Range | Above 1000 MHz |
|------|------------------|-----------------|----------------|

Antenna Polarity & Test Distance: Horizontal at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3825 | 40.03 | -65.19 | 7.60 | -57.59 | -13 | -44.59 |
| 2 | 5737.5 | 43.64 | -60.50 | 7.24 | -53.26 | -13 | -40.26 |
| 3 | 7650 | 47.37 | -55.25 | 4.43 | -50.82 | -13 | -37.82 |
| 4 | 9562.5 | 48.99 | -52.63 | 4.18 | -48.45 | -13 | -35.45 |
| 5 | 11475 | 51.30 | -50.16 | 3.71 | -46.45 | -13 | -33.45 |
| 6 | 13387.5 | 50.87 | -49.45 | 3.57 | -45.88 | -13 | -32.88 |
| 7 | 15300 | 57.59 | -39.76 | 3.70 | -36.06 | -13 | -23.06 |
| 8 | 17212.5 | 51.67 | -45.68 | 3.70 | -41.98 | -13 | -28.98 |

Antenna Polarity & Test Distance: Vertical at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3825 | 39.82 | -65.40 | 7.60 | -57.80 | -13 | -44.80 |
| 2 | 5737.5 | 44.94 | -59.20 | 7.24 | -51.96 | -13 | -38.96 |
| 3 | 7650 | 47.90 | -54.72 | 4.43 | -50.29 | -13 | -37.29 |
| 4 | 9562.5 | 50.50 | -51.12 | 4.18 | -46.94 | -13 | -33.94 |
| 5 | 11475 | 52.65 | -48.81 | 3.71 | -45.10 | -13 | -32.10 |
| 6 | 13387.5 | 49.91 | -50.41 | 3.57 | -46.84 | -13 | -33.84 |
| 7 | 15300 | 58.49 | -38.86 | 3.70 | -35.16 | -13 | -22.16 |
| 8 | 17212.5 | 52.74 | -44.61 | 3.70 | -40.91 | -13 | -27.91 |

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 25: 10 MHz

| | | | |
|------|------------------|-----------------|----------------|
| Mode | TX channel 26090 | Frequency Range | Above 1000 MHz |
|------|------------------|-----------------|----------------|

Antenna Polarity & Test Distance: Horizontal at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3710 | 41.39 | -62.58 | 7.71 | -54.87 | -13 | -41.87 |
| 2 | 5565 | 43.19 | -61.68 | 7.07 | -54.61 | -13 | -41.61 |
| 3 | 7420 | 47.99 | -54.63 | 4.61 | -50.02 | -13 | -37.02 |
| 4 | 9275 | 48.94 | -53.25 | 4.23 | -49.02 | -13 | -36.02 |
| 5 | 11130 | 49.93 | -51.59 | 3.27 | -48.32 | -13 | -35.32 |
| 6 | 12985 | 50.62 | -50.23 | 4.48 | -45.75 | -13 | -32.75 |
| 7 | 14840 | 57.20 | -40.15 | 3.70 | -36.45 | -13 | -23.45 |
| 8 | 16695 | 52.08 | -45.27 | 3.70 | -41.57 | -13 | -28.57 |

Antenna Polarity & Test Distance: Vertical at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3710 | 39.82 | -64.15 | 7.71 | -56.44 | -13 | -43.44 |
| 2 | 5565 | 44.84 | -60.03 | 7.07 | -52.96 | -13 | -39.96 |
| 3 | 7420 | 49.08 | -53.54 | 4.61 | -48.93 | -13 | -35.93 |
| 4 | 9275 | 51.05 | -51.14 | 4.23 | -46.91 | -13 | -33.91 |
| 5 | 11130 | 53.90 | -47.62 | 3.27 | -44.35 | -13 | -31.35 |
| 6 | 12985 | 50.73 | -50.12 | 4.48 | -45.64 | -13 | -32.64 |
| 7 | 14840 | 57.18 | -40.17 | 3.70 | -36.47 | -13 | -23.47 |
| 8 | 16695 | 52.31 | -45.04 | 3.70 | -41.34 | -13 | -28.34 |

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

| | | | |
|------|------------------|-----------------|----------------|
| Mode | TX channel 26365 | Frequency Range | Above 1000 MHz |
|------|------------------|-----------------|----------------|

Antenna Polarity & Test Distance: Horizontal at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3765 | 41.44 | -63.83 | 7.63 | -56.21 | -13 | -43.21 |
| 2 | 5647.5 | 42.86 | -61.88 | 7.02 | -54.86 | -13 | -41.86 |
| 3 | 7530 | 46.98 | -55.64 | 4.53 | -51.11 | -13 | -38.11 |
| 4 | 9412.5 | 49.95 | -51.68 | 4.22 | -47.46 | -13 | -34.46 |
| 5 | 11295 | 50.47 | -51.02 | 3.48 | -47.54 | -13 | -34.54 |
| 6 | 13177.5 | 50.68 | -49.93 | 4.06 | -45.86 | -13 | -32.86 |
| 7 | 15060 | 55.98 | -41.37 | 3.70 | -37.67 | -13 | -24.67 |
| 8 | 16942.5 | 51.48 | -45.87 | 3.70 | -42.17 | -13 | -29.17 |

Antenna Polarity & Test Distance: Vertical at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3765 | 39.03 | -66.24 | 7.63 | -58.62 | -13 | -45.62 |
| 2 | 5647.5 | 45.78 | -58.96 | 7.02 | -51.94 | -13 | -38.94 |
| 3 | 7530 | 49.72 | -52.90 | 4.53 | -48.37 | -13 | -35.37 |
| 4 | 9412.5 | 49.17 | -52.46 | 4.22 | -48.24 | -13 | -35.24 |
| 5 | 11295 | 54.28 | -47.21 | 3.48 | -43.73 | -13 | -30.73 |
| 6 | 13177.5 | 50.27 | -50.34 | 4.06 | -46.27 | -13 | -33.27 |
| 7 | 15060 | 57.53 | -39.82 | 3.70 | -36.12 | -13 | -23.12 |
| 8 | 16942.5 | 52.88 | -44.47 | 3.70 | -40.77 | -13 | -27.77 |

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

| | | | |
|------|------------------|-----------------|----------------|
| Mode | TX channel 26640 | Frequency Range | Above 1000 MHz |
|------|------------------|-----------------|----------------|

Antenna Polarity & Test Distance: Horizontal at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3820 | 41.32 | -63.90 | 7.60 | -56.30 | -13 | -43.30 |
| 2 | 5730 | 41.76 | -62.38 | 7.23 | -55.15 | -13 | -42.15 |
| 3 | 7640 | 47.90 | -54.72 | 4.43 | -50.29 | -13 | -37.29 |
| 4 | 9550 | 49.02 | -52.59 | 4.17 | -48.42 | -13 | -35.42 |
| 5 | 11460 | 51.18 | -50.28 | 3.73 | -46.54 | -13 | -33.54 |
| 6 | 13370 | 50.42 | -49.94 | 3.65 | -46.30 | -13 | -33.30 |
| 7 | 15280 | 55.91 | -41.44 | 3.70 | -37.74 | -13 | -24.74 |
| 8 | 17190 | 53.12 | -44.23 | 3.70 | -40.53 | -13 | -27.53 |

Antenna Polarity & Test Distance: Vertical at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3820 | 40.18 | -65.04 | 7.60 | -57.44 | -13 | -44.44 |
| 2 | 5730 | 44.50 | -59.64 | 7.23 | -52.41 | -13 | -39.41 |
| 3 | 7640 | 49.75 | -52.87 | 4.43 | -48.44 | -13 | -35.44 |
| 4 | 9550 | 49.42 | -52.19 | 4.17 | -48.02 | -13 | -35.02 |
| 5 | 11460 | 53.19 | -48.27 | 3.73 | -44.53 | -13 | -31.53 |
| 6 | 13370 | 49.95 | -50.41 | 3.65 | -46.77 | -13 | -33.77 |
| 7 | 15280 | 57.87 | -39.48 | 3.70 | -35.78 | -13 | -22.78 |
| 8 | 17190 | 51.87 | -45.48 | 3.70 | -41.78 | -13 | -28.78 |

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 25: 15 MHz

| | | | |
|------|------------------|-----------------|----------------|
| Mode | TX channel 26115 | Frequency Range | Above 1000 MHz |
|------|------------------|-----------------|----------------|

Antenna Polarity & Test Distance: Horizontal at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3715 | 40.16 | -65.16 | 7.65 | -57.52 | -13 | -44.52 |
| 2 | 5572.5 | 43.40 | -61.46 | 7.07 | -54.39 | -13 | -41.39 |
| 3 | 7430 | 47.38 | -55.24 | 4.61 | -50.63 | -13 | -37.63 |
| 4 | 9287.5 | 48.61 | -53.55 | 4.23 | -49.32 | -13 | -36.32 |
| 5 | 11145 | 51.20 | -50.32 | 3.29 | -47.03 | -13 | -34.03 |
| 6 | 13002.5 | 51.79 | -49.04 | 4.44 | -44.60 | -13 | -31.60 |
| 7 | 14860 | 56.43 | -41.14 | 3.50 | -37.64 | -13 | -24.64 |
| 8 | 16717.5 | 52.77 | -44.58 | 3.70 | -40.88 | -13 | -27.88 |

Antenna Polarity & Test Distance: Vertical at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3715 | 39.67 | -65.65 | 7.65 | -58.01 | -13 | -45.01 |
| 2 | 5572.5 | 45.18 | -59.68 | 7.07 | -52.61 | -13 | -39.61 |
| 3 | 7430 | 48.33 | -54.29 | 4.61 | -49.68 | -13 | -36.68 |
| 4 | 9287.5 | 49.43 | -52.73 | 4.23 | -48.50 | -13 | -35.50 |
| 5 | 11145 | 53.93 | -47.59 | 3.29 | -44.30 | -13 | -31.30 |
| 6 | 13002.5 | 51.02 | -49.81 | 4.44 | -45.37 | -13 | -32.37 |
| 7 | 14860 | 58.70 | -38.87 | 3.50 | -35.37 | -13 | -22.37 |
| 8 | 16717.5 | 52.87 | -44.48 | 3.70 | -40.78 | -13 | -27.78 |

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

| | | | |
|------|------------------|-----------------|----------------|
| Mode | TX channel 26365 | Frequency Range | Above 1000 MHz |
|------|------------------|-----------------|----------------|

Antenna Polarity & Test Distance: Horizontal at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3765 | 40.53 | -64.74 | 7.63 | -57.12 | -13 | -44.12 |
| 2 | 5647.5 | 43.21 | -61.53 | 7.02 | -54.51 | -13 | -41.51 |
| 3 | 7530 | 46.17 | -56.45 | 4.53 | -51.92 | -13 | -38.92 |
| 4 | 9412.5 | 48.38 | -53.25 | 4.22 | -49.03 | -13 | -36.03 |
| 5 | 11295 | 50.84 | -50.65 | 3.48 | -47.17 | -13 | -34.17 |
| 6 | 13177.5 | 50.30 | -50.31 | 4.06 | -46.24 | -13 | -33.24 |
| 7 | 15060 | 57.18 | -40.17 | 3.70 | -36.47 | -13 | -23.47 |
| 8 | 16942.5 | 51.95 | -45.40 | 3.70 | -41.70 | -13 | -28.70 |

Antenna Polarity & Test Distance: Vertical at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3765 | 39.89 | -65.38 | 7.63 | -57.76 | -13 | -44.76 |
| 2 | 5647.5 | 45.47 | -59.27 | 7.02 | -52.25 | -13 | -39.25 |
| 3 | 7530 | 49.55 | -53.07 | 4.53 | -48.54 | -13 | -35.54 |
| 4 | 9412.5 | 50.67 | -50.96 | 4.22 | -46.74 | -13 | -33.74 |
| 5 | 11295 | 52.61 | -48.88 | 3.48 | -45.40 | -13 | -32.40 |
| 6 | 13177.5 | 50.77 | -49.84 | 4.06 | -45.77 | -13 | -32.77 |
| 7 | 15060 | 58.04 | -39.31 | 3.70 | -35.61 | -13 | -22.61 |
| 8 | 16942.5 | 51.80 | -45.55 | 3.70 | -41.85 | -13 | -28.85 |

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

| | | | |
|------|------------------|-----------------|----------------|
| Mode | TX channel 26615 | Frequency Range | Above 1000 MHz |
|------|------------------|-----------------|----------------|

Antenna Polarity & Test Distance: Horizontal at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3815 | 40.08 | -65.15 | 7.61 | -57.54 | -13 | -44.54 |
| 2 | 5722.5 | 42.94 | -61.69 | 6.97 | -54.72 | -13 | -41.72 |
| 3 | 7630 | 47.82 | -54.80 | 4.43 | -50.37 | -13 | -37.37 |
| 4 | 9537.5 | 50.26 | -51.36 | 4.19 | -47.17 | -13 | -34.17 |
| 5 | 11445 | 50.50 | -50.97 | 3.67 | -47.30 | -13 | -34.30 |
| 6 | 13352.5 | 51.45 | -48.92 | 3.65 | -45.27 | -13 | -32.27 |
| 7 | 15260 | 57.85 | -39.50 | 3.70 | -35.80 | -13 | -22.80 |
| 8 | 17167.5 | 52.98 | -44.37 | 3.70 | -40.67 | -13 | -27.67 |

Antenna Polarity & Test Distance: Vertical at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3815 | 39.36 | -65.87 | 7.61 | -58.26 | -13 | -45.26 |
| 2 | 5722.5 | 44.15 | -60.48 | 6.97 | -53.51 | -13 | -40.51 |
| 3 | 7630 | 48.99 | -53.63 | 4.43 | -49.20 | -13 | -36.20 |
| 4 | 9537.5 | 50.67 | -50.95 | 4.19 | -46.76 | -13 | -33.76 |
| 5 | 11445 | 53.33 | -48.14 | 3.67 | -44.47 | -13 | -31.47 |
| 6 | 13352.5 | 51.41 | -48.96 | 3.65 | -45.31 | -13 | -32.31 |
| 7 | 15260 | 58.38 | -38.97 | 3.70 | -35.27 | -13 | -22.27 |
| 8 | 17167.5 | 53.13 | -44.22 | 3.70 | -40.52 | -13 | -27.52 |

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 25: 20 MHz

| | | | |
|------|------------------|-----------------|----------------|
| Mode | TX channel 26140 | Frequency Range | Above 1000 MHz |
|------|------------------|-----------------|----------------|

Antenna Polarity & Test Distance: Horizontal at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3720 | 40.93 | -63.08 | 7.70 | -55.37 | -13 | -42.37 |
| 2 | 5580 | 41.87 | -62.98 | 7.06 | -55.91 | -13 | -42.91 |
| 3 | 7440 | 46.88 | -55.67 | 4.60 | -51.07 | -13 | -38.07 |
| 4 | 9300 | 48.42 | -53.71 | 4.23 | -49.48 | -13 | -36.48 |
| 5 | 11160 | 50.18 | -51.34 | 3.31 | -48.02 | -13 | -35.02 |
| 6 | 13020 | 50.83 | -49.97 | 4.40 | -45.57 | -13 | -32.57 |
| 7 | 14880 | 57.80 | -39.55 | 3.70 | -35.85 | -13 | -22.85 |
| 8 | 16740 | 52.93 | -44.42 | 3.70 | -40.72 | -13 | -27.72 |

Antenna Polarity & Test Distance: Vertical at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3720 | 39.59 | -64.42 | 7.70 | -56.71 | -13 | -43.71 |
| 2 | 5580 | 43.94 | -60.91 | 7.06 | -53.84 | -13 | -40.84 |
| 3 | 7440 | 49.26 | -53.29 | 4.60 | -48.69 | -13 | -35.69 |
| 4 | 9300 | 50.80 | -51.33 | 4.23 | -47.10 | -13 | -34.10 |
| 5 | 11160 | 53.20 | -48.32 | 3.31 | -45.00 | -13 | -32.00 |
| 6 | 13020 | 51.09 | -49.71 | 4.40 | -45.31 | -13 | -32.31 |
| 7 | 14880 | 57.62 | -39.73 | 3.70 | -36.03 | -13 | -23.03 |
| 8 | 16740 | 52.99 | -44.36 | 3.70 | -40.66 | -13 | -27.66 |

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

| | | | |
|------|------------------|-----------------|----------------|
| Mode | TX channel 26365 | Frequency Range | Above 1000 MHz |
|------|------------------|-----------------|----------------|

Antenna Polarity & Test Distance: Horizontal at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3765 | 41.21 | -64.06 | 7.63 | -56.44 | -13 | -43.44 |
| 2 | 5647.5 | 42.53 | -62.21 | 7.02 | -55.19 | -13 | -42.19 |
| 3 | 7530 | 47.57 | -55.05 | 4.53 | -50.52 | -13 | -37.52 |
| 4 | 9412.5 | 48.80 | -52.83 | 4.22 | -48.61 | -13 | -35.61 |
| 5 | 11295 | 50.02 | -51.50 | 3.29 | -48.21 | -13 | -35.21 |
| 6 | 13177.5 | 50.37 | -51.12 | 3.48 | -47.64 | -13 | -34.64 |
| 7 | 15060 | 56.31 | -41.04 | 3.70 | -37.34 | -13 | -24.34 |
| 8 | 16942.5 | 52.32 | -45.03 | 3.70 | -41.33 | -13 | -28.33 |

Antenna Polarity & Test Distance: Vertical at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3765 | 39.36 | -65.91 | 7.63 | -58.29 | -13 | -45.29 |
| 2 | 5647.5 | 43.95 | -60.79 | 7.02 | -53.77 | -13 | -40.77 |
| 3 | 7530 | 47.88 | -54.74 | 4.53 | -50.21 | -13 | -37.21 |
| 4 | 9412.5 | 50.13 | -51.50 | 4.22 | -47.28 | -13 | -34.28 |
| 5 | 11295 | 53.55 | -47.97 | 3.29 | -44.68 | -13 | -31.68 |
| 6 | 13177.5 | 50.09 | -51.40 | 3.48 | -47.92 | -13 | -34.92 |
| 7 | 15060 | 59.13 | -38.22 | 3.70 | -34.52 | -13 | -21.52 |
| 8 | 16942.5 | 51.96 | -45.39 | 3.70 | -41.69 | -13 | -28.69 |

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

| | | | |
|------|------------------|-----------------|----------------|
| Mode | TX channel 26590 | Frequency Range | Above 1000 MHz |
|------|------------------|-----------------|----------------|

Antenna Polarity & Test Distance: Horizontal at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3810 | 41.79 | -63.43 | 7.60 | -55.83 | -13 | -42.83 |
| 2 | 5715 | 43.23 | -60.91 | 7.25 | -53.66 | -13 | -40.66 |
| 3 | 7620 | 46.48 | -56.14 | 4.44 | -51.70 | -13 | -38.70 |
| 4 | 9525 | 49.17 | -52.45 | 4.18 | -48.27 | -13 | -35.27 |
| 5 | 11430 | 50.87 | -50.59 | 3.69 | -46.90 | -13 | -33.90 |
| 6 | 13335 | 50.35 | -50.01 | 3.65 | -46.37 | -13 | -33.37 |
| 7 | 15240 | 57.02 | -40.33 | 3.70 | -36.63 | -13 | -23.63 |
| 8 | 17145 | 53.04 | -44.31 | 3.70 | -40.61 | -13 | -27.61 |

Antenna Polarity & Test Distance: Vertical at 3 M

| No. | Freq. (MHz) | Reading (dBm) | S.G Power Value (dBm) | Correction Factor (dB) | Emission Value (dBm) | Limit (dBm) | Margin (dB) |
|-----|-------------|---------------|-----------------------|------------------------|----------------------|-------------|-------------|
| 1 | 3810 | 39.08 | -66.14 | 7.60 | -58.54 | -13 | -45.54 |
| 2 | 5715 | 43.91 | -60.23 | 7.25 | -52.98 | -13 | -39.98 |
| 3 | 7620 | 48.19 | -54.43 | 4.44 | -49.99 | -13 | -36.99 |
| 4 | 9525 | 50.32 | -51.30 | 4.18 | -47.12 | -13 | -34.12 |
| 5 | 11430 | 52.53 | -48.93 | 3.69 | -45.24 | -13 | -32.24 |
| 6 | 13335 | 50.25 | -50.11 | 3.65 | -46.47 | -13 | -33.47 |
| 7 | 15240 | 57.67 | -39.68 | 3.70 | -35.98 | -13 | -22.98 |
| 8 | 17145 | 51.70 | -45.65 | 3.70 | -41.95 | -13 | -28.95 |

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

5 Pictures of Test Arrangements

Please refer to the attached file (Test Setup Photo).

Appendix – Information on the Testing Laboratories

We, Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch, were founded in 1988 to provide our best service in EMC, Radio, Telecom and Safety consultation. Our laboratories are accredited and approved according to ISO/IEC 17025.

If you have any comments, please feel free to contact us at the following:

Linko EMC/RF Lab

Tel: 886-2-26052180

Fax: 886-2-26051924

Hsin Chu EMC/RF/Telecom Lab

Tel: 886-3-6668565

Fax: 886-3-6668323

Hwa Ya EMC/RF/Safety Lab

Tel: 886-3-3183232

Fax: 886-3-3270892

Email: service.adt@tw.bureauveritas.com

Web Site: www.bureauveritas-adt.com

The address and road map of all our labs can be found in our web site also.

--- END ---