

LTE Band 41: 5MHz

Mode	TX channel 39675	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	161.03	32.26	-55.67	-0.84	-56.51	-25	-31.51
2	235.91	31.73	-63.57	3.83	-59.74	-25	-34.74
3	337.86	30.28	-67.60	3.67	-63.93	-25	-38.93
4	429.04	30.48	-68.73	2.78	-65.95	-25	-40.95
5	529.91	33.92	-61.15	2.86	-58.29	-25	-33.29
6	803.81	30.87	-67.60	1.52	-66.08	-25	-41.08

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	132.45	31.30	-64.85	-1.55	-66.40	-25	-41.40
2	260.6	30.10	-64.47	3.98	-60.49	-25	-35.49
3	304.73	30.75	-65.23	3.70	-61.53	-25	-36.53
4	410.45	32.09	-65.85	3.21	-62.64	-25	-37.64
5	670.05	30.28	-65.28	1.69	-63.59	-25	-38.59
6	737.3	31.00	-64.87	0.66	-64.21	-25	-39.21

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 40620	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	160.93	32.01	-55.92	-0.84	-56.76	-25	-31.76
2	235.8	31.53	-63.77	3.83	-59.94	-25	-34.94
3	337.01	30.41	-67.47	3.67	-63.80	-25	-38.80
4	428.25	29.54	-69.67	2.78	-66.89	-25	-41.89
5	529.41	33.75	-61.32	2.86	-58.46	-25	-33.46
6	802.86	30.39	-68.08	1.52	-66.56	-25	-41.56

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	131.77	31.32	-64.83	-1.55	-66.38	-25	-41.38
2	259.9	29.71	-64.86	3.98	-60.88	-25	-35.88
3	305.21	30.41	-65.57	3.70	-61.87	-25	-36.87
4	410.12	32.32	-65.62	3.21	-62.41	-25	-37.41
5	670.85	29.98	-65.58	1.69	-63.89	-25	-38.89
6	738.11	31.49	-64.38	0.66	-63.72	-25	-38.72

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 41565	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	161.13	33.23	-54.70	-0.84	-55.54	-25	-30.54
2	236.58	31.17	-64.13	3.83	-60.30	-25	-35.30
3	338.29	30.79	-67.09	3.67	-63.42	-25	-38.42
4	429.02	29.86	-69.35	2.78	-66.57	-25	-41.57
5	530.74	32.64	-62.43	2.86	-59.57	-25	-34.57
6	804.43	30.39	-68.08	1.52	-66.56	-25	-41.56

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	133.06	30.44	-65.71	-1.55	-67.26	-25	-42.26
2	259.86	29.56	-65.01	3.98	-61.03	-25	-36.03
3	304.88	31.18	-64.80	3.70	-61.10	-25	-36.10
4	410.89	32.33	-65.61	3.21	-62.40	-25	-37.40
5	670.8	30.85	-64.71	1.69	-63.02	-25	-38.02
6	737.95	30.31	-65.56	0.66	-64.90	-25	-39.90

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 41: 10MHz

Mode	TX channel 39700	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	160.83	33.83	-54.10	-0.84	-54.94	-25	-29.94
2	236.12	31.97	-63.33	3.83	-59.50	-25	-34.50
3	338.36	31.19	-66.69	3.67	-63.02	-25	-38.02
4	429.79	30.60	-68.61	2.78	-65.83	-25	-40.83
5	529.81	32.76	-62.31	2.86	-59.45	-25	-34.45
6	804.79	31.13	-67.34	1.52	-65.82	-25	-40.82

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	132.64	30.66	-65.49	-1.55	-67.04	-25	-42.04
2	259.62	29.27	-65.30	3.98	-61.32	-25	-36.32
3	304.32	30.67	-65.31	3.70	-61.61	-25	-36.61
4	411.15	31.98	-65.96	3.21	-62.75	-25	-37.75
5	669.76	29.35	-66.21	1.69	-64.52	-25	-39.52
6	737.36	30.58	-65.29	0.66	-64.63	-25	-39.63

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 40620	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	160.26	34.21	-53.72	-0.84	-54.56	-25	-29.56
2	237.34	31.39	-63.91	3.83	-60.08	-25	-35.08
3	337.67	31.44	-66.44	3.67	-62.77	-25	-37.77
4	429.26	30.41	-68.80	2.78	-66.02	-25	-41.02
5	529.75	33.11	-61.96	2.86	-59.10	-25	-34.10
6	805.22	30.16	-68.31	1.52	-66.79	-25	-41.79

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	131.5	31.27	-64.88	-1.55	-66.43	-25	-41.43
2	260.11	30.60	-63.97	3.98	-59.99	-25	-34.99
3	304.91	31.27	-64.71	3.70	-61.01	-25	-36.01
4	409.86	31.28	-66.66	3.21	-63.45	-25	-38.45
5	670.87	30.88	-64.68	1.69	-62.99	-25	-37.99
6	736.99	30.95	-64.92	0.66	-64.26	-25	-39.26

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 41540	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	160.61	33.94	-53.99	-0.84	-54.83	-25	-29.83
2	242.83	29.64	-65.66	3.83	-61.83	-25	-36.83
3	337.15	29.86	-68.02	3.67	-64.35	-25	-39.35
4	432.15	26.75	-72.46	2.78	-69.68	-25	-44.68
5	526.83	30.73	-64.34	2.86	-61.48	-25	-36.48
6	802.66	34.02	-64.45	1.52	-62.93	-25	-37.93

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	131.64	30.42	-65.73	-1.55	-67.28	-25	-42.28
2	260.52	30.77	-63.80	3.98	-59.82	-25	-34.82
3	304.56	31.70	-64.28	3.70	-60.58	-25	-35.58
4	410.17	31.75	-66.19	3.21	-62.98	-25	-37.98
5	669.48	31.08	-64.48	1.69	-62.79	-25	-37.79
6	737	30.74	-65.13	0.66	-64.47	-25	-39.47

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 41: 15MHz

Mode	TX channel 39725	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	160.4	31.53	-56.40	-0.84	-57.24	-25	-32.24
2	244.2	30.44	-64.86	3.83	-61.03	-25	-36.03
3	340.07	29.14	-68.74	3.67	-65.07	-25	-40.07
4	432.36	28.77	-70.44	2.78	-67.66	-25	-42.66
5	525.97	29.55	-65.52	2.86	-62.66	-25	-37.66
6	803.79	30.52	-67.95	1.52	-66.43	-25	-41.43

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	133.19	31.13	-65.02	-1.55	-66.57	-25	-41.57
2	259.85	30.96	-63.61	3.98	-59.63	-25	-34.63
3	304.55	29.97	-66.01	3.70	-62.31	-25	-37.31
4	411.27	31.52	-66.42	3.21	-63.21	-25	-38.21
5	670.63	29.60	-65.96	1.69	-64.27	-25	-39.27
6	736.75	30.67	-65.20	0.66	-64.54	-25	-39.54

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 40620	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	160.03	32.24	-55.69	-0.84	-56.53	-25	-31.53
2	244.12	29.61	-65.69	3.83	-61.86	-25	-36.86
3	339.76	29.67	-68.21	3.67	-64.54	-25	-39.54
4	432.41	29.05	-70.16	2.78	-67.38	-25	-42.38
5	525.02	30.26	-64.81	2.86	-61.95	-25	-36.95
6	804.21	31.04	-67.43	1.52	-65.91	-25	-40.91

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	132.39	32.05	-64.10	-1.55	-65.65	-25	-40.65
2	260.21	30.42	-64.15	3.98	-60.17	-25	-35.17
3	304.56	30.27	-65.71	3.70	-62.01	-25	-37.01
4	409.94	32.40	-65.54	3.21	-62.33	-25	-37.33
5	669.54	30.52	-65.04	1.69	-63.35	-25	-38.35
6	736.5	30.35	-65.52	0.66	-64.86	-25	-39.86

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 41515	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	159.88	32.09	-55.84	-0.84	-56.68	-25	-31.68
2	243.75	29.80	-65.50	3.83	-61.67	-25	-36.67
3	339.72	29.17	-68.71	3.67	-65.04	-25	-40.04
4	432.1	28.04	-71.17	2.78	-68.39	-25	-43.39
5	526.69	28.94	-66.13	2.86	-63.27	-25	-38.27
6	804.17	31.25	-67.22	1.52	-65.70	-25	-40.70

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	133.21	30.53	-65.62	-1.55	-67.17	-25	-42.17
2	260.91	30.89	-63.68	3.98	-59.70	-25	-34.70
3	304.47	29.90	-66.08	3.70	-62.38	-25	-37.38
4	411.24	31.22	-66.72	3.21	-63.51	-25	-38.51
5	670.06	29.98	-65.58	1.69	-63.89	-25	-38.89
6	737.68	30.89	-64.98	0.66	-64.32	-25	-39.32

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 41: 20MHz

Mode	TX channel 39750	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	160.92	31.90	-56.03	-0.84	-56.87	-25	-31.87
2	244.55	30.31	-64.99	3.83	-61.16	-25	-36.16
3	340.95	29.88	-68.00	3.67	-64.33	-25	-39.33
4	432.04	27.93	-71.28	2.78	-68.50	-25	-43.50
5	525.48	29.18	-65.89	2.86	-63.03	-25	-38.03
6	804.27	29.94	-68.53	1.52	-67.01	-25	-42.01

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	132.69	31.34	-64.81	-1.55	-66.36	-25	-41.36
2	260.49	30.28	-64.29	3.98	-60.31	-25	-35.31
3	305.56	31.07	-64.91	3.70	-61.21	-25	-36.21
4	410.4	31.99	-65.95	3.21	-62.74	-25	-37.74
5	670.95	30.56	-65.00	1.69	-63.31	-25	-38.31
6	736.86	30.61	-65.26	0.66	-64.60	-25	-39.60

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 40620	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	161.14	31.16	-56.77	-0.84	-57.61	-25	-32.61
2	243.6	30.54	-64.76	3.83	-60.93	-25	-35.93
3	340.48	29.94	-67.94	3.67	-64.27	-25	-39.27
4	431.64	28.90	-70.31	2.78	-67.53	-25	-42.53
5	525.9	29.76	-65.31	2.86	-62.45	-25	-37.45
6	803.78	31.17	-67.30	1.52	-65.78	-25	-40.78

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	132.9	31.27	-64.88	-1.55	-66.43	-25	-41.43
2	260.69	30.12	-64.45	3.98	-60.47	-25	-35.47
3	305.51	30.20	-65.78	3.70	-62.08	-25	-37.08
4	410.3	32.81	-65.13	3.21	-61.92	-25	-36.92
5	669.36	31.17	-64.39	1.69	-62.70	-25	-37.70
6	738.09	30.10	-65.77	0.66	-65.11	-25	-40.11

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 41490	Frequency Range	Below 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	159.78	32.25	-55.68	-0.84	-56.52	-25	-31.52
2	244.23	29.70	-65.60	3.83	-61.77	-25	-36.77
3	340.35	28.71	-69.17	3.67	-65.50	-25	-40.50
4	432.98	29.11	-70.10	2.78	-67.32	-25	-42.32
5	525.53	30.45	-64.62	2.86	-61.76	-25	-36.76
6	803.26	31.03	-67.44	1.52	-65.92	-25	-40.92

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	133.03	31.84	-64.31	-1.55	-65.86	-25	-40.86
2	261.57	30.31	-64.26	3.98	-60.28	-25	-35.28
3	303.74	31.37	-64.61	3.70	-60.91	-25	-35.91
4	410.77	32.61	-65.33	3.21	-62.12	-25	-37.12
5	670.17	29.37	-66.19	1.69	-64.50	-25	-39.50
6	737.77	31.72	-64.15	0.66	-63.49	-25	-38.49

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE CA_41C (10MHz+5MHz)

Mode	TX channel 39700+39844	Frequency Range	Below 1000 MHz
------	------------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	132.13	31.94	-64.21	-1.55	-65.76	-25	-40.76
2	259.71	29.57	-65.00	3.98	-61.02	-25	-36.02
3	304.68	32.65	-63.33	3.70	-59.63	-25	-34.63
4	410.53	32.19	-65.75	3.21	-62.54	-25	-37.54
5	669.42	30.79	-64.77	1.69	-63.08	-25	-38.08
6	741.92	29.07	-66.80	0.66	-66.14	-25	-41.14

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	160.54	33.73	-54.20	-0.84	-55.04	-25	-30.04
2	239.88	32.05	-63.25	3.83	-59.42	-25	-34.42
3	338.17	32.53	-65.35	3.67	-61.68	-25	-36.68
4	432.39	27.39	-71.82	2.78	-69.04	-25	-44.04
5	525.66	31.07	-64.00	2.86	-61.14	-25	-36.14
6	805.03	33.23	-65.24	1.52	-63.72	-25	-38.72

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 66: 1.4MHz

Mode	TX channel 131979	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	159.39	33.07	-54.86	-0.84	-55.70	-13	-42.70
2	241.27	29.12	-66.18	3.83	-62.35	-13	-49.35
3	335.87	30.29	-67.59	3.67	-63.92	-13	-50.92
4	432.14	28.31	-70.90	2.78	-68.12	-13	-55.12
5	525.82	32.41	-62.66	2.86	-59.80	-13	-46.80
6	802.72	31.41	-67.06	1.52	-65.54	-13	-52.54

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	130.91	32.48	-63.67	-1.55	-65.22	-13	-52.22
2	257.68	32.60	-61.97	3.98	-57.99	-13	-44.99
3	304.9	30.30	-65.68	3.70	-61.98	-13	-48.98
4	412.87	33.84	-64.10	3.21	-60.89	-13	-47.89
5	670.94	30.25	-65.31	1.69	-63.62	-13	-50.62
6	741.17	32.31	-63.56	0.66	-62.90	-13	-49.90

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 132322	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	157.29	32.30	-55.63	-0.84	-56.47	-13	-43.47
2	237.74	27.79	-67.51	3.83	-63.68	-13	-50.68
3	336.97	31.95	-65.93	3.67	-62.26	-13	-49.26
4	430.39	29.13	-70.08	2.78	-67.30	-13	-54.30
5	522.27	27.91	-67.16	2.86	-64.30	-13	-51.30
6	801.91	31.93	-66.54	1.52	-65.02	-13	-52.02

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	129.92	31.04	-65.11	-1.55	-66.66	-13	-53.66
2	257.99	31.70	-62.87	3.98	-58.89	-13	-45.89
3	305.78	29.48	-66.50	3.70	-62.80	-13	-49.80
4	411.9	31.57	-66.37	3.21	-63.16	-13	-50.16
5	670.9	30.42	-65.14	1.69	-63.45	-13	-50.45
6	741.68	31.72	-64.15	0.66	-63.49	-13	-50.49

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 132665	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	157.73	31.95	-55.98	-0.84	-56.82	-13	-43.82
2	238.66	27.51	-67.79	3.83	-63.96	-13	-50.96
3	337.37	31.28	-66.60	3.67	-62.93	-13	-49.93
4	430.8	29.42	-69.79	2.78	-67.01	-13	-54.01
5	522.82	28.55	-66.52	2.86	-63.66	-13	-50.66
6	802.54	31.92	-66.55	1.52	-65.03	-13	-52.03

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	129.99	31.32	-64.83	-1.55	-66.38	-13	-53.38
2	258.57	31.61	-62.96	3.98	-58.98	-13	-45.98
3	305.48	28.99	-66.99	3.70	-63.29	-13	-50.29
4	412.88	31.49	-66.45	3.21	-63.24	-13	-50.24
5	669.96	30.79	-64.77	1.69	-63.08	-13	-50.08
6	741.84	32.70	-63.17	0.66	-62.51	-13	-49.51

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 66: 3MHz

Mode	TX channel 131987	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	157.16	32.76	-55.17	-0.84	-56.01	-13	-43.01
2	238.72	27.89	-67.41	3.83	-63.58	-13	-50.58
3	336.17	31.50	-66.38	3.67	-62.71	-13	-49.71
4	429.99	29.62	-69.59	2.78	-66.81	-13	-53.81
5	521.33	28.57	-66.50	2.86	-63.64	-13	-50.64
6	802.83	32.29	-66.18	1.52	-64.66	-13	-51.66

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	129.69	31.06	-65.09	-1.55	-66.64	-13	-53.64
2	257.25	31.13	-63.44	3.98	-59.46	-13	-46.46
3	305.34	28.62	-67.36	3.70	-63.66	-13	-50.66
4	412.87	31.14	-66.80	3.21	-63.59	-13	-50.59
5	670.56	29.59	-65.97	1.69	-64.28	-13	-51.28
6	741.31	32.64	-63.23	0.66	-62.57	-13	-49.57

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 132322	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	156.9	32.16	-55.77	-0.84	-56.61	-13	-43.61
2	238.51	27.60	-67.70	3.83	-63.87	-13	-50.87
3	337.95	32.29	-65.59	3.67	-61.92	-13	-48.92
4	429.59	30.02	-69.19	2.78	-66.41	-13	-53.41
5	521.33	27.47	-67.60	2.86	-64.74	-13	-51.74
6	802.87	31.54	-66.93	1.52	-65.41	-13	-52.41

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	130.9	31.77	-64.38	-1.55	-65.93	-13	-52.93
2	258.23	32.08	-62.49	3.98	-58.51	-13	-45.51
3	305.61	29.34	-66.64	3.70	-62.94	-13	-49.94
4	412.73	32.45	-65.49	3.21	-62.28	-13	-49.28
5	671.61	30.50	-65.06	1.69	-63.37	-13	-50.37
6	741.17	30.77	-65.10	0.66	-64.44	-13	-51.44

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 132657	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	129.27	30.84	-57.09	-0.84	-57.93	-13	-44.93
2	257.1	30.85	-64.45	3.83	-60.62	-13	-47.62
3	306.08	29.33	-68.55	3.67	-64.88	-13	-51.88
4	411.76	32.56	-66.65	2.78	-63.87	-13	-50.87
5	670.92	29.87	-65.20	2.86	-62.34	-13	-49.34
6	741.15	32.06	-66.41	1.52	-64.89	-13	-51.89

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	85.5	26.51	-69.64	-1.55	-71.19	-13	-58.19
2	140.65	24.84	-69.73	3.98	-65.75	-13	-52.75
3	286.26	22.74	-73.24	3.70	-69.54	-13	-56.54
4	343.87	23.02	-74.92	3.21	-71.71	-13	-58.71
5	471.47	21.36	-74.20	1.69	-72.51	-13	-59.51
6	733.15	19.05	-76.82	0.66	-76.16	-13	-63.16

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 66: 5MHz

Mode	TX channel 131997	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	158.61	32.79	-55.14	-0.84	-55.98	-13	-42.98
2	236.51	27.40	-67.90	3.83	-64.07	-13	-51.07
3	337.41	32.44	-65.44	3.67	-61.77	-13	-48.77
4	429.39	28.17	-71.04	2.78	-68.26	-13	-55.26
5	520.98	29.89	-65.18	2.86	-62.32	-13	-49.32
6	802.09	31.76	-66.71	1.52	-65.19	-13	-52.19

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	130.92	31.00	-65.15	-1.55	-66.70	-13	-53.70
2	257.25	31.09	-63.48	3.98	-59.50	-13	-46.50
3	305.62	28.86	-67.12	3.70	-63.42	-13	-50.42
4	412.85	31.18	-66.76	3.21	-63.55	-13	-50.55
5	670.19	30.53	-65.03	1.69	-63.34	-13	-50.34
6	740.99	31.34	-64.53	0.66	-63.87	-13	-50.87

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 132322	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	158.98	31.63	-56.30	-0.84	-57.14	-13	-44.14
2	236.19	27.82	-67.48	3.83	-63.65	-13	-50.65
3	337.29	31.60	-66.28	3.67	-62.61	-13	-49.61
4	429.23	28.63	-70.58	2.78	-67.80	-13	-54.80
5	522.54	29.52	-65.55	2.86	-62.69	-13	-49.69
6	803.22	30.95	-67.52	1.52	-66.00	-13	-53.00

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	129.3	30.55	-65.60	-1.55	-67.15	-13	-54.15
2	257.89	32.36	-62.21	3.98	-58.23	-13	-45.23
3	305.92	29.37	-66.61	3.70	-62.91	-13	-49.91
4	411.99	32.11	-65.83	3.21	-62.62	-13	-49.62
5	671.31	30.33	-65.23	1.69	-63.54	-13	-50.54
6	742.56	30.73	-65.14	0.66	-64.48	-13	-51.48

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 132647	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	159.14	32.39	-55.54	-0.84	-56.38	-13	-43.38
2	237.12	28.22	-67.08	3.83	-63.25	-13	-50.25
3	336.64	32.44	-65.44	3.67	-61.77	-13	-48.77
4	429.78	28.59	-70.62	2.78	-67.84	-13	-54.84
5	520.77	29.31	-65.76	2.86	-62.90	-13	-49.90
6	803.04	31.84	-66.63	1.52	-65.11	-13	-52.11

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	129.79	30.12	-66.03	-1.55	-67.58	-13	-54.58
2	257.14	30.77	-63.80	3.98	-59.82	-13	-46.82
3	305.86	30.24	-65.74	3.70	-62.04	-13	-49.04
4	411.49	31.75	-66.19	3.21	-62.98	-13	-49.98
5	670.51	29.85	-65.71	1.69	-64.02	-13	-51.02
6	741.49	30.86	-65.01	0.66	-64.35	-13	-51.35

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 66: 10MHz

Mode	TX channel 132022	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	158.76	32.21	-55.72	-0.84	-56.56	-13	-43.56
2	236.06	28.35	-66.95	3.83	-63.12	-13	-50.12
3	337.22	31.45	-66.43	3.67	-62.76	-13	-49.76
4	429.95	28.16	-71.05	2.78	-68.27	-13	-55.27
5	521.07	28.90	-66.17	2.86	-63.31	-13	-50.31
6	802.03	31.35	-67.12	1.52	-65.60	-13	-52.60

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	130.29	31.73	-64.42	-1.55	-65.97	-13	-52.97
2	258.83	30.92	-63.65	3.98	-59.67	-13	-46.67
3	305.83	29.92	-66.06	3.70	-62.36	-13	-49.36
4	412.84	32.02	-65.92	3.21	-62.71	-13	-49.71
5	671.5	31.07	-64.49	1.69	-62.80	-13	-49.80
6	741.88	31.43	-64.44	0.66	-63.78	-13	-50.78

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 132322	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	157.77	31.56	-56.37	-0.84	-57.21	-13	-44.21
2	236.22	29.14	-66.16	3.83	-62.33	-13	-49.33
3	337.54	32.65	-65.23	3.67	-61.56	-13	-48.56
4	428.62	28.96	-70.25	2.78	-67.47	-13	-54.47
5	520.94	29.86	-65.21	2.86	-62.35	-13	-49.35
6	801.84	30.88	-67.59	1.52	-66.07	-13	-53.07

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	129.57	31.85	-64.30	-1.55	-65.85	-13	-52.85
2	258.69	31.71	-62.86	3.98	-58.88	-13	-45.88
3	306.42	30.28	-65.70	3.70	-62.00	-13	-49.00
4	411.36	31.06	-66.88	3.21	-63.67	-13	-50.67
5	670.7	29.79	-65.77	1.69	-64.08	-13	-51.08
6	741.86	31.13	-64.74	0.66	-64.08	-13	-51.08

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 132622	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	158.25	30.40	-57.53	-0.84	-58.37	-13	-45.37
2	237.04	28.56	-66.74	3.83	-62.91	-13	-49.91
3	336.85	31.59	-66.29	3.67	-62.62	-13	-49.62
4	428.88	28.24	-70.97	2.78	-68.19	-13	-55.19
5	520.18	29.86	-65.21	2.86	-62.35	-13	-49.35
6	802	30.01	-68.46	1.52	-66.94	-13	-53.94

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	130.75	30.99	-65.16	-1.55	-66.71	-13	-53.71
2	257.31	31.79	-62.78	3.98	-58.80	-13	-45.80
3	306.26	29.19	-66.79	3.70	-63.09	-13	-50.09
4	411.2	31.71	-66.23	3.21	-63.02	-13	-50.02
5	670.81	30.73	-64.83	1.69	-63.14	-13	-50.14
6	740.83	32.67	-63.20	0.66	-62.54	-13	-49.54

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 66: 15MHz

Mode	TX channel 132047	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	157.63	30.30	-57.63	-0.84	-58.47	-13	-45.47
2	236.57	28.03	-67.27	3.83	-63.44	-13	-50.44
3	337.75	32.40	-65.48	3.67	-61.81	-13	-48.81
4	429.45	28.79	-70.42	2.78	-67.64	-13	-54.64
5	519.94	29.07	-66.00	2.86	-63.14	-13	-50.14
6	802.82	29.70	-68.77	1.52	-67.25	-13	-54.25

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	129.68	30.92	-65.23	-1.55	-66.78	-13	-53.78
2	257.82	32.20	-62.37	3.98	-58.39	-13	-45.39
3	306.34	30.34	-65.64	3.70	-61.94	-13	-48.94
4	412.74	30.94	-67.00	3.21	-63.79	-13	-50.79
5	671.23	30.42	-65.14	1.69	-63.45	-13	-50.45
6	741.96	32.12	-63.75	0.66	-63.09	-13	-50.09

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 132322	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	157.08	30.83	-57.10	-0.84	-57.94	-13	-44.94
2	236.93	28.38	-66.92	3.83	-63.09	-13	-50.09
3	336.9	32.40	-65.48	3.67	-61.81	-13	-48.81
4	428.99	27.55	-71.66	2.78	-68.88	-13	-55.88
5	521.56	29.09	-65.98	2.86	-63.12	-13	-50.12
6	801.53	30.03	-68.44	1.52	-66.92	-13	-53.92

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	130.03	30.26	-65.89	-1.55	-67.44	-13	-54.44
2	258.87	30.93	-63.64	3.98	-59.66	-13	-46.66
3	305.41	28.77	-67.21	3.70	-63.51	-13	-50.51
4	411.58	31.12	-66.82	3.21	-63.61	-13	-50.61
5	671.63	29.86	-65.70	1.69	-64.01	-13	-51.01
6	741.94	32.33	-63.54	0.66	-62.88	-13	-49.88

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 132597	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	158.7	30.78	-57.15	-0.84	-57.99	-13	-44.99
2	236.94	28.39	-66.91	3.83	-63.08	-13	-50.08
3	337.84	32.14	-65.74	3.67	-62.07	-13	-49.07
4	428.73	28.12	-71.09	2.78	-68.31	-13	-55.31
5	521.16	28.38	-66.69	2.86	-63.83	-13	-50.83
6	802.82	29.73	-68.74	1.52	-67.22	-13	-54.22

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	130.06	30.64	-65.51	-1.55	-67.06	-13	-54.06
2	258.56	30.88	-63.69	3.98	-59.71	-13	-46.71
3	304.84	28.75	-67.23	3.70	-63.53	-13	-50.53
4	411.95	31.24	-66.70	3.21	-63.49	-13	-50.49
5	671.52	30.29	-65.27	1.69	-63.58	-13	-50.58
6	741.5	32.33	-63.54	0.66	-62.88	-13	-49.88

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 66: 20MHz

Mode	TX channel 132072	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	157.34	30.51	-57.42	-0.84	-58.26	-13	-45.26
2	235.91	29.00	-66.30	3.83	-62.47	-13	-49.47
3	337.12	32.36	-65.52	3.67	-61.85	-13	-48.85
4	428.88	28.41	-70.80	2.78	-68.02	-13	-55.02
5	520.95	28.76	-66.31	2.86	-63.45	-13	-50.45
6	801.39	30.28	-68.19	1.52	-66.67	-13	-53.67

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	130.25	31.19	-64.96	-1.55	-66.51	-13	-53.51
2	258.62	32.20	-62.37	3.98	-58.39	-13	-45.39
3	305.62	30.07	-65.91	3.70	-62.21	-13	-49.21
4	412.87	31.16	-66.78	3.21	-63.57	-13	-50.57
5	670.73	31.25	-64.31	1.69	-62.62	-13	-49.62
6	741.72	30.97	-64.90	0.66	-64.24	-13	-51.24

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 132322	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	156.98	31.53	-56.40	-0.84	-57.24	-13	-44.24
2	236.69	28.48	-66.82	3.83	-62.99	-13	-49.99
3	336.87	31.65	-66.23	3.67	-62.56	-13	-49.56
4	427.81	28.88	-70.33	2.78	-67.55	-13	-54.55
5	520.63	28.95	-66.12	2.86	-63.26	-13	-50.26
6	802.12	30.80	-67.67	1.52	-66.15	-13	-53.15

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	129.96	31.07	-65.08	-1.55	-66.63	-13	-53.63
2	257.13	31.33	-63.24	3.98	-59.26	-13	-46.26
3	305.75	30.38	-65.60	3.70	-61.90	-13	-48.90
4	412.63	31.32	-66.62	3.21	-63.41	-13	-50.41
5	671.62	30.08	-65.48	1.69	-63.79	-13	-50.79
6	742.29	31.86	-64.01	0.66	-63.35	-13	-50.35

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 132572	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	156.81	30.61	-57.32	-0.84	-58.16	-13	-45.16
2	236.35	28.55	-66.75	3.83	-62.92	-13	-49.92
3	336.64	31.26	-66.62	3.67	-62.95	-13	-49.95
4	427.75	27.74	-71.47	2.78	-68.69	-13	-55.69
5	520.15	29.75	-65.32	2.86	-62.46	-13	-49.46
6	802.35	29.79	-68.68	1.52	-67.16	-13	-54.16

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	130.68	31.00	-65.15	-1.55	-66.70	-13	-53.70
2	258.22	32.60	-61.97	3.98	-57.99	-13	-44.99
3	305.26	29.27	-66.71	3.70	-63.01	-13	-50.01
4	412.3	31.31	-66.63	3.21	-63.42	-13	-50.42
5	670.47	29.44	-66.12	1.69	-64.43	-13	-51.43
6	741.5	31.74	-64.13	0.66	-63.47	-13	-50.47

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 71: 5MHz

Mode	TX channel 133147	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	159.38	32.37	-55.56	-0.84	-56.40	-13	-43.40
2	240.74	28.77	-66.53	3.83	-62.70	-13	-49.70
3	336.71	29.87	-68.01	3.67	-64.34	-13	-51.34
4	432.9	27.68	-71.53	2.78	-68.75	-13	-55.75
5	527.19	32.58	-62.49	2.86	-59.63	-13	-46.63
6	802.94	32.46	-66.01	1.52	-64.49	-13	-51.49

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	133.01	30.75	-65.40	-1.55	-66.95	-13	-53.95
2	259.7	32.20	-62.37	3.98	-58.39	-13	-45.39
3	303.63	29.78	-66.20	3.70	-62.50	-13	-49.50
4	412.44	32.17	-65.77	3.21	-62.56	-13	-49.56
5	673.01	29.00	-66.56	1.69	-64.87	-13	-51.87
6	739.06	30.42	-65.45	0.66	-64.79	-13	-51.79

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 133297	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	158.65	33.19	-54.74	-0.84	-55.58	-13	-42.58
2	242.27	30.80	-64.50	3.83	-60.67	-13	-47.67
3	336.41	30.65	-67.23	3.67	-63.56	-13	-50.56
4	433.96	27.20	-72.01	2.78	-69.23	-13	-56.23
5	527.99	31.14	-63.93	2.86	-61.07	-13	-48.07
6	801.16	33.89	-64.58	1.52	-63.06	-13	-50.06

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	134.11	31.73	-64.42	-1.55	-65.97	-13	-52.97
2	259.3	31.19	-63.38	3.98	-59.40	-13	-46.40
3	303.68	32.15	-63.83	3.70	-60.13	-13	-47.13
4	409.81	34.72	-63.22	3.21	-60.01	-13	-47.01
5	671	28.95	-66.61	1.69	-64.92	-13	-51.92
6	737.85	30.24	-65.63	0.66	-64.97	-13	-51.97

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 133447	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	159.72	33.26	-54.67	-0.84	-55.51	-13	-42.51
2	241.74	30.92	-64.38	3.83	-60.55	-13	-47.55
3	336.2	30.03	-67.85	3.67	-64.18	-13	-51.18
4	434.08	26.75	-72.46	2.78	-69.68	-13	-56.68
5	526.28	31.54	-63.53	2.86	-60.67	-13	-47.67
6	800.97	32.52	-65.95	1.52	-64.43	-13	-51.43

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	133.62	28.88	-67.27	-1.55	-68.82	-13	-55.82
2	258.39	31.80	-62.77	3.98	-58.79	-13	-45.79
3	302.13	31.01	-64.97	3.70	-61.27	-13	-48.27
4	411.14	32.02	-65.92	3.21	-62.71	-13	-49.71
5	669.12	28.64	-66.92	1.69	-65.23	-13	-52.23
6	740.27	30.28	-65.59	0.66	-64.93	-13	-51.93

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 71: 10MHz

Mode	TX channel 133172	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	158.01	33.52	-54.41	-0.84	-55.25	-13	-42.25
2	241.34	30.97	-64.33	3.83	-60.50	-13	-47.50
3	337.7	29.13	-68.75	3.67	-65.08	-13	-52.08
4	433.33	26.52	-72.69	2.78	-69.91	-13	-56.91
5	526.93	32.61	-62.46	2.86	-59.60	-13	-46.60
6	800.95	33.87	-64.60	1.52	-63.08	-13	-50.08

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	134.57	29.35	-66.80	-1.55	-68.35	-13	-55.35
2	259.51	33.30	-61.27	3.98	-57.29	-13	-44.29
3	303.49	29.11	-66.87	3.70	-63.17	-13	-50.17
4	412.52	33.07	-64.87	3.21	-61.66	-13	-48.66
5	670.04	30.62	-64.94	1.69	-63.25	-13	-50.25
6	739.37	31.58	-64.29	0.66	-63.63	-13	-50.63

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 133297	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	157.99	33.76	-54.17	-0.84	-55.01	-13	-42.01
2	242.73	30.43	-64.87	3.83	-61.04	-13	-48.04
3	336.62	30.34	-67.54	3.67	-63.87	-13	-50.87
4	433.6	27.01	-72.20	2.78	-69.42	-13	-56.42
5	527.78	32.57	-62.50	2.86	-59.64	-13	-46.64
6	801.3	33.11	-65.36	1.52	-63.84	-13	-50.84

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	133.68	30.92	-65.23	-1.55	-66.78	-13	-53.78
2	260.47	33.23	-61.34	3.98	-57.36	-13	-44.36
3	304.3	31.65	-64.33	3.70	-60.63	-13	-47.63
4	412.98	30.76	-67.18	3.21	-63.97	-13	-50.97
5	671.21	28.28	-67.28	1.69	-65.59	-13	-52.59
6	740.54	31.57	-64.30	0.66	-63.64	-13	-50.64

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 133422	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	159.92	32.91	-55.02	-0.84	-55.86	-13	-42.86
2	242.09	30.19	-65.11	3.83	-61.28	-13	-48.28
3	337.14	29.85	-68.03	3.67	-64.36	-13	-51.36
4	432.78	27.43	-71.78	2.78	-69.00	-13	-56.00
5	527.14	31.21	-63.86	2.86	-61.00	-13	-48.00
6	802.76	33.60	-64.87	1.52	-63.35	-13	-50.35

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	132.56	30.67	-65.48	-1.55	-67.03	-13	-54.03
2	260.1	31.71	-62.86	3.98	-58.88	-13	-45.88
3	303.92	32.17	-63.81	3.70	-60.11	-13	-47.11
4	411.29	32.13	-65.81	3.21	-62.60	-13	-49.60
5	670.86	29.49	-66.07	1.69	-64.38	-13	-51.38
6	740.67	30.31	-65.56	0.66	-64.90	-13	-51.90

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 71: 15MHz

Mode	TX channel 133197	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	158.65	34.48	-53.45	-0.84	-54.29	-13	-41.29
2	241.32	30.45	-64.85	3.83	-61.02	-13	-48.02
3	337.75	29.06	-68.82	3.67	-65.15	-13	-52.15
4	432.54	26.57	-72.64	2.78	-69.86	-13	-56.86
5	528.01	32.47	-62.60	2.86	-59.74	-13	-46.74
6	801.89	33.87	-64.60	1.52	-63.08	-13	-50.08

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	134.07	31.57	-64.58	-1.55	-66.13	-13	-53.13
2	259.46	31.06	-63.51	3.98	-59.53	-13	-46.53
3	301.31	31.89	-64.09	3.70	-60.39	-13	-47.39
4	410.62	32.90	-65.04	3.21	-61.83	-13	-48.83
5	669.01	28.41	-67.15	1.69	-65.46	-13	-52.46
6	738.39	28.36	-67.51	0.66	-66.85	-13	-53.85

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 133297	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	158	34.30	-53.63	-0.84	-54.47	-13	-41.47
2	242.87	30.34	-64.96	3.83	-61.13	-13	-48.13
3	338.05	29.63	-68.25	3.67	-64.58	-13	-51.58
4	433.73	28.14	-71.07	2.78	-68.29	-13	-55.29
5	527.92	32.19	-62.88	2.86	-60.02	-13	-47.02
6	802.43	33.05	-65.42	1.52	-63.90	-13	-50.90

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	133.3	31.19	-64.96	-1.55	-66.51	-13	-53.51
2	260.66	34.07	-60.50	3.98	-56.52	-13	-43.52
3	302.79	32.46	-63.52	3.70	-59.82	-13	-46.82
4	413.15	32.84	-65.10	3.21	-61.89	-13	-48.89
5	672.76	30.62	-64.94	1.69	-63.25	-13	-50.25
6	739.85	28.53	-67.34	0.66	-66.68	-13	-53.68

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 133397	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	159.39	32.74	-55.19	-0.84	-56.03	-13	-43.03
2	241.44	31.15	-64.15	3.83	-60.32	-13	-47.32
3	336.9	29.43	-68.45	3.67	-64.78	-13	-51.78
4	433.39	27.56	-71.65	2.78	-68.87	-13	-55.87
5	526.47	31.12	-63.95	2.86	-61.09	-13	-48.09
6	802.19	32.74	-65.73	1.52	-64.21	-13	-51.21

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	132.09	31.56	-64.59	-1.55	-66.14	-13	-53.14
2	259.39	32.89	-61.68	3.98	-57.70	-13	-44.70
3	303.35	29.99	-65.99	3.70	-62.29	-13	-49.29
4	412.35	31.10	-66.84	3.21	-63.63	-13	-50.63
5	672.2	29.39	-66.17	1.69	-64.48	-13	-51.48
6	740.57	29.70	-66.17	0.66	-65.51	-13	-52.51

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 71: 20MHz

Mode	TX channel 133222	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	159.26	34.28	-53.65	-0.84	-54.49	-13	-41.49
2	242	30.35	-64.95	3.83	-61.12	-13	-48.12
3	337.63	29.20	-68.68	3.67	-65.01	-13	-52.01
4	432.91	27.86	-71.35	2.78	-68.57	-13	-55.57
5	526.36	30.85	-64.22	2.86	-61.36	-13	-48.36
6	802.33	33.87	-64.60	1.52	-63.08	-13	-50.08

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	132.62	30.28	-65.87	-1.55	-67.42	-13	-54.42
2	260.7	29.96	-64.61	3.98	-60.63	-13	-47.63
3	303.95	31.61	-64.37	3.70	-60.67	-13	-47.67
4	411.75	34.10	-63.84	3.21	-60.63	-13	-47.63
5	671.75	29.20	-66.36	1.69	-64.67	-13	-51.67
6	738.83	29.84	-66.03	0.66	-65.37	-13	-52.37

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 133297	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	158.63	33.96	-53.97	-0.84	-54.81	-13	-41.81
2	242.3	30.41	-64.89	3.83	-61.06	-13	-48.06
3	337.06	30.29	-67.59	3.67	-63.92	-13	-50.92
4	432.76	27.35	-71.86	2.78	-69.08	-13	-56.08
5	527.3	32.13	-62.94	2.86	-60.08	-13	-47.08
6	801.59	33.49	-64.98	1.52	-63.46	-13	-50.46

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	131.97	31.24	-64.91	-1.55	-66.46	-13	-53.46
2	260.04	32.50	-62.07	3.98	-58.09	-13	-45.09
3	303.68	31.15	-64.83	3.70	-61.13	-13	-48.13
4	411.87	33.33	-64.61	3.21	-61.40	-13	-48.40
5	673.7	29.67	-65.89	1.69	-64.20	-13	-51.20
6	737.19	28.06	-67.81	0.66	-67.15	-13	-54.15

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 133372	Frequency Range	Below 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	158.75	34.32	-53.61	-0.84	-54.45	-13	-41.45
2	242.2	30.43	-64.87	3.83	-61.04	-13	-48.04
3	336.57	29.25	-68.63	3.67	-64.96	-13	-51.96
4	433.83	27.38	-71.83	2.78	-69.05	-13	-56.05
5	526.54	31.86	-63.21	2.86	-60.35	-13	-47.35
6	802.14	32.39	-66.08	1.52	-64.56	-13	-51.56

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	132.93	30.84	-65.31	-1.55	-66.86	-13	-53.86
2	259.5	32.39	-62.18	3.98	-58.20	-13	-45.20
3	302.66	30.59	-65.39	3.70	-61.69	-13	-48.69
4	412.17	34.65	-63.29	3.21	-60.08	-13	-47.08
5	671.34	30.19	-65.37	1.69	-63.68	-13	-50.68
6	739.18	30.66	-65.21	0.66	-64.55	-13	-51.55

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

ABOVE 1GHz

WCDMA:

Mode	TX channel 1312	Frequency Range	Above 1000 MHz
------	-----------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3424.8	41.58	-61.34	7.90	-53.45	-13	-40.45
2	5137.2	36.86	-67.58	7.04	-60.54	-13	-47.54
3	6849.6	53.36	-48.48	5.10	-43.38	-13	-30.38
4	8562	49.44	-54.56	4.36	-50.20	-13	-37.20
5	10274.4	54.44	-47.94	3.79	-44.15	-13	-31.15
6	11986.8	46.06	-55.38	4.40	-50.98	-13	-37.98
7	13699.2	50.35	-49.52	2.82	-46.70	-13	-33.70
8	15411.6	51.72	-45.63	3.70	-41.93	-13	-28.93
9	17124	42.21	-55.14	3.70	-51.44	-13	-38.44

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3424.8	36.73	-66.19	7.90	-58.30	-13	-45.30
2	5137.2	38.37	-66.07	7.04	-59.03	-13	-46.03
3	6849.6	49.16	-52.68	5.10	-47.58	-13	-34.58
4	8562	43.01	-60.99	4.36	-56.63	-13	-43.63
5	10274.4	41.39	-60.99	3.79	-57.20	-13	-44.20
6	11986.8	44.92	-56.52	4.40	-52.12	-13	-39.12
7	13699.2	47	-52.87	2.82	-50.05	-13	-37.05
8	15411.6	45.31	-52.04	3.70	-48.34	-13	-35.34
9	17124	53.13	-44.22	3.70	-40.52	-13	-27.52

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 1413	Frequency Range	Above 1000 MHz
------	-----------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3465.2	42.05	-60.87	7.90	-52.98	-13	-39.98
2	5197.8	37.03	-67.41	7.04	-60.37	-13	-47.37
3	6930.4	52.57	-49.27	5.10	-44.17	-13	-31.17
4	8663	49.03	-54.97	4.36	-50.61	-13	-37.61
5	10395.6	55.44	-46.94	3.79	-43.15	-13	-30.15
6	12128.2	46.19	-55.25	4.40	-50.85	-13	-37.85
7	13860.8	49.36	-50.51	2.82	-47.69	-13	-34.69
8	15593.4	51.73	-45.62	3.70	-41.92	-13	-28.92
9	17326	42.96	-54.39	3.70	-50.69	-13	-37.69

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3465.2	32.49	-70.43	7.90	-62.54	-13	-49.54
2	5197.8	37.78	-66.66	7.04	-59.62	-13	-46.62
3	6930.4	48.61	-53.23	5.10	-48.13	-13	-35.13
4	8663	48.22	-55.78	4.36	-51.42	-13	-38.42
5	10395.6	45.27	-57.11	3.79	-53.32	-13	-40.32
6	12128.2	46.31	-55.13	4.40	-50.73	-13	-37.73
7	13860.8	44.96	-54.91	2.82	-52.09	-13	-39.09
8	15593.4	44.72	-52.63	3.70	-48.93	-13	-35.93
9	17326	54.29	-43.06	3.70	-39.36	-13	-26.36

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 1513	Frequency Range	Above 1000 MHz
------	-----------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3505.2	36.16	-66.76	7.90	-58.87	-13	-45.87
2	5257.8	38.83	-65.61	7.04	-58.57	-13	-45.57
3	7010.4	47.4	-54.44	5.10	-49.34	-13	-36.34
4	8763	48.23	-55.77	4.36	-51.41	-13	-38.41
5	10515.6	58.11	-44.27	3.79	-40.48	-13	-27.48
6	12268.2	46.49	-54.95	4.40	-50.55	-13	-37.55
7	14020.8	54.63	-45.24	2.82	-42.42	-13	-29.42
8	15773.4	48.76	-48.59	3.70	-44.89	-13	-31.89
9	17526	46.61	-50.74	3.70	-47.04	-13	-34.04

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3505.2	35.60	-67.32	7.90	-59.43	-13	-46.43
2	5257.8	39.81	-64.63	7.04	-57.59	-13	-44.59
3	7010.4	48.88	-52.96	5.10	-47.86	-13	-34.86
4	8763	45.32	-58.68	4.36	-54.32	-13	-41.32
5	10515.6	43.01	-59.37	3.79	-55.58	-13	-42.58
6	12268.2	43.49	-57.95	4.40	-53.55	-13	-40.55
7	14020.8	46.04	-53.83	2.82	-51.01	-13	-38.01
8	15773.4	44.9	-52.45	3.70	-48.75	-13	-35.75
9	17526	53.95	-43.40	3.70	-39.70	-13	-26.70

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 4: 1.4MHz

Mode	TX channel 19957	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3421.4	38.83	-64.24	7.87	-56.37	-13	-43.37
2	5132.1	45.61	-58.92	7.05	-51.86	-13	-38.86
3	6842.8	46.79	-55.15	5.03	-50.12	-13	-37.12
4	8553.5	47.82	-54.89	4.23	-50.66	-13	-37.66
5	10264.2	46.15	-55.52	2.24	-53.28	-13	-40.28
6	11974.9	47.98	-53.50	4.38	-49.12	-13	-36.12
7	13685.6	48.72	-51.13	1.93	-49.19	-13	-36.19
8	15396.3	51.27	-46.08	3.70	-42.38	-13	-29.38
9	17107	52.65	-46.37	3.77	-42.60	-13	-29.60

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3421.4	43.72	-59.35	7.87	-51.48	-13	-38.48
2	5132.1	41.23	-63.30	7.05	-56.24	-13	-43.24
3	6842.8	41.85	-60.09	5.03	-55.06	-13	-42.06
4	8553.5	45.13	-57.58	4.23	-53.35	-13	-40.35
5	10264.2	53.74	-47.93	2.24	-45.69	-13	-32.69
6	11974.9	49.05	-52.43	4.38	-48.05	-13	-35.05
7	13685.6	55.21	-44.64	1.93	-42.70	-13	-29.70
8	15396.3	58.01	-39.34	3.70	-35.64	-13	-22.64
9	17107	46.75	-52.27	3.77	-48.50	-13	-35.50

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 20175	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3465	36.60	-66.47	7.87	-58.60	-13	-45.60
2	5197.5	45.24	-60.25	7.33	-52.92	-13	-39.92
3	6930	47.93	-54.69	5.03	-49.66	-13	-36.66
4	8662.5	47.96	-55.79	4.34	-51.44	-13	-38.44
5	10395	45.78	-55.89	2.24	-53.65	-13	-40.65
6	12127.5	47.60	-54.57	4.26	-50.32	-13	-37.32
7	13860	49.22	-49.89	2.03	-47.86	-13	-34.86
8	15592.5	49.28	-48.07	3.70	-44.37	-13	-31.37
9	17325	51.21	-46.14	3.70	-42.44	-13	-29.44

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3465	43.77	-59.30	7.87	-51.43	-13	-38.43
2	5197.5	40.23	-65.26	7.33	-57.93	-13	-44.93
3	6930	42.41	-60.21	5.03	-55.18	-13	-42.18
4	8662.5	46.33	-57.42	4.34	-53.07	-13	-40.07
5	10395	54.39	-47.28	2.24	-45.04	-13	-32.04
6	12127.5	48.34	-53.83	4.26	-49.58	-13	-36.58
7	13860	55.60	-43.51	2.03	-41.48	-13	-28.48
8	15592.5	57.33	-40.02	3.70	-36.32	-13	-23.32
9	17325	45.86	-51.49	3.70	-47.79	-13	-34.79

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 20393	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3508.6	37.72	-65.51	7.84	-57.67	-13	-44.67
2	5262.9	45.06	-60.32	7.29	-53.03	-13	-40.03
3	7017.2	46.65	-55.97	4.43	-51.54	-13	-38.54
4	8771.5	47.68	-53.93	4.18	-49.76	-13	-36.76
5	10525.8	45.00	-56.64	2.43	-54.22	-13	-41.22
6	12280.1	48.30	-52.02	3.57	-48.45	-13	-35.45
7	14034.4	49.99	-47.36	3.70	-43.66	-13	-30.66
8	15788.7	50.53	-46.82	3.70	-43.12	-13	-30.12
9	17543	49.92	-47.43	3.70	-43.73	-13	-30.73

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3508.6	41.75	-61.48	7.84	-53.64	-13	-40.64
2	5262.9	42.43	-62.95	7.29	-55.66	-13	-42.66
3	7017.2	42.27	-60.35	4.43	-55.92	-13	-42.92
4	8771.5	45.34	-56.27	4.18	-52.10	-13	-39.10
5	10525.8	53.87	-47.77	2.43	-45.35	-13	-32.35
6	12280.1	48.57	-51.75	3.57	-48.18	-13	-35.18
7	14034.4	53.81	-43.54	3.70	-39.84	-13	-26.84
8	15788.7	57.30	-40.05	3.70	-36.35	-13	-23.35
9	17543	46.65	-50.70	3.70	-47.00	-13	-34.00

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 4: 3MHz

Mode	TX channel 19965	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3423	36.78	-66.14	7.90	-58.24	-13	-45.24
2	5134.5	46.44	-59.15	7.38	-51.78	-13	-38.78
3	6846	47.33	-54.51	5.10	-49.40	-13	-36.40
4	8557.5	48.85	-55.16	4.36	-50.80	-13	-37.80
5	10269	45.35	-56.35	2.07	-54.28	-13	-41.28
6	11980.5	47.02	-55.38	4.22	-51.16	-13	-38.16
7	13692	49.75	-49.61	1.78	-47.84	-13	-34.84
8	15403.5	50.05	-47.30	3.70	-43.60	-13	-30.60
9	17115	51.23	-46.12	3.70	-42.42	-13	-29.42

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3423	43.27	-59.65	7.90	-51.75	-13	-38.75
2	5134.5	41.48	-64.11	7.38	-56.74	-13	-43.74
3	6846	41.84	-60.00	5.10	-54.89	-13	-41.89
4	8557.5	44.92	-59.09	4.36	-54.73	-13	-41.73
5	10269	54.07	-47.63	2.07	-45.56	-13	-32.56
6	11980.5	48.83	-53.57	4.22	-49.35	-13	-36.35
7	13692	55.04	-44.32	1.78	-42.55	-13	-29.55
8	15403.5	57.24	-40.11	3.70	-36.41	-13	-23.41
9	17115	45.71	-51.64	3.70	-47.94	-13	-34.94

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 20175	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3465	36.56	-66.51	7.87	-58.64	-13	-45.64
2	5197.5	44.42	-61.07	7.33	-53.74	-13	-40.74
3	6930	46.64	-55.98	5.03	-50.95	-13	-37.95
4	8662.5	49.21	-54.54	4.34	-50.19	-13	-37.19
5	10395	45.15	-56.52	2.24	-54.28	-13	-41.28
6	12127.5	47.03	-55.14	4.26	-50.89	-13	-37.89
7	13860	50.24	-48.87	2.03	-46.84	-13	-33.84
8	15592.5	50.51	-46.84	3.70	-43.14	-13	-30.14
9	17325	51.51	-45.84	3.70	-42.14	-13	-29.14

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3465	42.68	-60.39	7.87	-52.52	-13	-39.52
2	5197.5	41.10	-64.39	7.33	-57.06	-13	-44.06
3	6930	42.78	-59.84	5.03	-54.81	-13	-41.81
4	8662.5	44.94	-58.81	4.34	-54.46	-13	-41.46
5	10395	54.41	-47.26	2.24	-45.02	-13	-32.02
6	12127.5	48.50	-53.67	4.26	-49.42	-13	-36.42
7	13860	54.14	-44.97	2.03	-42.94	-13	-29.94
8	15592.5	57.00	-40.35	3.70	-36.65	-13	-23.65
9	17325	45.25	-52.10	3.70	-48.40	-13	-35.40

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 20385	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3507	37.89	-65.34	7.84	-57.49	-13	-44.49
2	5260.5	45.25	-60.13	7.29	-52.84	-13	-39.84
3	7014	45.97	-56.65	4.43	-52.22	-13	-39.22
4	8767.5	49.37	-52.24	4.18	-48.07	-13	-35.07
5	10521	46.24	-55.41	2.42	-52.99	-13	-39.99
6	12274.5	47.64	-52.68	3.57	-49.11	-13	-36.11
7	14028	49.55	-47.80	3.70	-44.10	-13	-31.10
8	15781.5	50.45	-46.90	3.70	-43.20	-13	-30.20
9	17535	50.78	-46.57	3.70	-42.87	-13	-29.87

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3507	45.03	-58.20	7.84	-50.35	-13	-37.35
2	5260.5	40.33	-65.05	7.29	-57.76	-13	-44.76
3	7014	42.75	-59.87	4.43	-55.44	-13	-42.44
4	8767.5	45.87	-55.74	4.18	-51.57	-13	-38.57
5	10521	54.46	-47.19	2.42	-44.77	-13	-31.77
6	12274.5	49.84	-50.48	3.57	-46.91	-13	-33.91
7	14028	55.68	-41.67	3.70	-37.97	-13	-24.97
8	15781.5	58.34	-39.01	3.70	-35.31	-13	-22.31
9	17535	44.45	-52.90	3.70	-49.20	-13	-36.20

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 4: 5MHz

Mode	TX channel 19975	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3425	38.47	-64.46	7.90	-56.56	-13	-43.56
2	5137.5	47.21	-58.38	7.37	-51.01	-13	-38.01
3	6850	47.26	-54.58	5.10	-49.48	-13	-36.48
4	8562.5	46.36	-57.64	4.36	-53.28	-13	-40.28
5	10275	45.63	-56.07	2.08	-53.99	-13	-40.99
6	11987.5	45.49	-56.90	4.23	-52.67	-13	-39.67
7	13700	47.80	-51.55	1.79	-49.76	-13	-36.76
8	15412.5	50.68	-46.67	3.70	-42.97	-13	-29.97
9	17125	51.68	-45.67	3.70	-41.97	-13	-28.97

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3425	44.34	-58.59	7.90	-50.69	-13	-37.69
2	5137.5	42.63	-62.96	7.37	-55.59	-13	-42.59
3	6850	41.09	-60.75	5.10	-55.65	-13	-42.65
4	8562.5	45.07	-58.93	4.36	-54.57	-13	-41.57
5	10275	54.56	-47.14	2.08	-45.06	-13	-32.06
6	11987.5	47.63	-54.76	4.23	-50.53	-13	-37.53
7	13700	55.72	-43.63	1.79	-41.84	-13	-28.84
8	15412.5	57.05	-40.30	3.70	-36.60	-13	-23.60
9	17125	46.28	-51.07	3.70	-47.37	-13	-34.37

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 20175	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3465	37.09	-65.98	7.87	-58.11	-13	-45.11
2	5197.5	45.13	-60.36	7.33	-53.03	-13	-40.03
3	6930	47.12	-55.50	5.03	-50.47	-13	-37.47
4	8662.5	46.35	-57.40	4.34	-53.05	-13	-40.05
5	10395	46.08	-55.59	2.24	-53.35	-13	-40.35
6	12127.5	47.77	-54.40	4.26	-50.15	-13	-37.15
7	13860	50.15	-48.96	2.03	-46.93	-13	-33.93
8	15592.5	48.32	-49.03	3.70	-45.33	-13	-32.33
9	17325	51.04	-46.31	3.70	-42.61	-13	-29.61

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3465	43.23	-59.84	7.87	-51.97	-13	-38.97
2	5197.5	40.00	-65.49	7.33	-58.16	-13	-45.16
3	6930	40.51	-62.11	5.03	-57.08	-13	-44.08
4	8662.5	44.27	-59.48	4.34	-55.13	-13	-42.13
5	10395	54.54	-47.13	2.24	-44.89	-13	-31.89
6	12127.5	48.34	-53.83	4.26	-49.58	-13	-36.58
7	13860	54.10	-45.01	2.03	-42.98	-13	-29.98
8	15592.5	57.30	-40.05	3.70	-36.35	-13	-23.35
9	17325	47.18	-50.17	3.70	-46.47	-13	-33.47

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 20375	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3505	38.46	-64.76	7.84	-56.91	-13	-43.91
2	5257.5	46.75	-58.64	7.29	-51.35	-13	-38.35
3	7010	45.64	-56.98	4.43	-52.55	-13	-39.55
4	8762.5	47.46	-54.15	4.18	-49.98	-13	-36.98
5	10515	45.14	-56.51	2.41	-54.09	-13	-41.09
6	12267.5	46.05	-54.27	3.57	-50.70	-13	-37.70
7	14020	47.90	-49.45	3.70	-45.75	-13	-32.75
8	15772.5	50.45	-46.90	3.70	-43.20	-13	-30.20
9	17525	50.70	-46.65	3.70	-42.95	-13	-29.95

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3505	42.99	-60.23	7.84	-52.38	-13	-39.38
2	5257.5	42.44	-62.95	7.29	-55.66	-13	-42.66
3	7010	43.04	-59.58	4.43	-55.15	-13	-42.15
4	8762.5	44.55	-57.06	4.18	-52.89	-13	-39.89
5	10515	54.15	-47.50	2.41	-45.08	-13	-32.08
6	12267.5	48.71	-51.61	3.57	-48.04	-13	-35.04
7	14020	53.97	-43.38	3.70	-39.68	-13	-26.68
8	15772.5	56.60	-40.75	3.70	-37.05	-13	-24.05
9	17525	45.59	-51.76	3.70	-48.06	-13	-35.06

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 4: 10MHz

Mode	TX channel 20000	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3430	38.34	-64.60	7.89	-56.71	-13	-43.71
2	5145	46.50	-59.08	7.37	-51.71	-13	-38.71
3	6860	46.67	-55.18	5.09	-50.09	-13	-37.09
4	8575	47.04	-56.93	4.36	-52.57	-13	-39.57
5	10290	43.93	-57.76	2.10	-55.66	-13	-42.66
6	12005	47.41	-54.95	4.23	-50.72	-13	-37.72
7	13720	49.54	-49.78	1.82	-47.96	-13	-34.96
8	15435	50.02	-47.33	3.70	-43.63	-13	-30.63
9	17150	49.34	-48.01	3.70	-44.31	-13	-31.31

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3430	44.98	-57.96	7.89	-50.07	-13	-37.07
2	5145	40.39	-65.19	7.37	-57.82	-13	-44.82
3	6860	43.32	-58.53	5.09	-53.44	-13	-40.44
4	8575	43.80	-60.17	4.36	-55.81	-13	-42.81
5	10290	52.88	-48.81	2.10	-46.71	-13	-33.71
6	12005	47.19	-55.17	4.23	-50.94	-13	-37.94
7	13720	53.11	-46.21	1.82	-44.39	-13	-31.39
8	15435	57.43	-39.92	3.70	-36.22	-13	-23.22
9	17150	45.41	-51.94	3.70	-48.24	-13	-35.24

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 20175	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3465	37.42	-65.65	7.87	-57.78	-13	-44.78
2	5197.5	45.01	-60.48	7.33	-53.15	-13	-40.15
3	6930	46.55	-56.07	5.03	-51.04	-13	-38.04
4	8662.5	46.84	-56.91	4.34	-52.56	-13	-39.56
5	10395	45.87	-55.80	2.24	-53.56	-13	-40.56
6	12127.5	46.47	-55.70	4.26	-51.45	-13	-38.45
7	13860	49.02	-50.09	2.03	-48.06	-13	-35.06
8	15592.5	49.21	-48.14	3.70	-44.44	-13	-31.44
9	17325	51.36	-45.99	3.70	-42.29	-13	-29.29

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3465	43.74	-59.33	7.87	-51.46	-13	-38.46
2	5197.5	42.87	-62.62	7.33	-55.29	-13	-42.29
3	6930	42.66	-59.96	5.03	-54.93	-13	-41.93
4	8662.5	44.44	-59.31	4.34	-54.96	-13	-41.96
5	10395	56.21	-45.46	2.24	-43.22	-13	-30.22
6	12127.5	48.31	-53.86	4.26	-49.61	-13	-36.61
7	13860	54.23	-44.88	2.03	-42.85	-13	-29.85
8	15592.5	56.96	-40.39	3.70	-36.69	-13	-23.69
9	17325	47.26	-50.09	3.70	-46.39	-13	-33.39

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 20350	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3500	36.10	-67.10	7.85	-59.25	-13	-46.25
2	5250	45.71	-59.69	7.29	-52.40	-13	-39.40
3	7000	47.32	-55.30	4.43	-50.87	-13	-37.87
4	8750	47.32	-54.29	4.18	-50.12	-13	-37.12
5	10500	44.63	-57.02	2.39	-54.63	-13	-41.63
6	12250	47.10	-53.22	3.57	-49.65	-13	-36.65
7	14000	49.23	-48.12	3.70	-44.42	-13	-31.42
8	15750	51.56	-45.79	3.70	-42.09	-13	-29.09
9	17500	50.31	-47.04	3.70	-43.34	-13	-30.34

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3500	43.42	-59.78	7.85	-51.93	-13	-38.93
2	5250	39.90	-65.50	7.29	-58.21	-13	-45.21
3	7000	42.07	-60.55	4.43	-56.12	-13	-43.12
4	8750	44.57	-57.04	4.18	-52.87	-13	-39.87
5	10500	54.81	-46.84	2.39	-44.45	-13	-31.45
6	12250	47.68	-52.64	3.57	-49.07	-13	-36.07
7	14000	54.08	-43.27	3.70	-39.57	-13	-26.57
8	15750	54.85	-42.50	3.70	-38.80	-13	-25.80
9	17500	47.71	-49.64	3.70	-45.94	-13	-32.94

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 4: 15MHz

Mode	TX channel 20025	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3435	39.19	-63.77	7.89	-55.88	-13	-42.88
2	5152.5	44.68	-60.88	7.36	-53.52	-13	-40.52
3	6870	47.84	-54.02	5.08	-48.94	-13	-35.94
4	8587.5	46.61	-57.33	4.36	-52.97	-13	-39.97
5	10305	46.39	-55.30	2.12	-53.18	-13	-40.18
6	12022.5	46.81	-55.53	4.23	-51.29	-13	-38.29
7	13740	49.67	-49.62	1.85	-47.77	-13	-34.77
8	15457.5	50.76	-46.59	3.70	-42.89	-13	-29.89
9	17175	51.55	-45.80	3.70	-42.10	-13	-29.10

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3435	44.36	-58.60	7.89	-50.71	-13	-37.71
2	5152.5	41.47	-64.09	7.36	-56.73	-13	-43.73
3	6870	42.22	-59.64	5.08	-54.56	-13	-41.56
4	8587.5	43.93	-60.01	4.36	-55.65	-13	-42.65
5	10305	54.15	-47.54	2.12	-45.42	-13	-32.42
6	12022.5	46.53	-55.81	4.23	-51.57	-13	-38.57
7	13740	54.40	-44.89	1.85	-43.04	-13	-30.04
8	15457.5	55.44	-41.91	3.70	-38.21	-13	-25.21
9	17175	45.81	-51.54	3.70	-47.84	-13	-34.84

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 20175	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3465	38.56	-64.51	7.87	-56.64	-13	-43.64
2	5197.5	46.02	-59.47	7.33	-52.14	-13	-39.14
3	6930	47.51	-55.11	5.03	-50.08	-13	-37.08
4	8662.5	48.16	-55.59	4.34	-51.24	-13	-38.24
5	10395	45.13	-56.54	2.24	-54.30	-13	-41.30
6	12127.5	46.37	-55.80	4.26	-51.55	-13	-38.55
7	13860	49.80	-49.31	2.03	-47.28	-13	-34.28
8	15592.5	50.63	-46.72	3.70	-43.02	-13	-30.02
9	17325	49.58	-47.77	3.70	-44.07	-13	-31.07

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3465	42.27	-60.80	7.87	-52.93	-13	-39.93
2	5197.5	41.47	-64.02	7.33	-56.69	-13	-43.69
3	6930	42.46	-60.16	5.03	-55.13	-13	-42.13
4	8662.5	43.22	-60.53	4.34	-56.18	-13	-43.18
5	10395	53.06	-48.61	2.24	-46.37	-13	-33.37
6	12127.5	47.40	-54.77	4.26	-50.52	-13	-37.52
7	13860	52.96	-46.15	2.03	-44.12	-13	-31.12
8	15592.5	55.66	-41.69	3.70	-37.99	-13	-24.99
9	17325	46.21	-51.14	3.70	-47.44	-13	-34.44

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 20325	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3495	36.36	-66.82	7.85	-58.97	-13	-45.97
2	5242.5	46.71	-58.70	7.30	-51.40	-13	-38.40
3	6990	45.53	-57.09	4.43	-52.66	-13	-39.66
4	8737.5	47.98	-53.63	4.18	-49.46	-13	-36.46
5	10485	45.43	-56.22	2.37	-53.85	-13	-40.85
6	12232.5	46.42	-53.90	3.57	-50.33	-13	-37.33
7	13980	48.37	-48.98	3.70	-45.28	-13	-32.28
8	15727.5	49.22	-48.13	3.70	-44.43	-13	-31.43
9	17475	51.42	-45.93	3.70	-42.23	-13	-29.23

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3495	43.18	-60.00	7.85	-52.15	-13	-39.15
2	5242.5	41.31	-64.10	7.30	-56.80	-13	-43.80
3	6990	41.71	-60.91	4.43	-56.48	-13	-43.48
4	8737.5	44.83	-56.78	4.18	-52.61	-13	-39.61
5	10485	54.25	-47.40	2.37	-45.03	-13	-32.03
6	12232.5	47.76	-52.56	3.57	-48.99	-13	-35.99
7	13980	53.45	-43.90	3.70	-40.20	-13	-27.20
8	15727.5	55.43	-41.92	3.70	-38.22	-13	-25.22
9	17475	44.85	-52.50	3.70	-48.80	-13	-35.80

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 4: 20MHz

Mode	TX channel 20050	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3440	39.18	-63.80	7.89	-55.91	-13	-42.91
2	5160	45.69	-59.86	7.36	-52.50	-13	-39.50
3	6880	48.32	-53.56	5.07	-48.48	-13	-35.48
4	8600	46.17	-57.74	4.35	-53.38	-13	-40.38
5	10320	44.21	-57.48	2.14	-55.34	-13	-42.34
6	12040	48.34	-53.97	4.24	-49.73	-13	-36.73
7	13760	49.87	-49.39	1.88	-47.51	-13	-34.51
8	15480	50.98	-46.37	3.70	-42.67	-13	-29.67
9	17200	50.83	-46.52	3.70	-42.82	-13	-29.82

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3440	43.67	-59.31	7.89	-51.42	-13	-38.42
2	5160	40.99	-64.56	7.36	-57.20	-13	-44.20
3	6880	40.67	-61.21	5.07	-56.13	-13	-43.13
4	8600	44.15	-59.76	4.35	-55.40	-13	-42.40
5	10320	55.46	-46.23	2.14	-44.09	-13	-31.09
6	12040	47.59	-54.72	4.24	-50.48	-13	-37.48
7	13760	53.38	-45.88	1.88	-44.00	-13	-31.00
8	15480	55.27	-42.08	3.70	-38.38	-13	-25.38
9	17200	46.45	-50.90	3.70	-47.20	-13	-34.20

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 20175	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3465	35.82	-67.25	7.87	-59.38	-13	-46.38
2	5197.5	44.28	-61.21	7.33	-53.88	-13	-40.88
3	6930	46.64	-55.98	5.03	-50.95	-13	-37.95
4	8662.5	49.24	-54.51	4.34	-50.16	-13	-37.16
5	10395	45.82	-55.85	2.24	-53.61	-13	-40.61
6	12127.5	47.64	-54.53	4.26	-50.28	-13	-37.28
7	13860	48.80	-50.31	2.03	-48.28	-13	-35.28
8	15592.5	51.64	-45.71	3.70	-42.01	-13	-29.01
9	17325	51.16	-46.19	3.70	-42.49	-13	-29.49

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3465	42.89	-60.18	7.87	-52.31	-13	-39.31
2	5197.5	39.68	-65.81	7.33	-58.48	-13	-45.48
3	6930	42.90	-59.72	5.03	-54.69	-13	-41.69
4	8662.5	43.70	-60.05	4.34	-55.70	-13	-42.70
5	10395	53.83	-47.84	2.24	-45.60	-13	-32.60
6	12127.5	47.38	-54.79	4.26	-50.54	-13	-37.54
7	13860	52.94	-46.17	2.03	-44.14	-13	-31.14
8	15592.5	56.75	-40.60	3.70	-36.90	-13	-23.90
9	17325	46.48	-50.87	3.70	-47.17	-13	-34.17

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 20300	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3540	37.58	-65.77	7.82	-57.94	-13	-44.94
2	5310	46.37	-58.93	7.25	-51.68	-13	-38.68
3	7080	47.79	-54.83	4.43	-50.40	-13	-37.40
4	8850	47.78	-53.83	4.18	-49.66	-13	-36.66
5	10620	44.43	-57.20	2.56	-54.64	-13	-41.64
6	12390	45.84	-54.48	3.57	-50.91	-13	-37.91
7	14160	49.35	-48.00	3.70	-44.30	-13	-31.30
8	15930	50.34	-47.01	3.70	-43.31	-13	-30.31
9	17700	51.55	-45.80	3.70	-42.10	-13	-29.10

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3540	44.85	-58.50	7.82	-50.67	-13	-37.67
2	5310	42.73	-62.57	7.25	-55.32	-13	-42.32
3	7080	43.09	-59.53	4.43	-55.10	-13	-42.10
4	8850	45.22	-56.39	4.18	-52.22	-13	-39.22
5	10620	53.82	-47.81	2.56	-45.25	-13	-32.25
6	12390	47.46	-52.86	3.57	-49.29	-13	-36.29
7	14160	53.71	-43.64	3.70	-39.94	-13	-26.94
8	15930	55.44	-41.91	3.70	-38.21	-13	-25.21
9	17700	46.76	-50.59	3.70	-46.89	-13	-33.89

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 7: 5MHz

Mode	TX channel 20775	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5005	43.30	-60.94	7.01	-53.93	-25	-28.93
2	7507.5	46.56	-56.06	4.54	-51.52	-25	-26.52
3	10010	47.27	-54.30	4.03	-50.27	-25	-25.27
4	12512.5	43.39	-58.19	4.34	-53.85	-25	-28.85
5	15015	44.38	-52.97	3.70	-49.27	-25	-24.27
6	17517.5	42.64	-54.71	3.70	-51.01	-25	-26.01

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5005	44.02	-60.22	7.01	-53.21	-25	-28.21
2	7507.5	44.75	-57.87	4.54	-53.33	-25	-28.33
3	10010	43.09	-58.48	4.03	-54.45	-25	-29.45
4	12512.5	43.10	-58.48	4.34	-54.14	-25	-29.14
5	15015	45.77	-51.58	3.70	-47.88	-25	-22.88
6	17517.5	42.16	-55.19	3.70	-51.49	-25	-26.49

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 21100	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5070	42.80	-61.44	7.01	-54.43	-25	-29.43
2	7605	46.81	-55.81	4.54	-51.27	-25	-26.27
3	10140	47.38	-54.19	4.03	-50.16	-25	-25.16
4	12675	43.01	-58.57	4.34	-54.23	-25	-29.23
5	15210	44.89	-52.46	3.70	-48.76	-25	-23.76
6	17745	43.11	-54.24	3.70	-50.54	-25	-25.54

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5070	42.10	-62.14	7.01	-55.13	-25	-30.13
2	7605	43.27	-59.35	4.54	-54.81	-25	-29.81
3	10140	43.19	-58.38	4.03	-54.35	-25	-29.35
4	12675	41.85	-59.73	4.34	-55.39	-25	-30.39
5	15210	45.09	-52.26	3.70	-48.56	-25	-23.56
6	17745	40.19	-57.16	3.70	-53.46	-25	-28.46

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 21425	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5135	42.89	-61.35	7.01	-54.34	-25	-29.34
2	7702.5	45.61	-57.01	4.54	-52.47	-25	-27.47
3	10270	46.87	-54.70	4.03	-50.67	-25	-25.67
4	12837.5	43.51	-58.07	4.34	-53.73	-25	-28.73
5	15405	43.63	-53.72	3.70	-50.02	-25	-25.02
6	17972.5	42.05	-55.30	3.70	-51.60	-25	-26.60

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5135	43.36	-60.88	7.01	-53.87	-25	-28.87
2	7702.5	44.07	-58.55	4.54	-54.01	-25	-29.01
3	10270	42.76	-58.81	4.03	-54.78	-25	-29.78
4	12837.5	43.31	-58.27	4.34	-53.93	-25	-28.93
5	15405	44.67	-52.68	3.70	-48.98	-25	-23.98
6	17972.5	41.54	-55.81	3.70	-52.11	-25	-27.11

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 7: 10MHz

Mode	TX channel 20800	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5010	42.94	-61.30	7.01	-54.29	-25	-29.29
2	7515	47.16	-55.46	4.54	-50.92	-25	-25.92
3	10020	46.57	-55.00	4.03	-50.97	-25	-25.97
4	12525	42.82	-58.76	4.34	-54.42	-25	-29.42
5	15030	43.62	-53.73	3.70	-50.03	-25	-25.03
6	17535	43.01	-54.34	3.70	-50.64	-25	-25.64

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5010	42.61	-61.63	7.01	-54.62	-25	-29.62
2	7515	43.75	-58.87	4.54	-54.33	-25	-29.33
3	10020	43.87	-57.70	4.03	-53.67	-25	-28.67
4	12525	42.04	-59.54	4.34	-55.20	-25	-30.20
5	15030	44.69	-52.66	3.70	-48.96	-25	-23.96
6	17535	41.11	-56.24	3.70	-52.54	-25	-27.54

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 21100	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5070	42.74	-61.50	7.01	-54.49	-25	-29.49
2	7605	47.48	-55.14	4.54	-50.60	-25	-25.60
3	10140	47.33	-54.24	4.03	-50.21	-25	-25.21
4	12675	44.18	-57.40	4.34	-53.06	-25	-28.06
5	15210	43.92	-53.43	3.70	-49.73	-25	-24.73
6	17745	41.91	-55.44	3.70	-51.74	-25	-26.74

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5070	42.14	-62.10	7.01	-55.09	-25	-30.09
2	7605	44.96	-57.66	4.54	-53.12	-25	-28.12
3	10140	43.74	-57.83	4.03	-53.80	-25	-28.80
4	12675	43.02	-58.56	4.34	-54.22	-25	-29.22
5	15210	45.50	-51.85	3.70	-48.15	-25	-23.15
6	17745	42.14	-55.21	3.70	-51.51	-25	-26.51

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 21400	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5130	42.79	-61.45	7.01	-54.44	-25	-29.44
2	7695	46.75	-55.87	4.54	-51.33	-25	-26.33
3	10260	46.95	-54.62	4.03	-50.59	-25	-25.59
4	12825	43.48	-58.10	4.34	-53.76	-25	-28.76
5	15390	43.59	-53.76	3.70	-50.06	-25	-25.06
6	17955	42.59	-54.76	3.70	-51.06	-25	-26.06

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5130	42.68	-61.56	7.01	-54.55	-25	-29.55
2	7695	43.50	-59.12	4.54	-54.58	-25	-29.58
3	10260	42.60	-58.97	4.03	-54.94	-25	-29.94
4	12825	42.87	-58.71	4.34	-54.37	-25	-29.37
5	15390	44.30	-53.05	3.70	-49.35	-25	-24.35
6	17955	40.54	-56.81	3.70	-53.11	-25	-28.11

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 7: 15MHz

Mode	TX channel 20825	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5015	43.42	-60.82	7.01	-53.81	-25	-28.81
2	7522.5	46.25	-56.37	4.54	-51.83	-25	-26.83
3	10030	47.30	-54.27	4.03	-50.24	-25	-25.24
4	12537.5	42.89	-58.69	4.34	-54.35	-25	-29.35
5	15045	44.86	-52.49	3.70	-48.79	-25	-23.79
6	17552.5	43.30	-54.05	3.70	-50.35	-25	-25.35

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5015	42.38	-61.86	7.01	-54.85	-25	-29.85
2	7522.5	43.82	-58.80	4.54	-54.26	-25	-29.26
3	10030	43.24	-58.33	4.03	-54.30	-25	-29.30
4	12537.5	41.59	-59.99	4.34	-55.65	-25	-30.65
5	15045	45.58	-51.77	3.70	-48.07	-25	-23.07
6	17552.5	41.16	-56.19	3.70	-52.49	-25	-27.49

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 21100	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5070	42.70	-61.54	7.01	-54.53	-25	-29.53
2	7605	46.07	-56.55	4.54	-52.01	-25	-27.01
3	10140	47.38	-54.19	4.03	-50.16	-25	-25.16
4	12675	42.43	-59.15	4.34	-54.81	-25	-29.81
5	15210	44.22	-53.13	3.70	-49.43	-25	-24.43
6	17745	43.27	-54.08	3.70	-50.38	-25	-25.38

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5070	43.81	-60.43	7.01	-53.42	-25	-28.42
2	7605	43.37	-59.25	4.54	-54.71	-25	-29.71
3	10140	43.40	-58.17	4.03	-54.14	-25	-29.14
4	12675	41.39	-60.19	4.34	-55.85	-25	-30.85
5	15210	44.73	-52.62	3.70	-48.92	-25	-23.92
6	17745	40.48	-56.87	3.70	-53.17	-25	-28.17

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 21375	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5125	43.29	-60.95	7.01	-53.94	-25	-28.94
2	7687.5	46.61	-56.01	4.54	-51.47	-25	-26.47
3	10250	46.93	-54.64	4.03	-50.61	-25	-25.61
4	12812.5	42.84	-58.74	4.34	-54.40	-25	-29.40
5	15375	44.92	-52.43	3.70	-48.73	-25	-23.73
6	17937.5	42.96	-54.39	3.70	-50.69	-25	-25.69

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5125	43.43	-60.81	7.01	-53.80	-25	-28.80
2	7687.5	44.89	-57.73	4.54	-53.19	-25	-28.19
3	10250	43.48	-58.09	4.03	-54.06	-25	-29.06
4	12812.5	42.41	-59.17	4.34	-54.83	-25	-29.83
5	15375	44.66	-52.69	3.70	-48.99	-25	-23.99
6	17937.5	42.13	-55.22	3.70	-51.52	-25	-26.52

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 7: 20MHz

Mode	TX channel 20850	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5020	43.29	-60.95	7.01	-53.94	-25	-28.94
2	7530	45.94	-56.68	4.54	-52.14	-25	-27.14
3	10040	47.34	-54.23	4.03	-50.20	-25	-25.20
4	12550	44.07	-57.51	4.34	-53.17	-25	-28.17
5	15060	45.31	-52.04	3.70	-48.34	-25	-23.34
6	17570	41.91	-55.44	3.70	-51.74	-25	-26.74

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5020	43.85	-60.39	7.01	-53.38	-25	-28.38
2	7530	44.36	-58.26	4.54	-53.72	-25	-28.72
3	10040	43.75	-57.82	4.03	-53.79	-25	-28.79
4	12550	42.58	-59.00	4.34	-54.66	-25	-29.66
5	15060	44.41	-52.94	3.70	-49.24	-25	-24.24
6	17570	41.49	-55.86	3.70	-52.16	-25	-27.16

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 21100	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5070	42.99	-61.25	7.01	-54.24	-25	-29.24
2	7605	46.58	-56.04	4.54	-51.50	-25	-26.50
3	10140	47.33	-54.24	4.03	-50.21	-25	-25.21
4	12675	44.03	-57.55	4.34	-53.21	-25	-28.21
5	15210	43.52	-53.83	3.70	-50.13	-25	-25.13
6	17745	41.65	-55.70	3.70	-52.00	-25	-27.00

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5070	43.40	-60.84	7.01	-53.83	-25	-28.83
2	7605	45.00	-57.62	4.54	-53.08	-25	-28.08
3	10140	43.88	-57.69	4.03	-53.66	-25	-28.66
4	12675	42.35	-59.23	4.34	-54.89	-25	-29.89
5	15210	45.70	-51.65	3.70	-47.95	-25	-22.95
6	17745	42.05	-55.30	3.70	-51.60	-25	-26.60

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 21350	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5120	42.47	-61.77	7.01	-54.76	-25	-29.76
2	7680	46.53	-56.09	4.54	-51.55	-25	-26.55
3	10240	47.54	-54.03	4.03	-50.00	-25	-25.00
4	12800	42.83	-58.75	4.34	-54.41	-25	-29.41
5	15360	44.57	-52.78	3.70	-49.08	-25	-24.08
6	17920	42.01	-55.34	3.70	-51.64	-25	-26.64

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5120	42.79	-61.45	7.01	-54.44	-25	-29.44
2	7680	44.21	-58.41	4.54	-53.87	-25	-28.87
3	10240	42.52	-59.05	4.03	-55.02	-25	-30.02
4	12800	42.68	-58.90	4.34	-54.56	-25	-29.56
5	15360	45.13	-52.22	3.70	-48.52	-25	-23.52
6	17920	40.96	-56.39	3.70	-52.69	-25	-27.69

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE CA 7C (15MHz+20MHz)

Mode	TX channel 21206+21350	Frequency Range	Above 1000 MHz
------	------------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5120	36.95	-67.44	7.03	-60.40	-25	-35.40
2	7680	46.98	-55.64	4.41	-51.23	-25	-26.23
3	10240	52.64	-49.15	3.84	-45.31	-25	-20.31
4	12800	54.13	-47.07	4.39	-42.68	-25	-17.68
5	15360	52.88	-44.52	3.72	-40.81	-25	-15.81

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5120	39.75	-64.64	7.03	-57.60	-25	-32.60
2	7680	47.83	-54.79	4.41	-50.38	-25	-25.38
3	10240	45.76	-56.03	3.84	-52.19	-25	-27.19
4	12800	49.10	-52.10	4.39	-47.71	-25	-22.71
5	15360	47.36	-50.04	3.72	-46.33	-25	-21.33

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 12: 1.4MHz

Mode	TX channel 23017	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1399.4	36.74	-67.25	5.81	-61.44	-13	-48.44
2	2099.1	41.92	-58.57	6.85	-51.72	-13	-38.72
3	2798.8	39.26	-61.66	6.94	-54.72	-13	-41.72
4	3498.5	39.38	-63.81	7.85	-55.97	-13	-42.97
5	4198.2	39.94	-64.89	7.44	-57.45	-13	-44.45
6	4897.9	40.38	-63.70	6.99	-56.71	-13	-43.71
7	5597.6	42.61	-62.21	7.05	-55.15	-13	-42.15
8	6297.3	47.62	-56.52	6.27	-50.25	-13	-37.25
9	6997	50.07	-51.95	4.97	-46.97	-13	-33.97

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1399.4	31.81	-72.18	5.81	-66.37	-13	-53.37
2	2099.1	39.33	-61.16	6.85	-54.31	-13	-41.31
3	2798.8	38.52	-62.40	6.94	-55.46	-13	-42.46
4	3498.5	38.72	-64.47	7.85	-56.63	-13	-43.63
5	4198.2	42.19	-62.64	7.44	-55.20	-13	-42.20
6	4897.9	44.03	-60.05	6.99	-53.06	-13	-40.06
7	5597.6	44.38	-60.44	7.05	-53.38	-13	-40.38
8	6297.3	38.52	-65.62	6.27	-59.35	-13	-46.35
9	6997	44.80	-57.22	4.97	-52.24	-13	-39.24

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 23095	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1415	36.56	-67.43	5.81	-61.62	-13	-48.62
2	2122.5	42.71	-57.78	6.85	-50.93	-13	-37.93
3	2830	38.95	-61.97	6.94	-55.03	-13	-42.03
4	3537.5	39.77	-63.42	7.85	-55.58	-13	-42.58
5	4245	40.41	-64.42	7.44	-56.98	-13	-43.98
6	4952.5	39.67	-64.41	6.99	-57.42	-13	-44.42
7	5660	41.73	-63.09	7.05	-56.03	-13	-43.03
8	6367.5	47.27	-56.87	6.27	-50.60	-13	-37.60
9	7075	50.09	-51.93	4.97	-46.95	-13	-33.95

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1415	31.09	-72.90	5.81	-67.09	-13	-54.09
2	2122.5	39.67	-60.82	6.85	-53.97	-13	-40.97
3	2830	37.79	-63.13	6.94	-56.19	-13	-43.19
4	3537.5	38.05	-65.14	7.85	-57.30	-13	-44.30
5	4245	41.80	-63.03	7.44	-55.59	-13	-42.59
6	4952.5	43.49	-60.59	6.99	-53.60	-13	-40.60
7	5660	45.30	-59.52	7.05	-52.46	-13	-39.46
8	6367.5	37.72	-66.42	6.27	-60.15	-13	-47.15
9	7075	43.85	-58.17	4.97	-53.19	-13	-40.19

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 23173	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1430.6	36.64	-67.35	5.81	-61.54	-13	-48.54
2	2145.9	40.99	-59.50	6.85	-52.65	-13	-39.65
3	2861.2	39.00	-61.92	6.94	-54.98	-13	-41.98
4	3576.5	40.19	-63.00	7.85	-55.16	-13	-42.16
5	4291.8	40.45	-64.38	7.44	-56.94	-13	-43.94
6	5007.1	40.71	-63.37	6.99	-56.38	-13	-43.38
7	5722.4	42.37	-62.45	7.05	-55.39	-13	-42.39
8	6437.7	47.10	-57.04	6.27	-50.77	-13	-37.77
9	7153	49.73	-52.29	4.97	-47.31	-13	-34.31

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1430.6	32.30	-71.69	5.81	-65.88	-13	-52.88
2	2145.9	40.31	-60.18	6.85	-53.33	-13	-40.33
3	2861.2	38.94	-61.98	6.94	-55.04	-13	-42.04
4	3576.5	38.88	-64.31	7.85	-56.47	-13	-43.47
5	4291.8	41.24	-63.59	7.44	-56.15	-13	-43.15
6	5007.1	44.47	-59.61	6.99	-52.62	-13	-39.62
7	5722.4	45.14	-59.68	7.05	-52.62	-13	-39.62
8	6437.7	37.93	-66.21	6.27	-59.94	-13	-46.94
9	7153	44.63	-57.39	4.97	-52.41	-13	-39.41

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 12: 3MHz

Mode	TX channel 23025	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1401	36.32	-67.67	5.81	-61.86	-13	-48.86
2	2101.5	42.79	-57.70	6.85	-50.85	-13	-37.85
3	2802	40.09	-60.83	6.94	-53.89	-13	-40.89
4	3502.5	39.98	-63.21	7.85	-55.37	-13	-42.37
5	4203	39.10	-65.73	7.44	-58.29	-13	-45.29
6	4903.5	39.67	-64.41	6.99	-57.42	-13	-44.42
7	5604	42.07	-62.75	7.05	-55.69	-13	-42.69
8	6304.5	47.42	-56.72	6.27	-50.45	-13	-37.45
9	7005	49.39	-52.63	4.97	-47.65	-13	-34.65

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1401	32.68	-71.31	5.81	-65.50	-13	-52.50
2	2101.5	40.13	-60.36	6.85	-53.51	-13	-40.51
3	2802	38.10	-62.82	6.94	-55.88	-13	-42.88
4	3502.5	39.28	-63.91	7.85	-56.07	-13	-43.07
5	4203	41.61	-63.22	7.44	-55.78	-13	-42.78
6	4903.5	44.21	-59.87	6.99	-52.88	-13	-39.88
7	5604	45.12	-59.70	7.05	-52.64	-13	-39.64
8	6304.5	38.10	-66.04	6.27	-59.77	-13	-46.77
9	7005	44.21	-57.81	4.97	-52.83	-13	-39.83

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 23095	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1415	37.36	-66.63	5.81	-60.82	-13	-47.82
2	2122.5	42.85	-57.64	6.85	-50.79	-13	-37.79
3	2830	39.13	-61.79	6.94	-54.85	-13	-41.85
4	3537.5	39.33	-63.86	7.85	-56.02	-13	-43.02
5	4245	39.25	-65.58	7.44	-58.14	-13	-45.14
6	4952.5	39.40	-64.68	6.99	-57.69	-13	-44.69
7	5660	42.04	-62.78	7.05	-55.72	-13	-42.72
8	6367.5	48.44	-55.70	6.27	-49.43	-13	-36.43
9	7075	51.06	-50.96	4.97	-45.98	-13	-32.98

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1415	31.75	-72.24	5.81	-66.43	-13	-53.43
2	2122.5	38.99	-61.50	6.85	-54.65	-13	-41.65
3	2830	39.13	-61.79	6.94	-54.85	-13	-41.85
4	3537.5	37.85	-65.34	7.85	-57.50	-13	-44.50
5	4245	41.58	-63.25	7.44	-55.81	-13	-42.81
6	4952.5	44.02	-60.06	6.99	-53.07	-13	-40.07
7	5660	44.04	-60.78	7.05	-53.72	-13	-40.72
8	6367.5	38.83	-65.31	6.27	-59.04	-13	-46.04
9	7075	43.92	-58.10	4.97	-53.12	-13	-40.12

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 23165	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1429	36.92	-67.07	5.81	-61.26	-13	-48.26
2	2143.5	41.04	-59.45	6.85	-52.60	-13	-39.60
3	2858	39.86	-61.06	6.94	-54.12	-13	-41.12
4	3572.5	40.28	-62.91	7.85	-55.07	-13	-42.07
5	4287	40.43	-64.40	7.44	-56.96	-13	-43.96
6	5001.5	41.08	-63.00	6.99	-56.01	-13	-43.01
7	5716	41.71	-63.11	7.05	-56.05	-13	-43.05
8	6430.5	47.29	-56.85	6.27	-50.58	-13	-37.58
9	7145	49.78	-52.24	4.97	-47.26	-13	-34.26

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1429	31.50	-72.49	5.81	-66.68	-13	-53.68
2	2143.5	40.21	-60.28	6.85	-53.43	-13	-40.43
3	2858	38.34	-62.58	6.94	-55.64	-13	-42.64
4	3572.5	39.70	-63.49	7.85	-55.65	-13	-42.65
5	4287	42.07	-62.76	7.44	-55.32	-13	-42.32
6	5001.5	43.75	-60.33	6.99	-53.34	-13	-40.34
7	5716	44.66	-60.16	7.05	-53.10	-13	-40.10
8	6430.5	38.95	-65.19	6.27	-58.92	-13	-45.92
9	7145	43.81	-58.21	4.97	-53.23	-13	-40.23

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 12: 5MHz

Mode	TX channel 23035	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1403	37.00	-66.99	5.81	-61.18	-13	-48.18
2	2104.5	42.26	-58.23	6.85	-51.38	-13	-38.38
3	2806	38.51	-62.41	6.94	-55.47	-13	-42.47
4	3507.5	38.82	-64.37	7.85	-56.53	-13	-43.53
5	4209	40.74	-64.09	7.44	-56.65	-13	-43.65
6	4910.5	39.42	-64.66	6.99	-57.67	-13	-44.67
7	5612	43.12	-61.70	7.05	-54.64	-13	-41.64
8	6313.5	47.59	-56.55	6.27	-50.28	-13	-37.28
9	7015	50.36	-51.66	4.97	-46.68	-13	-33.68

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1403	32.11	-71.88	5.81	-66.07	-13	-53.07
2	2104.5	39.69	-60.80	6.85	-53.95	-13	-40.95
3	2806	37.76	-63.16	6.94	-56.22	-13	-43.22
4	3507.5	38.80	-64.39	7.85	-56.55	-13	-43.55
5	4209	42.01	-62.82	7.44	-55.38	-13	-42.38
6	4910.5	43.50	-60.58	6.99	-53.59	-13	-40.59
7	5612	44.02	-60.80	7.05	-53.74	-13	-40.74
8	6313.5	37.57	-66.57	6.27	-60.30	-13	-47.30
9	7015	43.90	-58.12	4.97	-53.14	-13	-40.14

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 23095	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1415	36.95	-67.04	5.81	-61.23	-13	-48.23
2	2122.5	41.25	-59.24	6.85	-52.39	-13	-39.39
3	2830	39.37	-61.55	6.94	-54.61	-13	-41.61
4	3537.5	39.06	-64.13	7.85	-56.29	-13	-43.29
5	4245	40.84	-63.99	7.44	-56.55	-13	-43.55
6	4952.5	39.79	-64.29	6.99	-57.30	-13	-44.30
7	5660	42.77	-62.05	7.05	-54.99	-13	-41.99
8	6367.5	48.23	-55.91	6.27	-49.64	-13	-36.64
9	7075	50.07	-51.95	4.97	-46.97	-13	-33.97

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1415	30.93	-73.06	5.81	-67.25	-13	-54.25
2	2122.5	38.59	-61.90	6.85	-55.05	-13	-42.05
3	2830	37.74	-63.18	6.94	-56.24	-13	-43.24
4	3537.5	37.96	-65.23	7.85	-57.39	-13	-44.39
5	4245	41.42	-63.41	7.44	-55.97	-13	-42.97
6	4952.5	44.42	-59.66	6.99	-52.67	-13	-39.67
7	5660	43.89	-60.93	7.05	-53.87	-13	-40.87
8	6367.5	37.66	-66.48	6.27	-60.21	-13	-47.21
9	7075	44.94	-57.08	4.97	-52.10	-13	-39.10

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 23155	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1427	36.82	-67.17	5.81	-61.36	-13	-48.36
2	2140.5	41.88	-58.61	6.85	-51.76	-13	-38.76
3	2854	39.53	-61.39	6.94	-54.45	-13	-41.45
4	3567.5	40.28	-62.91	7.85	-55.07	-13	-42.07
5	4281	39.17	-65.66	7.44	-58.22	-13	-45.22
6	4994.5	39.81	-64.27	6.99	-57.28	-13	-44.28
7	5708	42.73	-62.09	7.05	-55.03	-13	-42.03
8	6421.5	47.20	-56.94	6.27	-50.67	-13	-37.67
9	7135	50.98	-51.04	4.97	-46.06	-13	-33.06

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1427	31.53	-72.46	5.81	-66.65	-13	-53.65
2	2140.5	39.26	-61.23	6.85	-54.38	-13	-41.38
3	2854	38.94	-61.98	6.94	-55.04	-13	-42.04
4	3567.5	39.24	-63.95	7.85	-56.11	-13	-43.11
5	4281	42.24	-62.59	7.44	-55.15	-13	-42.15
6	4994.5	43.09	-60.99	6.99	-54.00	-13	-41.00
7	5708	43.45	-61.37	7.05	-54.31	-13	-41.31
8	6421.5	37.86	-66.28	6.27	-60.01	-13	-47.01
9	7135	45.27	-56.75	4.97	-51.77	-13	-38.77

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 12: 10MHz

Mode	TX channel 23060	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1408	37.51	-58.03	9.21	-48.83	-13	-35.83
2	2112	42.48	-68.19	9.49	-58.70	-13	-45.70
3	2816	39.71	-57.29	8.53	-48.76	-13	-35.76
4	3520	40.33	-76.48	5.28	-71.19	-13	-58.19
5	4224	39.51	-63.40	-6.39	-69.79	-13	-56.79
6	4928	39.75	-73.51	2.70	-70.81	-13	-57.81
7	5632	42.97	-68.81	-10.08	-78.89	-13	-65.89
8	6336	47.08	-50.27	3.70	-46.57	-13	-33.57
9	7040	50.35	-47.00	3.70	-43.30	-13	-30.30

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1408	32.66	-62.88	9.21	-53.68	-13	-40.68
2	2112	40.09	-70.58	9.49	-61.09	-13	-48.09
3	2816	37.76	-59.24	8.53	-50.71	-13	-37.71
4	3520	38.12	-78.69	5.28	-73.40	-13	-60.40
5	4224	42.49	-60.42	-6.39	-66.81	-13	-53.81
6	4928	43.14	-70.12	2.70	-67.42	-13	-54.42
7	5632	44.07	-67.71	-10.08	-77.79	-13	-64.79
8	6336	39.51	-57.84	3.70	-54.14	-13	-41.14
9	7040	44.97	-52.38	3.70	-48.68	-13	-35.68

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 23095	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1415	36.72	-58.85	9.20	-49.65	-13	-36.65
2	2122.5	42.33	-68.32	9.48	-58.84	-13	-45.84
3	2830	39.94	-62.68	8.55	-54.13	-13	-41.13
4	3537.5	39.44	-77.32	5.28	-72.04	-13	-59.04
5	4245	39.69	-63.21	-6.36	-69.57	-13	-56.57
6	4952.5	40.37	-72.85	2.70	-70.15	-13	-57.15
7	5660	42.02	-69.71	-10.04	-79.75	-13	-66.75
8	6367.5	47.81	-49.54	3.70	-45.84	-13	-32.84
9	7075	50.33	-47.02	3.70	-43.32	-13	-30.32

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1415	31.30	-64.27	9.20	-55.07	-13	-42.07
2	2122.5	39.71	-70.94	9.48	-61.46	-13	-48.46
3	2830	38.95	-63.67	8.55	-55.12	-13	-42.12
4	3537.5	38.36	-78.40	5.28	-73.12	-13	-60.12
5	4245	42.33	-60.57	-6.36	-66.93	-13	-53.93
6	4952.5	44.06	-69.16	2.70	-66.46	-13	-53.46
7	5660	45.33	-66.40	-10.04	-76.44	-13	-63.44
8	6367.5	37.63	-59.72	3.70	-56.02	-13	-43.02
9	7075	44.05	-53.30	3.70	-49.60	-13	-36.60

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 23130	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1422	35.88	-59.71	9.20	-50.52	-13	-37.52
2	2133	41.33	-69.31	9.47	-59.83	-13	-46.83
3	2844	38.49	-64.13	4.43	-59.70	-13	-46.70
4	3555	40.36	-61.25	4.18	-57.08	-13	-44.08
5	4266	40.49	-62.41	-6.33	-68.74	-13	-55.74
6	4977	40.38	-59.94	3.57	-56.37	-13	-43.37
7	5688	41.97	-55.38	3.70	-51.68	-13	-38.68
8	6399	46.96	-50.39	3.70	-46.69	-13	-33.69
9	7110	49.07	-48.28	3.70	-44.58	-13	-31.58

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1422	32.03	-63.56	9.20	-54.37	-13	-41.37
2	2133	38.83	-71.81	9.47	-62.33	-13	-49.33
3	2844	38.10	-64.52	4.43	-60.09	-13	-47.09
4	3555	38.54	-63.07	4.18	-58.90	-13	-45.90
5	4266	43.04	-59.86	-6.33	-66.19	-13	-53.19
6	4977	43.24	-57.08	3.57	-53.51	-13	-40.51
7	5688	44.33	-53.02	3.70	-49.32	-13	-36.32
8	6399	37.58	-59.77	3.70	-56.07	-13	-43.07
9	7110	45.34	-52.01	3.70	-48.31	-13	-35.31

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 13: 5MHz

Mode	TX channel 23205	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1559	36.18	-67.02	6.10	-60.91	-40	-20.91
2	2338.5	44.55	-54.72	6.73	-47.99	-13	-34.99
3	3118	37.07	-65.66	7.30	-58.36	-13	-45.36
4	3897.5	40.46	-64.67	7.57	-57.11	-13	-44.11
5	4677	39.57	-64.85	7.20	-57.65	-13	-44.65
6	5456.5	40.62	-64.43	7.15	-57.28	-13	-44.28
7	6236	43.66	-60.48	6.37	-54.11	-13	-41.11
8	7015.5	47.62	-54.42	4.96	-49.46	-13	-36.46
9	7795	48.36	-54.26	4.08	-50.18	-13	-37.18

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1559	34.40	-68.80	6.10	-62.69	-40	-22.69
2	2338.5	39.12	-60.15	6.73	-53.42	-13	-40.42
3	3118	36.54	-66.19	7.30	-58.89	-13	-45.89
4	3897.5	36.97	-68.16	7.57	-60.60	-13	-47.60
5	4677	41.48	-62.94	7.20	-55.74	-13	-42.74
6	5456.5	40.00	-65.05	7.15	-57.90	-13	-44.90
7	6236	42.60	-61.54	6.37	-55.17	-13	-42.17
8	7015.5	44.14	-57.90	4.96	-52.94	-13	-39.94
9	7795	47.34	-55.28	4.08	-51.20	-13	-38.20

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 23230	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1564	35.72	-67.48	6.10	-61.37	-40	-21.37
2	2346	45.13	-54.14	6.73	-47.41	-13	-34.41
3	3128	36.70	-66.03	7.30	-58.73	-13	-45.73
4	3910	40.64	-64.49	7.57	-56.93	-13	-43.93
5	4692	39.37	-65.05	7.20	-57.85	-13	-44.85
6	5474	41.63	-63.42	7.15	-56.27	-13	-43.27
7	6256	44.62	-59.52	6.37	-53.15	-13	-40.15
8	7038	47.20	-54.84	4.96	-49.88	-13	-36.88
9	7820	47.43	-55.19	4.08	-51.11	-13	-38.11

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1564	34.26	-68.94	6.10	-62.83	-40	-22.83
2	2346	38.71	-60.56	6.73	-53.83	-13	-40.83
3	3128	36.45	-66.28	7.30	-58.98	-13	-45.98
4	3910	35.24	-69.89	7.57	-62.33	-13	-49.33
5	4692	41.83	-62.59	7.20	-55.39	-13	-42.39
6	5474	39.74	-65.31	7.15	-58.16	-13	-45.16
7	6256	42.49	-61.65	6.37	-55.28	-13	-42.28
8	7038	43.89	-58.15	4.96	-53.19	-13	-40.19
9	7820	48.88	-53.74	4.08	-49.66	-13	-36.66

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 23255	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1569	36.82	-66.38	6.10	-60.27	-40	-20.27
2	2353.5	43.93	-55.34	6.73	-48.61	-13	-35.61
3	3138	36.36	-66.37	7.30	-59.07	-13	-46.07
4	3922.5	39.98	-65.15	7.57	-57.59	-13	-44.59
5	4707	40.10	-64.32	7.20	-57.12	-13	-44.12
6	5491.5	41.47	-63.58	7.15	-56.43	-13	-43.43
7	6276	44.87	-59.27	6.37	-52.90	-13	-39.90
8	7060.5	47.28	-54.76	4.96	-49.80	-13	-36.80
9	7845	46.57	-56.05	4.08	-51.97	-13	-38.97

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1569	34.84	-68.36	6.10	-62.25	-40	-22.25
2	2353.5	38.62	-60.65	6.73	-53.92	-13	-40.92
3	3138	35.86	-66.87	7.30	-59.57	-13	-46.57
4	3922.5	35.88	-69.25	7.57	-61.69	-13	-48.69
5	4707	40.89	-63.53	7.20	-56.33	-13	-43.33
6	5491.5	40.22	-64.83	7.15	-57.68	-13	-44.68
7	6276	42.74	-61.40	6.37	-55.03	-13	-42.03
8	7060.5	44.70	-57.34	4.96	-52.38	-13	-39.38
9	7845	48.61	-54.01	4.08	-49.93	-13	-36.93

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 13: 10MHz

Mode	TX channel 23230	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1564	35.19	-68.01	6.10	-61.90	-40	-21.90
2	2346	44.67	-54.60	6.73	-47.87	-13	-34.87
3	3128	37.24	-65.49	7.30	-58.19	-13	-45.19
4	3910	40.94	-64.19	7.57	-56.63	-13	-43.63
5	4692	40.73	-63.69	7.20	-56.49	-13	-43.49
6	5474	41.11	-63.94	7.15	-56.79	-13	-43.79
7	6256	43.34	-60.80	6.37	-54.43	-13	-41.43
8	7038	47.35	-54.69	4.96	-49.73	-13	-36.73
9	7820	47.66	-54.96	4.08	-50.88	-13	-37.88

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1564	34.89	-68.31	6.10	-62.20	-40	-22.20
2	2346	38.16	-61.11	6.73	-54.38	-13	-41.38
3	3128	35.99	-66.74	7.30	-59.44	-13	-46.44
4	3910	37.06	-68.07	7.57	-60.51	-13	-47.51
5	4692	41.52	-62.90	7.20	-55.70	-13	-42.70
6	5474	40.24	-64.81	7.15	-57.66	-13	-44.66
7	6256	43.36	-60.78	6.37	-54.41	-13	-41.41
8	7038	44.05	-57.99	4.96	-53.03	-13	-40.03
9	7820	47.46	-55.16	4.08	-51.08	-13	-38.08

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 17: 5MHz

Mode	TX channel 23755	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1413	36.84	-67.08	5.84	-61.24	-13	-48.24
2	2119.5	44.03	-56.36	6.84	-49.52	-13	-36.52
3	2826	36.57	-65.81	6.88	-58.92	-13	-45.92
4	3532.5	41.05	-62.27	7.83	-54.44	-13	-41.44
5	4239	40.60	-64.19	7.42	-56.77	-13	-43.77
6	4945.5	42.07	-62.08	7.00	-55.08	-13	-42.08
7	5652	43.78	-60.94	7.01	-53.93	-13	-40.93
8	6358.5	46.29	-58.45	6.20	-52.25	-13	-39.25
9	7065	47.62	-54.48	4.92	-49.56	-13	-36.56

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1413	33.98	-69.94	5.84	-64.10	-13	-51.10
2	2119.5	38.06	-62.33	6.84	-55.49	-13	-42.49
3	2826	35.93	-66.45	6.88	-59.56	-13	-46.56
4	3532.5	36.16	-67.16	7.83	-59.33	-13	-46.33
5	4239	41.69	-63.10	7.42	-55.68	-13	-42.68
6	4945.5	39.19	-64.96	7.00	-57.96	-13	-44.96
7	5652	43.63	-61.09	7.01	-54.08	-13	-41.08
8	6358.5	44.42	-60.32	6.20	-54.12	-13	-41.12
9	7065	48.33	-53.77	4.92	-48.85	-13	-35.85

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 23790	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1420	37.07	-66.85	5.84	-61.01	-13	-48.01
2	2130	45.03	-55.36	6.84	-48.52	-13	-35.52
3	2840	36.75	-65.63	6.88	-58.74	-13	-45.74
4	3550	41.78	-61.54	7.83	-53.71	-13	-40.71
5	4260	40.08	-64.71	7.42	-57.29	-13	-44.29
6	4970	41.19	-62.96	7.00	-55.96	-13	-42.96
7	5680	44.99	-59.73	7.01	-52.72	-13	-39.72
8	6390	46.18	-58.56	6.20	-52.36	-13	-39.36
9	7100	48.22	-53.88	4.92	-48.96	-13	-35.96

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1420	33.95	-69.97	5.84	-64.13	-13	-51.13
2	2130	38.38	-62.01	6.84	-55.17	-13	-42.17
3	2840	35.27	-67.11	6.88	-60.22	-13	-47.22
4	3550	35.88	-67.44	7.83	-59.61	-13	-46.61
5	4260	41.33	-63.46	7.42	-56.04	-13	-43.04
6	4970	39.73	-64.42	7.00	-57.42	-13	-44.42
7	5680	42.65	-62.07	7.01	-55.06	-13	-42.06
8	6390	45.13	-59.61	6.20	-53.41	-13	-40.41
9	7100	49.26	-52.84	4.92	-47.92	-13	-34.92

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 23825	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1427	35.98	-67.94	5.84	-62.10	-13	-49.10
2	2140.5	45.39	-55.00	6.84	-48.16	-13	-35.16
3	2854	37.03	-65.35	6.88	-58.46	-13	-45.46
4	3567.5	41.41	-61.91	7.83	-54.08	-13	-41.08
5	4281	40.85	-63.94	7.42	-56.52	-13	-43.52
6	4994.5	40.37	-63.78	7.00	-56.78	-13	-43.78
7	5708	44.86	-59.86	7.01	-52.85	-13	-39.85
8	6421.5	47.27	-57.47	6.20	-51.27	-13	-38.27
9	7135	47.66	-54.44	4.92	-49.52	-13	-36.52

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1427	34.67	-69.25	5.84	-63.41	-13	-50.41
2	2140.5	38.30	-62.09	6.84	-55.25	-13	-42.25
3	2854	35.97	-66.41	6.88	-59.52	-13	-46.52
4	3567.5	36.76	-66.56	7.83	-58.73	-13	-45.73
5	4281	41.70	-63.09	7.42	-55.67	-13	-42.67
6	4994.5	40.34	-63.81	7.00	-56.81	-13	-43.81
7	5708	42.76	-61.96	7.01	-54.95	-13	-41.95
8	6421.5	45.03	-59.71	6.20	-53.51	-13	-40.51
9	7135	48.79	-53.31	4.92	-48.39	-13	-35.39

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 17: 10MHz

Mode	TX channel 23780	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1418	35.97	-67.93	5.85	-62.08	-13	-49.08
2	2127	45.25	-55.10	6.83	-48.27	-13	-35.27
3	2836	36.55	-65.84	6.90	-58.94	-13	-45.94
4	3545	40.04	-63.32	7.82	-55.51	-13	-42.51
5	4254	40.68	-64.09	7.41	-56.68	-13	-43.68
6	4963	42.08	-62.09	7.00	-55.09	-13	-42.09
7	5672	44.00	-60.69	7.00	-53.69	-13	-40.69
8	6381	45.83	-58.81	6.16	-52.66	-13	-39.66
9	7090	47.71	-54.42	4.89	-49.52	-13	-36.52

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1418	35.36	-68.54	5.85	-62.69	-13	-49.69
2	2127	37.93	-62.42	6.83	-55.59	-13	-42.59
3	2836	36.48	-65.91	6.90	-59.01	-13	-46.01
4	3545	36.24	-67.12	7.82	-59.31	-13	-46.31
5	4254	41.16	-63.61	7.41	-56.20	-13	-43.20
6	4963	39.40	-64.77	7.00	-57.77	-13	-44.77
7	5672	43.60	-61.09	7.00	-54.09	-13	-41.09
8	6381	45.22	-59.42	6.16	-53.27	-13	-40.27
9	7090	48.54	-53.59	4.89	-48.69	-13	-35.69

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 23790	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1420	36.73	-67.17	5.85	-61.32	-13	-48.32
2	2130	45.66	-54.69	6.83	-47.86	-13	-34.86
3	2840	37.67	-64.72	6.90	-57.82	-13	-44.82
4	3550	41.90	-61.46	7.82	-53.65	-13	-40.65
5	4260	40.37	-64.40	7.41	-56.99	-13	-43.99
6	4970	41.75	-62.42	7.00	-55.42	-13	-42.42
7	5680	43.29	-61.40	7.00	-54.40	-13	-41.40
8	6390	46.01	-58.63	6.16	-52.48	-13	-39.48
9	7100	47.76	-54.37	4.89	-49.47	-13	-36.47

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1420	35.65	-68.25	5.85	-62.40	-13	-49.40
2	2130	37.91	-62.44	6.83	-55.61	-13	-42.61
3	2840	34.75	-67.64	6.90	-60.74	-13	-47.74
4	3550	37.20	-66.16	7.82	-58.35	-13	-45.35
5	4260	42.15	-62.62	7.41	-55.21	-13	-42.21
6	4970	40.71	-63.46	7.00	-56.46	-13	-43.46
7	5680	42.05	-62.64	7.00	-55.64	-13	-42.64
8	6390	44.27	-60.37	6.16	-54.22	-13	-41.22
9	7100	49.21	-52.92	4.89	-48.02	-13	-35.02

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 23800	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1422	36.58	-67.32	5.85	-61.47	-13	-48.47
2	2133	44.13	-56.22	6.83	-49.39	-13	-36.39
3	2844	37.19	-65.20	6.90	-58.30	-13	-45.30
4	3555	41.85	-61.51	7.82	-53.70	-13	-40.70
5	4266	40.56	-64.21	7.41	-56.80	-13	-43.80
6	4977	40.79	-63.38	7.00	-56.38	-13	-43.38
7	5688	44.60	-60.09	7.00	-53.09	-13	-40.09
8	6399	46.82	-57.82	6.16	-51.67	-13	-38.67
9	7110	48.23	-53.90	4.89	-49.00	-13	-36.00

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1422	33.78	-70.12	5.85	-64.27	-13	-51.27
2	2133	38.74	-61.61	6.83	-54.78	-13	-41.78
3	2844	36.47	-65.92	6.90	-59.02	-13	-46.02
4	3555	35.85	-67.51	7.82	-59.70	-13	-46.70
5	4266	41.45	-63.32	7.41	-55.91	-13	-42.91
6	4977	40.70	-63.47	7.00	-56.47	-13	-43.47
7	5688	43.48	-61.21	7.00	-54.21	-13	-41.21
8	6399	43.64	-61.00	6.16	-54.85	-13	-41.85
9	7110	48.29	-53.84	4.89	-48.94	-13	-35.94

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 30: 5MHz

Mode	TX channel 27685	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	4615	42.63	-61.82	7.24	-54.59	-40	-14.59
2	6922.5	44.50	-57.43	5.04	-52.39	-40	-12.39
3	9230	43.73	-58.58	4.24	-54.34	-40	-14.34
4	11537.5	41.63	-59.82	3.84	-55.98	-40	-15.98
5	13845	44.68	-54.99	2.50	-52.50	-40	-12.50
6	16152.5	40.54	-56.81	3.70	-53.11	-40	-13.11

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	4615	43.92	-60.53	7.24	-53.30	-40	-13.30
2	6922.5	43.48	-58.45	5.04	-53.41	-40	-13.41
3	9230	42.85	-59.46	4.24	-55.22	-40	-15.22
4	11537.5	41.60	-59.85	3.84	-56.01	-40	-16.01
5	13845	45.75	-53.92	2.50	-51.43	-40	-11.43
6	16152.5	40.87	-56.48	3.70	-52.78	-40	-12.78

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 27710	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	4620	41.78	-62.67	7.24	-55.44	-40	-15.44
2	6930	45.87	-56.06	5.04	-51.02	-40	-11.02
3	9240	45.46	-56.85	4.24	-52.61	-40	-12.61
4	11550	44.08	-57.37	3.84	-53.53	-40	-13.53
5	13860	44.83	-54.84	2.50	-52.35	-40	-12.35
6	16170	43.61	-53.74	3.70	-50.04	-40	-10.04

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	4620	43.10	-61.35	7.24	-54.12	-40	-14.12
2	6930	43.76	-58.17	5.04	-53.13	-40	-13.13
3	9240	42.48	-59.83	4.24	-55.59	-40	-15.59
4	11550	41.83	-59.62	3.84	-55.78	-40	-15.78
5	13860	45.78	-53.89	2.50	-51.40	-40	-11.40
6	16170	41.90	-55.45	3.70	-51.75	-40	-11.75

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 27735	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	4625	43.14	-61.31	7.24	-54.08	-40	-14.08
2	6937.5	44.76	-57.17	5.04	-52.13	-40	-12.13
3	9250	45.73	-56.58	4.24	-52.34	-40	-12.34
4	11562.5	44.03	-57.42	3.84	-53.58	-40	-13.58
5	13875	46.06	-53.61	2.50	-51.12	-40	-11.12
6	16187.5	43.71	-53.64	3.70	-49.94	-40	-9.94

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	4625	43.07	-61.38	7.24	-54.15	-40	-14.15
2	6937.5	43.69	-58.24	5.04	-53.20	-40	-13.20
3	9250	44.06	-58.25	4.24	-54.01	-40	-14.01
4	11562.5	42.30	-59.15	3.84	-55.31	-40	-15.31
5	13875	45.97	-53.70	2.50	-51.21	-40	-11.21
6	16187.5	40.60	-56.75	3.70	-53.05	-40	-13.05

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 30: 10MHz

Mode	TX channel 27710	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	4620	43.04	-61.41	7.24	-54.18	-40	-14.18
2	6930	45.99	-55.94	5.04	-50.90	-40	-10.90
3	9240	46.62	-55.69	4.24	-51.45	-40	-11.45
4	11550	44.27	-57.18	3.84	-53.34	-40	-13.34
5	13860	45.38	-54.29	2.50	-51.80	-40	-11.80
6	16170	42.74	-54.61	3.70	-50.91	-40	-10.91

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	4620	43.09	-61.36	7.24	-54.13	-40	-14.13
2	6930	44.17	-57.76	5.04	-52.72	-40	-12.72
3	9240	43.24	-59.07	4.24	-54.83	-40	-14.83
4	11550	42.35	-59.10	3.84	-55.26	-40	-15.26
5	13860	45.18	-54.49	2.50	-52.00	-40	-12.00
6	16170	41.19	-56.16	3.70	-52.46	-40	-12.46

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 38: 5MHz

Mode	TX channel 37775	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5145	43.51	-60.94	7.04	-53.90	-25	-28.90
2	7717.5	43.58	-59.04	4.36	-54.68	-25	-29.68
3	10290	43.63	-58.25	3.77	-54.49	-25	-29.49
4	12862.5	40.88	-60.14	4.77	-55.37	-25	-30.37
5	15435	45.50	-51.85	3.70	-48.15	-25	-23.15

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5145	44.41	-60.04	7.04	-53.00	-25	-28.00
2	7717.5	43.33	-59.29	4.36	-54.93	-25	-29.93
3	10290	42.59	-59.29	3.77	-55.53	-25	-30.53
4	12862.5	40.75	-60.27	4.77	-55.50	-25	-30.50
5	15435	45.81	-51.54	3.70	-47.84	-25	-22.84

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 38000	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5190	41.87	-62.58	7.04	-55.54	-25	-30.54
2	7785	43.63	-58.99	4.36	-54.63	-25	-29.63
3	10380	43.18	-58.70	3.77	-54.94	-25	-29.94
4	12975	42.38	-58.64	4.77	-53.87	-25	-28.87
5	15570	45.19	-52.16	3.70	-48.46	-25	-23.46

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5190	44.73	-59.72	7.04	-52.68	-25	-27.68
2	7785	43.29	-59.33	4.36	-54.97	-25	-29.97
3	10380	42.81	-59.07	3.77	-55.31	-25	-30.31
4	12975	41.15	-59.87	4.77	-55.10	-25	-30.10
5	15570	46.08	-51.27	3.70	-47.57	-25	-22.57

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 38225	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5235	42.17	-62.28	7.04	-55.24	-25	-30.24
2	7852.5	44.31	-58.31	4.36	-53.95	-25	-28.95
3	10470	43.32	-58.56	3.77	-54.80	-25	-29.80
4	13087.5	41.99	-59.03	4.77	-54.26	-25	-29.26
5	15705	44.43	-52.92	3.70	-49.22	-25	-24.22

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5235	44.10	-60.35	7.04	-53.31	-25	-28.31
2	7852.5	44.16	-58.46	4.36	-54.10	-25	-29.10
3	10470	43.00	-58.88	3.77	-55.12	-25	-30.12
4	13087.5	42.21	-58.81	4.77	-54.04	-25	-29.04
5	15705	45.44	-51.91	3.70	-48.21	-25	-23.21

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 38: 10MHz

Mode	TX channel 37800	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5150	43.35	-61.10	7.04	-54.06	-25	-29.06
2	7725	44.19	-58.43	4.36	-54.07	-25	-29.07
3	10300	43.96	-57.92	3.77	-54.16	-25	-29.16
4	12875	41.42	-59.60	4.77	-54.83	-25	-29.83
5	15450	44.44	-52.91	3.70	-49.21	-25	-24.21

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5150	43.10	-61.35	7.04	-54.31	-25	-29.31
2	7725	43.69	-58.93	4.36	-54.57	-25	-29.57
3	10300	41.95	-59.93	3.77	-56.17	-25	-31.17
4	12875	41.67	-59.35	4.77	-54.58	-25	-29.58
5	15450	44.97	-52.38	3.70	-48.68	-25	-23.68

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 38000	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5190	42.53	-61.92	7.04	-54.88	-25	-29.88
2	7785	44.84	-57.78	4.36	-53.42	-25	-28.42
3	10380	44.29	-57.59	3.77	-53.83	-25	-28.83
4	12975	41.86	-59.16	4.77	-54.39	-25	-29.39
5	15570	44.20	-53.15	3.70	-49.45	-25	-24.45

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5190	43.60	-60.85	7.04	-53.81	-25	-28.81
2	7785	42.92	-59.70	4.36	-55.34	-25	-30.34
3	10380	43.32	-58.56	3.77	-54.80	-25	-29.80
4	12975	42.34	-58.68	4.77	-53.91	-25	-28.91
5	15570	46.06	-51.29	3.70	-47.59	-25	-22.59

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 38200	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5230	41.90	-62.55	7.04	-55.51	-25	-30.51
2	7845	43.83	-58.79	4.36	-54.43	-25	-29.43
3	10460	43.39	-58.49	3.77	-54.73	-25	-29.73
4	13075	41.36	-59.66	4.77	-54.89	-25	-29.89
5	15690	45.66	-51.69	3.70	-47.99	-25	-22.99

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5230	43.24	-61.21	7.04	-54.17	-25	-29.17
2	7845	44.47	-58.15	4.36	-53.79	-25	-28.79
3	10460	43.71	-58.17	3.77	-54.41	-25	-29.41
4	13075	42.43	-58.59	4.77	-53.82	-25	-28.82
5	15690	45.06	-52.29	3.70	-48.59	-25	-23.59

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 38: 15MHz

Mode	TX channel 37825	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5155	43.33	-61.13	7.04	-54.09	-25	-29.09
2	7732.5	45.24	-57.38	4.35	-53.03	-25	-28.03
3	10310	44.40	-57.94	3.75	-54.18	-25	-29.18
4	12887.5	42.38	-58.62	4.42	-54.20	-25	-29.20
5	15465	43.75	-53.60	3.70	-49.90	-25	-24.90

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5155	43.45	-61.01	7.04	-53.97	-25	-28.97
2	7732.5	42.81	-59.81	4.35	-55.46	-25	-30.46
3	10310	43.56	-58.78	3.75	-55.02	-25	-30.02
4	12887.5	41.21	-59.79	4.42	-55.37	-25	-30.37
5	15465	46.09	-51.26	3.70	-47.56	-25	-22.56

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 38000	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5190	41.90	-62.56	7.04	-55.52	-25	-30.52
2	7785	45.27	-57.35	4.35	-53.00	-25	-28.00
3	10380	44.55	-57.79	3.75	-54.03	-25	-29.03
4	12975	40.66	-60.34	4.42	-55.92	-25	-30.92
5	15570	45.53	-51.82	3.70	-48.12	-25	-23.12

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5190	43.48	-60.98	7.04	-53.94	-25	-28.94
2	7785	42.62	-60.00	4.35	-55.65	-25	-30.65
3	10380	42.57	-59.77	3.75	-56.01	-25	-31.01
4	12975	42.52	-58.48	4.42	-54.06	-25	-29.06
5	15570	46.44	-50.91	3.70	-47.21	-25	-22.21

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 38175	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5225	42.76	-61.70	7.04	-54.66	-25	-29.66
2	7837.5	45.30	-57.32	4.35	-52.97	-25	-27.97
3	10450	44.68	-57.66	3.75	-53.90	-25	-28.90
4	13062.5	40.91	-60.09	4.42	-55.67	-25	-30.67
5	15675	44.27	-53.08	3.70	-49.38	-25	-24.38

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5225	43.59	-60.87	7.04	-53.83	-25	-28.83
2	7837.5	43.90	-58.72	4.35	-54.37	-25	-29.37
3	10450	42.33	-60.01	3.75	-56.25	-25	-31.25
4	13062.5	41.98	-59.02	4.42	-54.60	-25	-29.60
5	15675	45.15	-52.20	3.70	-48.50	-25	-23.50

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 38: 20MHz

Mode	TX channel 37850	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5160	42.88	-61.58	7.04	-54.54	-25	-29.54
2	7740	44.08	-58.54	4.35	-54.19	-25	-29.19
3	10320	43.67	-58.67	3.75	-54.91	-25	-29.91
4	12900	41.61	-59.39	4.42	-54.97	-25	-29.97
5	15480	45.67	-51.68	3.70	-47.98	-25	-22.98

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5160	43.46	-61.00	7.04	-53.96	-25	-28.96
2	7740	43.39	-59.23	4.35	-54.88	-25	-29.88
3	10320	43.47	-58.87	3.75	-55.11	-25	-30.11
4	12900	42.52	-58.48	4.42	-54.06	-25	-29.06
5	15480	45.67	-51.68	3.70	-47.98	-25	-22.98

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 38000	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5190	42.81	-61.65	7.04	-54.61	-25	-29.61
2	7785	44.23	-58.39	4.35	-54.04	-25	-29.04
3	10380	44.35	-57.99	3.75	-54.23	-25	-29.23
4	12975	41.47	-59.53	4.42	-55.11	-25	-30.11
5	15570	44.35	-53.00	3.70	-49.30	-25	-24.30

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5190	44.32	-60.14	7.04	-53.10	-25	-28.10
2	7785	43.01	-59.61	4.35	-55.26	-25	-30.26
3	10380	41.95	-60.39	3.75	-56.63	-25	-31.63
4	12975	41.13	-59.87	4.42	-55.45	-25	-30.45
5	15570	45.41	-51.94	3.70	-48.24	-25	-23.24

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 38150	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5220	42.11	-62.35	7.04	-55.31	-25	-30.31
2	7830	45.01	-57.61	4.35	-53.26	-25	-28.26
3	10440	43.58	-58.76	3.75	-55.00	-25	-30.00
4	13050	41.59	-59.41	4.42	-54.99	-25	-29.99
5	15660	45.07	-52.28	3.70	-48.58	-25	-23.58

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5220	44.34	-60.12	7.04	-53.08	-25	-28.08
2	7830	43.05	-59.57	4.35	-55.22	-25	-30.22
3	10440	41.87	-60.47	3.75	-56.71	-25	-31.71
4	13050	41.15	-59.85	4.42	-55.43	-25	-30.43
5	15660	46.71	-50.64	3.70	-46.94	-25	-21.94

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE CA_38C (15MHz+15MHz)

Mode	TX channel 37825+37975	Frequency Range	Above 1000 MHz
------	------------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5185	36.51	-68.05	7.06	-60.99	-25	-35.99
2	7777.5	48.45	-54.17	4.26	-49.91	-25	-24.91
3	10370	50.36	-51.80	3.56	-48.24	-25	-23.24
4	12962.5	49.65	-51.11	4.33	-46.78	-25	-21.78
5	15555	51.24	-46.23	3.74	-42.49	-25	-17.49

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5185	38.78	-65.78	7.06	-58.72	-25	-33.72
2	7777.5	45.93	-56.69	4.26	-52.43	-25	-27.43
3	10370	46.49	-55.67	3.56	-52.11	-25	-27.11
4	12962.5	46.68	-54.08	4.33	-49.75	-25	-24.75
5	15555	45.09	-52.38	3.74	-48.64	-25	-23.64

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 41: 5MHz

Mode	TX channel 39675	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	4997	41.82	-62.41	7.01	-55.40	-25	-30.40
2	7495.5	46.55	-56.07	4.55	-51.52	-25	-26.52
3	9994	46.56	-54.99	4.04	-50.95	-25	-25.95
4	12492.5	42.41	-59.20	4.34	-54.87	-25	-29.87
5	14991	43.95	-53.40	3.70	-49.70	-25	-24.70
6	17489.5	42.44	-54.91	3.70	-51.21	-25	-26.21

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	4997	42.05	-62.18	7.01	-55.17	-25	-30.17
2	7495.5	43.89	-58.73	4.55	-54.18	-25	-29.18
3	9994	42.95	-58.60	4.04	-54.56	-25	-29.56
4	12492.5	43.09	-58.52	4.34	-54.19	-25	-29.19
5	14991	46.06	-51.29	3.70	-47.59	-25	-22.59
6	17489.5	41.01	-56.34	3.70	-52.64	-25	-27.64

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 40620	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5186	42.25	-61.98	7.01	-54.97	-25	-29.97
2	7779	46.79	-55.83	4.55	-51.28	-25	-26.28
3	10372	47.97	-53.58	4.04	-49.54	-25	-24.54
4	12965	42.14	-59.47	4.34	-55.14	-25	-30.14
5	15558	43.64	-53.71	3.70	-50.01	-25	-25.01

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5186	43.31	-60.92	7.01	-53.91	-25	-28.91
2	7779	44.21	-58.41	4.55	-53.86	-25	-28.86
3	10372	43.09	-58.46	4.04	-54.42	-25	-29.42
4	12965	42.79	-58.82	4.34	-54.49	-25	-29.49
5	15558	45.98	-51.37	3.70	-47.67	-25	-22.67

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 41565	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5375	42.38	-61.85	7.01	-54.84	-25	-29.84
2	8062.5	47.08	-55.54	4.55	-50.99	-25	-25.99
3	10750	48.21	-53.34	4.04	-49.30	-25	-24.30
4	13437.5	43.25	-58.36	4.34	-54.03	-25	-29.03
5	16125	43.80	-53.55	3.70	-49.85	-25	-24.85

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5375	42.23	-62.00	7.01	-54.99	-25	-29.99
2	8062.5	43.91	-58.71	4.55	-54.16	-25	-29.16
3	10750	42.43	-59.12	4.04	-55.08	-25	-30.08
4	13437.5	43.18	-58.43	4.34	-54.10	-25	-29.10
5	16125	44.18	-53.17	3.70	-49.47	-25	-24.47

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 41: 10MHz

Mode	TX channel 39700	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5002	42.03	-62.20	7.01	-55.19	-25	-30.19
2	7503	46.54	-56.08	4.55	-51.53	-25	-26.53
3	10004	47.02	-54.53	4.04	-50.49	-25	-25.49
4	12505	42.23	-59.38	4.34	-55.05	-25	-30.05
5	15006	44.37	-52.98	3.70	-49.28	-25	-24.28
6	17507	42.01	-55.34	3.70	-51.64	-25	-26.64

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5002	43.40	-60.83	7.01	-53.82	-25	-28.82
2	7503	43.72	-58.90	4.55	-54.35	-25	-29.35
3	10004	42.74	-58.81	4.04	-54.77	-25	-29.77
4	12505	43.59	-58.02	4.34	-53.69	-25	-28.69
5	15006	44.91	-52.44	3.70	-48.74	-25	-23.74
6	17507	41.93	-55.42	3.70	-51.72	-25	-26.72

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 40620	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5186	41.89	-62.34	7.01	-55.33	-25	-30.33
2	7779	47.51	-55.11	4.55	-50.56	-25	-25.56
3	10372	47.35	-54.20	4.04	-50.16	-25	-25.16
4	12965	43.39	-58.22	4.34	-53.89	-25	-28.89
5	15558	45.05	-52.30	3.70	-48.60	-25	-23.60

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5186	42.33	-61.90	7.01	-54.89	-25	-29.89
2	7779	43.63	-58.99	4.55	-54.44	-25	-29.44
3	10372	42.19	-59.36	4.04	-55.32	-25	-30.32
4	12965	42.53	-59.08	4.34	-54.75	-25	-29.75
5	15558	44.96	-52.39	3.70	-48.69	-25	-23.69

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 41540	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5370	41.91	-62.32	7.01	-55.31	-25	-30.31
2	8055	46.05	-56.57	4.55	-52.02	-25	-27.02
3	10740	47.41	-54.14	4.04	-50.10	-25	-25.10
4	13425	43.55	-58.06	4.34	-53.73	-25	-28.73
5	16110	44.90	-52.45	3.70	-48.75	-25	-23.75

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5370	42.86	-61.37	7.01	-54.36	-25	-29.36
2	8055	44.10	-58.52	4.55	-53.97	-25	-28.97
3	10740	41.68	-59.87	4.04	-55.83	-25	-30.83
4	13425	42.85	-58.76	4.34	-54.43	-25	-29.43
5	16110	44.74	-52.61	3.70	-48.91	-25	-23.91

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 41: 15MHz

Mode	TX channel 39725	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5007	43.22	-61.02	7.01	-54.01	-25	-29.01
2	7510.5	46.33	-56.29	4.54	-51.75	-25	-26.75
3	10014	48.37	-53.21	4.02	-49.18	-25	-24.18
4	12517.5	42.24	-59.33	4.34	-54.99	-25	-29.99
5	15021	43.69	-53.66	3.70	-49.96	-25	-24.96
6	17524.5	41.52	-55.83	3.70	-52.13	-25	-27.13

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5007	42.94	-61.30	7.01	-54.29	-25	-29.29
2	7510.5	44.55	-58.07	4.54	-53.53	-25	-28.53
3	10014	41.75	-59.83	4.02	-55.80	-25	-30.80
4	12517.5	42.55	-59.02	4.34	-54.68	-25	-29.68
5	15021	45.44	-51.91	3.70	-48.21	-25	-23.21
6	17524.5	40.48	-56.87	3.70	-53.17	-25	-28.17

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 40620	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5186	42.22	-62.02	7.01	-55.01	-25	-30.01
2	7779	47.43	-55.19	4.54	-50.65	-25	-25.65
3	10372	46.89	-54.69	4.02	-50.66	-25	-25.66
4	12965	42.99	-58.58	4.34	-54.24	-25	-29.24
5	15558	45.26	-52.09	3.70	-48.39	-25	-23.39

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5186	42.04	-62.20	7.01	-55.19	-25	-30.19
2	7779	43.97	-58.65	4.54	-54.11	-25	-29.11
3	10372	42.50	-59.08	4.02	-55.05	-25	-30.05
4	12965	43.03	-58.54	4.34	-54.20	-25	-29.20
5	15558	44.69	-52.66	3.70	-48.96	-25	-23.96

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 41515	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5365	42.23	-62.01	7.01	-55.00	-25	-30.00
2	8047.5	45.76	-56.86	4.54	-52.32	-25	-27.32
3	10730	47.17	-54.41	4.02	-50.38	-25	-25.38
4	13412.5	42.49	-59.08	4.34	-54.74	-25	-29.74
5	16095	44.89	-52.46	3.70	-48.76	-25	-23.76

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5365	42.53	-61.71	7.01	-54.70	-25	-29.70
2	8047.5	44.42	-58.20	4.54	-53.66	-25	-28.66
3	10730	43.52	-58.06	4.02	-54.03	-25	-29.03
4	13412.5	42.53	-59.04	4.34	-54.70	-25	-29.70
5	16095	44.77	-52.58	3.70	-48.88	-25	-23.88

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 41: 20MHz

Mode	TX channel 39750	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5012	41.82	-62.42	7.01	-55.41	-25	-30.41
2	7518	46.33	-56.29	4.54	-51.75	-25	-26.75
3	10024	47.80	-53.78	4.02	-49.75	-25	-24.75
4	12530	43.70	-57.87	4.34	-53.53	-25	-28.53
5	15036	45.55	-51.80	3.70	-48.10	-25	-23.10
6	17542	41.45	-55.90	3.70	-52.20	-25	-27.20

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5012	42.30	-61.94	7.01	-54.93	-25	-29.93
2	7518	43.89	-58.73	4.54	-54.19	-25	-29.19
3	10024	42.50	-59.08	4.02	-55.05	-25	-30.05
4	12530	42.67	-58.90	4.34	-54.56	-25	-29.56
5	15036	45.67	-51.68	3.70	-47.98	-25	-22.98
6	17542	41.46	-55.89	3.70	-52.19	-25	-27.19

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 40620	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5186	41.90	-62.34	7.01	-55.33	-25	-30.33
2	7779	46.78	-55.84	4.54	-51.30	-25	-26.30
3	10372	47.32	-54.26	4.02	-50.23	-25	-25.23
4	12965	43.75	-57.82	4.34	-53.48	-25	-28.48
5	15558	44.43	-52.92	3.70	-49.22	-25	-24.22

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5186	41.24	-63.00	7.01	-55.99	-25	-30.99
2	7779	43.39	-59.23	4.54	-54.69	-25	-29.69
3	10372	41.85	-59.73	4.02	-55.70	-25	-30.70
4	12965	42.48	-59.09	4.34	-54.75	-25	-29.75
5	15558	45.23	-52.12	3.70	-48.42	-25	-23.42

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 41490	Frequency Range	Above 1000 MHz
------	------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5360	43.12	-61.12	7.01	-54.11	-25	-29.11
2	8040	46.50	-56.12	4.54	-51.58	-25	-26.58
3	10720	47.81	-53.77	4.02	-49.74	-25	-24.74
4	13400	41.88	-59.69	4.34	-55.35	-25	-30.35
5	16080	44.18	-53.17	3.70	-49.47	-25	-24.47

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5360	43.30	-60.94	7.01	-53.93	-25	-28.93
2	8040	43.51	-59.11	4.54	-54.57	-25	-29.57
3	10720	42.44	-59.14	4.02	-55.11	-25	-30.11
4	13400	43.13	-58.44	4.34	-54.10	-25	-29.10
5	16080	44.79	-52.56	3.70	-48.86	-25	-23.86

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE CA_41C (10MHz+20MHz)

Mode	TX channel 39700+39844	Frequency Range	Above 1000 MHz
------	------------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5030.8	35.57	-68.96	7.05	-61.91	-25	-36.91
2	7546.2	45.64	-56.98	4.29	-52.69	-25	-27.69
3	10061.6	51.63	-50.56	3.55	-47.01	-25	-22.01
4	12577	50.94	-49.89	4.44	-45.45	-25	-20.45
5	15092.4	51.33	-46.13	3.73	-42.39	-25	-17.39

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	5030.8	44.01	-60.52	7.05	-53.47	-25	-28.47
2	7546.2	46.67	-55.95	4.29	-51.66	-25	-26.66
3	10061.6	45.17	-57.02	3.55	-53.47	-25	-28.47
4	12577	48.97	-51.86	4.44	-47.42	-25	-22.42
5	15092.4	47.24	-50.22	3.73	-46.48	-25	-21.48

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 66: 1.4MHz

Mode	TX channel 131979	Frequency Range	Above 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3421.4	37.96	-65.11	7.87	-57.24	-13	-44.24
2	5132.1	45.96	-58.57	7.05	-51.51	-13	-38.51
3	6842.8	46.51	-55.43	5.03	-50.40	-13	-37.40
4	8553.5	48.31	-54.40	4.23	-50.17	-13	-37.17
5	10264.2	45.45	-56.22	2.24	-53.98	-13	-40.98
6	11974.9	47.85	-53.63	4.38	-49.25	-13	-36.25
7	13685.6	48.69	-51.16	1.93	-49.22	-13	-36.22
8	15396.3	50.79	-46.56	3.70	-42.86	-13	-29.86
9	17107	51.88	-47.14	3.77	-43.37	-13	-30.37

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3421.4	43.51	-59.56	7.87	-51.69	-13	-38.69
2	5132.1	41.17	-63.36	7.05	-56.30	-13	-43.30
3	6842.8	41.95	-59.99	5.03	-54.96	-13	-41.96
4	8553.5	45.62	-57.09	4.23	-52.86	-13	-39.86
5	10264.2	54.57	-47.10	2.24	-44.86	-13	-31.86
6	11974.9	48.33	-53.15	4.38	-48.77	-13	-35.77
7	13685.6	54.46	-45.39	1.93	-43.45	-13	-30.45
8	15396.3	57.54	-39.81	3.70	-36.11	-13	-23.11
9	17107	46.09	-52.93	3.77	-49.16	-13	-36.16

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 132322	Frequency Range	Above 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3490	37.56	-65.60	7.85	-57.75	-13	-44.75
2	5235	45.26	-60.17	7.31	-52.86	-13	-39.86
3	6980	46.97	-55.65	4.99	-50.66	-13	-37.66
4	8725	47.68	-55.91	4.33	-51.58	-13	-38.58
5	10470	45.64	-56.02	2.35	-53.67	-13	-40.67
6	12215	47.11	-54.93	4.28	-50.65	-13	-37.65
7	13960	49.62	-49.33	2.17	-47.16	-13	-34.16
8	15705	50.17	-47.18	3.70	-43.48	-13	-30.48
9	17450	50.95	-46.40	3.70	-42.70	-13	-29.70

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3490	43.16	-60.00	7.85	-52.15	-13	-39.15
2	5235	40.94	-64.49	7.31	-57.18	-13	-44.18
3	6980	41.55	-61.07	4.99	-56.08	-13	-43.08
4	8725	46.08	-57.51	4.33	-53.18	-13	-40.18
5	10470	54.00	-47.66	2.35	-45.31	-13	-32.31
6	12215	47.90	-54.14	4.28	-49.86	-13	-36.86
7	13960	55.44	-43.51	2.17	-41.34	-13	-28.34
8	15705	57.33	-40.02	3.70	-36.32	-13	-23.32
9	17450	45.50	-51.85	3.70	-48.15	-13	-35.15

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 132665	Frequency Range	Above 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3558.6	37.13	-66.28	7.81	-58.47	-13	-45.47
2	5337.9	45.52	-59.73	7.23	-52.50	-13	-39.50
3	7117.2	46.51	-56.11	4.43	-51.68	-13	-38.68
4	8896.5	46.90	-54.71	4.18	-50.54	-13	-37.54
5	10675.8	45.13	-56.48	2.64	-53.85	-13	-40.85
6	12455.1	47.48	-52.84	3.57	-49.27	-13	-36.27
7	14234.4	49.33	-48.02	3.70	-44.32	-13	-31.32
8	16013.7	51.10	-46.25	3.70	-42.55	-13	-29.55
9	17793	50.08	-47.27	3.70	-43.57	-13	-30.57

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3558.6	42.69	-60.72	7.81	-52.91	-13	-39.91
2	5337.9	41.57	-63.68	7.23	-56.45	-13	-43.45
3	7117.2	41.44	-61.18	4.43	-56.75	-13	-43.75
4	8896.5	45.78	-55.83	4.18	-51.66	-13	-38.66
5	10675.8	53.70	-47.91	2.64	-45.28	-13	-32.28
6	12455.1	48.49	-51.83	3.57	-48.26	-13	-35.26
7	14234.4	54.33	-43.02	3.70	-39.32	-13	-26.32
8	16013.7	57.39	-39.96	3.70	-36.26	-13	-23.26
9	17793	46.50	-50.85	3.70	-47.15	-13	-34.15

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 66: 3MHz

Mode	TX channel 131987	Frequency Range	Above 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3423	37.35	-65.57	7.90	-57.67	-13	-44.67
2	5134.5	46.13	-59.46	7.38	-52.09	-13	-39.09
3	6846	46.50	-55.34	5.10	-50.23	-13	-37.23
4	8557.5	47.92	-56.09	4.36	-51.73	-13	-38.73
5	10269	45.94	-55.76	2.07	-53.69	-13	-40.69
6	11980.5	46.29	-56.11	4.22	-51.89	-13	-38.89
7	13692	49.43	-49.93	1.78	-48.16	-13	-35.16
8	15403.5	50.94	-46.41	3.70	-42.71	-13	-29.71
9	17115	50.57	-46.78	3.70	-43.08	-13	-30.08

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3423	43.19	-59.73	7.90	-51.83	-13	-38.83
2	5134.5	41.71	-63.88	7.38	-56.51	-13	-43.51
3	6846	42.33	-59.51	5.10	-54.40	-13	-41.40
4	8557.5	44.82	-59.19	4.36	-54.83	-13	-41.83
5	10269	53.69	-48.01	2.07	-45.94	-13	-32.94
6	11980.5	48.45	-53.95	4.22	-49.73	-13	-36.73
7	13692	55.38	-43.98	1.78	-42.21	-13	-29.21
8	15403.5	56.89	-40.46	3.70	-36.76	-13	-23.76
9	17115	46.50	-50.85	3.70	-47.15	-13	-34.15

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 132322	Frequency Range	Above 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3490	37.04	-66.12	7.85	-58.27	-13	-45.27
2	5235	45.24	-60.19	7.31	-52.88	-13	-39.88
3	6980	46.81	-55.81	4.99	-50.82	-13	-37.82
4	8725	48.67	-54.92	4.33	-50.59	-13	-37.59
5	10470	45.55	-56.11	2.35	-53.76	-13	-40.76
6	12215	47.24	-54.80	4.28	-50.52	-13	-37.52
7	13960	49.75	-49.20	2.17	-47.03	-13	-34.03
8	15705	49.69	-47.66	3.70	-43.96	-13	-30.96
9	17450	50.75	-46.60	3.70	-42.90	-13	-29.90

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3490	42.61	-60.55	7.85	-52.70	-13	-39.70
2	5235	40.95	-64.48	7.31	-57.17	-13	-44.17
3	6980	42.83	-59.79	4.99	-54.80	-13	-41.80
4	8725	45.58	-58.01	4.33	-53.68	-13	-40.68
5	10470	54.05	-47.61	2.35	-45.26	-13	-32.26
6	12215	47.89	-54.15	4.28	-49.87	-13	-36.87
7	13960	53.85	-45.10	2.17	-42.93	-13	-29.93
8	15705	57.42	-39.93	3.70	-36.23	-13	-23.23
9	17450	45.97	-51.38	3.70	-47.68	-13	-34.68

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 132657	Frequency Range	Above 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3557	37.69	-65.72	7.81	-57.91	-13	-44.91
2	5335.5	44.70	-60.56	7.24	-53.32	-13	-40.32
3	7114	46.61	-56.01	4.43	-51.58	-13	-38.58
4	8892.5	48.39	-53.22	4.18	-49.05	-13	-36.05
5	10671	45.51	-56.11	2.63	-53.48	-13	-40.48
6	12449.5	47.09	-53.23	3.57	-49.66	-13	-36.66
7	14228	50.46	-46.89	3.70	-43.19	-13	-30.19
8	16006.5	50.28	-47.07	3.70	-43.37	-13	-30.37
9	17785	50.77	-46.58	3.70	-42.88	-13	-29.88

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3557	44.44	-58.97	7.81	-51.16	-13	-38.16
2	5335.5	40.90	-64.36	7.24	-57.12	-13	-44.12
3	7114	41.92	-60.70	4.43	-56.27	-13	-43.27
4	8892.5	46.51	-55.10	4.18	-50.93	-13	-37.93
5	10671	54.47	-47.15	2.63	-44.52	-13	-31.52
6	12449.5	49.14	-51.18	3.57	-47.61	-13	-34.61
7	14228	54.86	-42.49	3.70	-38.79	-13	-25.79
8	16006.5	57.39	-39.96	3.70	-36.26	-13	-23.26
9	17785	45.39	-51.96	3.70	-48.26	-13	-35.26

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 66: 5MHz

Mode	TX channel 131997	Frequency Range	Above 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3425	37.92	-65.01	7.90	-57.11	-13	-44.11
2	5137.5	46.25	-59.34	7.37	-51.97	-13	-38.97
3	6850	47.88	-53.96	5.10	-48.86	-13	-35.86
4	8562.5	47.21	-56.79	4.36	-52.43	-13	-39.43
5	10275	44.85	-56.85	2.08	-54.77	-13	-41.77
6	11987.5	46.30	-56.09	4.23	-51.86	-13	-38.86
7	13700	48.67	-50.68	1.79	-48.89	-13	-35.89
8	15412.5	50.15	-47.20	3.70	-43.50	-13	-30.50
9	17125	51.58	-45.77	3.70	-42.07	-13	-29.07

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3425	44.23	-58.70	7.90	-50.80	-13	-37.80
2	5137.5	41.84	-63.75	7.37	-56.38	-13	-43.38
3	6850	41.81	-60.03	5.10	-54.93	-13	-41.93
4	8562.5	46.02	-57.98	4.36	-53.62	-13	-40.62
5	10275	54.49	-47.21	2.08	-45.13	-13	-32.13
6	11987.5	48.16	-54.23	4.23	-50.00	-13	-37.00
7	13700	55.33	-44.02	1.79	-42.23	-13	-29.23
8	15412.5	57.11	-40.24	3.70	-36.54	-13	-23.54
9	17125	46.71	-50.64	3.70	-46.94	-13	-33.94

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 132322	Frequency Range	Above 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3490	37.27	-65.89	7.85	-58.04	-13	-45.04
2	5235	44.97	-60.46	7.31	-53.15	-13	-40.15
3	6980	47.83	-54.79	4.99	-49.80	-13	-36.80
4	8725	47.01	-56.58	4.33	-52.25	-13	-39.25
5	10470	46.38	-55.28	2.35	-52.93	-13	-39.93
6	12215	47.66	-54.38	4.28	-50.10	-13	-37.10
7	13960	50.53	-48.42	2.17	-46.25	-13	-33.25
8	15705	49.19	-48.16	3.70	-44.46	-13	-31.46
9	17450	50.86	-46.49	3.70	-42.79	-13	-29.79

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3490	42.87	-60.29	7.85	-52.44	-13	-39.44
2	5235	40.95	-64.48	7.31	-57.17	-13	-44.17
3	6980	41.27	-61.35	4.99	-56.36	-13	-43.36
4	8725	44.98	-58.61	4.33	-54.28	-13	-41.28
5	10470	54.85	-46.81	2.35	-44.46	-13	-31.46
6	12215	47.54	-54.50	4.28	-50.22	-13	-37.22
7	13960	54.07	-44.88	2.17	-42.71	-13	-29.71
8	15705	56.56	-40.79	3.70	-37.09	-13	-24.09
9	17450	46.94	-50.41	3.70	-46.71	-13	-33.71

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 132647	Frequency Range	Above 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3555	38.55	-64.85	7.81	-57.04	-13	-44.04
2	5332.5	46.02	-59.24	7.24	-52.00	-13	-39.00
3	7110	46.60	-56.02	4.43	-51.59	-13	-38.59
4	8887.5	47.08	-54.53	4.18	-50.36	-13	-37.36
5	10665	45.79	-55.83	2.62	-53.21	-13	-40.21
6	12442.5	46.96	-53.36	3.57	-49.79	-13	-36.79
7	14220	48.83	-48.52	3.70	-44.82	-13	-31.82
8	15997.5	49.65	-47.70	3.70	-44.00	-13	-31.00
9	17775	50.83	-46.52	3.70	-42.82	-13	-29.82

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3555	42.79	-60.61	7.81	-52.80	-13	-39.80
2	5332.5	41.59	-63.67	7.24	-56.43	-13	-43.43
3	7110	42.76	-59.86	4.43	-55.43	-13	-42.43
4	8887.5	45.04	-56.57	4.18	-52.40	-13	-39.40
5	10665	54.22	-47.40	2.62	-44.78	-13	-31.78
6	12442.5	48.88	-51.44	3.57	-47.87	-13	-34.87
7	14220	54.83	-42.52	3.70	-38.82	-13	-25.82
8	15997.5	56.70	-40.65	3.70	-36.95	-13	-23.95
9	17775	45.32	-52.03	3.70	-48.33	-13	-35.33

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 66: 10MHz

Mode	TX channel 132022	Frequency Range	Above 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3430	38.05	-64.89	7.89	-57.00	-13	-44.00
2	5145	45.65	-59.93	7.37	-52.56	-13	-39.56
3	6860	45.98	-55.87	5.09	-50.78	-13	-37.78
4	8575	47.94	-56.03	4.36	-51.67	-13	-38.67
5	10290	44.78	-56.91	2.10	-54.81	-13	-41.81
6	12005	47.01	-55.35	4.23	-51.12	-13	-38.12
7	13720	48.87	-50.45	1.82	-48.63	-13	-35.63
8	15435	49.78	-47.57	3.70	-43.87	-13	-30.87
9	17150	50.17	-47.18	3.70	-43.48	-13	-30.48

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3430	44.38	-58.56	7.89	-50.67	-13	-37.67
2	5145	41.10	-64.48	7.37	-57.11	-13	-44.11
3	6860	42.82	-59.03	5.09	-53.94	-13	-40.94
4	8575	44.63	-59.34	4.36	-54.98	-13	-41.98
5	10290	53.84	-47.85	2.10	-45.75	-13	-32.75
6	12005	47.37	-54.99	4.23	-50.76	-13	-37.76
7	13720	53.93	-45.39	1.82	-43.57	-13	-30.57
8	15435	56.58	-40.77	3.70	-37.07	-13	-24.07
9	17150	45.32	-52.03	3.70	-48.33	-13	-35.33

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 132322	Frequency Range	Above 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3490	37.42	-65.74	7.85	-57.89	-13	-44.89
2	5235	45.01	-60.42	7.31	-53.11	-13	-40.11
3	6980	46.55	-56.07	4.99	-51.08	-13	-38.08
4	8725	46.84	-56.75	4.33	-52.42	-13	-39.42
5	10470	45.87	-55.79	2.35	-53.44	-13	-40.44
6	12215	46.47	-55.57	4.28	-51.29	-13	-38.29
7	13960	49.02	-49.93	2.17	-47.76	-13	-34.76
8	15705	49.21	-48.14	3.70	-44.44	-13	-31.44
9	17450	51.36	-45.99	3.70	-42.29	-13	-29.29

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3490	43.60	-59.56	7.85	-51.71	-13	-38.71
2	5235	41.90	-63.53	7.31	-56.22	-13	-43.22
3	6980	41.97	-60.65	4.99	-55.66	-13	-42.66
4	8725	45.02	-58.57	4.33	-54.24	-13	-41.24
5	10470	55.53	-46.13	2.35	-43.78	-13	-30.78
6	12215	48.89	-53.15	4.28	-48.87	-13	-35.87
7	13960	54.46	-44.49	2.17	-42.32	-13	-29.32
8	15705	56.82	-40.53	3.70	-36.83	-13	-23.83
9	17450	46.43	-50.92	3.70	-47.22	-13	-34.22

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 132622	Frequency Range	Above 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3550	37.03	-66.35	7.82	-58.54	-13	-45.54
2	5325	45.36	-59.91	7.24	-52.67	-13	-39.67
3	7100	46.87	-55.75	4.43	-51.32	-13	-38.32
4	8875	47.62	-53.99	4.18	-49.82	-13	-36.82
5	10650	44.83	-56.79	2.60	-54.19	-13	-41.19
6	12425	47.92	-52.40	3.57	-48.83	-13	-35.83
7	14200	48.64	-48.71	3.70	-45.01	-13	-32.01
8	15975	50.89	-46.46	3.70	-42.76	-13	-29.76
9	17750	50.50	-46.85	3.70	-43.15	-13	-30.15

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3550	43.19	-60.19	7.82	-52.38	-13	-39.38
2	5325	40.77	-64.50	7.24	-57.26	-13	-44.26
3	7100	42.21	-60.41	4.43	-55.98	-13	-42.98
4	8875	44.67	-56.94	4.18	-52.77	-13	-39.77
5	10650	54.46	-47.16	2.60	-44.56	-13	-31.56
6	12425	47.87	-52.45	3.57	-48.88	-13	-35.88
7	14200	53.81	-43.54	3.70	-39.84	-13	-26.84
8	15975	55.47	-41.88	3.70	-38.18	-13	-25.18
9	17750	46.78	-50.57	3.70	-46.87	-13	-33.87

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 66: 15MHz

Mode	TX channel 132047	Frequency Range	Above 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3435	38.55	-64.41	7.89	-56.52	-13	-43.52
2	5152.5	45.40	-60.16	7.36	-52.80	-13	-39.80
3	6870	47.86	-54.00	5.08	-48.92	-13	-35.92
4	8587.5	46.71	-57.23	4.36	-52.87	-13	-39.87
5	10305	46.26	-55.43	2.12	-53.31	-13	-40.31
6	12022.5	46.74	-55.60	4.23	-51.36	-13	-38.36
7	13740	49.45	-49.84	1.85	-47.99	-13	-34.99
8	15457.5	50.55	-46.80	3.70	-43.10	-13	-30.10
9	17175	50.61	-46.74	3.70	-43.04	-13	-30.04

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3435	43.84	-59.12	7.89	-51.23	-13	-38.23
2	5152.5	41.34	-64.22	7.36	-56.86	-13	-43.86
3	6870	43.05	-58.81	5.08	-53.73	-13	-40.73
4	8587.5	44.47	-59.47	4.36	-55.11	-13	-42.11
5	10305	53.64	-48.05	2.12	-45.93	-13	-32.93
6	12022.5	47.24	-55.10	4.23	-50.86	-13	-37.86
7	13740	54.31	-44.98	1.85	-43.13	-13	-30.13
8	15457.5	56.14	-41.21	3.70	-37.51	-13	-24.51
9	17175	46.35	-51.00	3.70	-47.30	-13	-34.30

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 132322	Frequency Range	Above 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3490	37.67	-65.49	7.85	-57.64	-13	-44.64
2	5235	45.09	-60.34	7.31	-53.03	-13	-40.03
3	6980	46.92	-55.70	4.99	-50.71	-13	-37.71
4	8725	48.35	-55.24	4.33	-50.91	-13	-37.91
5	10470	45.23	-56.43	2.35	-54.08	-13	-41.08
6	12215	46.48	-55.56	4.28	-51.28	-13	-38.28
7	13960	49.38	-49.57	2.17	-47.40	-13	-34.40
8	15705	50.87	-46.48	3.70	-42.78	-13	-29.78
9	17450	50.01	-47.34	3.70	-43.64	-13	-30.64

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3490	42.64	-60.52	7.85	-52.67	-13	-39.67
2	5235	41.76	-63.67	7.31	-56.36	-13	-43.36
3	6980	41.51	-61.11	4.99	-56.12	-13	-43.12
4	8725	44.08	-59.51	4.33	-55.18	-13	-42.18
5	10470	53.77	-47.89	2.35	-45.54	-13	-32.54
6	12215	47.43	-54.61	4.28	-50.33	-13	-37.33
7	13960	53.19	-45.76	2.17	-43.59	-13	-30.59
8	15705	55.06	-42.29	3.70	-38.59	-13	-25.59
9	17450	45.88	-51.47	3.70	-47.77	-13	-34.77

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 132597	Frequency Range	Above 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3545	37.03	-66.33	7.82	-58.52	-13	-45.52
2	5317.5	45.88	-59.41	7.25	-52.16	-13	-39.16
3	7090	46.24	-56.38	4.43	-51.95	-13	-38.95
4	8862.5	47.97	-53.64	4.18	-49.47	-13	-36.47
5	10635	45.25	-56.37	2.58	-53.79	-13	-40.79
6	12407.5	46.55	-53.77	3.57	-50.20	-13	-37.20
7	14180	48.94	-48.41	3.70	-44.71	-13	-31.71
8	15952.5	49.61	-47.74	3.70	-44.04	-13	-31.04
9	17725	50.89	-46.46	3.70	-42.76	-13	-29.76

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3545	43.04	-60.32	7.82	-52.51	-13	-39.51
2	5317.5	41.11	-64.18	7.25	-56.93	-13	-43.93
3	7090	42.71	-59.91	4.43	-55.48	-13	-42.48
4	8862.5	43.93	-57.68	4.18	-53.51	-13	-40.51
5	10635	53.83	-47.79	2.58	-45.21	-13	-32.21
6	12407.5	47.99	-52.33	3.57	-48.76	-13	-35.76
7	14180	53.84	-43.51	3.70	-39.81	-13	-26.81
8	15952.5	55.91	-41.44	3.70	-37.74	-13	-24.74
9	17725	45.80	-51.55	3.70	-47.85	-13	-34.85

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 66: 20MHz

Mode	TX channel 132072	Frequency Range	Above 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3440	38.56	-64.42	7.89	-56.53	-13	-43.53
2	5160	44.83	-60.72	7.36	-53.36	-13	-40.36
3	6880	47.46	-54.42	5.07	-49.34	-13	-36.34
4	8600	46.72	-57.19	4.35	-52.83	-13	-39.83
5	10320	45.16	-56.53	2.14	-54.39	-13	-41.39
6	12040	47.88	-54.43	4.24	-50.19	-13	-37.19
7	13760	50.22	-49.04	1.88	-47.16	-13	-34.16
8	15480	50.08	-47.27	3.70	-43.57	-13	-30.57
9	17200	50.77	-46.58	3.70	-42.88	-13	-29.88

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3440	43.78	-59.20	7.89	-51.31	-13	-38.31
2	5160	41.54	-64.01	7.36	-56.65	-13	-43.65
3	6880	41.23	-60.65	5.07	-55.57	-13	-42.57
4	8600	44.99	-58.92	4.35	-54.56	-13	-41.56
5	10320	54.78	-46.91	2.14	-44.77	-13	-31.77
6	12040	48.57	-53.74	4.24	-49.50	-13	-36.50
7	13760	53.72	-45.54	1.88	-43.66	-13	-30.66
8	15480	55.61	-41.74	3.70	-38.04	-13	-25.04
9	17200	46.15	-51.20	3.70	-47.50	-13	-34.50

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 132322	Frequency Range	Above 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3490	36.65	-66.51	7.85	-58.66	-13	-45.66
2	5235	44.26	-61.17	7.31	-53.86	-13	-40.86
3	6980	47.57	-55.05	4.99	-50.06	-13	-37.06
4	8725	48.42	-55.17	4.33	-50.84	-13	-37.84
5	10470	45.77	-55.89	2.35	-53.54	-13	-40.54
6	12215	47.74	-54.30	4.28	-50.02	-13	-37.02
7	13960	49.55	-49.40	2.17	-47.23	-13	-34.23
8	15705	50.93	-46.42	3.70	-42.72	-13	-29.72
9	17450	51.06	-46.29	3.70	-42.59	-13	-29.59

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3490	42.40	-60.76	7.85	-52.91	-13	-39.91
2	5235	39.98	-65.45	7.31	-58.14	-13	-45.14
3	6980	42.87	-59.75	4.99	-54.76	-13	-41.76
4	8725	44.17	-59.42	4.33	-55.09	-13	-42.09
5	10470	54.26	-47.40	2.35	-45.05	-13	-32.05
6	12215	47.43	-54.61	4.28	-50.33	-13	-37.33
7	13960	53.55	-45.40	2.17	-43.23	-13	-30.23
8	15705	55.86	-41.49	3.70	-37.79	-13	-24.79
9	17450	46.46	-50.89	3.70	-47.19	-13	-34.19

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 132572	Frequency Range	Above 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3540	38.48	-64.87	7.82	-57.04	-13	-44.04
2	5310	45.94	-59.36	7.25	-52.11	-13	-39.11
3	7080	47.57	-55.05	4.43	-50.62	-13	-37.62
4	8850	47.68	-53.93	4.18	-49.76	-13	-36.76
5	10620	45.24	-56.39	2.56	-53.83	-13	-40.83
6	12390	46.51	-53.81	3.57	-50.24	-13	-37.24
7	14160	48.79	-48.56	3.70	-44.86	-13	-31.86
8	15930	50.81	-46.54	3.70	-42.84	-13	-29.84
9	17700	51.52	-45.83	3.70	-42.13	-13	-29.13

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	3540	44.00	-59.35	7.82	-51.52	-13	-38.52
2	5310	41.76	-63.54	7.25	-56.29	-13	-43.29
3	7080	42.91	-59.71	4.43	-55.28	-13	-42.28
4	8850	45.47	-56.14	4.18	-51.97	-13	-38.97
5	10620	53.68	-47.95	2.56	-45.39	-13	-32.39
6	12390	48.37	-51.95	3.57	-48.38	-13	-35.38
7	14160	53.53	-43.82	3.70	-40.12	-13	-27.12
8	15930	56.33	-41.02	3.70	-37.32	-13	-24.32
9	17700	47.08	-50.27	3.70	-46.57	-13	-33.57

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 71: 5MHz

Mode	TX channel 133147	Frequency Range	Above 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1331	38.08	-65.91	5.81	-60.10	-13	-47.10
2	1996.5	40.79	-59.70	6.85	-52.85	-13	-39.85
3	2662	38.48	-62.44	6.94	-55.50	-13	-42.50
4	3327.5	40.86	-62.33	7.85	-54.49	-13	-41.49
5	3993	42.67	-62.16	7.44	-54.72	-13	-41.72
6	4658.5	37.12	-66.96	6.99	-59.97	-13	-46.97
7	5324	43.90	-60.92	7.05	-53.86	-13	-40.86
8	5989.5	48.34	-55.80	6.27	-49.53	-13	-36.53
9	6655	51.98	-50.04	4.97	-45.06	-13	-32.06

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1331	31.01	-72.98	5.81	-67.17	-13	-54.17
2	1996.5	39.27	-61.22	6.85	-54.37	-13	-41.37
3	2662	38.83	-62.09	6.94	-55.15	-13	-42.15
4	3327.5	37.68	-65.51	7.85	-57.67	-13	-44.67
5	3993	43.36	-61.47	7.44	-54.03	-13	-41.03
6	4658.5	43.72	-60.36	6.99	-53.37	-13	-40.37
7	5324	44.71	-60.11	7.05	-53.05	-13	-40.05
8	5989.5	39.48	-64.66	6.27	-58.39	-13	-45.39
9	6655	43.72	-58.30	4.97	-53.32	-13	-40.32

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 133297	Frequency Range	Above 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1361	38.24	-65.75	5.81	-59.94	-13	-46.94
2	2041.5	39.92	-60.57	6.85	-53.72	-13	-40.72
3	2722	37.79	-63.13	6.94	-56.19	-13	-43.19
4	3402.5	41.38	-61.81	7.85	-53.97	-13	-40.97
5	4083	42.96	-61.87	7.44	-54.43	-13	-41.43
6	4763.5	37.17	-66.91	6.99	-59.92	-13	-46.92
7	5444	43.10	-61.72	7.05	-54.66	-13	-41.66
8	6124.5	48.21	-55.93	6.27	-49.66	-13	-36.66
9	6805	52.39	-49.63	4.97	-44.65	-13	-31.65

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1361	31.68	-72.31	5.81	-66.50	-13	-53.50
2	2041.5	39.74	-60.75	6.85	-53.90	-13	-40.90
3	2722	39.43	-61.49	6.94	-54.55	-13	-41.55
4	3402.5	37.63	-65.56	7.85	-57.72	-13	-44.72
5	4083	42.70	-62.13	7.44	-54.69	-13	-41.69
6	4763.5	43.37	-60.71	6.99	-53.72	-13	-40.72
7	5444	44.78	-60.04	7.05	-52.98	-13	-39.98
8	6124.5	38.81	-65.33	6.27	-59.06	-13	-46.06
9	6805	43.56	-58.46	4.97	-53.48	-13	-40.48

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 133447	Frequency Range	Above 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1391	37.57	-66.42	5.81	-60.61	-13	-47.61
2	2086.5	41.65	-58.84	6.85	-51.99	-13	-38.99
3	2782	38.58	-62.34	6.94	-55.40	-13	-42.40
4	3477.5	40.79	-62.40	7.85	-54.56	-13	-41.56
5	4173	41.92	-62.91	7.44	-55.47	-13	-42.47
6	4868.5	37.62	-66.46	6.99	-59.47	-13	-46.47
7	5564	44.23	-60.59	7.05	-53.53	-13	-40.53
8	6259.5	48.04	-56.10	6.27	-49.83	-13	-36.83
9	6955	51.44	-50.58	4.97	-45.60	-13	-32.60

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1391	32.00	-71.99	5.81	-66.18	-13	-53.18
2	2086.5	39.16	-61.33	6.85	-54.48	-13	-41.48
3	2782	38.51	-62.41	6.94	-55.47	-13	-42.47
4	3477.5	37.63	-65.56	7.85	-57.72	-13	-44.72
5	4173	43.63	-61.20	7.44	-53.76	-13	-40.76
6	4868.5	44.45	-59.63	6.99	-52.64	-13	-39.64
7	5564	45.35	-59.47	7.05	-52.41	-13	-39.41
8	6259.5	40.27	-63.87	6.27	-57.60	-13	-44.60
9	6955	42.80	-59.22	4.97	-54.24	-13	-41.24

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 71: 10MHz

Mode	TX channel 133172	Frequency Range	Above 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1336	37.47	-57.81	9.25	-48.55	-13	-35.55
2	2004	41.11	-69.74	9.56	-60.18	-13	-47.18
3	2672	37.78	-59.05	8.65	-50.40	-13	-37.40
4	3340	41.54	-75.73	5.32	-70.41	-13	-57.41
5	4008	42.61	-60.34	-6.69	-67.03	-13	-54.03
6	4676	37.61	-76.04	2.64	-73.40	-13	-60.40
7	5344	43.17	-69.05	-10.50	-79.55	-13	-66.55
8	6012	49.22	-48.13	3.70	-44.43	-13	-31.43
9	6680	52.68	-44.67	3.70	-40.97	-13	-27.97

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1336	31.29	-63.99	9.25	-54.73	-13	-41.73
2	2004	38.76	-72.09	9.56	-62.53	-13	-49.53
3	2672	38.18	-58.65	8.65	-50.00	-13	-37.00
4	3340	37.72	-79.55	5.32	-74.23	-13	-61.23
5	4008	43.60	-59.35	-6.69	-66.04	-13	-53.04
6	4676	44.51	-69.14	2.64	-66.50	-13	-53.50
7	5344	44.34	-67.88	-10.50	-78.38	-13	-65.38
8	6012	39.57	-57.78	3.70	-54.08	-13	-41.08
9	6680	43.49	-53.86	3.70	-50.16	-13	-37.16

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 133297	Frequency Range	Above 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1361	37.43	-57.94	9.24	-48.70	-13	-35.70
2	2041.5	39.94	-70.85	9.54	-61.31	-13	-48.31
3	2722	38.01	-64.61	8.64	-55.97	-13	-42.97
4	3402.5	39.94	-77.17	5.31	-71.86	-13	-58.86
5	4083	43.41	-59.52	-6.59	-66.11	-13	-53.11
6	4763.5	37.77	-75.74	2.66	-73.08	-13	-60.08
7	5444	43.67	-68.40	-10.36	-78.75	-13	-65.75
8	6124.5	49.21	-48.14	3.70	-44.44	-13	-31.44
9	6805	51.01	-46.34	3.70	-42.64	-13	-29.64

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1361	31.44	-63.93	9.24	-54.69	-13	-41.69
2	2041.5	39.50	-71.29	9.54	-61.75	-13	-48.75
3	2722	39.68	-62.94	8.64	-54.30	-13	-41.30
4	3402.5	38.18	-78.93	5.31	-73.62	-13	-60.62
5	4083	43.84	-59.09	-6.59	-65.68	-13	-52.68
6	4763.5	43.31	-70.20	2.66	-67.54	-13	-54.54
7	5444	44.65	-67.42	-10.36	-77.77	-13	-64.77
8	6124.5	39.32	-58.03	3.70	-54.33	-13	-41.33
9	6805	43.33	-54.02	3.70	-50.32	-13	-37.32

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 133422	Frequency Range	Above 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1386	39.02	-56.44	9.22	-47.22	-13	-34.22
2	2079	39.87	-70.86	9.51	-61.35	-13	-48.35
3	2772	39.13	-63.49	4.43	-59.06	-13	-46.06
4	3465	40.29	-61.32	4.18	-57.15	-13	-44.15
5	4158	42.89	-60.03	-6.48	-66.51	-13	-53.51
6	4851	37.36	-62.96	3.57	-59.39	-13	-46.39
7	5544	43.60	-53.75	3.70	-50.05	-13	-37.05
8	6237	48.53	-48.82	3.70	-45.12	-13	-32.12
9	6930	52.21	-45.14	3.70	-41.44	-13	-28.44

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1386	31.26	-64.20	9.22	-54.98	-13	-41.98
2	2079	40.02	-70.71	9.51	-61.20	-13	-48.20
3	2772	38.28	-64.34	4.43	-59.91	-13	-46.91
4	3465	37.08	-64.53	4.18	-60.36	-13	-47.36
5	4158	44.22	-58.70	-6.48	-65.18	-13	-52.18
6	4851	44.22	-56.10	3.57	-52.53	-13	-39.53
7	5544	45.15	-52.20	3.70	-48.50	-13	-35.50
8	6237	40.20	-57.15	3.70	-53.45	-13	-40.45
9	6930	44.40	-52.95	3.70	-49.25	-13	-36.25

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 71: 15MHz

Mode	TX channel 133197	Frequency Range	Above 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1341	37.87	-66.12	5.81	-60.31	-13	-47.31
2	2011.5	41.18	-59.31	6.85	-52.46	-13	-39.46
3	2682	39.24	-61.68	6.94	-54.74	-13	-41.74
4	3352.5	40.68	-62.51	7.85	-54.67	-13	-41.67
5	4023	42.92	-61.91	7.44	-54.47	-13	-41.47
6	4693.5	37.52	-66.56	6.99	-59.57	-13	-46.57
7	5364	44.18	-60.64	7.05	-53.58	-13	-40.58
8	6034.5	48.57	-55.57	6.27	-49.30	-13	-36.30
9	6705	52.98	-49.04	4.97	-44.06	-13	-31.06

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1341	31.96	-72.03	5.81	-66.22	-13	-53.22
2	2011.5	38.59	-61.90	6.85	-55.05	-13	-42.05
3	2682	39.10	-61.82	6.94	-54.88	-13	-41.88
4	3352.5	36.72	-66.47	7.85	-58.63	-13	-45.63
5	4023	43.39	-61.44	7.44	-54.00	-13	-41.00
6	4693.5	43.77	-60.31	6.99	-53.32	-13	-40.32
7	5364	44.59	-60.23	7.05	-53.17	-13	-40.17
8	6034.5	38.61	-65.53	6.27	-59.26	-13	-46.26
9	6705	43.30	-58.72	4.97	-53.74	-13	-40.74

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 133297	Frequency Range	Above 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1361	37.53	-66.46	5.81	-60.65	-13	-47.65
2	2041.5	40.85	-59.64	6.85	-52.79	-13	-39.79
3	2722	38.15	-62.77	6.94	-55.83	-13	-42.83
4	3402.5	41.27	-61.92	7.85	-54.08	-13	-41.08
5	4083	43.58	-61.25	7.44	-53.81	-13	-40.81
6	4763.5	36.59	-67.49	6.99	-60.50	-13	-47.50
7	5444	43.82	-61.00	7.05	-53.94	-13	-40.94
8	6124.5	48.41	-55.73	6.27	-49.46	-13	-36.46
9	6805	51.32	-50.70	4.97	-45.72	-13	-32.72

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1361	30.54	-73.45	5.81	-67.64	-13	-54.64
2	2041.5	39.88	-60.61	6.85	-53.76	-13	-40.76
3	2722	37.87	-63.05	6.94	-56.11	-13	-43.11
4	3402.5	38.56	-64.63	7.85	-56.79	-13	-43.79
5	4083	43.76	-61.07	7.44	-53.63	-13	-40.63
6	4763.5	42.84	-61.24	6.99	-54.25	-13	-41.25
7	5444	45.44	-59.38	7.05	-52.32	-13	-39.32
8	6124.5	40.47	-63.67	6.27	-57.40	-13	-44.40
9	6805	44.42	-57.60	4.97	-52.62	-13	-39.62

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 133397	Frequency Range	Above 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1381	38.23	-65.76	5.81	-59.95	-13	-46.95
2	2071.5	40.09	-60.40	6.85	-53.55	-13	-40.55
3	2762	39.08	-61.84	6.94	-54.90	-13	-41.90
4	3452.5	40.66	-62.53	7.85	-54.69	-13	-41.69
5	4143	43.14	-61.69	7.44	-54.25	-13	-41.25
6	4833.5	36.96	-67.12	6.99	-60.13	-13	-47.13
7	5524	44.84	-59.98	7.05	-52.92	-13	-39.92
8	6214.5	47.35	-56.79	6.27	-50.52	-13	-37.52
9	6905	51.04	-50.98	4.97	-46.00	-13	-33.00

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1381	30.23	-73.76	5.81	-67.95	-13	-54.95
2	2071.5	38.41	-62.08	6.85	-55.23	-13	-42.23
3	2762	38.15	-62.77	6.94	-55.83	-13	-42.83
4	3452.5	37.48	-65.71	7.85	-57.87	-13	-44.87
5	4143	42.41	-62.42	7.44	-54.98	-13	-41.98
6	4833.5	44.29	-59.79	6.99	-52.80	-13	-39.80
7	5524	45.31	-59.51	7.05	-52.45	-13	-39.45
8	6214.5	39.50	-64.64	6.27	-58.37	-13	-45.37
9	6905	43.41	-58.61	4.97	-53.63	-13	-40.63

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 71: 20MHz

Mode	TX channel 133222	Frequency Range	Above 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1346	38.45	-65.54	5.81	-59.73	-13	-46.73
2	2019	40.59	-59.90	6.85	-53.05	-13	-40.05
3	2692	37.91	-63.01	6.94	-56.07	-13	-43.07
4	3365	40.66	-62.53	7.85	-54.69	-13	-41.69
5	4038	43.63	-61.20	7.44	-53.76	-13	-40.76
6	4711	36.42	-67.66	6.99	-60.67	-13	-47.67
7	5384	43.46	-61.36	7.05	-54.30	-13	-41.30
8	6057	49.30	-54.84	6.27	-48.57	-13	-35.57
9	6730	52.41	-49.61	4.97	-44.63	-13	-31.63

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1346	30.62	-73.37	5.81	-67.56	-13	-54.56
2	2019	40.15	-60.34	6.85	-53.49	-13	-40.49
3	2692	38.82	-62.10	6.94	-55.16	-13	-42.16
4	3365	38.34	-64.85	7.85	-57.01	-13	-44.01
5	4038	43.56	-61.27	7.44	-53.83	-13	-40.83
6	4711	42.94	-61.14	6.99	-54.15	-13	-41.15
7	5384	44.89	-59.93	7.05	-52.87	-13	-39.87
8	6057	39.61	-64.53	6.27	-58.26	-13	-45.26
9	6730	43.61	-58.41	4.97	-53.43	-13	-40.43

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 133297	Frequency Range	Above 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1361	38.28	-65.71	5.81	-59.90	-13	-46.90
2	2041.5	39.89	-60.60	6.85	-53.75	-13	-40.75
3	2722	38.73	-62.19	6.94	-55.25	-13	-42.25
4	3402.5	41.09	-62.10	7.85	-54.26	-13	-41.26
5	4083	42.22	-62.61	7.44	-55.17	-13	-42.17
6	4763.5	37.82	-66.26	6.99	-59.27	-13	-46.27
7	5444	44.68	-60.14	7.05	-53.08	-13	-40.08
8	6124.5	48.81	-55.33	6.27	-49.06	-13	-36.06
9	6805	52.35	-49.67	4.97	-44.69	-13	-31.69

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1361	30.77	-73.22	5.81	-67.41	-13	-54.41
2	2041.5	38.87	-61.62	6.85	-54.77	-13	-41.77
3	2722	37.90	-63.02	6.94	-56.08	-13	-43.08
4	3402.5	36.79	-66.40	7.85	-58.56	-13	-45.56
5	4083	42.72	-62.11	7.44	-54.67	-13	-41.67
6	4763.5	44.44	-59.64	6.99	-52.65	-13	-39.65
7	5444	44.47	-60.35	7.05	-53.29	-13	-40.29
8	6124.5	39.75	-64.39	6.27	-58.12	-13	-45.12
9	6805	43.18	-58.84	4.97	-53.86	-13	-40.86

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 133372	Frequency Range	Above 1000 MHz
------	-------------------	-----------------	----------------

Antenna Polarity & Test Distance: Horizontal at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1376	37.99	-66.00	5.81	-60.19	-13	-47.19
2	2064	41.24	-59.25	6.85	-52.40	-13	-39.40
3	2752	39.38	-61.54	6.94	-54.60	-13	-41.60
4	3440	41.16	-62.03	7.85	-54.19	-13	-41.19
5	4128	42.06	-62.77	7.44	-55.33	-13	-42.33
6	4816	37.31	-66.77	6.99	-59.78	-13	-46.78
7	5504	43.59	-61.23	7.05	-54.17	-13	-41.17
8	6192	47.80	-56.34	6.27	-50.07	-13	-37.07
9	6880	51.31	-50.71	4.97	-45.73	-13	-32.73

Antenna Polarity & Test Distance: Vertical at 3 M

No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	Emission Value (dBm)	Limit (dBm)	Margin (dB)
1	1376	31.36	-72.63	5.81	-66.82	-13	-53.82
2	2064	39.45	-61.04	6.85	-54.19	-13	-41.19
3	2752	39.19	-61.73	6.94	-54.79	-13	-41.79
4	3440	37.38	-65.81	7.85	-57.97	-13	-44.97
5	4128	42.61	-62.22	7.44	-54.78	-13	-41.78
6	4816	43.79	-60.29	6.99	-53.30	-13	-40.30
7	5504	44.01	-60.81	7.05	-53.75	-13	-40.75
8	6192	39.49	-64.65	6.27	-58.38	-13	-45.38
9	6880	43.25	-58.77	4.97	-53.79	-13	-40.79

Remarks:

1. Emission Value (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

5 Pictures of Test Arrangements

Please refer to the attached file (Test Setup Photo).

Appendix – Information on the Testing Laboratories

We, Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch, were founded in 1988 to provide our best service in EMC, Radio, Telecom and Safety consultation. Our laboratories are accredited and approved according to ISO/IEC 17025.

If you have any comments, please feel free to contact us at the following:

Linko EMC/RF Lab

Tel: 886-2-26052180

Fax: 886-2-26051924

Hsin Chu EMC/RF Lab/Telecom Lab

Tel: 886-3-6668565

Fax: 886-3-6668323

Hwa Ya EMC/RF/Safety

Tel: 886-3-3183232

Fax: 886-3-3270892

Email: service.adt@tw.bureauveritas.com

Web Site: www.bureauveritas-adt.com

The address and road map of all our labs can be found in our web site also.

--- END ---