

APPLICANT: SHINWOO TELECOM CO., LTD.

FCC ID: MQUST-946A

TABLE OF CONTENTS

TEST REPORT CONTAINING:

PAGE 1.....15.214(d) - SECURITY CODING INFORMATION AND TEST PROC.
PAGE 2.....TEST PROCEDURE CONTINUED
PAGE 3-4.....CIRCUIT DESCRIPTIONS
PAGE 5.....RADIATION INTERFERENCE TEST DATA - BASE
PAGE 6.....RADIATION INTERFERENCE TEST DATA - HANDSET
PAGE 7.....OCCUPIED BANDWIDTH TEST DATA
PAGE 8.....POWERLINE CONDUCTED TEST DATA

EXHIBITS CONTAINING:

EXHIBIT 1.....POWER OF ATTORNEY LETTER
EXHIBIT 2.....BLOCK DIAGRAM - BASE MAIN
EXHIBIT 3.....BLOCK DIAGRAM - BASE RF
EXHIBIT 4.....BLOCK DIAGRAMS - HANDSET RF
EXHIBIT 5.....SCHEMATIC - BASE MAIN
EXHIBIT 6.....SCHEMATIC - BASE RF
EXHIBIT 7.....SCHEMATIC - HANDSET MAIN
EXHIBIT 8.....SCHEMATIC - HANDSET RF
EXHIBIT 9.....FCC ID LABEL SAMPLES
EXHIBIT 10.....SKETCH OF FCC ID LABEL LOCATION - BASE
EXHIBIT 11.....SKETCH OF FCC ID LABEL LOCATION - HANDSET
EXHIBIT 12.....EXTERNAL PHOTO TOP/FRONT VIEW TELEPHONE SET
EXHIBIT 13.....EXTERNAL PHOTO FRONT VIEW HANDSET AND BASE
EXHIBIT 14.....EXTERNAL PHOTO REAR VIEW HANDSET AND BASE
EXHIBIT 15.....INTERNAL PHOTO - SOLDER HANDSET, COMPONENT BASE
EXHIBIT 16.....INTERNAL PHOTO - COMPONENT HANDSET, SOLDER BASE
EXHIBIT 17A-17U....INSTRUCTION MANUAL
EXHIBIT 18A....POWERLINE CONDUCTED INTERFERENCE PLOT - LINE 1
EXHIBIT 18B....POWERLINE CONDUCTED INTEFERENCE PLOT - LINE 2
EXHIBIT 19A....OCCUPIED BANDWIDTH PLOT - HANDSET - NO MODULATION
EXHIBIT 19B....OCCUPIED BANDWIDTH PLOT - HANDSET - LOUD VOICE
EXHIBIT 19C....OCCUPIED BANDWIDTH PLOT - BASE - MODULATED 2500 Hz
EXHIBIT 19D....OCCUPIED BANDWIDTH PLOT - BASE - NO MODULATION

APPLICANT: SHINWOO TELECOM CO., LTD.

FCC ID: MQUST-946A

REPORT #: F:S\SHINWOO\SHI330B8.RPT

PAGE: TABLE OF CONTENTS

SECURITY CODING INFORMATION

15.214(d) - THIS DEVICE COMPLIES WITH THE SECURITY CODE REQUIREMENTS OF 15.214(d)(1)(2) AND (3) BY MEANS OF THE FOLLOWING:

THIS PHONE IS EQUIPPED WITH A DIGITAL SECURITY SYSTEM WITH OVER 1 MILLION CODE COMBINATIONS.

WHEN MAKING A CALL, THE TELEPHONE SEARCHES THROUGH ITS 60 AVAILABLE CHANNELS AUTO CHANNEL SCAN TO FIND THE CLEAREST ONE.

THE RECEIVER PORTION OF THIS TELEPHONE, FCC ID: MQUST-946A, WAS TESTED WITH PASSING RESULTS. A VERIFICATION REPORT HAS BEEN ISSUED PER FCC RULES PART 15.109.

TEST EQUIPMENT LIST

1. Spectrum Analyzer: Hewlett Packard 8566B - Opt 462, w/ preselector 85685A, & Quasi-Peak Adapter HP 85650A, & HP 8449B - OPT H02 Cal. 6/26/98
2. Signal Generator, Hewlett Packard 8640B, cal. 10/1/98
3. Eaton Biconical Antenna Model 94455-1
20-200 MHz Serial No. 0997 Cal. 5/15/98
4. Electro-Metric Dipole Kit, 20-1000 MHz, Model TDA-30 10/15/98
5. Electro-Metric Horn 1-18 GHz, Model RGA-180, Cal. 8/15/98
6. Electro-Metric Antennas Model TDS-25-1, TDS-25-2, 5/15/97
7. Electro-Metric Line Impedance Stabilization Network Model No. EM-7821, Serial No. 101; 100KHz-30MHz 50uH. 12/3/97
8. Electro-Metric Line Impedance Stabilization Network Model No. EM-7820, Serial No. 2682; 10KHz-30MHz 50uH. 12/3/97
9. Special low loss cable was used above 1 GHz
10. Tenney Temperature Chamber

TEST PROCEDURE

GENERAL: This report shall NOT be reproduced except in full without the written approval of TIMCO ENGINEERING, INC.

RADIATION INTERFERENCE: The test procedure used was ANSI STANDARD C63.4-1992 using a HEWLETT PACKARD spectrum analyzer with a preselector. The bandwidth of the spectrum analyzer was 100 kHz with an appropriate sweep speed. The analyzer was calibrated in dB above a microvolt at the output of the antenna. The resolution bandwidth was 100KHz and the video bandwidth was 300KHz. The ambient temperature of the UUT was 53oF with a humidity of 70%.

APPLICANT: SHINWOO TELECOM CO., LTD.

FCC ID: MQUST-946A

REPORT #: F:S\SHINWOO\SHI330B8.RPT

PAGE #: 1

TEST PROCEDURE (CONT)

ANSI STANDARD C63.4-1992 10.1.7 MEASUREMENT PROCEDURES: The UUT was placed on a table 80 cm high and with dimensions of 1m by 1.5m. The UUT was placed flush with the back of the table (1.5m side). The table used for radiated measurements is capable of continuous rotation.

When an emission was found, the table was rotated to produce the maximum signal strength. At this point, the antenna was raised and lowered from 1m to 4m. The antenna was placed in both the horizontal and vertical planes.

The situation was similar for the conducted measurement except that the table did not rotate. The EUT was setup as described in ANSIC63.4-1992 with the EUT 40 cm from the vertical ground wall.

FORMULA OF CONVERSION FACTORS: The Field Strength at 3m was established by adding the meter reading of the spectrum analyzer (which is set to read in units of dBuV) to the antenna correction factor supplied by the antenna manufacturer. The antenna correction factors are stated in terms of dB. The gain of the Preselector was accounted for in the Spectrum Analyzer Meter Reading.

Example:

Freq (MHz) METER READING + ACF = FS
33 20 dBuV + 10.36 dB = 30.36 dBuV/m @ 3m

POWER LINE CONDUCTED INTERFERENCE: The procedure used was ANSI STANDARD C63.4-1992 using a 50uH LISN. Both lines were observed. The bandwidth of the spectrum analyzer was 10kHz with an appropriate sweep speed. The ambient temperature of the UUT was 53oF with a humidity of 70%.

APPLICANT: SHINWOO TELECOM CO., LTD.
FCC ID: MQUST-946A

CIRCUIT_DESCRIPTION:

BASE UNIT

The incoming signal comes in on the antenna and is fed through the duplexer to the LNA, Q500 and then to a SAW band pass filter, FL501. The frequency range of the base receiver is 925-928MHz. From the band pass filter the signal is fed to the mixer, Q501 which converts the signal down to 10.7MHz. From Q501 the signal is fed to the IF filter FL501 and then to the integrated circuit U500. In the U500 the signal is converted down to 450KHz and then to the detector for FM signal. From the detector the audio is fed to a low pass filter and to the Channel Detector Indicator. From the low pass filter the audio is fed into another low pass filter and shaper and then to the CPU, U311. From the CPU, U311, the audio is fed to a speaker amplifier and the telephone line depending which is selected. From the CPU the line audio is fed to IC8 and then to Q3 then to IC3D and then to Q8 and then the telephone coupling transformer, T1. The CPU also compares the SECURITY CODES and provides the outgoing SECURITY CODE.

On the transmitting side, when a ring signal is detected the transmitter is turned on by photo complier integrated circuit U301 and the ring detect signal is fed into the CPU, IC8, which in turn triggers the transmitter and send a ring signal to the handset. The base transmit frequency range is 902-906MHz. When the handset answers the base unit connects to the phone line and telephone line audio is fed into the speech network and then to an audio amplifier, IC3A. The audio is then fed into the compressor IC1. From IC1 the audio is fed into the VCO, Q505 which modulated the outgoing carrier. From the VCO the signal is fed through a series of amplifiers, Q505 & Q504. From Q504 the signal is fed to the antenna.

APPLICANT: SHINWOO TELECOM CO., LTD.
FCC ID: MQUST-946A
REPORT #: F:S\SHINWOO\SHI330B8.RPT
PAGE #: 3

APPLICANT: SHINWOO TELECOM CO., LTD.
FCC ID: MQUST-946A

CIRCUIT_DESCRIPTIONS CONTD.

HANDSET

The incoming signal comes in on the antenna and is fed through the duplexer to the LNA, Q300 and then to the tuned band pass circuit. The frequency range of the handset receiver is 902-906MHz. From the band pass filter the signal is fed to the mixer, Q301 which converts the signal down to 10.7MHz. From Q301 the signal is fed to the IF filter FL301 and then to the integrated circuit U300. In the U300 the signal is converted down to 450KHz and then to the detector for FM signal. From the detector, p/o U100 the audio is fed to the MPU which performs the RING Detector function and triggers the Ring Indicator. From the low pass filter the audio is fed simultaneously to the earphone element and to the MPU, IC6. The earphone audio is fed into IC6 and then to the receiver element, RC1. The MPU uses the data to continuously monitor the security code.

The transmitter frequency range is 926-928MHz. The outgoing audio is picked up by the microphone and fed to the audio integrated circuit IC8A. This audio integrated circuit feeds an additional amplifier IC7 and then to a low pass filter then feed the signal to the VCO, Q305. From the VCO the signal is fed in to the amplifier Q305 and Q304 to the duplexer and then to the antenna.

ANTENNA_AND_GROUND_CIRCUITRY

This unit makes use of a short, antenna. The antenna is inductively coupled. The antenna is self contained, no provision is made for an external antenna.

No ground connection is provided. The unit relies on the ground tract of the printed circuit board.

APPLICANT: SHINWOO TELECOM CO., LTD.
FCC ID: MQUST-946A
REPORT #: F:S\SHINWOO\SHI330B8.RPT
PAGE #: 4

APPLICANT: SHINWOO TELECOM CO., LTD.

FCC ID: MQUST-946A (BASE)

NAME OF TEST: RADIATION INTERFERENCE

RULES PART NO.: 15.249

REQUIREMENTS: Carrier frequency will not exceed 94.0 dBuV/m

| FREQUENCY | LEVEL |
|---------------|----------------|
| ____MHz____ | ____dBuV/M____ |
| 902- 928 MHz | 54.0 dBuV/M |
| ABOVE 960 MHz | 54.0 dBuV/M |

TEST DATA:

| EMISSION FREQUENCY | METER READING AT 3 METERS | COAX LOSS | ANTENNA CORRECTION FACTOR | FIELD STRENGTH dBuV/m@3m | MARGIN dB | ANT. POL. |
|--------------------------------|---------------------------|-----------|---------------------------|--------------------------|-----------|-----------|
| MHz | dBuV | dB | | | | |
| BASE TUNED FREQUENCY 902.39MHz | | | | | | |
| 902.39 | 45.80 | 2.90 | 24.19 | 72.89 | 21.11 | H |
| 1804.78 | 9.30 | 1.00 | 27.22 | 37.52 | 16.48 | V |
| 2707.17 | 0.70 | 1.14 | 29.77 | 31.60 | 22.40 | V |
| 3609.56 | 0.10 | 1.27 | 32.02 | 33.40 | 20.60 | V |
| 4511.95 | 0.30 | 1.41 | 33.58 | 35.28 | 18.72 | H |
| 5414.34 | 0.30 | 1.54 | 34.59 | 36.43 | 17.57 | V |
| 6316.73 | 2.60 | 1.68 | 35.61 | 39.88 | 14.12 | V |
| 7219.12 | 2.10 | 1.81 | 36.62 | 40.54 | 13.46 | V |
| 8121.51 | 2.50 | 1.95 | 37.57 | 42.02 | 11.98 | V |
| 9023.90 | 1.90 | 2.05 | 38.18 | 42.13 | 11.87 | V |
| BASE TUNED FREQUENCY 905.09MHz | | | | | | |
| 905.09 | 49.80 | 2.90 | 24.18 | 76.88 | 17.12 | H |
| 1810.18 | 11.00 | 1.00 | 27.24 | 39.24 | 14.76 | H |
| 2715.27 | 1.40 | 1.14 | 29.79 | 32.33 | 21.67 | H |
| 3620.36 | 1.00 | 1.27 | 32.05 | 34.32 | 19.68 | H |
| 4525.45 | 0.60 | 1.41 | 33.59 | 35.60 | 18.40 | V |
| 5430.54 | 1.30 | 1.55 | 34.61 | 37.45 | 16.55 | V |
| 6332.63 | 1.70 | 1.68 | 35.62 | 39.00 | 15.00 | V |
| 7240.72 | 3.20 | 1.82 | 36.65 | 41.66 | 12.34 | H |
| 8145.81 | 3.30 | 1.95 | 37.59 | 42.84 | 11.16 | V |
| 9050.90 | 2.90 | 2.06 | 38.19 | 43.15 | 10.85 | V |

SAMPLE CALCULATION: $FS_{dBuV/m} = MR_{(dBuV)} + ACF_{dB}$.

METHOD OF MEASUREMENT: The procedure used was ANSI STANDARD. Measurements were made at Timco Engineering, Inc. 6051 N.W. 19th Lane, Gainesville, FL 32605.

TEST RESULTS: The unit DOES meet the FCC requirements.

PERFORMED BY: _____ DATE: 12/17/98

REPORT #: F:S\SHINWOO\SHI330B8.RPT
PAGE #: 5

APPLICANT: SHINWOO TELECOM CO., LTD.

FCC ID: MQUEST-946A (HANDSET)

NAME OF TEST: RADIATION INTERFERENCE PAGE 1 OF 1

RULES PART NO.: 15.249

REQUIREMENTS: Carrier frequency will not exceed 94.0 dBuV/m

| FREQUENCY | LEVEL |
|---------------|-------------|
| MHz | dBuV/M |
| 902- 928 MHz | 54.0 dBuV/M |
| ABOVE 960 MHz | 54.0 dBuV/M |

TEST DATA:

| EMISSION FREQUENCY | METER READING AT 3 METERS | COAX LOSS | ANTENNA CORRECTION FACTOR | FIELD STRENGTH dBuV/m@3m | MARGIN dB | ANT. POL. |
|-----------------------------------|---------------------------|-----------|---------------------------|--------------------------|-----------|-----------|
| MHz | dBuV | dB | | | | |
| HANDSET TUNED FREQUENCY 925.11MHz | | | | | | |
| 925.11 | 58.00 | 2.90 | 24.10 | 85.00 | 9.00 | V |
| 1850.22 | 13.20 | 1.01 | 27.40 | 41.61 | 12.39 | V |
| 2775.33 | 0.60 | 1.15 | 29.94 | 31.68 | 22.32 | V |
| 3700.44 | 0.50 | 1.29 | 32.25 | 34.04 | 19.96 | V |
| 4625.55 | 0.50 | 1.42 | 33.70 | 35.63 | 18.37 | V |
| 5550.66 | 0.80 | 1.56 | 34.74 | 37.11 | 16.89 | V |
| 6475.77 | 3.00 | 1.70 | 35.79 | 40.49 | 13.51 | V |
| 7400.88 | 1.20 | 1.84 | 36.83 | 39.87 | 14.13 | V |
| 7400.88 | 1.20 | 1.84 | 36.83 | 39.87 | 14.13 | V |
| 8325.99 | 2.50 | 1.98 | 37.71 | 42.19 | 11.81 | V |
| 9251.10 | 2.20 | 2.07 | 38.33 | 42.60 | 11.40 | V |
| HANDSET TUNED FREQUENCY 927.84MHz | | | | | | |
| 927.84 | 57.90 | 2.90 | 24.12 | 84.92 | 9.08 | V |
| 1855.68 | 8.70 | 1.01 | 27.42 | 37.13 | 16.87 | H |
| 2783.52 | 2.10 | 1.15 | 29.96 | 33.21 | 20.79 | V |
| 3711.36 | 0.70 | 1.29 | 32.28 | 34.27 | 19.73 | H |
| 4639.20 | 0.50 | 1.43 | 33.72 | 35.65 | 18.35 | V |
| 5567.04 | 0.70 | 1.57 | 34.76 | 37.03 | 16.97 | V |
| 6494.88 | 3.00 | 1.70 | 35.81 | 40.51 | 13.49 | V |
| 7422.72 | 1.90 | 1.84 | 36.85 | 40.59 | 13.41 | V |
| 8350.56 | 2.50 | 1.98 | 37.72 | 42.21 | 11.79 | V |
| 9278.40 | 2.40 | 2.08 | 38.35 | 42.82 | 11.18 | V |

SAMPLE CALCULATION: $FS_{dBuV/m} = MR_{(dBuV)} + ACF_{dB}$.

METHOD OF MEASUREMENT: The procedure used was ANSI STANDARD C63.4-1992 with the following exception: the unit was operated into its own antenna with the antenna at a height of four feet. Measurements were made at Timco Engineering, Inc. 6051 N.W. 19th Lane, Gainesville, FL 32605.

TEST RESULTS: The unit DOES meet the FCC requirements.

PERFORMED BY: _____ DATE: 12/17/98

REPORT #: F:S\SHINWOO\SHI330B8.RPT
PAGE #: 6

APPLICANT: SHINWOO TELECOM CO., LTD.

FCC ID: MQUEST-946A

NAME OF TEST: Occupied Bandwidth

RULES PART NO.: 15.233

REQUIREMENTS: The field strength of any emissions appearing between the band edges and up to 10 kHz above and below the band edges shall be attenuated at least 26 dB below the level of the unmodulated carrier or to the general limits of 15.209, whichever permits the higher emission levels.

THE GRAPHS IN EXHIBITS 18A-18B REPRESENT THE EMISSIONS TAKEN FOR THIS DEVICE.

METHOD OF MEASUREMENT: A small sample of the transmitter output was fed into the spectrum analyzer and the above photo was taken. The vertical scale is set to -10 dBm per division. The horizontal scale is set to 5 kHz per division.

TEST RESULTS: The unit DOES meet the FCC requirements.

PERFORMED BY: _____ 12/17/98

APPLICANT: SHINWOO TELECOM CO., LTD.
FCC ID: MQUEST-946A
REPORT #: F:S\SHINWOO\SHI330B8.RPT
PAGE #: 7

APPLICANT: SHINWOO TELECOM CO., LTD.

FCC ID: MQUEST-946A

NAME OF TEST: POWER LINE CONDUCTED INTERFERENCE

RULES PART NUMBER: 15.207

MINIMUM REQUIREMENTS: FREQUENCY LEVEL
 MHz uV
 0.450-30 250

TEST PROCEDURE: ANSI STANDARD C63.4-1992

THE HIGHEST EMISSION READ FOR LINE 1 WAS 24.237 uV @ 1.22 MHz.

THE HIGHEST EMISSION READ FOR LINE 2 WAS 9.005 uV @ 800 kHz.

THE GRAPHS IN EXHIBITS 19A-19D REPRESENT THE EMISSIONS READ FOR POWERLINE CONDUCTED FOR THIS DEVICE.

TEST RESULTS: Both lines were observed. The measurements indicate that the unit DOES appear to meet the FCC requirements for this class of equipment.

PERFORMED BY: _____ DATE: 12/17/98

APPLICANT: SHINWOO TELECOM CO., LTD.
FCC ID: MQUEST-946A
REPORT #: F:S\SHINWOO\SHI330B8.RPT
PAGE #: 8