

# RF Exposure Evaluation declaration

Product Name : Wireless-AC1900 Dual Band Gigabit Router  
Model No. : RT-AC68U, RT-AC68R  
FCC ID. : MSQ-RTAC68U

Applicant : ASUSTeK COMPUTER INC.

Address : 4F, No. 150, Li-Te Rd., Peitou, Taipei, Taiwan

Date of Receipt : 2014/01/22

Date of Declaration : 2014/01/23

Report No. : 1410433R-RF-US-Exp

Report Version : V1.0



The declaration results relate only to the samples calculated.

The declaration shall not be reproduced except in full without the written approval of Quietek Corporation.

## 1. RF Exposure Evaluation

### 1.1. Limits

According to FCC 1.1310: The criteria listed in the following table shall be used to evaluate the environment impact of human exposure to radio frequency (RF) radiation as specified in 1.1307(b)

#### LIMITS FOR MAXIMUM PERMISSIBLE EXPOSURE (MPE)

Frequency Range (MHz)	Electric Field Strength (V/m)	Magnetic Field Strength (A/m)	Power Density (mW/cm <sup>2</sup> )	Average Time (Minutes)
(A) Limits for Occupational/ Control Exposures				
300-1500	--	--	F/300	6
1500-100,000	--	--	5	6
(B) Limits for General Population/ Uncontrolled Exposures				
300-1500	--	--	F/1500	6
1500-100,000	--	--	1	30

F= Frequency in MHz

Friis Formula

Friis transmission formula:  $P_d = (P_{out} * G) / (4 * \pi * r^2)$

Where

$P_d$  = power density in mW/cm<sup>2</sup>

$P_{out}$  = output power to antenna in mW

G = gain of antenna in linear scale

$\pi$  = 3.1416

R = distance between observation point and center of the radiator in cm

$P_d$  is the limit of MPE, 1 mW/cm<sup>2</sup>. If we know the maximum gain of the antenna and the total power input to the antenna, through the calculation, we will know the distance r where the MPE limit is reached.

### 1.2. Test Procedure

Software provided by client enabled the EUT to transmit and receive data at lowest, middle and highest channel individually.

The temperature and related humidity: 18°C and 78% RH.

### 1.3. Test Result of RF Exposure Evaluation

Product	Wireless-AC1900 Dual Band Gigabit Router
Test Mode	Transmit (CDD Mode)
Test Condition	RF Exposure Evaluation

#### Antenna Gain

Antenna Gain: The maximum Gain measured in fully anechoic chamber is 1.91dBi or 1.55 in linear scale.

#### Output Power into Antenna & RF Exposure Evaluation Distance:

IEEE 802.11b			
WLAN Function			
Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density at R = 20 cm (mW/cm <sup>2</sup> )
1	2412	220.8005	0.06809
6	2437	246.6039	0.07604
11	2462	338.8442	0.10449

IEEE 802.11g			
WLAN Function			
Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density at R = 20 cm (mW/cm <sup>2</sup> )
1	2412	255.8586	0.07890
6	2437	765.5966	0.23608
11	2462	191.4256	0.05903

The power density Pd (4th column) at a distance of 20 cm calculated from the Friis transmission formula is far below the limit of 1 mW/cm<sup>2</sup>.

Product	Wireless-AC1900 Dual Band Gigabit Router
Test Mode	Transmit (CDD Mode)
Test Condition	RF Exposure Evaluation

### Antenna Gain

Antenna Gain: The maximum Gain measured in fully anechoic chamber is 1.91dBi or 1.55 in linear scale.

### Output Power into Antenna & RF Exposure Evaluation Distance:

IEEE 802.11n (20MHz) ANT 0+1+2			
WLAN Function			
Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density at R = 20 cm (mW/cm <sup>2</sup> )
1	2412	176.1976	0.05433
6	2437	599.7911	0.18495
11	2462	165.1962	0.05094

IEEE 802.11n (40MHz) ANT 0+1+2			
WLAN Function			
Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density at R = 20 cm (mW/cm <sup>2</sup> )
3	2422	133.3521	0.04192
6	2437	220.8005	0.06940
9	2452	107.8947	0.03391

The power density Pd (4th column) at a distance of 20 cm calculated from the Friis transmission formula is far below the limit of 1 mW/cm<sup>2</sup>.

Product	Wireless-AC1900 Dual Band Gigabit Router
Test Mode	Transmit (CDD Mode)
Test Condition	RF Exposure Evaluation

### Antenna Gain

Antenna Gain: The maximum Gain measured in fully anechoic chamber is 4.04dBi or 2.54 in linear scale.

### Output Power into Antenna & RF Exposure Evaluation Distance:

IEEE 802.11a			
WLAN Function			
Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density at R = 20 cm (mW/cm <sup>2</sup> )
36	5180	16.4816	0.00833
44	5220	17.0608	0.00862
48	5240	16.5196	0.00835

IEEE 802.11a			
WLAN Function			
Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density at R = 20 cm (mW/cm <sup>2</sup> )
149	5745	831.7638	0.42030
157	5785	939.7233	0.47486
165	5825	905.7326	0.45768

The power density Pd (4th column) at a distance of 20 cm calculated from the Friis transmission formula is far below the limit of 1 mW/cm<sup>2</sup>.

Product	Wireless-AC1900 Dual Band Gigabit Router
Test Mode	Transmit (CDD Mode)
Test Condition	RF Exposure Evaluation

### Antenna Gain

Antenna Gain: The maximum Gain measured in fully anechoic chamber is 4.04dBi or 2.54 in linear scale.

### Output Power into Antenna & RF Exposure Evaluation Distance:

IEEE 802.11 n(20MHz) ANT 0+1+2			
WLAN Function			
Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density at R = 20 cm (mW/cm <sup>2</sup> )
36	5180	16.7109	0.00844
44	5220	16.3305	0.00825
48	5240	16.8267	0.00850

IEEE 802.11 n(20MHz) ANT 0+1+2			
WLAN Function			
Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density at R = 20 cm (mW/cm <sup>2</sup> )
149	5745	801.6781	0.40510
157	5785	957.1941	0.48369
165	5825	933.2543	0.47159

The power density Pd (4th column) at a distance of 20 cm calculated from the Friis transmission formula is far below the limit of 1 mW/cm<sup>2</sup>.

Product	Wireless-AC1900 Dual Band Gigabit Router
Test Mode	Transmit (CDD Mode)
Test Condition	RF Exposure Evaluation

### Antenna Gain

Antenna Gain: The maximum Gain measured in fully anechoic chamber is 4.04dBi or 2.54 in linear scale.

### Output Power into Antenna & RF Exposure Evaluation Distance:

IEEE 802.11 n(40MHz) ANT 0+1+2			
WLAN Function			
Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density at R = 20 cm (mW/cm <sup>2</sup> )
38	5190	37.6704	0.01904
46	5230	35.9749	0.01818

IEEE 802.11 n(40MHz) ANT 0+1+2			
WLAN Function			
Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density at R = 20 cm (mW/cm <sup>2</sup> )
151	5755	695.0243	0.35121
159	5795	895.3648	0.45244

The power density Pd (4th column) at a distance of 20 cm calculated from the Friis transmission formula is far below the limit of 1 mW/cm<sup>2</sup>.

Product	Wireless-AC1900 Dual Band Gigabit Router
Test Mode	Transmit (CDD Mode)
Test Condition	RF Exposure Evaluation

**Antenna Gain**

Antenna Gain: The maximum Gain measured in fully anechoic chamber is 4.04dBi or 2.54 in linear scale.

**Output Power into Antenna & RF Exposure Evaluation Distance:**

IEEE 802.11 ac(80MHz) ANT 0+1+2			
WLAN Function			
Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density at R = 20 cm (mW/cm <sup>2</sup> )
42	5210	47.9733	0.02424

IEEE 802.11 ac(80MHz) ANT 0+1+2			
WLAN Function			
Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density at R = 20 cm (mW/cm <sup>2</sup> )
155	5775	454.9881	0.22991

The power density Pd (4th column) at a distance of 20 cm calculated from the Friis transmission formula is far below the limit of 1 mW/cm<sup>2</sup>.



Product	Wireless-AC1900 Dual Band Gigabit Router
Test Mode	Transmit (Beamforming Mode)
Test Condition	RF Exposure Evaluation

### Antenna Gain

Antenna Gain: The maximum Gain measured in fully anechoic chamber is 1.91dBi or 1.55 in linear scale.

### Output Power into Antenna & RF Exposure Evaluation Distance:

IEEE 802.11b			
WLAN Function			
Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density at R = 20 cm (mW/cm <sup>2</sup> )
1	2412	187.4995	0.05782
6	2437	189.2344	0.05835
11	2462	154.5254	0.04765

IEEE 802.11g			
WLAN Function			
Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density at R = 20 cm (mW/cm <sup>2</sup> )
1	2412	97.2747	0.03000
6	2437	317.6874	0.09796
11	2462	68.3912	0.02109

The power density Pd (4th column) at a distance of 20 cm calculated from the Friis transmission formula is far below the limit of 1 mW/cm<sup>2</sup>.

Product	Wireless-AC1900 Dual Band Gigabit Router
Test Mode	Transmit (Beamforming Mode)
Test Condition	RF Exposure Evaluation

### Antenna Gain

Antenna Gain: The maximum Gain measured in fully anechoic chamber is 1.91dBi or 1.55 in linear scale.

### Output Power into Antenna & RF Exposure Evaluation Distance:

IEEE 802.11n (20MHz) ANT 0+1+2			
WLAN Function			
Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density at R = 20 cm (mW/cm <sup>2</sup> )
1	2412	171.0015	0.05273
6	2437	522.3962	0.16109
11	2462	147.2313	0.04540

IEEE 802.11n (40MHz) ANT 0+1+2			
WLAN Function			
Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density at R = 20 cm (mW/cm <sup>2</sup> )
3	2422	119.1791	0.03675
6	2437	177.1740	0.05463
9	2452	78.8860	0.02433

The power density Pd (4th column) at a distance of 20 cm calculated from the Friis transmission formula is far below the limit of 1 mW/cm<sup>2</sup>.

Product	Wireless-AC1900 Dual Band Gigabit Router
Test Mode	Transmit (Beamforming Mode)
Test Condition	RF Exposure Evaluation

### Antenna Gain

Antenna Gain: The maximum Gain measured in fully anechoic chamber is 4.04dBi or 2.54 in linear scale.

### Output Power into Antenna & RF Exposure Evaluation Distance:

IEEE 802.11a			
WLAN Function			
Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density at R = 20 cm (mW/cm <sup>2</sup> )
36	5180	21.4783	0.01085
44	5220	20.8930	0.01056
48	5240	21.0863	0.01066

IEEE 802.11a			
WLAN Function			
Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density at R = 20 cm (mW/cm <sup>2</sup> )
149	5745	386.3670	0.19524
157	5785	399.9447	0.20210
165	5825	377.5722	0.19079

The power density Pd (4th column) at a distance of 20 cm calculated from the Friis transmission formula is far below the limit of 1 mW/cm<sup>2</sup>.

Product	Wireless-AC1900 Dual Band Gigabit Router
Test Mode	Transmit (Beamforming Mode)
Test Condition	RF Exposure Evaluation

### Antenna Gain

Antenna Gain: The maximum Gain measured in fully anechoic chamber is 4.04dBi or 2.54 in linear scale.

### Output Power into Antenna & RF Exposure Evaluation Distance:

IEEE 802.11 n(20MHz) ANT 0+1+2			
WLAN Function			
Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density at R = 20 cm (mW/cm <sup>2</sup> )
36	5180	21.6272	0.01093
44	5220	21.7270	0.01098
48	5240	21.7771	0.01100

IEEE 802.11 n(20MHz) ANT 0+1+2			
WLAN Function			
Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density at R = 20 cm (mW/cm <sup>2</sup> )
149	5745	463.4469	0.23419
157	5785	476.4310	0.24075
165	5825	460.2566	0.23257

The power density Pd (4th column) at a distance of 20 cm calculated from the Friis transmission formula is far below the limit of 1 mW/cm<sup>2</sup>.

Product	Wireless-AC1900 Dual Band Gigabit Router
Test Mode	Transmit (Beamforming Mode)
Test Condition	RF Exposure Evaluation

### Antenna Gain

Antenna Gain: The maximum Gain measured in fully anechoic chamber is 4.04dBi or 2.54 in linear scale.

### Output Power into Antenna & RF Exposure Evaluation Distance:

IEEE 802.11 n(40MHz) ANT 0+1+2			
WLAN Function			
Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density at R = 20 cm (mW/cm <sup>2</sup> )
38	5190	21.0863	0.01066
46	5230	23.3884	0.01182

IEEE 802.11 n(40MHz) ANT 0+1+2			
WLAN Function			
Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density at R = 20 cm (mW/cm <sup>2</sup> )
151	5755	461.3176	0.23311
159	5795	476.4310	0.24075

The power density Pd (4th column) at a distance of 20 cm calculated from the Friis transmission formula is far below the limit of 1 mW/cm<sup>2</sup>.

Product	Wireless-AC1900 Dual Band Gigabit Router
Test Mode	Transmit (Beamforming Mode)
Test Condition	RF Exposure Evaluation

### Antenna Gain

Antenna Gain: The maximum Gain measured in fully anechoic chamber is 4.04dBi or 2.54 in linear scale.

### Output Power into Antenna & RF Exposure Evaluation Distance:

IEEE 802.11 ac(80MHz) ANT 0+1+2			
WLAN Function			
Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density at R = 20 cm (mW/cm <sup>2</sup> )
42	5210	21.5278	0.01088

IEEE 802.11 ac(80MHz) ANT 0+1+2			
WLAN Function			
Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density at R = 20 cm (mW/cm <sup>2</sup> )
155	5775	454.8600	0.23151

The power density Pd (4th column) at a distance of 20 cm calculated from the Friis transmission formula is far below the limit of 1 mW/cm<sup>2</sup>.