

Uni-Art Precise Products Ltd.

Application
For
Certification

43/49MHz 25 Channel Analog Modulation Cordless Headset Telephone

(FCC ID: MVABE-250-001FA)

WO# 9810582
ALO/at
February 8, 1999

- The test results reported in this report shall refer only to the sample actually tested and shall not refer or be deemed to refer to bulk from which such a sample may be said to have been obtained.
- This report shall not be reproduced except in full without prior authorization from Intertek Testing Services Limited

FCC ID: MVABE-250-001FA

LIST OF EXHIBITS

INTRODUCTION

<i>EXHIBIT 1:</i>	General Description
<i>EXHIBIT 2:</i>	System Test Configuration
<i>EXHIBIT 3:</i>	Emission Results
<i>EXHIBIT 4:</i>	Frequency Deviation
<i>EXHIBIT 5:</i>	Operating Bandwidth
<i>EXHIBIT 6:</i>	Equipment Photographs
<i>EXHIBIT 7:</i>	Product Labelling
<i>EXHIBIT 8:</i>	Technical Specifications
<i>EXHIBIT 9:</i>	Instruction Manual
<i>EXHIBIT 10:</i>	Security Code Information
<i>EXHIBIT 11:</i>	Automatic Channel Selection

INTERTEK TESTING SERVICES

MEASUREMENT/TECHNICAL REPORT

Uni-Art Precise Products Ltd. - MODEL: BE-25FA, TT-25FA
FCC ID: MVABE-250-001FA

This report concerns (check one:) Original Grant X Class II Change

Equipment Type: Cordless Telephone (example: computer, modem, transmitter, etc.)

Deferred grant requested per 47 CFR 0.457(d)(1)(ii)? Yes No X

If yes, defer until : _____
date

Company Name agrees to notify the Commission by: _____
date

of the intended date of announcement of the product so that the grant can be issued on that date.

Transition Rules Request per 15.37? Yes No X

If no, assumed Part 15, Subpart C for intentional radiator - the new 47 CFR [10-1-96 Edition] provision.

Report prepared by:

Alfred Lo
Intertek Testing Services.
2/F., Garment Centre,
576 Castle Peak Road,
Kowloon, Hong Kong.
Phone: 852-2746-8217
Fax: 852-2785-5487

INTERTEK TESTING SERVICES

Table of Contents

1.0 <u>General Description</u>	1
1.1 Product Description	2
1.2 Related Submittal(s) Grants	3
1.3 Test Methodology	3
1.4 Test Facility	3
2.0 <u>System Test Configuration</u>	4
2.1 Justification	5
2.2 EUT Exercising Software	5
2.3 Support Equipment List and Description	6
2.4 Equipment Modification	7
3.0 <u>Emission Results</u>	9
3.1 Field Strength Calculation	10
3.2 Radiated Emission Configuration Photograph - Base Unit	11
3.3 Radiated Emission Data - Base Unit	12
3.4 Radiated Emission Configuration Photograph - Handset	17
3.5 Radiated Emission Configuration Data - Handset	18
3.6 Line Conducted Configuration Photograph - Base Unit	21
3.7 Line Conducted Data - Base Unit	22
4.0 <u>Frequency Deviation</u>	25
4.1 Base Unit	26
4.2 Handset	30
5.0 <u>Operating Bandwidth</u>	35
5.1 Base Unit	36
5.2 Handset	38
6.0 <u>Equipment Photographs</u>	41
7.0 <u>Product Labelling</u>	43
8.0 <u>Technical Specifications</u>	45
9.0 <u>Instruction Manual</u>	47
10.0 <u>Security Code Information</u>	49
11.0 <u>Automatic Channel Selection</u>	51

INTERTEK TESTING SERVICES

List of attached file

Exhibit type	File Description	filename
Cover Letter	Letter of Agency	letter.pdf
Test Report	Test Report	report.doc
Operation Description	Technical Description	descrip.pdf
Test Setup Photo	Radiated Emission for Base	base1.jpg, base2.jpg
Test Setup Photo	Radiated Emission for Headset	headset1.jpg, headset2.jpg
Test Setup Photo	Conducted Emission	conduct1.jpg to conduct3.jpg
Test Report	Conducted Emission Test Result	conduct.pdf
Test Report	Base Bandwidth Plot	bsbw.pdf
Test Report	Handset Bandwidth Plot	hsbw.pdf
External Photo	External Photo	ophoto1.jpg, ophoto2.jpg
Internal Photo	Internal Photo	ipphoto1.jpg to ipphoto11.jpg
Block Diagram	Block Diagram	block.pdf
Schematics	Circuit Diagram	circuit.pdf
ID Label/Location	Label Artwork and Location	label.pdf
User Manual	User Manual	manual.pdf
Test Report	Auto Channel Selection Mechanism	auto.pdf

EXHIBIT 1
GENERAL DESCRIPTION

INTERTEK TESTING SERVICES

1.0 **General Description**

1.1 Product Description

The Bell Equipment Sonecor BE-25FA is a 43/49MHz 25 Channel Analog Modulation Cordless Headset Telephone. The unit is capable of either tone or pulse dialing. The internal power supply's isolation is accomplished through a power transformer having an adequate dielectric rating. The circuit wiring is consistent under the requirement of part 68.

The TT Systems TT-25FA is identical to Bell Equipment Sonecor BE-25FA as far as hardware, software, features and functionality. The additional model number is for market purposes only.

The headset unit consists of a keypad with twelve standard keys (0,...9,*,#), four function keys Flash, Redial, Intercom, Memo, and one channel switch key. A Talk key is provided to control pick/release telephone line in a toggle base.

The base unit consists of a keypad with twelve standard keys (0,...9,*,#), five function keys Memo, Flash, Redial, Tone, Pause and one speakerphone key. An Intercom key is provided to begin intercom conversation between the base unit and the headset. In addition, it is also used to page the headset.

The circuit description is saved with filename: descri.pdf

Connection between the device and the telephone network is accomplished through the use of USOC RJ11C in the 2-wire loop calling central office line.

INTERTEK TESTING SERVICES

1.2 Related Submittal(s) Grants

This is an Application for Certification of a cordless telephone system. Two transmitters are included in this Application. This specific report details the emission characteristics of each transmitter. The receivers are subject to the verification authorization process, in accordance with 15.101(b). A verification report has been prepared for the receiver sections of each device. The device is also subject to Part 68 Registration.

1.3 Test Methodology

Both AC mains line-conducted and radiated emission measurements were performed according to the procedures in ANSI C63.4 (1992). All measurements were performed in Open Area Test Sites. Preliminary scans were performed in the Open Area Test Sites only to determine worst case modes. For each scan, the procedure for maximizing emissions in Appendices D and E were followed. All Radiated tests were performed at an antenna to EUT distance of 3 meters, unless stated otherwise in the "**Justification Section**" of this Application.

1.4 Test Facility

The open area test site and conducted measurement facility used to collect the radiated data is located at Garment Centre, 576 Castle Peak Road, Kowloon, Hong Kong. This test facility and site measurement data have been fully placed on file with the FCC.

EXHIBIT 2
SYSTEM TEST CONFIGURATION

2.0 **System Test Configuration**

2.1 Justification

For emission testing, the equipment under test (EUT) was configured for testing in a typical fashion (as a customer would normally use it). During testing, all cables were manipulated to produce worst case emissions. The headset was powered by a fully charged battery.

For the measurements, the EUT is attached to a cardboard box and placed on the wooden turntable. If the base unit attaches to peripherals, they are connected and operational (as typical as possible). The headset is remotely located as far from the antenna and the base as possible to ensure full power transmission from the base. Else, the base is wired to transmit full power without modulation.

The signal is maximized through rotation and placement in the three orthogonal axes. The antenna height and polarization are varied during the search for maximum signal level. The antenna height is varied from 1 to 4 meters. Detector function is in peak mode. Radiated emissions are taken at three meters unless the signal level is too low for measurement at that distance. If necessary, a pre-amplifier is used and/or the test is conducted at a closer distance.

All readings are extrapolated back to the equivalent three meter reading using inverse scaling with distance. Analyzer resolution is 100 kHz or greater. All emissions greater than 20 dB μ V/m are recorded.

Radiated emission measurement were performed from 30 MHz to 1000 MHz.

2.2 EUT Exercising Software

The EUT exercise program used during radiated and conducted testing was designed to exercise the various system components in a manner similar to a typical use.

For emissions testing, the units were setup to transmit continuously to simplify the measurement methodology. Care was taken to ensure proper power supply voltages during testing.

INTERTEK TESTING SERVICES

2.3 Support Equipment List and Description

The FCC ID's for all equipment, plus descriptions of all cables used in the tested system (included inserted cards, which have grants) are:

HARDWARE:

The unit was operated standalone. An AC adapter (provided with the unit) was used to power the device. Its description is listed below.

- (1) AC adapter with two meter unshielded power cord permanently affixed.

CABLES:

- (1) Telecommunication cable with RJ11C connectors (1m, unshielded), terminated
- (2) 1 set of audio cable (1m, unshielded) which was connected to the speaker jack.
- (3) 1 set of audio cable (1m, shielded) which was connected to the Mic jack.

OTHERS:

- (1) Audio Signal Generator
- (2) Resistive Load

INTERTEK TESTING SERVICES

2.4 Equipment Modification

Any modifications installed previous to testing by Uni-Art Precise Products Ltd. will be incorporated in each production model sold/leased in the United States.

No modifications were installed by ETL Division, Intertek Testing Services Hong Kong Ltd.

All the items listed under section 2.0 of this report are confirmed by:

Confirmed by:

*Alfred Lo
Technical Supervisor
Intertek Testing Services
Agent for Uni-Art Precise Products Ltd.*



Signature

February 8, 1999 Date

EXHIBIT 3
EMISSION RESULTS

3.0 **Emission Results**

Data is included of the worst case configuration (the configuration which resulted in the highest emission levels). A sample calculation, configuration photographs and data tables of the emissions are included.

3.1 Field Strength Calculation

The field strength is calculated by adding the Antenna Factor and Cable Factor, and subtracting the Amplifier Gain (if any) from the measured reading. The basic equation with a sample calculation is as follows:

$$FS = RA + AF + CF - AG$$

where FS = Field Strength in dB μ V/m
 RA = Receiver Amplitude (including preamplifier) in dB μ V
 CF = Cable Attenuation Factor in dB
 AF = Antenna Factor in dB
 AG = Amplifier Gain in dB

In the following table(s), the reading shown on the data table reflects the preamplifier gain. An example for the calculations in the following table is as follows:-

$$FS = RR + LF$$

where FS = Field Strength in dB μ V/m
 RR = RA - AG in dB μ V
 LF = CF + AF in dB

Assume a receiver reading of 52.0 dB μ V is obtained. The antenna factor of 7.4 dB and cable factor of 1.6 dB is added. The amplifier gain of 29 dB is subtracted, giving a field strength of 32 dB μ V/m. This value in dB μ V/m was converted to its corresponding level in μ V/m.

RA = 52.0 dB μ V/m	
AF = 7.4 dB	RR = 23.0 dB μ V
CF = 1.6 dB	LF = 9.0 dB
AG = 29.0 dB	
FS = RR + LF	
FS = 23 + 9 = 32 dB μ V/m	

Level in μ V/m = Common Antilogarithm [(32 dB μ V/m)/20] = 39.8 μ V/m

3.2 Radiated Emission Configuration Photograph - Base Unit

Worst Case Radiated Emission

at 140.910 MHz

For electronic filing, the worst case radiated emission configuration photograph is saved with filename: base1.jpg, base2.jpg

INTERTEK TESTING SERVICES

3.3 Radiated Emission Data - Base Unit

The data on the following pages list the significant emission frequencies, the limit and the margin of compliance.

Judgement : Passed by 9.9 dB

TEST PERSONNEL:



Tester Signature

H. Y. Vu, Engineer

Typed/Printed Name

February 8, 1999

Date

INTERTEK TESTING SERVICES

Company: Uni-Art Precise Products Ltd.
Model: Bell Equipment Sonacor BE-25FA
Mode : TX-Channel 1

Date of Test: January 19, 1999

Table 1, Base unit

Radiated Emissions

Polarity	Frequency (M H z)	Reading (dB μ V)	Antenna Factor (dB)	Pre-Amp Gain (dB)	Net at 3m (dB μ V /m)	L i m i t (dB μ V /m)	M a r g i n (dB)
V	43.720	73.1	10	16	67.1	80.0	-12.9
V	87.440	36.8	7	16	27.8	40.0	-12.2
H	131.160	33.8	13	16	30.8	43.5	-12.7
H	174.880	24.8	19	16	27.8	43.5	-15.7
H	218.600	28.6	17	16	29.6	46.0	-16.4
H	262.320	27.0	21	16	32.0	46.0	-14.0
H	302.177	24.6	22	16	30.6	46.0	-15.4

NOTES: 1. Peak Detector data

2. All measurements were made at 3 meters. Harmonic emissions not detected at the 3-meter distance were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.

3. Negative signs (-) in the margin column signify levels below the limits.

Test Engineer: H. Y. Vu

INTERTEK TESTING SERVICES

Company: Uni-Art Precise Products Ltd.
Model: Bell Equipment Sonacor BE-25FA
Mode : TX-Channel 25

Date of Test: January 19, 1999

Table 2, Base unit

Radiated Emissions

Polarity	Frequency (M H z)	Reading (dB μ V)	Antenna Factor (dB)	Pre-Amp Gain (dB)	Net at 3m (dB μ V /m)	L i m i t (dB μ V /m)	M a r g i n (dB)
V	46.970	74.0	11	16	69.0	80.0	-11.0
V	93.940	38.6	10	16	32.6	43.5	-10.9
H	140.910	36.6	13	16	33.6	43.5	-9.9
H	187.880	32.9	16	16	32.9	43.5	-10.6
H	234.850	28.8	19	16	31.8	46.0	-14.2
H	281.820	28.6	22	16	34.6	46.0	-11.4
H	328.790	25.4	24	16	33.4	46.0	-12.6
H	375.760	25.5	24	16	33.5	46.0	-12.5

NOTES: 1. Peak Detector data

2. All measurements were made at 3 meters. Harmonic emissions not detected at the 3-meter distance were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.

3. Negative signs (-) in the margin column signify levels below the limits.

Test Engineer: H. Y. Vu

INTERTEK TESTING SERVICES

Company: Uni-Art Precise Products Ltd.
Model: Bell Equipment Sonacor BE-25FA
Mode : Stand by

Date of Test: January 19, 1999

Table 3, Base unit

Radiated Emissions

Polarity	Frequency (M H z)	Reading (dB μ V)	Antenna Factor (dB)	Pre-Amp Gain (dB)	Net at 3m (dB μ V /m)	L i m i t (dB μ V /m)	M a r g i n (dB)
V	39.269	37.8	10	16	31.8	40.0	-8.2
H	157.807	26.4	15	16	25.4	43.5	-18.1
H	157.077	25.9	15	16	24.9	43.5	-18.6

NOTES: 1. Peak Detector data

- All measurements were made at 3 meters. Harmonic emissions not detected at the 3-meter distance were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.
- Negative signs (-) in the margin column signify levels below the limits.

Test Engineer: H. Y. Vu

INTERTEK TESTING SERVICES

Company: Uni-Art Precise Products Ltd.
Model: Bell Equipment Sonacor BE-25FA
Mode : Charging

Date of Test: January 19, 1999

Table 3, Base unit

Radiated Emissions

Polarity	Frequency (M H z)	Reading (dB μ V)	Antenna Factor (dB)	Pre-Amp Gain (dB)	Net at 3m (dB μ V /m)	L i m i t (dB μ V /m)	M a r g i n (dB)
V	39.269	37.8	10	16	31.8	40.0	-8.2
H	157.807	26.4	15	16	25.4	43.5	-18.1
H	157.077	25.9	15	16	24.9	43.5	-18.6

NOTES: 1. Peak Detector data

- All measurements were made at 3 meters. Harmonic emissions not detected at the 3-meter distance were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.
- Negative signs (-) in the margin column signify levels below the limits.

Test Engineer: H. Y. Vu

INTERTEK TESTING SERVICES

3.4 Radiated Emission Configuration Photograph - Headset

Worst Case Radiated Emission

at 49.991 MHz

For electronic filing, the worst case radiated emission configuration photographs are saved with filenames: headset1.jpg, headset2.jpg

INTERTEK TESTING SERVICES

3.5 Radiated Emission Data - Headset

The data on the following pages list the significant emission frequencies, the limit and the margin of compliance.

Judgement : Passed by 13.6 dB

TEST PERSONNEL:



Tester Signature

H. Y. Vu, Engineer
Typed/Printed Name

February 8, 1999
Date

INTERTEK TESTING SERVICES

Company: Uni-Art Precise Products Ltd.
Model: Bell Equipment Sonacor BE-25FA
Mode : Headset-Channel 1

Date of Test: January 19, 1999

Table 4, Base unit

Radiated Emissions

Polarity	Frequency (M H z)	Reading (dB μ V)	Antenna Factor (dB)	Pre-Amp Gain (dB)	Net at 3m (dB μ V /m)	L i m i t (dB μ V /m)	M a r g i n (dB)
V	48.760	64.6	11	16	59.6	80.0	-20.4
H	146.282	30.9	13	16	27.9	43.5	-15.6
H	292.553	25.8	22	16	31.8	46.0	-14.2

NOTES: 1. Peak Detector data

- All measurements were made at 3 meters. Harmonic emissions not detected at the 3-meter distance were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.
- Negative signs (-) in the margin column signify levels below the limits.

Test Engineer: H. Y. Vu

INTERTEK TESTING SERVICES

Company: Uni-Art Precise Products Ltd.
Model: Bell Equipment Sonacor BE-25FA
Mode : Headset-Channel 24

Date of Test: January 19, 1999

Table 5, Base unit

Radiated Emissions

Polarity	Frequency (M H z)	Reading (dB μ V)	Antenna Factor (dB)	Pre-Amp Gain (dB)	Net at 3m (dB μ V /m)	L i m i t (dB μ V /m)	M a r g i n (dB)
V	49.991	71.4	11	16	66.4	80.0	-13.6
H	149.976	30.4	13	16	27.4	43.5	-16.1
H	199.969	26.8	16	16	26.8	43.5	-16.7

NOTES: 1. Peak Detector data

- All measurements were made at 3 meters. Harmonic emissions not detected at the 3-meter distance were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.
- Negative signs (-) in the margin column signify levels below the limits.

Test Engineer: H. Y. Vu

3.6 Line Conducted Configuration Photograph - Base Unit

Worst Case Line-Conducted Configuration

For electronic filing, the worst case line-conducted configuration photograph are saved with filename: conduct1.jpg to conduct3.jpg

INTERTEK TESTING SERVICES

3.7 Line Conducted Emission Configuration Data

The data on the following pages list the significant emission frequencies, the limit, and the margin of compliance.

Judgement : Passed by more than 20 dB

* All readings are peak unless stated otherwise.

TEST PERSONNEL:



Tester Signature

H. Y. Vu, Engineer

Typed/Printed Name

February 8, 1999

Date

INTERTEK TESTING SERVICES

Company: Uni-Art Precise Products Ltd
Model: Bell Equipment Sonacor BE-25FA

Date of Test: January 19, 1999

Conducted Emissions

For electronic filing, the conducted emission test result is saved with filename: conduct.pdf

EXHIBIT 4
FREQUENCY DEVIATION

4.0 **Frequency Deviation**

Two stability tests were performed -- Frequency stability versus input voltage and frequency stability versus temperature. For both measurements, a 1 GHz frequency counter with temperature controlled time base is used.

The counter is coupled to the transmitter by coiling a pickup wire over the transmitter antenna or directly attaching it to the antenna, assuming a 50 Ω antenna is used.

The frequency stability is measured at room temperature by varying the supply voltage (AC or DC, as required) from 85% through 115% of normal operating voltage. This test is not applicable if the unit uses battery power. For battery powered equipment, the batteries are new and fully charged.

Stability versus temperature testing is carried out with the aid of a Tabai Espec Corp, Model PR-3F(W) environmental chamber. The following procedure is followed during testing:

1. Cool the device to -20°C and allow it to stabilize for 30 minutes. Record the frequency.
2. Heat the oven to +50°C and allow it to stabilize for 30 minutes. Record the frequency of operation.
3. Compare the measurements and a room temperature measurement against the assigned frequency tolerance.

The frequency tolerance of the carrier signal shall be maintained within $\pm 0.01\%$ of the operating frequency.

INTERTEK TESTING SERVICES

4.1.1 Measurement Data - Base Unit

Channel Frequency

Channel	Assigned Frequency (MHz)	Measured Frequency (MHz)	Tolerance %
1	43.72000	43.72013	0.00030
2	43.74000	43.74015	0.00034
3	43.82000	43.81996	-0.00009
4	43.84000	43.84015	0.00034
5	43.92000	43.91995	-0.00011
6	43.96000	43.96013	0.00030
7	44.12000	44.11990	-0.00023
8	44.16000	44.15992	-0.00018
9	44.18000	44.17991	-0.00020
10	44.20000	44.19991	0.00020
11	44.32000	44.32187	0.00422
12	44.36000	44.36084	0.00189
13	44.40000	44.40065	0.00146

INTERTEK TESTING SERVICES

4.1.1 Measurement Data - Base Unit (Cont'd...)

Channel Frequency

Channel	Assigned Frequency (MHz)	Measured Frequency (MHz)	Tolerance %
14	44.46000	44.46055	0.00124
15	44.48000	44.48041	0.00092
16	46.61000	46.60994	-0.00013
17	46.63000	46.62995	-0.00011
18	46.67000	46.66995	-0.00011
19	46.71000	46.70996	-0.00009
20	46.73000	46.72995	-0.00011
21	46.77000	46.76995	-0.00011
22	46.83000	46.82996	-0.00009
23	46.87000	46.87018	0.00038
24	46.93000	46.93048	0.00102
25	46.97000	46.96999	-0.00002

INTERTEK TESTING SERVICES

4.1.2 Measurement Data - Base Unit - Channel 1

Frequency Stability

Frequency Stability versus Source Voltage

	Voltage (Vac)	Assigned Frequency (kHz)	Measured Frequency (kHz)	Frequency deviation (kHz)	Tolerance % (x 10 ⁻³)
Nominal	120	43,720.00	43,720.13	0.13	0.30
85 %	102	43,720.00	43,719.87	-0.13	-0.30
115 %	138	43,720.00	43,719.84	-0.16	-0.37

Frequency Stability versus Temperature

Temperature (°C)	Assigned Frequency (kHz)	Measured Frequency (kHz)	Frequency deviation (kHz)	Tolerance (%) (x 10 ⁻³)
-20	43,720.00	43,719.91	-0.09	-0.21
25	43,720.00	43,720.13	0.13	0.30
50	43,720.00	43,719.96	-0.04	-0.09

Notes: All readings taken at base of antenna.

Legend (where appropriate)

* No emission was recorded at this environment. Thus, no frequency deviation can be found.

INTERTEK TESTING SERVICES

4.1.2 Measurement Data - Base Unit - Channel 25

Frequency Stability

Frequency Stability versus Source Voltage

	Voltage (Vac)	Assigned Frequency (kHz)	Measured Frequency (kHz)	Frequency deviation (kHz)	Tolerance % (x 10 ⁻³)
Nominal	120	46,970.00	46,969.99	-0.01	-0.02
85 %	102	46,970.00	46,969.86	-0.14	-0.30
115 %	138	46,970.00	46,969.87	-0.13	-0.28

Frequency Stability versus Temperature

Temperature (°C)	Assigned Frequency (kHz)	Measured Frequency (kHz)	Frequency deviation (kHz)	Tolerance (%) (x 10 ⁻³)
-20	46,970.00	46,969.90	-0.10	-0.21
25	46,970.00	46,969.99	-0.01	-0.02
50	46,970.00	46,969.89	-0.11	-0.23

Notes: All readings taken at base of antenna.

Legend (where appropriate)

* No emission was recorded at this environment. Thus, no frequency deviation can be found.

Test Results : From the two sets of tables for Base Unit - channel 1 & channel 25, the largest deviation from nominal frequency was 160 Hz, which was 0.00037% compared to the standard test frequency. The required minimum standard is 0.01% in §15.233(g)

INTERTEK TESTING SERVICES

4.2.1 Measurement Data - Headset

Channel Frequency

Channel	Assigned Frequency (MHz)	Measured Frequency (MHz)	Tolerance %
1	48.76000	48.75997	-0.00006
2	48.84000	48.83986	-0.00029
3	48.86000	48.85986	-0.00029
4	48.92000	48.91969	-0.00063
5	49.02000	49.01965	-0.00071
6	49.08000	49.07965	-0.00071
7	49.10000	49.09968	-0.00065
8	49.16000	49.15966	-0.00069
9	49.20000	49.19969	-0.00063
10	49.24000	49.23965	-0.00071
11	49.28000	49.27964	-0.00073
12	49.36000	49.35971	-0.00059
13	49.40000	49.39971	-0.00059

INTERTEK TESTING SERVICES

4.2.1 Measurement Data - Headset (Cont'd...)

Channel Frequency

Channel	Assigned Frequency (MHz)	Measured Frequency (MHz)	Tolerance %
14	49.46000	49.45965	-0.00071
15	49.50000	49.49973	-0.00055
16	49.67000	49.66973	-0.00054
17	49.84500	49.84488	-0.00024
18	49.86000	49.85973	-0.00054
19	49.77000	49.76966	-0.00068
20	49.87500	49.87490	-0.00020
21	49.83000	49.82981	-0.00038
22	49.89000	49.88983	-0.00034
23	49.93000	49.92955	-0.00090
24	49.99000	49.98945	-0.00110
25	49.97000	49.96976	-0.00048

INTERTEK TESTING SERVICES

4.2.2 Measurement Data - Headset - Channel 1

Frequency Stability

Frequency Stability versus Source Voltage

	Voltage (Vdc)	Assigned Frequency (kHz)	Measured Frequency (kHz)	Frequency deviation (kHz)	Tolerance % (x 10 ⁻³)
Nominal	3.6	48,760.00	48,759.97	-0.03	-0.06
85 %	3.06	48,760.00	48,759.71	-0.29	-0.59
115 %	4.14	48,760.00	48,759.67	-0.33	-0.68

Frequency Stability versus Temperature

Temperature (°C)	Assigned Frequency (kHz)	Measured Frequency (kHz)	Frequency deviation (kHz)	Tolerance (%) (x 10 ⁻³)
-20	48,760.00	48,759.55	-0.45	-0.92
25	48,760.00	48,759.97	-0.03	-0.06
50	48,760.00	48,759.87	-0.13	-0.27

Legend (where appropriate)

- * No emission was recorded at this environment. Thus, no frequency deviation can be found.

INTERTEK TESTING SERVICES

4.2.2 Measurement Data - Headset - Channel 25

Frequency Stability

Frequency Stability versus Source Voltage

	Voltage (Vdc)	Assigned Frequency (kHz)	Measured Frequency (kHz)	Frequency deviation (kHz)	Tolerance % (x 10 ⁻³)
Nominal	3.6	49,970.00	49,969.76	-0.24	-0.48
85 %	3.06	49,970.00	49,969.73	-0.27	-0.54
115 %	4.14	49,970.00	49,969.64	-0.36	-0.72

Frequency Stability versus Temperature

Temperature (°C)	Assigned Frequency (kHz)	Measured Frequency (kHz)	Frequency deviation (kHz)	Tolerance (%) (x 10 ⁻³)
-20	49,970.00	49,969.36	--0.64	-1.28
25	49,970.00	49,969.76	-0.29	-0.48
50	49,970.00	49,969.86	-0.14	-0.28

Legend (where appropriate)

* No emission was recorded at this environment. Thus, no frequency deviation can be found.

Test Results : From the two sets of tables for Headset - channel 1 & channel 25, the largest deviation from nominal frequency was 640 Hz, which was 0.00128% compared to the standard test frequency. The required minimum standard is 0.01% in §15.233(g)

EXHIBIT 5
OPERATING BANDWIDTH

5.0 **Operating Bandwidth**

For measurements of bandwidth, the following procedure was followed by the test engineer:

- (1) Set up the equipment such that the antenna is located close enough to give a full scale deflection of the unmodulated carrier.
- (2) Plot the unmodulated carrier. Any residual guard tones should be left in place, as these will be present at all times in actual operation.
- (3) Plot the bandwidth with all alerting tones active. These include ringing and "call" signals from the base, and any intercom functions available in the handset.
- (4) Determine the worst case bandwidth using the following procedure:
 - (a) Disable all internal modulations, if possible.
 - (b) Apply a 2500 Hz signal to the audio input.
 - (c) Vary the input signal level and observe on the spectrum analyzer the waveform. Vary unit until a maximum deflection is observed. Record the input signal level. Record and plot the bandwidth deflection (100% modulation) measured at -26 dBC.
 - (d) **FOR A DEVICE WITH MODULATION LIMITING:**

Apply a 2500 Hz signal with the input level 16 dB greater than the level which produces 50% modulation. Plot and record the bandwidth.
 - (e) **FOR A DEVICE WITHOUT MODULATION LIMITING:**

Apply a 2500 Hz signal with the input level set for 85% modulation. If not possible, maximize the modulation percentage. Plot and record bandwidth.
- (5) Complete the tables on the following pages.

INTERTEK TESTING SERVICES

5.1 Base Unit - Channel 1

Operating Bandwidth

kHz from Carrier	Amplitude Down from Carrier (dB)	Limit (kHz)
-6.13/6.12	26.00	±10
- 20	61.25	N/A
+ 20	61.25	N/A

Base Unit - Channel 25

kHz from Carrier	Amplitude Down from Carrier (dB)	Limit (kHz)
-6.13/6.12	26.00	±10
- 20	66.67	N/A
+ 20	66.67	N/A

Test Result: From the above two tables for Base Unit-channel 1 & channel 25, the modulated signal from base unit closest to band edge was 3.87 kHz above the lower band edge 46.960 MHz and 43.710MHz according to §15.233(d)

Bandwidth Plot - Base Unit

For electronic filing, the bandwidth plot is saved with filename: bsbw.pdf

INTERTEK TESTING SERVICES

5.2 Headset - Channel 1

Operating Bandwidth

kHz from Carrier	Amplitude Down from Carrier (dB)	Limit (kHz)
-6.00/6.00	26.00	±10
- 20	68.33	N/A
+ 20	68.33	N/A

Handset - Channel 25

kHz from Carrier	Amplitude Down from Carrier (dB)	Limit (kHz)
-5.88/5.87	26.00	±10
- 20	60.00	N/A
+ 20	60.00	N/A

Test Result: From the above two tables for Headset-channel 1 & channel 25, the modulated signal from base unit closest to band edge were 4.00 kHz above the lower band edge 48.750 MHz and 4.00kHz below the upper band edge 48.770MHz according to §15.233(d)

Bandwidth Plot - Handset

For electronic filing, the bandwidth plot is saved with filename: hsbw.pdf

EXHIBIT 6
EQUIPMENT PHOTOGRAPHS

6.0 **Equipment Photographs**

For electronic filing, the photographs are saved with filename: ophoto1.jpg to ophoto2.jpg & iphoto1.jpg to iphoto11.jpg

EXHIBIT 7
PRODUCT LABELLING

7.0 **Product Labelling**

For electronic filing, the FCC ID artwork and location are saved with filename: label.pdf

EXHIBIT 8
TECHNICAL SPECIFICATIONS

8.0 **Technical Specifications**

For electronic filing, the block diagram and circuit diagram are saved with filename:
block.pdf and circuit.pdf

EXHIBIT 9
INSTRUCTION MANUAL

INTERTEK TESTING SERVICES

9.0 Instruction Manual

For electronic filing, a preliminary copy of the Instruction Manual is saved with filename: manual.pdf.

Please note that the required FCC Information to the User can be found on Page 24 and 25 of this manual.

This manual will be provided to the end-user with each unit sold/leased in the United States.

EXHIBIT 10
SECURITY CODE INFORMATION

10.0 Security code information

The telephone has an internal security code with 65,536 possible combinations. Each time you pick up the HANDSET, the code is randomly set to a new combination.

Communication between HANDSET and BASE UNIT may not be possible in any of the following situation:

1. After a power failure.
2. After relocation the BASE UNIT by disconnecting the AC adaptor.
3. After replacing the HANDSET battery.

To reset, place the HANDSET on the BASE UNIT for 2 to 5 seconds.

EXHIBIT 11
AUTOMATIC CHANNEL SELECTION

11.0 Automatic Channel Selection

The mechanism of automatic channel selection is saved with filename: auto.pdf