

Tuned Frequency MHz	Emission Frequency MHz	*	Meter Reading dBuV	Ant. Polarity	Coax Loss dB	Correction Factor dB	Duty Cycle Factor dB	Field Strength dBuV/m	Margin dB
433.9	433.90		55.8	H	1.23	16.62	5.10	68.55	12.27
433.9	433.90		60.3	V	1.23	16.18	5.10	72.61	8.21
433.9	867.80		6.2	H	1.93	22.96	5.10	25.99	34.83
433.9	867.80		6.6	V	1.93	22.40	5.10	25.83	34.99
433.9	1,301.80	**	13.7	H	2.34	28.00	5.10	38.94	15.06
433.9	1,301.80	**	14.9	V	2.34	28.00	5.10	40.14	13.86
433.9	1,735.70		14.5	V	2.69	29.70	5.10	41.79	19.04
433.9	1,735.70		14.7	H	2.69	29.70	5.10	41.99	18.84
433.9	2,169.50		8.0	V	3.02	31.94	5.10	37.86	22.97
433.9	2,169.50		8.5	H	3.02	31.94	5.10	38.36	22.47
433.9	2,603.40		7.7	H	3.32	32.77	5.10	38.69	22.13
433.9	2,603.40		11.4	V	3.32	32.77	5.10	42.39	18.43
433.9	3,037.30		8.1	H	3.63	33.39	5.10	40.02	20.80
433.9	3,037.30		9.1	V	3.63	33.39	5.10	41.02	19.80
433.9	3,471.20		7.3	V	4.02	33.31	5.10	39.53	21.29
433.9	3,471.20		7.5	H	4.02	33.31	5.10	39.73	21.09
433.9	3,905.10	**	8.8	V	4.41	33.79	5.10	41.90	12.10
433.9	3,905.10	**	8.8	H	4.41	33.79	5.10	41.90	12.10
433.9	4,339.00	**	7.8	H	4.67	34.44	5.10	41.81	12.19
433.9	4,339.00	**	7.8	V	4.67	34.44	5.10	41.81	12.19