



**Produkte**  
*Products*

<b>Prüfbericht - Nr.: 14003929 003</b>		Seite 1 von 10 Page 1 of 10	
<i>Test Report No.:</i>			
<b>Auftraggeber:</b> <i>Client:</i>		Zaptoys International Limited Unit 1105, 11/F, Tower II South Seas Centre T.S.T. East, Kowloon Hong Kong	
<b>Gegenstand der Prüfung:</b> <i>Test Item:</i>		Superregenerative Receiver (49MHz)	
<b>Bezeichnung:</b> <i>Identification:</i>	Please refer to page 5 Model list for details	<b>Serien-Nr.:</b> <i>Serial No.:</i>	Engineering sample
<b>Wareneingangs-Nr.:</b> <i>Receipt No.:</i>	071113006-2	<b>Eingangsdatum:</b> <i>Date of Receipt:</i>	13.11.2007
<b>Prüfort:</b> <i>Testing Location:</i>	TÜV Rheinland Hong Kong Ltd. 9th Floor, Oriental News Building, 7 Wang Tai Road, Kowloon Bay, Kowloon, Hong Kong Hong Kong Productivity Council HKPC Building, 78 Tat Chee Avenue, Kowloon, Hong Kong		
<b>Prüfgrundlage:</b> <i>Test Specification:</i>	FCC Part 15, Subpart B		
<b>Prüfergebnis:</b> <i>Test Result:</i>	Der Prüfgegenstand entspricht oben genannter Prüfgrundlage(n). <i>The test item passed the test specification(s).</i>		
<b>Prüflaboratorium:</b> <i>Testing Laboratory:</i>	TÜV Rheinland Hong Kong Ltd. 9th Floor, Oriental News Building, 7 Wang Tai Road, Kowloon Bay, Kowloon, Hong Kong		
<b>geprüft / tested by:</b>		<b>kontrolliert / reviewed by:</b>	
12.02.2008	Hugo Wan Project Engineer	12.02.2008	Thomas Berns Manager
<i>Datum</i> <i>Date</i>	<i>Name/Stellung</i> <i>Name/Position</i>	<i>Datum</i> <i>Date</i>	<i>Name/Stellung</i> <i>Name/Position</i>
	 <i>Unterschrift</i> <i>Signature</i>		 <i>Unterschrift</i> <i>Signature</i>
<b>Sonstiges / Other Aspects:</b>			
<b>FCCID: NEX-9374-75-49</b>			
<b>Abkürzungen:</b> P(ass) = entspricht Prüfgrundlage F(ail) = entspricht nicht Prüfgrundlage N/A = nicht anwendbar N/T = nicht getestet		<b>Abbreviations:</b> P(ass) = passed F(ail) = failed N/A = not applicable N/T = not tested	
Dieser Prüfbericht bezieht sich nur auf das o.g. Prüfmuster und darf ohne Genehmigung der Prüfstelle nicht auszugsweise vervielfältigt werden. Dieser Bericht berechtigt nicht zur Verwendung eines Prüfzeichens. <i>This test report relates to the a. m. test sample. Without permission of the test center this test report is not permitted to be duplicated in extracts. This test report does not entitle to carry any safety mark on this or similar products.</i>			

[www.tuv.com](http://www.tuv.com)

# Test Summary

## Spurious Radiated Emissions

*Result: Pass*

## Contents

<b>List of Test and Measurement Instruments.....</b>	<b>4</b>
<b>General Product Information .....</b>	<b>5</b>
Product Function and Intended Use.....	5
Circuit Description.....	6
Ratings and System Details.....	6
Independent Operation Modes.....	7
Submitted Documents .....	7
Related Submittal(s) Grants .....	7
<b>Test Set-up and Operation Mode.....</b>	<b>8</b>
Principle of Configuration Selection .....	8
Test Operation and Test Software .....	8
Special Accessories and Auxiliary Equipment .....	8
Countermeasures to achieve EMC Compliance .....	8
<b>Test Methodology .....</b>	<b>9</b>
Radiated Emission.....	9
Field Strength Calculation .....	9
<b>Test Results .....</b>	<b>10</b>
Spurious Radiated Emissions   Section 15.109.....	10
<b>Appendix 1 Test Setup</b>	
<b>Appendix 2 EUT External Photo</b>	
<b>Appendix 3 EUT Internal Photo</b>	

## List of Test and Measurement Instruments

Hong Kong Productivity Council (Registration number: 90656)

Kind of Equipment	Manufacturer	Type	S/N	Cal Due Date
Semi-anechoic Chamber	Frankonia	Nil	Nil	28 Mar 08
Test Receiver	Rohde & Schwarz	ESU26	100050	06 Aug 08
Biconical Antenna	Rohde & Schwarz	HK116	841489/016	08 Feb 08
Log.-Periodic Antenna	Rohde & Schwarz	HL223	841516/020	03 Feb 08
Horn Antenna	EMCO	3115	9002-3347	02 Feb 08

## General Product Information

### Product Function and Intended Use

The equipment under test (EUT) is a RC toy car operating at 49.86MHz. The EUT moves forward, backward, left and right according to the command of the associate transmitter.

#### FCCID: NEX-9374-75-49

Models	Product descriptions
9374	11" Toyota Supra Tuning Car
8421	1:14 Citroen/Subaru Twin Pack
8422	1:14 Citroen/Ford Twin Pack
8425	1:14 Subaru/Ford Twin Pack
8427	1:14 Citroen/Mitsubishi Twin Pack
8428	1:14 Subaru/Mitsubishi Twin Pack
8429	1:14 Mitsubishi/Ford Twin Pack
9373	11" Toyota - Lexus IS300 Tuning Car
9375	11" Mitsubishi Lancer Evolution VII
9388	RC Nissan Skyline Tuner Car
9392	RC Saleen w light
9398	1:14 RC Citroen
9399	1:14 Ford Focus
9400	1:14 RC Mitsubishi
9402	1:14 RC Subaru
9442	1:12 Ford GT
9458	1:14 RC Aston Martin Vantage 8
9464	1:14 Subaru WRX Street Version
9465	1:14 Mitsubishi Lancer VIII Street Version
9468	1:14 RC McLaren SLR
9473	1:14 AC Schnitzer Z4
9500	1:14 RC Subaru WRC
9524	9" FF RC Bluntz
9525	9" FF RC Dodge Charger
9526	9" FF RC Generic
9527	9" FF RC Dodge Charger 06
9532	Plug & Play Generic Controller + 9" FF RC Bluntz Generic
9541	1:14 Dodge Charger 2006
9561	1:12 Citroen C4
9561N	1:12 Citroen C4
9563	11" Toyota Supra Tuning Car
9582	9" Bluntz Surf VW Bus
9603	FFRC Venom
9604	1:14 RC Ford Explorer Sport Trac
9605	1:14 2008 Dodge Viper STR10
9606	1:14 Mitsubishi Lancer Exvo X
9607	1:14 BMW X5

The client declares that the above models shares the same electrical circuit design, layout, components used and internal wiring. Hence the model 9374 was selected as a representative for testing.

[www.tuv.com](http://www.tuv.com)

## Circuit Description

The receiver was modified from previous model “9374” in test report 14003929 001. The circuit design, components, wiring and outlook are the same except the PCB layout is reduced in size.

## Ratings and System Details

	Receiver
Frequency range	: 49.86MHz
Number of channels	: 1
Type of antenna	: Fixed External Antenna
Power supply	: Battery operated: 4 x 1.5V “AA” size batteries
Ports	: none
Protection Class	: III

[www.tuv.com](http://www.tuv.com)

## **Independent Operation Modes**

The basic operation modes are:

- Power: On and Off
- Motor movement: left and right, forward and backward.

For further information refer to User Manual

## **Submitted Documents**

The submitted documents are listed as follow:

- Circuit diagram
- Block diagram
- User manual
- Label artwork

## **Related Submittal(s) Grants**

This is a test report regarding the modified sample which is going to be reviewed by TCB for permissive class change.

## Test Set-up and Operation Mode

### Principle of Configuration Selection

**Emission:** The equipment under test (EUT) was configured to measure its highest possible radiation level. The test modes were adapted accordingly in reference to the instructions for use.

### Test Operation and Test Software

Test operation should refer to test methodology.

- There was no special software to exercise the device.

### Special Accessories and Auxiliary Equipment

The product has been tested together with the following additional accessories:

- none

### Countermeasures to achieve EMC Compliance

The test sample, which has been tested, contained the noise suppression parts as described in the Circuit Diagram or the Technical Construction File. No additional measures were employed to achieve compliance.



## Test Methodology

### Radiated Emission

The radiated emission measurements were performed according to the procedures in ANSI C63.4-2003.

The equipment under test (EUT) was placed at the middle of the 80 cm height turntable, and the turntable is 3 meters far from the measuring antenna. During the testing, the EUT was operated standalone and arranged for maximum emissions. The EUT was tested in three orthogonal planes.

The investigation is performed with the EUT rotated 360 °, the antenna height scanned between 1m and 4m, and the antenna rotated to repeat the measurements for both the horizontal and vertical antenna polarizations. Repeat the measurement steps until the maximum emissions were obtained.

All radiated tests were performed at an antenna to EUT with 3 meters distance, unless stated otherwise in section 7.1.1 and 7.1.2 of this test report.

### Field Strength Calculation

The field strength at 3 m was established by adding the meter reading of the spectrum analyzer to the factors associated with antenna correction factor, cable loss, preamplifiers and filter attenuation.

The equation is expressed as follow:

$$FS = R + AF + CF + FA - PA$$

Where FS = Field Strength in dBuV/m at 3 meters.  
R = Reading of Spectrum Analyzer in dBuV.  
AF = Antenna Factor in dB.  
CF = Cable Attenuation Factor in dB.  
FA = Filter Attenuation Factor in dB.  
PA = Preamplifier Factor in dB.

FA and PA are only be used for the measuring frequency above 1 GHz.

## Test Results

### Spurious Radiated Emissions

### Section 15.109

#### RESULT:

**Pass**

Test Specification : FCC Part 15 Section 15.109  
 Test Method : ANSI 63.4-2003  
 Measurement Location : Semi Anechoic Chamber  
 Measurement Distance : 3m  
 Detector Function : Quasi Peak  
 Measurement BW : 120 kHz  
 Supply Voltage : DC 6V  
 Measuring Frequency Range : 30-1000MHz  
 Mode of operation : Standby

#### Polarization: Vertical

Frequency (MHz)	Field strength at 3m (dBμV/m)	Limit at 3m (dBμV/m)	Delta to Limit (dB)
46.020	34.9	40.0	-5.1
50.576	34.8	40.0	-5.2
90.900	24.8	43.5	-18.7
180.870	25.4	43.5	-18.1
202.615	22.2	43.5	-21.3
249.500	24.3	46.0	-21.7

#### Polarization: Horizontal

Frequency (MHz)	Field strength at 3m (dBμV/m)	Limit at 3m (dBμV/m)	Delta to Limit (dB)
50.576	14.2	40.0	-25.8
230.840	15.6	46.0	-30.4

#### Limit

#### Section 15.109

The field strength of radiated emissions from unintentional radiators at a distance of 3 meters:

Frequency (MHz)	Field strength (μV/m)	Field strength (dBμV/m)	Measurement distance (m)
30-88	100	$20 \cdot \log(100) = 40.00$	3
88-216	150	$20 \cdot \log(150) = 43.52$	3
216-960	200	$20 \cdot \log(200) = 46.02$	3
Above 960	500	$20 \cdot \log(500) = 53.98$	3