

### Empfänger RCi01-3...

#### Anschließen:

- Spannungsversorgung: IN1, IN2
- Verbraucher: NO1-COM1 Schliesser  
NC1-COM1 Öffner

#### Sender lernen:

- Taste TA1 für ca. 3 Sek. betätigen.
- Die LED blinkt für ca. 10 Sek.
- Innerhalb der 10 Sek. Sendertaste betätigen.

Hat der Empfänger den Sendercode gespeichert, blinkt die LED für ca. 2 Sekunden schnell.

#### Technische Daten:

Spannungsversorgung: 24V AC/DC  $\pm$  20%  
Stromaufnahme: ca. 32 mA  
Ausgang: Impuls 1 Sek.,  
Ausgangsbelastung: 60V DC/1A/30W  
125V AC/1A/62VA  
Temperaturbereich: -20°C ... +60°C

### Receiver RCi01-3...

#### Connecting:

- Power supply : IN1, IN2
- Consumer: NO1-COM1 (NO-contact)  
NC1-COM1 (NC-contact)


#### Learning the transmitter:

- Press button TA1 for approx. 3 sec.
- The LED flashes up for approx. 10 sec.
- During the 10 sec, press the transmitter button.

If the receiver has learned the transmitter coding, the LED flashes up rapidly for approx. 2 Sec.

#### Specifications:

Power supply: 24V AC/DC  $\pm$  20%  
Current Input: approx. 32 mA  
Output: Impulse 1 Sec.  
Output rating: 60V DC/1A/30W  
125V AC/1A/62VA  
Temperature range: -20°C ... +60°C



08016678 0002