

Empfänger RCI02-3...

Anschließen:

- Spannungsversorgung: IN1, IN2
- Verbraucher1: NO1-COM1 Schliesser
NC1-COM1 Öffner
- Verbraucher2: NO2-COM2 Schliesser
NC2-COM2 Öffner

Sender lernen:

- Kanal 1 oder Kanal 2: Taste TA1 oder TA2 für ca. 3 Sek. betätigen.
- Die LED blinkt für ca. 10 Sek.
- Innerhalb der 10 Sek. Sendertaste betätigen.

Hat der Empfänger den Sendercode gespeichert, blinkt die LED für ca. 2 Sekunden schnell.

Technische Daten:

Spannungsversorgung: 24V AC/DC \pm 20%
Stromaufnahme: ca. 40 mA
Ausgang: Impuls 1 Sek.,
Ausgangsbelastung: 60V DC/1A/30W
125V AC/1A/62VA
Temperaturbereich: -20°C ... +60°C

Receiver RCI02-3...

Connecting:

- Power supply : IN1, IN2
- Consumer1: NO1-COM1 (NO-contact)
NC1-COM1 (NC-contact)
- Consumer2: NO2-COM2 (NO-contact)
NC2-COM2 (NC-contact)


Learning the transmitter:

- Channel 1 or Channel 2: Press button TA1 or TA2 for approx. 3 sec.
- The LED flashes up for approx. 10 sec.
- During the 10 sec. press the transmitter button.

If the receiver has learned the transmitter coding, the LED flashes up rapidly for approx. 2 Sec.

Specifications:

Power supply: 24V AC/DC \pm 20%
Current input: approx. 40 mA
Output: Impulse 1 Sec.
Output rating: 60V DC/1A/30W
125V AC/1A/62VA
Temperature range: -20°C ... +60°C



08013679 0002

FCC Compliance Statement:

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Information to the user:

Any modification to the unit could void the users Authority to operate the equipment