



July 25, 2011

Attn: Application Examiner, Reviewing Engineer

Since the Spectrum AWS Path1/PCS Path 1 MRAU is a low power device that is not hand-held, its antenna would rarely be within 20 cm of an individual, it operates above 1.5 GHz, and the ERP is less than 3 watts, we are in compliance with SAR requirements of 2.1091.

The maximum TX output power from the EUT antenna port is 25.76 dBm.
The maximum gain antenna that could be for use with the EUT has a gain of 9.01dBi.
From the following equations:

Peak Output of EUT at antenna Connector (dBm) + Gain of Antenna (dBd) = Peak TX Power (dBm) ERP

$10 * \text{Log}_{10}(\text{Peak TX Power} * E^3 \text{ Watts}) = \text{Peak TX Power (dBm) ERP}$

$25.76 \text{ dBm} + 9.01 \text{ dBi} = 34.77 \text{ dBm EIRP}$

$34.77 \text{ dBm ERP} = 3.0 \text{ Watts EIRP}$

To convert to EIRP use the relation: $\text{EIRP} = \text{ERP} * 1.64$. ($2.55 \text{ EIRP} = 1.56 \text{ ERP}$)

To convert to dBi to dBd use the relation: $\text{dBi} = \text{dBd} + 2.14$. ($7.14 \text{ dBi} = 5.0 \text{ dBd}$)

Per OET 65:

Maximum Permissible Exposure is 1.0 mW/cm^2 over 30 minutes. (1500 MHz - 100,000 MHz)

The following equations determine the distance from the antenna that the power density is $\leq 1.0 \text{ mW/cm}^2$.

$3.0 \text{ Watts EIRP} = 3.0 * 10^3 \text{ mWatts ERP}$

$1.0 \text{ mW/cm}^2 = 3.0 * 10^3 \text{ mW} / (4 * \pi * r^2)$

$r = \text{SQRT}(3.0 * 10^3 / 4 * \pi * 1.0)$

$r = 15.45 \text{ cm}$ or 0.1545 Meters

In addition, the following statement is in our installation manual:

To comply with Maximum Permissible Exposure (MPE) requirements, antennas must be installed to provide at least 20 centimeters of separation from all persons per FCC 47CFR, Part 2.1091 and IC RSS-102, Section 2.5.2.

Sincerely,

A handwritten signature in blue ink, appearing to read 'Joshua J. Wittman', is written over a horizontal blue line.

Joshua J. Wittman

Compliance Engineer

Tele: 952 403-8322

Fax: 952 403-8858

Email: joshua.wittman@te.com