



August 2, 2012

Attn: Application Examiner, Reviewing Engineer

August 2, 2012

Attn: Application Examiner, Reviewing Engineer

The maximum TX output power of the Spectrum 700 Path 2/AWS Path 2 SRAU from the AWS EUT antenna port 2 is 20.10 dBm. The maximum gain antenna that could be for use with the EUT has a gain of 14.67 dBi.

From the following equations:

Peak Output of EUT at antenna Connector (dBm) + Gain of Antenna (dBd) = Peak TX Power (dBm) ERP

$10 \cdot \log_{10}(\text{Peak TX Power} \cdot E^3 \text{ Watts}) = \text{Peak TX Power (dBm) ERP}$

20.10 dBm + 14.67 dBi = 34.77 dBm EIRP

34.77 dBm EIRP = 3.0 Watts EIRP

To convert to EIRP use the relation: EIRP = ERP \times 1.64. (2.55 EIRP = 1.56 ERP)

To convert to dBi to dBd use the relation: dBi = dBd + 2.14. (7.14 dBi = 5.0 dBd)

Per OET 65:

Maximum Permissible Exposure is 1.0 mW/cm² over 30 minutes. (1500 MHz - 100,000 MHz)

The following equations determine the distance from the antenna that the power density is $\leq 1.0 \text{ mW/cm}^2$.

3.0 Watts EIRP = $3.0 \cdot 10^3 \text{ mWatts EIRP}$

$1.0 \text{ mW/cm}^2 = 3.0 \cdot 10^3 \text{ mW} / (4 \cdot \pi \cdot r^2)$

$r = \text{SQRT}(3.0 \cdot 10^3 / 4 \cdot \pi \cdot 1.0)$

$r = 15.45 \text{ cm or } 0.1545 \text{ Meters}$

In addition, the following statement is in our installation manual:

To comply with Maximum Permissible Exposure (MPE) requirements, antennas must be installed to provide at least 20 centimeters of separation from all persons per FCC 47CFR, Part 2.1091 and IC RSS-102, Section 2.5.2

Sincerely,

A handwritten signature in blue ink, reading "Joshua J. Wittman", is written over a horizontal line.

Joshua J. Wittman
Compliance Engineer
Tele: 952 403-8322
Fax: 952 403-8858

Mailing Address: 1187 Park Place, Shakopee, Minnesota 55379
www.te.com

Email: joshua.wittman@te.com



Mailing Address: 1187 Park Place, Shakopee, Minnesota 55379
www.te.com



August 1, 2012

Attn: Application Examiner, Reviewing Engineer

The maximum TX output power of the Spectrum 700 Path2/AWS Path 2 SRAU from the EUT antenna port for the 700 path 2 band is 21.11 dBm. The maximum gain antenna that could be for use with the EUT has a gain of 13.66 dBi.

From the following equations:

Peak Output of EUT at antenna Connector (dBm) + Gain of Antenna (dBd) = Peak TX Power (dBm) ERP

$10 \cdot \log_{10}(\text{Peak TX Power} \cdot E^3 \text{ Watts}) = \text{Peak TX Power (dBm) ERP}$

21.11 dBm + 13.66 dBi = 34.77 dBm EIRP

34.77 dBm EIRP = 3.0 Watts EIRP

To convert to EIRP use the relation: EIRP = ERP \times 1.64. (2.55 EIRP = 1.56 ERP)

To convert to dBi to dBd use the relation: dBd = dBi + 2.14. (7.14 dBi = 5.0 dBd)

Power Density = $\text{EIRP(mW)} / (4 \cdot \pi \cdot r^2)$

$0.1491 \text{ mW/cm}^2 = (129.1)(23.22) / (4 \cdot \pi \cdot 40^2)$

Per OET 65:

Maximum Permissible Exposure is $\text{Freq. (MHz)} / 1500 = \text{MPE mW/cm}^2$

$737.0 \text{ MHz} / 1500 = 0.4913 \text{ mW/cm}^2$

In addition, the following statement is in our installation manual:

To comply with Maximum Permissible Exposure (MPE) requirements, antennas must be installed to provide at least 40 centimeters of separation from all persons per FCC 47CFR, Part 2.1091 and IC RSS-102, Section 2.5.2.

Sincerely,

A handwritten signature in blue ink, reading 'Joshua J. Wittman', is written over a horizontal blue line.

Joshua J. Wittman
Compliance Engineer

Tele: 952 403-8322

Fax: 952 403-8858

Email: joshua.wittman@te.com