

Model Name: BRFMS
 Type of product: Battery Radiofrequency Module
 Brand Name: Visteon
 Manufacturer: Visteon Corporation
 Manufacturer Address: One Village center drive, Van Buren Township
 48111-5711 Michigan
 United States of America

BRFM features:

The BRFM is an electronic module intended to aggregate data from up to 24 CMU units and module temperatures from the High Voltage battery bus in addition to pack voltage and current data collected from the Battery Disconnect Signal Board (BDSB) and from multiple Cell Monitoring Units (CMUs) to communicate them to the Vehicle Integration Control Module (VICM3).

All cell voltages, module temperatures, pack voltage and current are reported directly to the VICM3 on a regular periodic basis.

BRFM Single variant has a single wireless RFIC (Pinnacle) and one antenna.

The BRFM implements a Pinnacle IC (ADRF8850), this is an IC that provides wireless communication between the Battery Cell Monitoring chip and the Battery Management System Controller.

The BRFM includes a voltage supervisor/windowed watchdog (TPS3850) counter which generates a wake up signal to the VICM3 when any of the battery cells reports a critical condition when the VICM3 is sleeping.

The BRFM has two redundant sets of sensors that monitor the battery pack for excessive temperature, pressure, or hydrogen concentration that indicate a battery cell thermal runaway or thermal propagation.

System interaction:

<i>Module-to-Vehicle Electrical Interface</i>	
Analog Input	<i>VICM3 provides power to BRFM module. Power nominal value is 5.4V Minimum voltage expected is 5.2V and maximum is 5.6V.</i>
Analog Output	<i>BDSB Power Output is provided or enabled by BRFM module depending on variant. BDSB Power is provided by Single BRFM variant. BDSB Power nominal value is 5V. Minimum voltage expected is 4.2V and maximum is 5.5V</i>
Digital (discrete state) Output	<i>BDSB Power Output is provided or enabled by BRFM module depending on variant. BDSB Power is enabled by sending commands through the Dual BRFM variant. BDSB Power nominal value is 5V. Minimum voltage expected is 4.2V and maximum is 5.5V</i>
Communication Bus	<i>isoSPI communication serves as interface between BRFM and VICM3, as well as BRFM and BDSB. isoSPI lines shall be monitored to ensure proper performance. Amplitude and timing measurements should be captured. 1Mbps nominal is expected.</i>
RF Link(s)	<i>ISM Band (2.4GHz to 2.5GHz) used to communicate with CMU modules. Rx sensitivity shall be around 50% of PER, where each measurement shall vary by no more than +/- 2.0dB from the golden sample. Tx output power shall vary by no more than +/-2.5dB from the golden sample. Radio frequency reference shall be within ± 20PPM from desired frequency (2.44GHz, channel 7).</i>
<i>Module-to-Vehicle Non-Electrical Interface</i>	
<i>Pressure Sensors -> Values shall be between 50kPa and 150kPa ± 1% (0 – 150C) and ±2% (-40C – 0C)</i>	
<i>Hydrogen Sensors -> Values shall be between 0PPM and 65,000PPM ± 100PPM (5% of accuracy)</i>	
<i>Temperature Sensors -> Detection range shall be between -40C and 150C ± 1% of measured value</i>	
<i>Internal Interface</i>	
<i>Note: For these internal I/O, monitoring shall only occur via communication bus data or via indirect methods. Direct monitoring using attachments leads to external monitoring devices shall not be included.</i>	
Switching & Clock	<i>SPI communication shall be 1Mbps nominal. Used to communicate between RF manager to Sensors ASIC and RF Manager to isoSPI Transceiver.</i>

Frequency Content	RF Manager IC XTAL frequency shall be 40MHz nominal. Pressure sensor frequency shall be 20kHz. Hydrogen sensor frequency shall be 24.5kHz. UART communication between RF Manager 1 and RF Manager 2 for Dual BRFM variant. These shall be 1Mbps nominal.
Analog Output	
Digital (discrete state) Output	3.3V voltage output from U7/U9 shall be within the following range: $+3.25V < VOUT < +3.35V$ Main power supply (U30001) shall have an output voltage of 3.3V with $\pm 5mV$ peak-to-peak ripple voltage
Communication Bus	
<p>Note: This section assumes that production software is not mandatory; the use of specialized software is acceptable.</p> <p>Note: Software diagnostic timers should be reset to minimum detection values, to facilitate assertion of potential diagnostic flags during the RF exposure time (maximum 2 seconds).</p> <p>Note: States/faults/issues shall be reported directly over the communication bus (i.e., Class 2, Controller Area Network (CAN), etc.) or indirectly if the communication bus is not available via the cycling of output(s) (e.g., PWM duty cycle change, telltale flash rate change, etc.)</p> <p>Note: Unless otherwise specified in the EMC Test Plan, in order to ensure a refreshed value, all information related to data monitoring (such as analog input voltages, operating states, etc.) shall be via parameter requests (e.g., Parameter ID (PID)) and not via scheduled, or periodic, broadcast messages. This ensures bi-directional communications during immunity testing.</p>	

Harness Pinout, Capacities, and Use

Connector ID / Cavity #	Name	Description	Termination (R-L-C) etc.	Wire Gauge (AWG) Used in Vehicle	Twist w/ Cavity #	Shielded w/ Cavity #	Applicable Bands		
							Required for Module Operation	External Antenna Band WiFi	External Antenna Band YYYY
X1-1	BUF5V I	5V Input Power from VICM		16	n/a	n/a	Yes	n/a	n/a
X1-2	NC	NC		n/a	n/a	n/a	n/a	n/a	n/a
X1-3	NC	NC		n/a	n/a	n/a	n/a	n/a	n/a
X1-4	VICM_WU_SIG	Vehicle Integration Control Module Wake Up Signal	Connect to 5V	16	n/a	n/a	Yes	n/a	n/a
X1-5	BUF5V O	5V Output Power to BDSB	BDSB or simulator	16	n/a	n/a	Yes	n/a	n/a
X1-6	NC	NC		n/a	n/a	n/a	n/a	n/a	n/a
X1-7	RTN_5 VO	Ground to BDSB		16	n/a	n/a	Yes	n/a	n/a
X1-8	RTN_5 VI	Ground to VICM		16	n/a	n/a	Yes	n/a	n/a
X1-9	BRFM_SPLY_V_2	Battery Radio Frequency Module Supply Voltage 2		16	n/a	n/a	Yes	n/a	n/a
X1-10	NC	NC		n/a	n/a	n/a	n/a	n/a	n/a
X1-11	ISOSPI_PV2	isoSPI Positive 2 to VICM	100 ohm cross positive and negative	20	n/a	n/a	Yes	n/a	n/a
X1-12	ISOSPI_NV2	isoSPI Negative 2 to VICM							
X1-13	ISOSPI_PV1	isoSPI Positive 1 to VICM	100 ohm cross positive and negative	20	n/a	n/a	Yes	n/a	n/a

X1-14	ISOSPI_NV1	isoSPI Negative 1 to VICM							
X1-15	ISOSPI_PB1	isoSPI Positive 1 to BDSB 1	100 ohm cross positive and negative	20	n/a	n/a	Yes	n/a	n/a
X1-16	ISOSPI_NB1	isoSPI Negative 1 to BDSB 1							
X1-17	ISOSPI_PB2	isoSPI Positive 2 to BDSB 2	100 ohm cross positive and negative	20	n/a	n/a	Yes	n/a	n/a
X1-18	ISOSPI_NB2	IsoSPI Negative 2 to BDSB 2							
X1-19	NC	NC		n/a	n/a	n/a	n/a	n/a	n/a
X1-20	BRFM_RTN_2	Battery Radio Frequency Module Return 2	BDSB or simulation	16	n/a	n/a	Yes	n/a	n/a

The following information shall also be included in the case of radio equipment intentionally emitting radio waves:

- a. Frequency band : 2.4 – 2.5 GHz
- b. Maximum radio-frequency power transmitted in the frequency band(s) in which the radio equipment operates. Max output power = 10dBm

(U.S.A. and Canada)

FCC

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) The device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

RF exposure safety

*This device complies with the FCC RF exposure limits and has been evaluated in compliance with **portable** exposure conditions.*

*The equipment must be installed and operated and was evaluated with minimum distance of **11 cm** of the human body. This distance or greater is maintained by vehicle design and ensures compliance by normal use of the vehicle.*

ISED CANADA

This device complies with Industry Canada License-exempt RSS standard(s). Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) The device must accept any interference received, including interference that may cause undesired operation.

Le présent appareil est conforme aux CNR d'Industrie Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes:

- (1) l'appareil ne doit pas produire de brouillage, et,
- (2) l'utilisateur de l'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

RF exposure safety

*This device complies with ISED RF exposure limits and has been evaluated in compliance with **portable** exposure conditions.*

*The equipment must be installed and operated and was evaluated with minimum distance of **11 cm** of the human body. This distance or greater is maintained by vehicle design and ensures compliance by normal use of the vehicle.*

CAN ICES-003

Les changements ou modifications non expressément approuvés par la partie responsable de la conformité peuvent annuler le droit de l'utilisateur à utiliser l'équipement.

Sécurité d'exposition aux RF

*Cet appareil est conforme aux limites d'exposition RF d'ISDE et a été évalué conformément aux conditions d'exposition **portable**.*

*L'équipement doit être installé et utilisé à une distance minimale de **11 cm** du corps humain.*

CAN NMB-003

Cet appareil numérique de classe B est conforme à la norme canadienne NMB-003.

Part 15 – Interference Statement (On Part and in Owners Manual, or in Owners Manual)

NOTE: When the device is so small or for such use that it is not practicable to place the Interference Statement on it (e.g. TPMS), the below statement shall be placed in the Owners Manual:

"This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation."

Interference Statement (On Part and in Owners Manual, or in Owners Manual)

Licence-exempt radio apparatus shall contain the following or equivalent notice in a conspicuous location in the user manual or alternatively on the device or both.

This device complies with Innovation, Science, and Economic Development Canada (ISED) licence-exempt RSS standard(s).

Operation is subject to the following two conditions: (1) this device may not cause interference, and (2) this device must accept any interference, including interference that may cause undesired operation of the device