



RF EXPOSURE REPORT

Applicant	Lenovo (Shanghai) Electronics Technology Co., Ltd.
Address	Section 304-305, Building No. 4, # 222, Meiyue Road, China (Shanghai) Pilot Free Trade Zone

Manufacturer or Supplier	Lenovo PC HK Limited
Address	23/F, Lincoln House, Taikoo Place 979 King's Road, Quarry Bay, Hong Kong, China
Product	Lenovo Smart Clock
Brand Name	Lenovo
Model	Lenovo CD-4N342Y
Additional Model & Model Difference	N/A
Date of tests	Jul. 13, 2021 ~ Aug. 23, 2021

- ☒ FCC Part 2 (Section 2.1091)
☒ KDB 447498 D01
☒ IEEE C95.1

CONCLUSION: The submitted sample was found to COMPLY with the test requirement

Tested by Andy Zhu Supervisor / EMC Department	Approved by Glyn He Assistant Manager / EMC Department
	
	Date: Sep. 03, 2021

This report is governed by, and incorporates by reference, CPS Conditions of Service as posted at the date of issuance of this report at <https://www.cps.bureauveritas.com/terms-conditions> and is intended for your exclusive use. Any copying or replication of this report to or for any other person or entity, or use of our name or trademark, is permitted only with our prior written permission. This report sets forth our findings solely with respect to the test samples identified herein. The results set forth in this report are not indicative or representative of the quality or characteristics of the lot from which a test sample was taken or any similar or identical product unless specifically and expressly noted. Our report includes all of the tests requested by you and the results thereof based upon the information that you provided to us. Measurement uncertainty is only provided upon request for accredited tests. You have 60 days from date of issuance of this report to notify us of any material error or omission caused by our negligence or if you require measurement uncertainty; provided, however, that such notice shall be in writing and shall specifically address the issue you wish to raise. A failure to raise such issue within the prescribed time shall constitute your unqualified acceptance of the completeness of this report, the tests conducted and the correctness of the report contents.

TABLE OF CONTENTS

RELEASE CONTROL RECORD	3
1. CERTIFICATION.....	4
2. RF EXPOSURE LIMIT	5
3. MPE CALCULATION FORMULA.....	5
4. CLASSIFICATION	5
5. ANTENNA GAIN	6
6. CALCULATION RESULT OF MAXIMUM CONDUCTED POWER.....	6

RELEASE CONTROL RECORD

ISSUE NO.	REASON FOR CHANGE	DATE ISSUED
FM2107WDG0137	Original release	Sep. 03, 2021



Test Report No.: FM2107WDG0137

1. CERTIFICATION

PRODUCT: Lenovo Smart Clock

BRAND NAME: Lenovo

MODEL NO.: Lenovo CD-4N342Y

ADDITIONAL MODEL: N/A

FCC ID: O57CD4N342Y

TEST SAMPLE: ENGINEERING SAMPLE

APPLICANT: Lenovo (Shanghai) Electronics Technology Co., Ltd.

TESTED DATES: Jul. 13, 2021 ~ Aug. 23, 2021

STANDARDS: FCC Part 2 (Section 2.1091)
KDB 447498 D01
IEEE C95.1

2. RF EXPOSURE LIMIT

LIMITS FOR MAXIMUM PERMISSIBLE EXPOSURE (MPE)

FREQUENCY RANGE (MHz)	ELECTRIC FIELD STRENGTH (V/m)	MAGNETIC FIELD STRENGTH (A/m)	POWER DENSITY (mW/cm ²)	AVERAGE TIME (minutes)
LIMITS FOR GENERAL POPULATION / UNCONTROLLED EXPOSURE				
300-1500	F/1500	30
1500-100,000	1.0	30

F = Frequency in MHz

3. MPE CALCULATION FORMULA

$$P_d = (P_{out} \cdot G) / (4 \cdot \pi \cdot r^2)$$

where

P_d = power density in mW/cm²

P_{out} = output power to antenna in mW

G = gain of antenna in linear scale

π = 3.1416

R = distance between observation point and center of the radiator in cm

4. CLASSIFICATION

The antenna of this product, under normal use condition, is at least 20cm away from the body of the user. So, this device is classified as **Mobile Device**.

5. ANTENNA GAIN

The antennas provided to the EUT, please refer to the following table:

Frequency Band	Antenna Gain (dBi)	Antenna Type
BT	2.64	FPC Antenna
Wi-Fi 2.4GHz	2.64	FPC Antenna

6. CALCULATION RESULT OF MAXIMUM CONDUCTED POWER

The tuned conducted Average Power (declared by client)

Mode	Frequency (MHz)	Target Power (dBm)	Tolerance (dBm)	Lower Tolerance (dBm)	Upper Tolerance (dBm)
BT (GFSK)	2402-2480MHz	4	+1	3	5
BT (8DPSK)	2402-2480MHz	5	+1	4	6
BT-LE (GFSK)	2402-2480MHz	5	+2	3	7
802.11b	2412-2462MHz	14	+2	12	16
802.11g	2412-2462MHz	12	+2	10	14
802.11n HT20	2412-2462MHz	11	+2	9	13

The measured conducted Average Power

Mode	Frequency (MHz)	Averaged Power (dBm)
BT (GFSK)	2480	3.76
BT (8DPSK)	2480	5.18
BT-LE (GFSK)	2480	6.19
802.11b	2462	14.83
802.11g	2462	11.56
802.11n HT20	2462	10.96

FREQUENCY BAND (MHz)	MAX AVERAGE POWER (dBm)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/cm ²)	LIMIT (mW/cm ²)
BT	7	2.64	20	0.001831	1.0
Wi-Fi 2.4GHz	16	2.64	20	0.014546	1.0

CONCLUSION:

The BT and Wi-Fi can transmit simultaneously, the formula of calculated the MPE is:

$$CPD1 / LPD1 + CPD2 / LPD2 + \dots \text{etc.} < 1$$

CPD = Calculation power density

LPD = Limit of power density

$$(0.001831/1) + (0.014546/1) = 0.016377 < 1, \text{ which is less than the "1" limit.}$$

--- END ---