

CPE Antenna Gain	16 dBi	Integrated, Directional
-------------------------	---------------	-------------------------

Channel Spacing: 7MHz

Freq (MHz)	Gant (dBi)	BW (MHz)	TX set (dBm)	PPSD (cond) (dBm/MHz)	PPSD EIRP (dBm/MHz)	PPSD EIRP Limit (dBm/MHz)	Margin dB
3662.5	16	7	10	13.15	29.15	30	0.85

Channel Spacing: 3.5MHz

Freq (MHz)	Gant (dBi)	BW (MHz)	TX set (dBm)	PPSD (cond) (dBm/MHz)	PPSD EIRP (dBm/MHz)	PPSD EIRP Limit (dBm/MHz)	Margin dB
3662.5	16	3.5	9	13.9	29.9	30	0.1

AP Antenna Gain	16.5 dBi	External, Sectorized, 60deg
	1 dB	Cable loss

Channel Spacing: 7MHz

Freq (MHz)	Gant (dBi)	BW (MHz)	TX set (dBm)	PPSD (cond) (dBm/MHz)	PPSD EIRP (dBm/MHz)	PPSD EIRP Limit (dBm/MHz)	Margin dB
3662.5	15.5	7	10	14.45	29.95	30	0.05

Channel Spacing: 3.5MHz

Freq (MHz)	Gant (dBi)	BW (MHz)	TX set (dBm)	PPSD (cond) (dBm/MHz)	PPSD EIRP (dBm/MHz)	PPSD EIRP Limit (dBm/MHz)	Margin dB
3662.5	15.5	3.5	8	14.49	29.99	30	0.01

AP Antenna Gain	14 dBi	External, Sectorized, 90deg
	1 dB	Cable loss

Channel Spacing: 7MHz

Freq (MHz)	Gant (dBi)	BW (MHz)	TX set (dBm)	PPSD (cond) (dBm/MHz)	PPSD EIRP (dBm/MHz)	PPSD EIRP Limit (dBm/MHz)	Margin dB
3662.5	13	7	12	16.95	29.95	30	0.05

Channel Spacing: 3.5MHz

Freq (MHz)	Gant (dBi)	BW (MHz)	TX set (dBm)	PPSD (cond) (dBm/MHz)	PPSD EIRP (dBm/MHz)	PPSD EIRP Limit (dBm/MHz)	Margin dB
3662.5	13	3.5	10	16.97	29.97	30	0.03

AP Antenna Gain	10 dBi	External, Omni
	1 dB	Cable loss

Channel Spacing: 7MHz

Freq (MHz)	Gant (dBi)	BW (MHz)	TX set (dBm)	PPSD (cond) (dBm/MHz)	PPSD EIRP (dBm/MHz)	PPSD EIRP Limit (dBm/MHz)	Margin dB
3662.5	9	7	16	20.95	29.95	30	0.05

Channel Spacing: 3.5MHz

Freq (MHz)	Gant (dBi)	BW (MHz)	TX set (dBm)	PPSD (cond) (dBm/MHz)	PPSD EIRP (dBm/MHz)	PPSD EIRP Limit (dBm/MHz)	Margin dB
3662.5	9	3.5	14	20.97	29.97	30	0.03