

P2301B MOUSE BOM

ID	VALUE	REF	UNIT	Remark
1	Resistor			
2	RR0603L000JT	R50	1	
3	RR0603L470JT	R32	1	
4	RR0603L100JT	R42	1	
5	RR0603L221JT	R28	1	
6	RR0603L102JT	R16,R51	2	
7	RR0603L222JT	R52,R53	2	
8	RR0603L472JT	R49,R55	2	
9	RC-03K9101FC	R40	1	
10	RR0603L103JT	R20,R21,R22,R23,R24	5	
11	RR0603L223JT	R1,R2,R3,R4,R5,R6,R7,R8,R9,R10, R11,R12,R13,R19	14	
12	RR0603L333JT	R44	1	
13	RR0603L473JT	R26,R27,R29,R30,R31	5	
14	RC-03K6802FC	R39	1	
15	RR0603L104JT	R25	1	
16	RR0603L184JT	R48	1	
17	RR0603L224JT	R14,R15	2	
18	RR0603L274JT	R43	1	
19	RR0603L225JT	R54	1	
20	RC-05K120JT	R33,R34,R35,R36,R37,R38	6	
21	RC-05K331JT	R41	1	
22	RC-05K471JT	R17	1	
23	Capacitor			
24	C1608C0G1H150JT000A	C27	1	
25	C1608C0G1H270JT000A	C26	1	
26	C1608C0G1H300JT000A	C6,C7,C8,C21,C22	5	
27	C1608C0G1H101JT000A	C15,C16,C18,C19	4	
28	C1608C0G1H221JT000A	C40	1	
29	C1608X7R1H102KT000N	C24,C25	2	
30	C1608Y5V1H104ZT000N	C1,C2,C3,C4,C5,C10, C11,C12,C31,C36	10	
31	C1608Y5V1C105ZT000N	C29,C30	2	
32	C1608Y5V0J475Z	C32	1	
33	C2012X7R1E105KT	C35	1	
34	TAJB226K010RNJ	C38	1	
35	CD11X-25V-10uF±20%	C14	1	
36	CD11X-16V-22uF±20%	C28	1	
37	CD11X-16V-100uF±20%	C9,C13	2	
38	CD288H-25V-47uF±20%	C17	1	
39	Inductor			
40	CMI321611U2R2KT	L2	1	

P2301B MOUSE BOM

41	EC36-8R2J-T5	L3	1	
42	PK0608-221K	L1	1	
43	Diode			
44	1N372R0	D2	1	
45	1N4007	D3	1	
46	1N5819	D1	1	
47	1N4148	D4,D6,D7,D8,D9,D10	6	
48	ZMM5V1	ZW1	1	
49	Transistor			
50	KSC2223Y	Q1	1	
51	9014	Q2,Q7,Q8,Q9,Q10	5	
52	MMBT3906	Q11,Q12,Q13	3	
53	8550	Q3,Q4,Q5,Q6	4	
54	Photoelectricity module			
55	Infrared LED HLMP-ED80	LED1	1	P BIN
56	IC ADNS-2051	U1	1	
57	LED Cover B-SB-LED		1	
58	IC			
59	NE556	U6	1	
60	KS24C010	U2	1	
61	RT9261-33CX	U4	1	
62	XC61CN2402MR	U5	1	
63	RT9808-21CX	U9	1	
64	JS5618	U3	1	
65	Ceramic resonator			
66	XZT 18.432M2	X1	1	
67	XZT 6.00M2	X2	1	
68	Crystal Oscillator			
69	HC-49U/S 27.145MHz	X4	1	
70	Switch			
71	Micro switch KW10-01	SW1, SW2, SW3	3	
72	Encoder CER-B3F-NB	SW4	1	
73	Touch switch 2A055	SW5	1	
74	Other			
75	Jump JP100	SW6	1	Jump1、2PIN
76	White Wire B-DYX-30-180-3	ANT2	1	
77	Buzzer ATE1206-03	B1	1	
78	Linker PH2.54 1*4P L11.6/3.0 S/T	PA-1	1	
79	Linker PH2.54 1*5P L11.6/3.0 S/T	PB-1	1	
80	Linker FH2.54*6.8 1*4P S/T	PA-2	1	
81	Linker FH2.54*6.8 1*4P S/T	PB-2	1	
82	PCB P2302BV21-PCB1		1	

P2301B MOUSE BOM

83	PCB P2302BV21-PCB2		1	
84	Structural member			
85	Up cover	MP2302-01	1	
86	Bottom cover	P2302	1	
87	Battery cover	B-SB-DCM-7	1	
88	Mouse wheel	B-SB-LTGL	1	
89	Lens	HDNS-2100 #001	1	
90	AAA Battery Unite Spring	B-LJTH-7	1	
91	AAA Battery Cathode Spring	B-FJTH-7	1	
92	Battery Positive Spring	B-ZJTH-7	1	
93	Charge Plate metal	P2302-JCP	2	
94	Wheel rubber ring	B-SB-YWJQ	1	
95	Screw	HBB 1.8*4	5	
96	Screw	HBB 2.6*10	1	
97	"QC PASS" Label		1	
98	Black Wire	B-DYX-26-50-1	1	
99	Red Wire	B-DYX-26-60-2	1	
100	Black Wire	B-DYX-26-30-1	1	
101	Red Wire	B-DYX-26-30-2	1	
102	AAA batteries	550mAh Ni-MH	2	
103	Bottom mat	B-SB-JD-69*6	4	

Table:

Auditing :

Pass: