

**** MPE Calculations ****

The MPE calculation for this exposure is shown below.

The peak radiated output power (EIRP) is calculated as follows:

EIRP = P + G EIRP = 18.71dBm + 1.47 dBi EIRP = 20.18 dBm	Where, P = Power input to the antenna (mW) G = Power gain of the antenna (dBi)
--	--

Power density at the specific separation:

S = PG/(4R ² π) S = (74.30 * 1.34) / (4 * 20 ² * π) S = 0.0198 mW/cm ²	Where, S = Maximum power density (mW/cm ²) P = Power input to the antenna (mW) G = Numeric power gain of the antenna R = Distance to the center of the radiation of the antenna (20 cm = limit for MPE)
---	--

The Maximum permissible exposure (MPE) for the general population is 1 mW/cm² .

The power density does not exceed the 1 mW/cm² limit.

Therefore, the exposure condition is compliant with FCC rules.

Estimated safe separation:

R = √(PG / 4 π) R = √(74.30*1.34 / 4 π) R = 2.81 cm	Where, P = Power input to the antenna (mW) G = Numeric power gain of the antenna R = Distance to the center of the radiation of the antenna (20 cm = limit for MPE)
---	---

The numeric gain(G) of the antenna with a gain specified in dB is determined by:

$$G = \text{Log}^{-1} (\text{dB antenna gain} / 10)$$

$$G = \text{Log}^{-1} (1.47 / 10)$$

$$G = 1.34$$