



RF Exposure Evaluation Declaration

FCC ID: P27ME221

APPLICANT: Sercomm Corporation

Application Type: Class III Permissive Change

Product: Dual Band WiFi Mesh

Model No.: AME-4221SR

Brand Name: Airtel

FCC Classification: Unlicensed National Information Infrastructure (NII)

FCC Rule Part(s): 2.1091

Test Date: January 25~27, 2021

Reviewed By:

Oscar Shi

Oscar Shi

Approved By:

Robin Wu

Robin Wu



The test results relate only to the samples tested.

The test results shown in the test report are traceable to the national/international standards through the calibration of the equipment and evaluated measurement uncertainty herein.

The test report shall not be reproduced except in full without the written approval of MRT Technology (Suzhou) Co., Ltd.

Revision History

Report No.	Version	Description	Issue Date	Note
2012RSU016-U3	Rev. 01	Initial Report	04-13-2021	Valid

Note: Adding band U-NII-2A and U-NII-2C, requests a Class III Permissive Change for its application with FCC ID: P27OT221 granted on 10-26-2020 and 12-06-2020.

CONTENTS

Description	Page
1. GENERAL INFORMATION	4
1.1. Applicant	4
1.2. Manufacturer	4
1.3. Testing Facility	4
2. PRODUCT INFORMATION	5
2.1. Equipment Description	5
3. RF Exposure Evaluation.....	6
3.1. Limits	6
3.2. Test Result of RF Exposure Evaluation	7
Appendix A - EUT Photograph	8

1. GENERAL INFORMATION

1.1. Applicant

Sercomm Corporation

8F, No. 3-1, YuanQu St., NanKang, Taipei 115, Taiwan, R.O.C.

1.2. Manufacturer

Sercomm Corporation

8F, No. 3-1, YuanQu St., NanKang, Taipei 115, Taiwan, R.O.C.

1.3. Testing Facility

<input checked="" type="checkbox"/>	Test Site – MRT Suzhou Laboratory
	Laboratory Location (Suzhou – Wuzhong) D8 Building, No.2 Tian’edang Rd., Wuzhong Economic Development Zone, Suzhou, China
	Laboratory Location (Suzhou – SIP) 4b Building, Liando U Valley, No.200 Xingpu Rd., Shengpu Town, Suzhou Industrial Park, China
	Laboratory Accreditations
	A2LA: 3628.01 FCC: CN1166 VCCI: R-20025, G-20034, C-20020, T-20020
<input type="checkbox"/>	Test Site – MRT Shenzhen Laboratory
	Laboratory Location (Shenzhen) 1G, Building A, Junxiangda Building, Zhongshanyuan Road West, Nanshan District, Shenzhen, China
	Laboratory Accreditations
	A2LA: 3628.02 FCC: CN1284
<input type="checkbox"/>	Test Site – MRT Taiwan Laboratory
	Laboratory Location (Taiwan) No. 38, Fuxing 2 nd Rd., Guishan Dist., Taoyuan City 333, Taiwan (R.O.C.)
	Laboratory Accreditations
	TAF: L3261-190725 FCC: 291082, TW3261

2. PRODUCT INFORMATION

2.1. Equipment Description

Product Name	Dual Band WiFi Mesh
Model No.	AME-4221SR
Brand Name	Airtel
Serial No.	20210127Sample#01 (Conducted Sample)
Hardware Version	6.0
Software Version	AME4221SR_R1.9
Wi-Fi Specification	802.11a/b/g/n/ac
Antenna Delivery	2*T _X + 2*R _X

2.2. Description of Available Antennas

Antenna Type	Frequency Band (MHz)	T _X Paths	Max Antenna Gain (dBi)	Beamforming Directional Gain (dBi)	CDD Directional Gain (dBi)	
					For Power	For PSD
PIFA Antenna	2412 ~ 2462	2	3.30	6.31	3.30	6.31
	5250 ~ 5350	2	3.50	6.51	3.50	6.51
	5470~5725	2	3.40	6.41	3.40	6.41

Note 1: The EUT supports Cyclic Delay Diversity (CDD) technology for 802.11a/b/g/n/ac mode and beamforming technology for 802.11n/ac.

Note 2: The EUT CDD and beamforming mode signals are correlated.

If all antennas have the same gain, G_{ANT} , Directional gain = G_{ANT} + Array Gain, where Array Gain is as follows.

- For power spectral density (PSD) measurements on all devices,
Array Gain = $10 \log (N_{ANT} / N_{SS})$ dB = 3.01;
- For power measurements on IEEE 802.11 devices,
Array Gain = 0 dB for $N_{ANT} \leq 4$;

If antenna gains are not equal, Directional gain may be calculated by using the formulas applicable to equal gain antennas with G_{ANT} set equal to the gain of the antenna having the highest gain.

Note 3: The antenna gain is declared by manufacture.

3. RF Exposure Evaluation

3.1. Limits

According to FCC 1.1310: The criteria listed in the following table shall be used to evaluate the environment impact of human exposure to radio frequency (RF) radiation as specified in 1.1307(b)

LIMITS FOR MAXIMUM PERMISSIBLE EXPOSURE (MPE)

Frequency Range (MHz)	Electric Field Strength (V/m)	Magnetic Field Strength (A/m)	Power Density (mW/cm ²)	Average Time (Minutes)
(A) Limits for Occupational/ Control Exposures				
300-1500	--	--	f/300	6
1500-100,000	--	--	5	6
(B) Limits for General Population/ Uncontrolled Exposures				
300-1500	--	--	f/1500	6
1500-100,000	--	--	1	30

f= Frequency in MHz

Calculation Formula: $P_d = (P_{out} * G) / (4 * \pi * r^2)$

Where

P_d = power density in mW/cm²

P_{out} = output power to antenna in mW

G = gain of antenna in linear scale

π = 3.1416

r = distance between observation point and center of the radiator in cm

P_d is the limit of MPE, 1mW/cm². If we know the maximum gain of the antenna and the total power input to the antenna, through the calculation, we will know the distance r where the MPE limit is reached.

3.2. Test Result of RF Exposure Evaluation

Product	Dual Band WiFi Mesh
Test Item	RF Exposure Evaluation

Test Mode	Frequency Band (MHz)	Maximum EIRP (dBm)	Power Density at R = 20 cm (mW/cm ²)	Limit (mW/cm ²)
Wi-Fi	2412 ~ 2462	32.87	0.3854	1
	5150 ~ 5850	33.30	0.4256	1

CONCLUSION:

2.4G Wi-Fi and 5G Wi-Fi can transmit simultaneously.

Therefore, the Max Power Density at R (20 cm) = $0.3854 \text{ mW/cm}^2 + 0.4256 \text{ mW/cm}^2 = 0.8110 \text{ mW/cm}^2 < 1 \text{ mW/cm}^2$.

So the safety distance is 20cm for Dual Band WiFi Mesh installed without any other radio equipment

_____ The End _____

Appendix - EUT Photograph

Refer to “2101RSU064-UE” file.