

**Wireless Headset System**  
Wireless Headset Model: AD688H  
Base unit Model: AD688B  
User's Guide



## Package Contents



## Get Ready

- Insert AA battery into Base.
- Dock headset onto base to charge.

## Get Set

- Allow 4 hours for full charge.
- Insert coiled cord into base and cell phone headset jacks.

## Go

- Use your phone and Docker headset just like a wired headset.

## When not in use

- Dock the headset to the base.
- The base will automatically keep the headset fully charged.

### Battery Care

- Insert AA Battery
  - Battery button end (+) at the flat spring
  - Green Light Indicates normal operation
  - Red light indicates AA battery is low. Replace the battery at your earliest convenience.
  - Remove spent batteries from the housing to avoid damage from leakage.
- Docking charges the headset
  - Solid light for 5 to 30 seconds while the base checks the headset battery level.
  - Light blinks once every 3 seconds during charge.
  - Light turns off when the headset is fully charged.

### Connecting to your phone

- A short coiled cord is provided
- Insert one end into the Docker headset jack
- Insert the other end into the cell phone.
- The light will blink once per second when the headset is removed from the base.

### To suspend headset operation

- Dock the headset to the base
- Hold the Flash button until the LED blinks rapidly (about 5 times per second)
- Release Flash button
- Headset will turn on for use when removed from the dock.

### Trouble Indicator

- An amber flashing light on the base indicates trouble. Dock the headset and wait for a blinking green light

### Customize your headset for your convenience.

- Adjust Headset volume with the volume button.

Tone	Meaning
1 Beep	Volume was changed
2 High Beeps	Maximum Volume
2 Low Beeps	Minimum Volume

- The headset will retain the volume setting for the next time you use the phone, but it can be readjusted any time.

### Change the ear you use

- Grasp the hook at the base near the headset post.
- Gently but firmly pull the ear-hook off of the post.
- Turn the ear hook over.
- Push the ear hook back over the post

### Flash Button Use

- Your Docker headset will send flash signals to your phone when the Flash button is pushed.
- Your phone will determine what the Flash button will initiate. (Refer to your phone's user Manual.)
- Many phones with voice recognition will be enabled for voice reception by a flash

### Tones Provide Status Information

Tone	Meaning
2 quick beeps per second for 8 seconds	Base and headset are out of range
3 quick beeps every 45 seconds	Low headset battery
6 quick beeps	Headset is shutting down due to a critically low battery

## Specifications

<b>Audio Jack</b>	<b>2.5mm, 3 pin</b>
<b>Adapters Included</b>	<b>Yes</b>
<b>Typical Use</b>	<b>3 months</b> Based on an average of 500 minutes use per month
<b>Range</b>	<b>1.5 Meters</b>
<b>Base Battery</b>	<b>AA Alkaline</b>
<b>Headset Battery</b>	<b>40mAH NiMH</b> chargeable, non-replaceable
<b>Headset Weight</b>	<b>18 grams</b>
<b>Base Weight</b>	<b>50 grams with AA</b>
<b>Headset Dimensions</b>	<b>L105 X W21mm</b>
<b>Base Dimensions</b>	<b>L64 X W46 X H21mm</b>
<b>Earhook</b>	<b>Replaceable</b> Extra provided
<b>End call (flash) ready</b>	<b>Yes</b>
<b>End call tone</b>	<b>Yes</b>
<b>Headset volume control</b>	<b>Yes</b>
<b>Battery low warning</b>	<b>Yes - Tones / LED</b>
<b>Out of range warning</b>	<b>Yes - Tones</b>
<b>Charge indicator</b>	<b>Yes - LED</b>
<b>Belt attachment</b>	<b>Yes</b>
<b>FCC Compliance</b>	<b>By manufacturer</b>
<b>Transmission type</b>	<b>Magnetic Induction</b>

## Troubleshooting

<b>Problem</b>	<b>Solution</b>
No Light No sound	1. Check AA battery orientation 2. Replace AA Battery, Charge Headset
Red light	Replace AA battery at your earliest convenience
Flashing Orange Light	Dock the headset and wait up to 30 seconds for normal flashing green light
Phone does not respond to the headset	Coiled cord is not properly connected to the phone
People say my voice is too faint (or too loud)	Adjust the microphone volume 1. Undock the headset 2. Place a phone call to someone who will help you set a comfortable level 3. Hold the volume button down until the light is continuously lit 4. Release the volume button 5. Light will blink 1, 2, 3, times (low medium or high) to indicate the current microphone setting. 6. Press and release the volume button once for each level change to cycle through the settings. 7. Confirm the best setting with the call recipient. 8. Wait 15 seconds without pressing any buttons for the units to return to normal operation.

## Safety and Additional Information

- Avoid extreme temperatures, moisture and dust
- Clean only with a soft, dry cloth
- Do not attempt to open the units. There are no user serviceable parts inside. Doing so will void the warranty
- Keep the headset docked to the base when not in Use
- Replace the AA Base battery when the light turns red.
- Do not bend the housing or microphone boom.
- Check laws and regulations for the use of mobile phones and hands free equipment in your area
- Always give full attention to driving and pull off the road and park before making or answering a call if driving conditions so require.
- Your Docker headset operates at 13.56 MHz at power levels typically less than 1/10,000,000 that of your cell phone.
- Do not use your Docker headset near medical equipment without requesting permission.
- If you are using any personal medical devices e.g. a pace maker or hearing aid, please refer to the appropriate documentation or the medical equipment manufacturer.
- Turn off all electronic devices in any area with a potentially explosive or flammable atmosphere
- Follow directions to suspend operation when instructed by aircraft personnel to turn off all electronic devices.
- Recharge your headset only at temperatures between 0 and 65 C or battery damage may occur.

## Warranty

Aura Communications warrants that Products delivered hereunder, under normal use, shall be free of defects in materials and workmanship and comply with the Aura's Product Specification for a period of three (3) months from the date of purchase. If, during this warranty period, any Product is defective, the buyer shall return the unit with dated proof of purchase to Aura Communications, 187 Ballardvale St., Wilmington MA, 01887. Aura may at its sole option repair, replace, or credit Buyer the purchase price of such Product.

**AURA MAKES NO OTHER WARRANTIES, EXPRESS OR IMPLIED, WITH RESPECT TO PRODUCTS OR TO ANY OTHER MATERIALS, GOODS OR SERVICES FURNISHED HEREUNDER, AND HEREBY SPECIFICALLY DISCLAIMS ALL IMPLIED WARRANTIES, BY OPERATION OF LAW OR OTHERWISE, INCLUDING WITHOUT LIMITATION WARRANTIES OF MERCHANTABILITY, AND FITNESS FOR ANY PURPOSE.**

## Regulatory Information

### USA

1. This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

2. This device has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in the residential installation. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of these measures:

- reorient or relocate the receiving antenna
- increase the separation between the equipment and receiver
- consult the dealer or experienced radio/TV technician for help

3. This device has been evaluated and found to comply with FCC radio frequency human exposure limits.

**Caution: Any changes or modification by user, not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.**

### **Battery replacement and disposal**

This device contains rechargeable Ni-MH battery in the Headset unit and disposable AA battery in the Base unit. It is recommended that replacement of Ni-MH battery should be done by Aura Communications Inc. or authorized third party personnel. Under local law it may be illegal to dispose old Ni-MH batteries by putting them in the trash. Please contact the local authorities or Aura Communications Inc. to find out the proper recycling information for the old batteries.



## **Contact Information:**

### **Corporate Headquarters**

Aura Communications

187 Ballardvale St.

Wilmington, MA. 01887

Tel: +1.978.988.0088

Fax: +1.978.988.3977

Email: [info@auracomm.com](mailto:info@auracomm.com)

[www.auracomm.com](http://www.auracomm.com)

Copyright 2003 Aura Communications, all rights reserved. Aura and LibertyLink are trademarks of Aura Communications which may be registered in certain jurisdictions. Aura Communications reserves the right to make changes to this specification without notice.

---