



# CTC Laboratories, Inc. (FCC Designation Number: CN1208)

Room 101 Building B, No. 7, Lanqing 1st Road, Luhua Community, Guanhu Subdistrict, Longhua District, Shenzhen, Guangdong, China

Tel: +86-755-27521059 Fax: +86-755-27521011 <http://www.sz-ctc.org.cn>

## Maximum Permissible Exposure Evaluation

FCC ID: PADWF151

According to FCC 1.1310: The criteria listed in the following table shall be used to evaluate the environment impact of human exposure to radio frequency (RF) Radiation as specified in §1.1307(b).

### EUT Specification

Applicant	Wahoo Fitness LLC
Address	90 W. Wieuca Road #110, Atlanta, GA 30342, United States
Product Name:	Speed Sensor
Trade Mark:	/
Model/Type Reference:	WF151
Listed Model(s):	/
Model Differences:	/
Frequency Band (Operating)	BT: 2402~2480MHz ANT+: 2457MHz
Device Category	<input type="checkbox"/> Portable (<5mm separation) <input type="checkbox"/> Mobile (>20cm separation) <input checked="" type="checkbox"/> Fixed (>20cm separation) <input type="checkbox"/> Others ____
Exposure Classification	<input type="checkbox"/> Occupational/Controlled exposure (S=5mW/cm <sup>2</sup> ) <input checked="" type="checkbox"/> General Population/Uncontrolled exposure (S=1mW/cm <sup>2</sup> )
Antenna Diversity	<input checked="" type="checkbox"/> Single antenna <input type="checkbox"/> Multiple antennas <input type="checkbox"/> TX diversity <input type="checkbox"/> RX diversity <input type="checkbox"/> TX/RX diversity
Antenna Gain (Max)	-0.21dBi
Evaluation Applied	<input checked="" type="checkbox"/> MPE Evaluation <input type="checkbox"/> SAR Evaluation

CTC Laboratories, Inc.

Room 101 Building B, No. 7, Lanqing 1st Road, Luhua Community, Guanhu Subdistrict, Longhua District, Shenzhen, Guangdong, China  
Tel.: (86)755-27521059 Fax: (86)755-27521011 [Http://www.sz-ctc.org.cn](http://www.sz-ctc.org.cn)



For anti-fake verification, please visit the official website of Certification and Accreditation Administration of the People's Republic of China : [yz.cnca.cn](http://yz.cnca.cn)

**Limits for Maximum Permissible Exposure (MPE)**

Frequency Range (MHz)	Electric Field Strength (V/m)	Magnetic Field Strength (A/m)	Power Density (mW/cm <sup>2</sup> )	Averaging Time (minutes)
(A) Limits for Occupational/Controlled Exposure				
300-1500	--	--	F/300	<6
1500-100000	--	--	5	<6
(B) Limits for General Population/Uncontrolled Exposure				
300-1500	--	--	F/1500	<30
1500-100000	--	--	1	<30

**Calculation Method**

Friis transmission formula:  $P_d = (P_{out} * G) / (4 * \pi * R^2)$

Where:

$P_d$  = Power density in mW/cm<sup>2</sup>

$P_{out}$  = output power to antenna in mW

G = gain of antenna in linear scale

$\pi$  = 3.1416

R = distance between observation point and center of the radiator in cm

$P_d$  limit of MPE is 1mW/cm<sup>2</sup>. If we know the maximum gain of the antenna and total power input to the antenna, through the calculation, we will know the distance where the MPE limit is reached.

$$eirp = pt \times gt = (E \times d)^2 / 30$$

where:

pt = transmitter output power in watts,

gt = numeric gain of the transmitting antenna (unitless),

E = electric field strength in V/m, ---  $10^{((dBuV/m)/20)/10^6}$

d = measurement distance in meters (m), --- 3m

$$\text{So } pt = (E \times d)^2 / (30 \times gt)$$

ANT+ 2457MHz Field strength = 85.41 dBuV/m @3m

Ant gain = -0.21dBi, Ant numeric gain = 0.95

$$\text{So } pt = \{ [10^{(85.41/20)} / 10^6 \times 3]^2 / (30 \times 0.95) \} \times 1000 \text{ mW} = 0.1094 \text{ mW} = -9.61 \text{ dBm}$$



Measurement Result

Mode	Frequency (MHz)	Antenna Gain (dBi)	Maximum Power (dBm)	Tune Up Tolerance (dB)	Max. Tune Up Power (dBm)	Power Density at 20cm (mW/cm <sup>2</sup> )	Limit (mW/cm <sup>2</sup> )	Result
BLE 1M	2402	-0.21	3.06	± 1	4.00	0.00048	1	Pass
ANT+	2457	-0.21	-9.61	± 1	-8.50	0.00003	1	Pass

Note:

1. Calculate in the worst-case mode.
2. Max. Tune Up Power is declared by manufacturer, and used to calculate.
3. For a more detailed features description, please refer to the RF Test Report.
4. BLE and ANT+ can't transmit simultaneously.

\*\*\*\*\*THE END\*\*\*\*\*