

**** MPE Calculations ****

The MPE calculation for this exposure is shown below.

The peak radiated output power (EIRP) is calculated as follows:

EIRP = P + G EIRP = 9.07 dBm + 3.423 dBi EIRP = 12.49 dBm	Where, P = Power input to the antenna (mW) G = Power gain of the antenna (dBi)
---	--

Power density at the specific separation:

$S = PG / (4R^2 \pi)$ $S = (8.07 * 2.20) / (4 * 20^2 * \pi)$ $S = 0.0035 \text{ mW/cm}^2$	Where, S = Maximum power density (mW/cm ²) P = Power input to the antenna (mW) G = Numeric power gain of the antenna R = Distance to the center of the radiation of the antenna (20cm = limit for MPE)
---	---

The Maximum permissible exposure (MPE) for the general population is 1 mW/cm².

The power density does not exceed the 1 mW/cm² limit.

Therefore, the exposure condition is compliant with FCC rules.

Estimated safe separation:

$R = \sqrt{PG / 4 \pi}$ $R = \sqrt{8.07 * 2.20 / 4 \pi}$ $R = 1.19 \text{ Cm}$	Where, P = Power input to the antenna (mW) G = Numeric power gain of the antenna R = Distance to the center of the radiation of the antenna (20cm = limit for MPE)
--	--

The numeric gain(G) of the antenna with a gain specified in dB is determined by:

$$G = \text{Log}^{-1} (\text{dB antenna gain} / 10)$$

$$G = \text{Log}^{-1} (3.423 / 10)$$

$$G = 2.20$$