

# **MPE Calculations**

Systems operating under the provision of 47 CFR 1.1307(b)(1) shall be operated in a manor that ensures that the public is not exposed to radio frequency energy levels in excess of the FCC guidelines.

The EUT will only be used with a separation of 20 centimeters or greater between the antenna and the body of the user or nearby persons and can therefore be considered a mobile transmitter per 47 CFR 2.1091(b). The MPE calculation for this exposure is shown below.

### Using the Antennas with highest output power:

### The peak radiated output power (EIRP) is calculated as follows:

Antenna	Frequency (GHz)	Power input to the antenna (P) (dBm)	Power gain of the antenna (G) (dBi)	EIRP (P+G) (dBm)	EIRP Log <sup>-1(dBm/10)</sup> (mW)
Fujitsu Falcon/Fennec	2.4	24.84	1.66	26.50	446.68
Fujitsu Falcon/Fennec	5	19.80	3.19	22.99	199.07

EIRP = P + G

Where

P = Power input to the antenna (mW).

G = Power gain of the antenna (dBi)

## The numeric gain (G) of the antenna with a gain specified in dB is determined by:

Antenna	Frequency (GHz)	Antenna Gain (G) (dBi)	Numeric Antenna Gain Log <sup>-1(dBm/10)</sup> (dB)
Fujitsu Falcon/Fennec	2.4	1.66	1.47
Fujitsu Falcon/Fennec	5	3.19	2.08

 $G = Log^{-1}$  (dB antenna gain/10)

#### Power density at the specific separation:

Antenna	Frequency (GHz)	Power input to the antenna (P) (mW)	Numeric Power Gain of the Antenna (G) (dB)	Maximum Power Spectral Density S=PG/(4R <sup>2</sup> π) (mW/cm <sup>2</sup> )	Maximum Power Spectral Density Limit (mW/cm <sup>2</sup> )
Fujitsu Falcon/Fennec	2.4	304.79	1.47	0.089	1.00
Fujitsu Falcon/Fennec	5	95.50	2.08	0.040	1.00

 $S = PG/(4R^2\pi)$ 

Where

S = Maximum power density (mW/cm<sup>2</sup>)

P = Power input to the antenna (mW).

G = Numeric power gain of the antenna

R = Distance to the center of the radiation of the antenna (20cm = limit for MPE)

The maximum permissible exposure (MPE) for the general population is 1mW/cm<sup>2</sup>.

The power density at 20cm does not exceed the 1mW/cm<sup>2</sup> limit. Therefore, the exposure condition is compliant with FCC rules.