



FCC TEST REPORT

REPORT NO.: RF911026R01A

MODEL NO.: WMP55AG

ACCORDING: FCC Guidelines for Human Exposure
IEEE C95.1

APPLICANT: The Linksys Group, Inc.

ADDRESS: 17401 Armstrong Ave., Irvine, CA 92614

ISSUED BY: Advance Data Technology Corporation

LAB LOCATION: 47 14th Lin, Chiapau Tsun, Linko, Taipei,
Taiwan, R.O.C.



0528
ILAC MRA



Lab Code: 200102-0



RF Exposure Measurement

1. Introduction

In this document, we try to prove the safety of radiation harmfulness to the human body for our product. The limit for Maximum Permissible Exposure (MPE) specified in FCC 1.1310 is followed. The Gain of the antenna used in this product is measured in a Fully Anechoic Chamber (FAC) calibrated for antenna measurement in ADT, and also the maximum total power input to the antenna is measured. Through the Friis transmission formula and the maximum gain of the antenna, we can calculate the distance, away from the product, where the limit of MPE is reached.

Although the Friis transmission formula is a far field assumption, the calculated result of that is an over-prediction for near field power density. We will take that as the worst case to specify the safety range.

2. RF Exposure Limit

According to FCC 1.1310: The criteria listed in the following table shall be used to evaluate the environmental impact of human exposure to radio-frequency (RF) radiation as specified in 1.1307(b)

LIMITS FOR MAXIMUM PERMISSIBLE EXPOSURE (MPE)

Frequency Range (MHz)	Electric Field Strength (V/m)	Magnetic Field Strength (A/m)	Power Density (mW/cm ²)	Average Time (minutes)
(A)Limits For Occupational / Control Exposures				
300-1500	F/300	6
1500-100,000	5	6
(B)Limits For General Population / Uncontrolled Exposure				
300-1500	F/1500	6
1500-100,000	1.0	30

F = Frequency in MHz



3. Friis Formula

Friis transmission formula : $P_d = (P_{out} * G) / (4 * \pi * r^2)$

where

P_d = power density in mW/cm^2

P_{out} = output power to antenna in mW

G = gain of antenna in linear scale

π = 3.1416

R = distance between observation point and center of the radiator in cm

P_d is the limit of MPE, $1 mW/cm^2$. If we know the maximum Gain of the antenna and the total power input to the antenna, through the calculation, we will know the MPE value at distance 20cm.

Ref. : David K. Cheng, *Field and Wave Electromagnetics*, Second Edition,
Page 640, Eq. (11-133).

4 EUT Operating condition

The software provided by Manufacturer enabled the EUT to transmit and receive data at lowest, middle and highest channel individually.

5 Climate Condition

The temperature and related humidity: 20 deg. C and 63 % RH

6. Classification

This device is not fixed inside the host equipment, it is connected with host through wire. So it is easy to be re-located in the place where at least 20 cm far away from the body of the user. Warning statement to the user for keeping at least 20cm or more separation distance with the antenna should be included in users manual. So, this device is classified as **Mobile Device**.



7 Test Results

7.1 Antenna Gain

The maximum Gain measured in Fully Anechoic Chamber are 1dBi or 1.26 (numeric) for 2.4GHz and 2dBi or 1.58 (numeric) for 5GHz.

7.2 Output Power Into Antenna & RF Exposure value at distance 20cm:

For 802.11b (2.4GHz Band):

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm ²)	Limit of Power Density (mW/cm ²)
1	2412	93.33	0.023	1.0
6	2437	85.51	0.021	1.0
11	2462	81.10	0.020	1.0

For 802.11a (5GHz Band):

Normal Mode :

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm ²)	Limit of Power Density (mW/cm ²)
1	5180	41.88	0.013	1.0
4	5240	45.29	0.014	1.0
5	5260	36.90	0.012	1.0
8	5320	41.59	0.013	1.0
9	5745	31.62	0.010	1.0
12	5805	30.20	0.010	1.0

Turbo Mode :

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm ²)	Limit of Power Density (mW/cm ²)
1	5210	46.24	0.015	1.0
2	5250	37.76	0.012	1.0
3	5290	39.26	0.012	1.0
4	5760	28.18	0.009	1.0
5	5800	25.12	0.008	1.0