

chapter 5:Hardware Installation

Please follow these steps in order to assure that your series of mainboard installation is successful. Please refer to the back chapters for further information regarding boot-up and configurations. An anti-static wrist band is recommended when handling electronic components, be sure your work area is static free before you begin this section.

1.Reference User Manual,Check the setting of mainboard accord with describe.

2.Installing the Central Processing Unit

The mainboard provides a 478 pins, CPU Socket. Simply disengage the lever from the locking latch, lift it to its vertical position. Match the triangle markings on both the CPU and the Socket478, Carefully drop the CPU into the socket such that all the CPU pins entered the holes in the socket. Apply slight pressure if necessary. Make sure the CPU is level with the surface of the socket. Maintain a slight pressure on the CPU and rotate the lever back to its horizontal (or locking) position, and snap the lever back to the locking latch.

