



3301 E. Deseret Drive, St. George, UT 84790
www.wilsonelectronics.com • info@wilsonelectronics.com
phone 1-800-204-4104 • fax 1-435-656-2432

March 9, 2017
Subject: Antenna Kitting
Re: FCC ID: PWO460021
To Whom It May Concern:

The antenna kitting options for model 460021 signal booster were done for 51 Outside Antenna kit options and 19 Inside Antenna kit options. The order of the attached calculations is as follows:

Outside Antenna Kit Options:

Fixed

1. Kit 314411-40075
2. Kit 314411-5825
3. Kit 314475-0630
4. Kit 301111-0675
5. Kit 301111-5850
6. Kit 311203-40020
7. Kit 314453-5825
8. Kit 311203-5820
9. Kit 311201-0620
10. Kit 301126
11. Kit 301111-11140
12. Kit 311201-1120
13. Kit 314453-40075
14. Kit 314473-0640
15. Kit 311141-0620
16. Kit 311141-1120
17. Kit 314473-1175
18. Kit 314475-1175
19. Kit 301111-400170
20. Kit 304421-1120
21. Kit 304421-17410
22. Kit 304421-0610
23. Kit 304421-5810

Mobile

24. Kit 304422-40020
25. Kit 304422-5810
26. Kit 304422-1120
1. Kit 311703
2. Kits 301103, 311125,
311128, 314202
3. Kit 311130-5810
4. Kit 311114
5. Kit 311102
6. Kit 311104-5810
7. Kit 311701
8. Kit 311119
9. Kit 311133
10. Kit 311104-17410
11. Kit 301113
12. Kit 311112-5810
13. Kit 314203-5810
14. Kit 311112-17410
15. Kit 314203-17410
16. Kit 311101
17. Kit 304414, 304415
18. Kit 304416
19. Kit 304420

Inside Antenna Kit Options:

Mobile

1. Kit 301152
2. Kit 311106
3. Kit 311249

Fixed

1. Kit 311135-40060
2. Kit 311155-40060
3. Kit 311135-5820
4. Kit 311155-0630
5. Kit 309900-50N
6. Kit 309902-75F
7. Kit 309903-75F
8. Kit 309904-75F
9. Kit 309905-50N
10. Kit 311155-1150
11. Kit 304412-40010
12. Kit 304412-5810
13. Kit 304419-1110
14. Kit 304419-17410
15. Kit 304419-0610
16. Kit 301211

All equivalent or lesser antennas and cables are suitable for use with 460021 signal booster.

Sincerely,

Patrick L. Cook
Chief Technology Officer



Fixed Outside Antenna Kit Options

FCC ID: PWO460021

Final Output Power Limited to 30 dBm EIRP in all frequency bands

Uplink Frequency (MHz)	698-716	777-787	824-849	1710-1755	1850-1915
Uplink Output Power (dBm)	24.84	24.35	24.1	21.3	24.4

1 Wide Band Directional Antenna With 75' Wilson 400 314411-40075

Antenna Gains (dBi)	7.3	7.2	7.8	7.9	9.1
Coax Loss (dB)	2.8	3.0	3.6	4.4	5.4
Final Gain less Loss (dB)	4.5	4.2	4.2	3.5	3.7
Output Power plus Final Gain (dBm EIRP)	29.34	28.55	28.3	24.8	28.1

2 Wide Band Directional Antenna With 25' RG-58 314411-5825

Antenna Gains (dBi)	7.3	7.2	7.8	7.9	9.1
Coax Loss (dB)	2.9	3.1	3.2	5.1	5.4
Final Gain less Loss (dB)	4.4	4.1	4.6	2.8	3.7
Output Power plus Final Gain (dBm EIRP)	29.2	28.5	28.7	24.1	28.1

3 Wide Band Directional Antenna With 30' RG-6 314475-0630

Antenna Gains (dBi)	7.3	7.2	7.8	7.9	9.1
Coax Loss (dB)	3.0	3.2	3.4	5.1	5.3
Final Gain less Loss (dB)	4.3	4	4.4	2.8	3.8
Output Power plus Final Gain (dBm EIRP)	29.14	28.4	28.5	24.1	28.2

4 Yagi Antenna 301111 With 75' RG-6 301111-0675

Antenna Gains (dBi)	10.0	10.0	10.8	-6.8	-13.8
Coax Loss (dB)	5.7	6.075	6.3	9.525	9.975
Final Gain less Loss (dB)	4.3	3.925	4.5	-16.325	-23.775
Output Power plus Final Gain (dBm EIRP)	29.14	28.3	28.6	5.0	0.6

5 Yagi Antenna 301111 With 50' RG-58 301111-5850

Antenna Gains (dBi)	10.0	10.0	10.8	-6.8	-13.8
Coax Loss (dB)	5.8	6.2	6.5	10.3	10.7
Final Gain less Loss (dB)	4.2	3.8	4.3	-17.1	-24.5
Output Power plus Final Gain (dBm EIRP)	29.0	28.1	28.4	4.2	-0.1

6 Omni Directional Antenna (311203) With 20' Wilson 400 311203-40020

Antenna Gains (dBi)	-1.5	-0.24	0.57	-2.51	5.09
Coax Loss (dB)	0.7	0.7	0.7	1.1	1.1
Final Gain less Loss (dB)	-2.2	-0.94	-0.13	-3.61	4.0
Output Power plus Final Gain (dBm EIRP)	22.6	23.4	24.0	17.7	28.4



Fixed Outside Antenna Kit Options

FCC ID: PWO460021

Final Output Power Limited to 30 dBm EIRP in all frequency bands

Uplink Frequency (MHz)	698-716	777-787	824-849	1710-1755	1850-1915
Uplink Output Power (dBm)	24.84	24.35	24.1	21.3	24.4

7 Panel Antenna With 25' RG-58 314453-5825

Antenna Gains (dBi)	3.84	3.63	4.4	8.21	10.04
Coax Loss (dB)	2.9	3.1	3.2	5.1	5.4
Final Gain less Loss (dB)	0.9	0.5	1.2	3.1	4.6
Output Power plus Final Gain (dBm EIRP)	25.8	24.9	25.3	24.4	29.0

8 Omni Directional Antenna (311203) With 20' RG-58 311203-5820

Antenna Gains (dBi)	-1.5	-0.24	0.57	-2.51	5.09
Coax Loss (dB)	2.3	2.5	2.6	4.1	4.3
Final Gain less Loss (dB)	-3.8	-2.74	-2.03	-6.61	0.79
Output Power plus Final Gain (dBm EIRP)	21.04	21.6	22.1	14.7	25.2

9 Omni Directional Antenna (311201) With 20' RG-6 311201-0620

Antenna Gains (dBi)	-1.5	-0.24	0.57	-2.51	5.09
Coax Loss (dB)	1.5	1.6	1.7	2.5	2.7
Final Gain less Loss (dB)	-3	-1.84	-1.13	-5.01	2.39
Output Power plus Final Gain (dBm EIRP)	21.8	22.5	23.0	16.3	26.8

10 Mini-Mag Antenna With 12.5' RG-174 301126

Antenna Gains (dBi)	-1.42	-1.69	-1.4	-0.59	0.42
Coax Loss (dB)	2.8	3.0	3.7	4.5	4.7
Final Gain less Loss (dB)	-4.22	-4.69	-5.1	-5.09	-4.28
Output Power plus Final Gain (dBm EIRP)	20.6	19.7	19.0	16.2	20.1

11 Yagi 301111 With 140' RG-11 301111-11140

Antenna Gains (dBi)	10	10	10.8	-6.8	-14.9
Coax Loss (dB)	5.76	6.17	6.43	10.36	10.94
Final Gain less Loss (dB)	4.24	3.83	4.37	-17.16	-25.84
Output Power plus Final Gain (dBm EIRP)	29.1	28.2	28.5	4.1	-1.4

12 Omni Directional Antenna 311201 With 20' RG-11 311201-1120

Antenna Gains (dBi)	-1.5	-0.2	0.6	-2.5	5.1
Coax Loss (dB)	0.8	0.9	0.9	1.5	1.6
Final Gain less Loss (dB)	-2.32	-1.12	-0.34	-3.99	3.53
Output Power plus Final Gain (dBm EIRP)	22.5	23.2	23.8	17.3	27.9



Fixed Outside Antenna Kit Options

FCC ID: PWO460021

Final Output Power Limited to 30 dBm EIRP in all frequency bands

Uplink Frequency (MHz)	698-716	777-787	824-849	1710-1755	1850-1915
Uplink Output Power (dBm)	24.84	24.35	24.1	21.3	24.4

13 Panel Antenna With 75' Wilson 400 314453-40075

Antenna Gains (dBi)	3.84	3.63	4.4	8.21	10.04
Coax Loss (dB)	2.8	3.0	3.6	4.4	5.4
Final Gain less Loss (dB)	1.04	0.63	0.8	3.81	4.64
Output Power plus Final Gain (dBm EIRP)	25.9	25.0	24.9	25.1	29.0

14 Panel Antenna With 40' RG-6 314473-0640

Antenna Gains (dBi)	3.84	3.63	4.4	8.21	10.04
Coax Loss (dB)	3.0	3.2	3.4	5.1	5.3
Final Gain less Loss (dB)	0.84	0.43	1.0	3.11	4.74
Output Power plus Final Gain (dBm EIRP)	25.7	24.8	25.1	24.4	29.1

15 Grey Brick w/20' RG-6 311141-0620

Antenna Gains (dBi)	-2.9	-0.6	1.2	-0.4	5.5
Coax Loss (dB)	1.5	1.6	1.7	2.5	2.7
Final Gain less Loss (dB)	-4.4	-2.2	-0.5	-2.9	2.8
Output Power plus Final Gain (dBm EIRP)	20.44	22.15	23.6	18.4	27.2

16 Grey Panel With 20' RG-11 311141-1120

Antenna Gains (dBi)	-2.9	-0.6	1.2	-0.4	5.5
Coax Loss (dB)	0.9	0.9	1.0	1.5	1.6
Final Gain less Loss (dB)	-3.75	-1.48	0.25	-1.88	3.94
Output Power plus Final Gain (dBm EIRP)	21.1	22.9	24.4	19.4	28.3

17 Panel Antenna With 75' RG-11 314473-1175

Antenna Gains (dBi)	3.8	3.6	4.4	8.2	10
Coax Loss (dB)	3.0	3.3	3.4	5.5	5.8
Final Gain less Loss (dB)	0.77	0.34	0.98	2.66	4.18
Output Power plus Final Gain (dBm EIRP)	25.6	24.7	25.1	24.0	28.6

18 Wide Band Directional Antenna With 75' RG-11 314475-1175

Antenna Gains (dBi)	7.3	7.2	7.8	7.9	9.1
Coax Loss (dB)	3.07	3.3	3.42	5.55	5.9
Final Gain less Loss (dB)	4.23	3.91	4.38	2.35	3.24
Output Power plus Final Gain (dBm EIRP)	29.1	28.3	28.5	23.7	27.6



Fixed Outside Antenna Kit Options

FCC ID: PWO460021

Final Output Power Limited to 30 dBm EIRP in all frequency bands

Uplink Frequency (MHz)	698-716	777-787	824-849	1710-1755	1850-1915
Uplink Output Power (dBm)	24.84	24.35	24.1	21.3	24.4

19 Yagi Antenna 301111 With 170' Wilson 400 301111-400170

Antenna Gains (dBi)	10.0	10.0	10.8	-6.8	-13.8
Coax Loss (dB)	5.8	6.1	6.3	9.4	9.8
Final Gain less Loss (dB)	4.2	3.9	4.5	-16.2	-23.6
Output Power plus Final Gain (dBm EIRP)	29.04	28.3	28.6	5.1	0.8

20 Omni Consumer 304421 With 20' RG-11 304421-1120

Antenna Gains (dBi)	1.9	0.0	1.16	5.11	3.81
Coax Loss (dB)	0	0	0.0	1.3	0
Final Gain less Loss (dB)	1.9	0.02	1.16	3.81	3.81
Output Power plus Final Gain (dBm EIRP)	26.8	24.4	25.3	25.1	28.2

21 Omni Consumer 304421 With 10' RG-174 304421-17410

Antenna Gains (dBi)	1.9	0.0	1.16	5.11	3.81
Coax Loss (dB)	0	0	0.0	1.3	0
Final Gain less Loss (dB)	1.9	0.02	1.16	3.81	3.81
Output Power plus Final Gain (dBm EIRP)	26.8	24.4	25.3	25.1	28.2

22 Omni Consumer 304421 With 10' RG-6 304421-0610

Antenna Gains (dBi)	1.9	0.0	1.16	5.11	3.81
Coax Loss (dB)	0	0	0.0	1.3	0
Final Gain less Loss (dB)	1.9	0.02	1.16	3.81	3.81
Output Power plus Final Gain (dBm EIRP)	26.8	24.4	25.3	25.1	28.2

23 Omni Consumer 304421 With 10' RG-58 304421-5810

Antenna Gains (dBi)	1.9	0.0	1.16	5.11	3.81
Coax Loss (dB)	0	0	0.0	1.3	0
Final Gain less Loss (dB)	1.9	0.02	1.16	3.81	3.81
Output Power plus Final Gain (dBm EIRP)	26.8	24.4	25.3	25.1	28.2

24 Omni Enterprise 304422 With 20' Wilson 400 304422-40020

Antenna Gains (dBi)	1.33	1.02	1.34	4.76	4.65
Coax Loss (dB)	0.0	0.0	0.0	1.0	0.0
Final Gain less Loss (dB)	1.3	1.0	1.3	3.81	4.7
Output Power plus Final Gain (dBm EIRP)	26.2	25.4	25.4	25.1	29.1



Fixed Outside Antenna Kit Options

FCC ID:

PWO460021

Final Output Power Limited to 30 dBm EIRP in all frequency bands

Uplink Frequency (MHz)	698-716	777-787	824-849	1710-1755	1850-1915
Uplink Output Power (dBm)	24.84	24.35	24.1	21.3	24.4

25 Omni Enterprise 304422 With 10' RG-58		304422-5810			
Antenna Gains (dBi)	1.33	1.02	1.34	4.76	4.65
Coax Loss (dB)	0.0	0.0	0.0	1.0	0.0
Final Gain less Loss (dB)	1.3	1.0	1.3	3.81	4.7
Output Power plus Final Gain (dBm EIRP)	26.2	25.4	25.4	25.1	29.1

26 Omni Enterprise 304422 With 20' RG-11		304422-1120			
Antenna Gains (dBi)	1.33	1.02	1.34	4.76	4.65
Coax Loss (dB)	0.0	0.0	0.0	1.0	0.0
Final Gain less Loss (dB)	1.3	1.0	1.3	3.81	4.7
Output Power plus Final Gain (dBm EIRP)	26.2	25.4	25.4	25.1	29.1



Mobile Outside Antenna Kit Options

FCC ID: PWO460021

Final Output Power Limited to 30 dBm EIRP in all frequency bands

Uplink Frequency (MHz)	698-716	777-787	824-849	1710-1755	1850-1915
Uplink Output Power (dBm)	24.84	24.35	24.1	21.3	24.4

1 Magnet Mount w/12.5' RG-174 311703

Antenna Gains (dBi)	-15.07	-4.23	0.69	-1.99	1.13
Coax Loss (dB)	2.8	3.0	3.7	4.5	4.7
Final Gain less Loss (dB)	-17.9	-7.2	-3.0	-6.5	-3.6
Output Power plus Final Gain (dBm EIRP)	7.0	17.1	21.1	14.8	20.8

2 Magnet Mount w/12.5' RG-174 301103 314202 311125 311128

Antenna Gains (dBi)	-4.88	0.09	1.97	-6.99	2.51
Coax Loss (dB)	2.8	3.0	3.7	4.5	4.7
Final Gain less Loss (dB)	-7.7	-2.9	-1.7	-11.5	-2.2
Output Power plus Final Gain (dBm EIRP)	17.2	21.4	22.4	9.81	22.2

3 Marine Antenna w/10' RG-58 311130-5810

Antenna Gains (dBi)	-1.0	-1.6	0.65	-1.68	3.57
Coax Loss (dB)	1.2	1.2	1.3	2.1	2.1
Final Gain less Loss (dB)	-2.2	-2.9	-0.6	-3.7	1.4
Output Power plus Final Gain (dBm EIRP)	22.7	21.5	23.5	17.6	25.8

4 Glass Mount w/14' RG-58 311102

Antenna Gains (dBi)	-3.68	-2.54	-0.86	2.19	3.39
Coax Loss (dB)	1.6	1.7	1.8	2.9	3.0
Final Gain less Loss (dB)	-5.3	-4.2	-2.7	-0.7	0.4
Output Power plus Final Gain (dBm EIRP)	19.6	20.1	21.4	20.6	24.8

5 NMO Antenna w/10' RG-58 311104-5810

Antenna Gains (dBi)	-4.1	-0.9	2.48	-3.51	1.8
Coax Loss (dB)	1.2	1.2	1.3	2.1	2.1
Final Gain less Loss (dB)	-5.3	-2.1	1.2	-5.6	-0.3
Output Power plus Final Gain (dBm EIRP)	19.6	22.2	25.3	15.7	24.1

6 Trucker Antenna w/10.5' RG-58 311701

Antenna Gains (dBi)	-14.11	-0.71	2.18	-0.15	2.66
Coax Loss (dB)	1.2	1.3	1.4	2.2	2.3
Final Gain less Loss (dB)	-15.3	-2.0	0.8	-2.4	0.4
Output Power plus Final Gain (dBm EIRP)	9.5	22.3	24.9	19.0	24.8



Mobile Outside Antenna Kit Options

FCC ID: PWO460021

Final Output Power Limited to 30 dBm EIRP in all frequency bands

Uplink Frequency (MHz)	698-716	777-787	824-849	1710-1755	1850-1915
Uplink Output Power (dBm)	24.84	24.35	24.1	21.3	24.4

7 Trucker Antenna w/13.5' RG-58 311119

Antenna Gains (dBi)	-1.36	0.36	1.21	-2.3	3.57
Coax Loss (dB)	1.6	1.7	1.7	2.8	2.9
Final Gain less Loss (dB)	-3.0	-1.3	-0.5	-5.1	0.7
Output Power plus Final Gain (dBm EIRP)	21.9	23.0	23.6	16.2	25.1

8 Trucker Antenna w/13.5' RG-58 311133

Antenna Gains (dBi)	-3.3	0.2	1.15	-4.75	4.22
Coax Loss (dB)	1.6	1.7	1.7	2.8	2.9
Final Gain less Loss (dB)	-4.9	-1.6	-0.6	-7.6	1.3
Output Power plus Final Gain (dBm EIRP)	20.0	22.8	23.6	13.8	25.7

9 NMO Antenna 10' RG-174 311104-17410

Antenna Gains (dBi)	-4.1	-0.9	2.48	-3.51	1.8
Coax Loss (dB)	2.3	2.4	3.0	3.6	3.8
Final Gain less Loss (dB)	-6.4	-3.3	-0.5	-7.1	-2.0
Output Power plus Final Gain (dBm EIRP)	18.5	21.0	23.6	14.2	22.4

10 Mini-Mag Mount w/12.5' RG-174 301126 301113

Antenna Gains (dBi)	-1.4	-1.7	-1.4	-0.6	0.4
Coax Loss (dB)	2.8	3	3.7	4.5	4.7
Final Gain less Loss (dB)	-4.2	-4.7	-5.1	-5.1	-4.3
Output Power plus Final Gain (dBm EIRP)	20.64	19.65	19	16.2	20.1

11 Marine Antenna w/20' RG-58 304415 304420

Antenna Gains (dBi)	2.86	1.2	1.69	2.78	5.01
Coax Loss (dB)	2.4	2.4	2.7	4.2	4.6
Final Gain less Loss (dB)	0.5	-1.2	-1.0	-1.4	0.4
Output Power plus Final Gain (dBm EIRP)	25.3	23.1	23.1	19.9	24.8

12 NMO Antenna w/10' RG-58 311112-5810

Antenna Gains (dBi)	-3.16	-0.45	2.47	-2.6	-0.65
Coax Loss (dB)	1.2	1.2	1.3	2.1	2.1
Final Gain less Loss (dB)	-4.4	-1.7	1.2	-4.7	-2.8
Output Power plus Final Gain (dBm EIRP)	20.5	22.7	25.3	16.6	21.7



Mobile Outside Antenna Kit Options

FCC ID:

PWO460021

Final Output Power Limited to 30 dBm EIRP in all frequency bands

Uplink Frequency (MHz)	698-716	777-787	824-849	1710-1755	1850-1915
Uplink Output Power (dBm)	24.84	24.35	24.1	21.3	24.4

13 NMO Antenna w/10' RG-58 314203-5810

Antenna Gains (dBi)	-1.57	0.48	1.82	-5.74	0.75
Coax Loss (dB)	1.2	1.2	1.3	2.1	2.1
Final Gain less Loss (dB)	-2.8	-0.7	0.5	-7.8	-1.4
Output Power plus Final Gain (dBm EIRP)	22.1	23.6	24.6	13.5	23.1

14 NMO Antenna 10' RG-174 311112-17410

Antenna Gains (dBi)	-3.16	-0.45	2.47	-2.6	-0.65
Coax Loss (dB)	2.3	2.4	3.0	3.6	3.8
Final Gain less Loss (dB)	-5.5	-2.9	-0.5	-6.2	-4.5
Output Power plus Final Gain (dBm EIRP)	19.4	21.5	23.6	15.1	20.0

15 NMO Antenna 10' RG-174 314203-17410

Antenna Gains (dBi)	-1.57	0.48	1.82	-5.74	0.75
Coax Loss (dB)	2.3	2.4	3.0	3.6	3.8
Final Gain less Loss (dB)	-3.9	-1.9	-1.2	-9.3	-3.1
Output Power plus Final Gain (dBm EIRP)	21.0	22.4	22.9	12.0	21.4

16 Trucker Antenna w/10.5' RG-58 311101

Antenna Gains (dBi)	-4.51	0.4	1.72	-3.62	6.12
Coax Loss (dB)	1.2	1.3	1.4	2.2	2.3
Final Gain less Loss (dB)	-5.7	-0.9	0.3	-5.8	3.8
Output Power plus Final Gain (dBm EIRP)	19.1	23.4	24.4	15.5	28.2



Mobile Outside Antenna Kit Options

FCC ID:

PWO460021

Final Output Power Limited to 30 dBm EIRP in all frequency bands

Uplink Frequency (MHz)	698-716	777-787	824-849	1710-1755	1850-1915
Uplink Output Power (dBm)	24.84	24.35	24.1	21.3	24.4

17 Trucker Antenna w/15' RG-58 304414 304415

Antenna Gains (dBi)	2.86	1.2	1.69	2.78	5.01
Coax Loss (dB)	1.8	1.8	2.0	3.2	3.5
Final Gain less Loss (dB)	1.1	-0.6	-0.3	-0.4	1.6
Output Power plus Final Gain (dBm EIRP)	25.9	23.7	23.8	20.9	26.0

18 Marine Antenna 304416 w/20' L-195 304416

Antenna Gains (dBi)	2.9	1.2	1.7	2.8	5
Coax Loss (dB)	2.4	2.4	2.7	4.2	4.6
Final Gain less Loss (dB)	0.5	-1.2	-1.0	-1.4	0.4
Output Power plus Final Gain (dBm EIRP)	24.8	24.4	24.1	21.3	24.4

19 Marine Antenna 304420 w/20' L-195 304420

Antenna Gains (dBi)	2.9	1.2	1.7	2.8	5
Coax Loss (dB)	2.4	2.4	2.7	4.2	4.6
Final Gain less Loss (dB)	0.5	-1.2	-1.0	-1.4	0.4
Output Power plus Final Gain (dBm EIRP)	25.9	23.7	23.8	20.9	26.0

Uplink Frequency Band (MHz)	698-716	777-787	824-849	1710-1755	1850-1915
Measured Uplink Gain (dB)	45.74	47.05	45.20	43.50	44.23
Measured RSSI Shutoff (dBm/MHz)	-51	-51.40	-52.07	-48.31	-49.30
MSCL Minimum (dB)	28.74	29.65	27.13	29.19	28.93
1.5' Separation Distance Path Loss (dB)	34.70	35.57	36.16	42.48	43.21
Polarity Loss (dB)	3.0	3.0	3.0	3.0	3.0
Max Antenna Gain Less Cable Loss (dB)	8.96	8.92	12.03	15.00	17.00

1 Inside Antenna Kit 311127: Slim Low Profile with 10' RG-174

Antenna Gain Less Cable Loss (dB)	-5.1	-3.6	-1.7	-6.2	-6.9
	okay	okay	okay	okay	okay
	-14.05	-12.47	-13.68	-21.19	-23.91

2 Inside Antenna Kit 311106: Low Profile with 14' RG-58

Antenna Gain Less Cable Loss (dB)	-7.2	-5.9	-3.3	-1.8	-0.7
	okay	okay	okay	okay	okay
	-16.19	-14.80	-15.32	-16.83	-17.65

Uplink Frequency Band (MHz)	698-716	777-787	824-849	1710-1755	1850-1915
Measured Uplink Gain (dB)	45.74	47.05	45.2	43.5	44.23
Measured RSSI Shutoff (dBm/MHz)	-51	-51.4	-52.07	-48.31	-49.3
MSCL Minimum (dB)	28.74	29.65	27.13	29.19	28.93
3' Separation Distance Path Loss (dB)	28.68	29.55	30.14	36.46	37.18
Polarity Loss (dB)	3.0	3.0	3.0	3.0	3.0
Max Antenna Gain Less Cable Loss (dB)	2.94	2.90	6.01	10.27	11.25

3 Inside Antenna Kit 311249: DT with 13' RG-58

Antenna Gain Less Cable Loss (dB)	0.4	0.7	2.1	-0.6	-1.2
	okay	okay	okay	okay	okay
	-2.54	-2.20	-3.91	-10.87	-12.45



FCC ID: PWO460021

Uplink Frequency Band (MHz)	698-716	777-787	824-849	1710-1755	1850-1915
Measured Uplink Gain (dB)	45.74	47.05	45.20	43.50	44.23
Measured RSSI Shutoff (dBm/MHz)	-44.50	-44.50	-45.20	-44.00	-43.20
MSCL Minimum (dB)	28.74	29.65	27.13	29.19	28.93
6' Separation Distance Path Loss (dB)	34.70	35.57	36.16	42.48	43.21
Polarity Loss	3.0	3.0	3.0	3.0	3.0
Max Antenna Gain Less Cable Loss (dB)	8.96	8.92	12.03	15.00	15.08

1 Inside Antenna Kit 311135-40060: Panel w/60' LMR 400

Antenna Gain Less Cable Loss (dB)	1.54	1.21	1.46	4.66	5.68
	okay	okay	okay	okay	okay
Margin (dB)	-7.42	-7.71	-10.57	-10.34	-9.40

2 Inside Antenna Kit 311155-40060: Panel w/60' LMR 400

Antenna Gain Less Cable Loss (dB)	1.54	1.21	1.46	4.66	5.68
	okay	okay	okay	okay	okay
Margin (dB)	-7.42	-7.71	-10.57	-10.34	-9.40

3 Inside Antenna Kit 311135-5820: Panel w/20' RG-58

Antenna Gain Less Cable Loss (dB)	1.52	1.14	1.82	4.09	5.75
	okay	okay	okay	okay	okay
Margin (dB)	-7.44	-7.78	-10.21	-10.91	-9.33

4 Inside Antenna Kit 311155-0630: Panel w/30' RG-6

Antenna Gain Less Cable Loss (dB)	1.56	1.20	1.88	4.40	6.05
	okay	okay	okay	okay	okay
Margin (dB)	-7.40	-7.72	-10.15	-10.60	-9.03

5 Inside Antenna Kit 309900-50N: 2 Panel Antennas and a 50 Ohm 3-Way Splitter

Antenna Gain Less Cable/Splitter Loss (dB)	2.13	2.13	1.33	5.09	7.49
	okay	okay	okay	okay	okay
Margin (dB)	-6.83	-6.79	-10.70	-9.91	-7.59

6 Inside Antenna Kit 309902-75F: 2 Panel Antennas and a 75 Ohm 3-Way Splitter

Antenna Gain Less Cable/Splitter Loss (dB)	2.13	2.13	1.33	5.09	7.49
	okay	okay	okay	okay	okay
Margin (dB)	-6.83	-6.79	-10.70	-9.91	-7.59

7 Inside Antenna Kit 309903-75F: 3 Panel Antennas and three 75 Ohm 2-Way Splitter

Antenna Gain Less Cable/Splitter Loss (dB)	2.13	2.13	1.33	5.09	7.49
	okay	okay	okay	okay	okay
Margin (dB)	-6.83	-6.79	-10.70	-9.91	-7.59

8 Inside Antenna Kit 309904-75F: 1 Panel Antenna and a 75 Ohm 2-Way Splitter

Antenna Gain Less Cable/Splitter Loss (dB)	2.13	2.13	1.33	5.09	7.49
	okay	okay	okay	okay	okay
Margin (dB)	-6.83	-6.79	-10.70	-9.91	-7.59

9 Inside Antenna Kit 309905-50N: 3 Panel Antennas and three 50 Ohm 2-Way Splitter

Antenna Gain Less Cable/Splitter Loss (dB)	2.13	2.13	1.33	5.09	7.49
	okay	okay	okay	okay	okay
Margin (dB)	-6.83	-6.79	-10.70	-9.91	-7.59

10 Inside Antenna Kit 311155-1150: Panel w/50' RG-11

Antenna Gain Less Cable Loss (dB)	1.80	1.44	2.12	4.51	6.13
	okay	okay	okay	okay	okay
Margin (dB)	-7.16	-7.48	-9.91	-10.49	-8.95

11 Inside Antenna Kit 304412-40010: Dome w/10' LMR 400

Antenna Gain Less Cable Loss (dB)	0.64	1.56	0.95	4.62	4.88
	okay	okay	okay	okay	okay
Margin (dB)	-8.32	-7.36	-11.08	-10.38	-10.20

12 Inside Antenna Kit 304412-5810: Dome Antenna w/10' RG-58

Antenna Gain Less Cable Loss (dB)	0.07	0.93	0.36	3.36	3.67
	okay	okay	okay	okay	okay
Margin (dB)	-8.89	-7.99	-11.67	-11.64	-11.41

13 Inside Antenna Kit 304419-1110: Dome w/10' RG-11

Antenna Gain Less Cable Loss (dB)	0.82	1.73	1.19	4.68	5.03
	okay	okay	okay	okay	okay
Margin (dB)	-8.14	-7.19	-10.84	-10.32	-10.05

14 Inside Antenna Kit 304419-17410: Dome Antenna w/10' RG-174

Antenna Gain Less Cable Loss (dB)	-1.04	-0.23	-1.32	1.79	2.02
	okay	okay	okay	okay	okay
Margin (dB)	-10.00	-9.15	-13.35	-13.21	-13.06

15 Inside Antenna Kit 304419-0610: Dome Antenna w/10' RG-6

Antenna Gain Less Cable Loss (dB)	0.47	1.36	0.81	4.15	4.48
	okay	okay	okay	okay	okay
Margin (dB)	-8.49	-7.56	-11.22	-10.85	-10.60

Uplink Frequency Band (MHz)	698-716	777-787	824-849	1710-1755	1850-1915
Measured Uplink Gain (dB)	45.74	47.05	45.2	43.5	44.23
Measured RSSI Shutoff (dBm/MHz)	-44.50	-44.50	-45.20	-44.00	-43.20
MSCL Minimum (dB)	28.74	29.65	27.13	29.19	28.93
3' Separation Distance Path Loss (dB)	28.68	29.55	30.14	36.46	37.18
Polarity Loss	3.0	3.0	3.0	3.0	3.0
Max Antenna Gain Less Cable Loss (dB)	2.94	2.90	6.01	10.27	11.25

16 Inside Antenna Kit 301211: Desktop Antenna w/5' RG-174

Antenna Gain Less Cable Loss (dB)	-0.73	-2.07	-1.28	-1.43	-0.98
	okay	okay	okay	okay	okay
Margin (dB)	-3.67	-4.97	-7.29	-11.70	-12.23