



3301 E. Deseret Drive, St. George, UT 84790
www.wilsonelectronics.com • info@wilsonelectronics.com
phone 1-800-204-4104 • fax 1-435-656-2432

July 7, 2017

Subject: RF MPE EXPOSURE
Re: FCC ID: PWO460035

To Whom It May Concern:

The MPE calculations for model 460035 signal booster were done for each frequency band: 700 MHz Band 12, 700 MHz Band 13, 800 MHz, 1900 MHz, and 1700 MHz. For each band one calculation was done; this included the worst case scenario for each of mobile outside antennas that may be connected to this signal booster. The order of the attached calculations is as follows:

700 MHz Band 12:

1. Outside Antenna: 304415

700 MHz Band 13:

1. Outside Antenna: 304415

800 MHz band:

1. Outside Antenna: 311104

1900 MHz band:

1. Outside Antenna: 311101

1700MHz band:

1. Outside Antenna: 304415

A booster's uplink power must not exceed 1 watt equivalent isotropic radiated power (EIRP) for each band of operation. Composite downlink power must not exceed 0.05 watt EIRP for each band of operation (20.21(e)(8)(i)(D)). The following formula was used to calculate the equivalent isotropic radiated power:

$$\text{EIRP} = \text{Power Out (Watts)} * \text{Duty Cycle Percent} * \text{Antenna Gain (non-log)} * \text{Coax loss (non-log)}$$

The power density (mW/cm^2) is calculated using the following formula:

$$\text{Calculated Power Density} = 1000 * \text{EIRP (Watts)} / (4 * \pi * (\text{Distance from Antenna (cm)})^2)$$

Sincerely,

A handwritten signature in black ink, appearing to read 'Patrick L. Cook'.

Patrick L. Cook
Chief Technology Officer



Minimum Safe Distance From Antennas Based upon FCC OET Bulletin 65 and other FCC Sources

INPUT DATA

| | |
|-----------------------------|---------|
| Frequency MHz | 698 |
| Pout Watts | 0.07482 |
| Duty Cycle Percent | 100.0% |
| Ant. Gain dBi | 2.90 |
| Coax Loss dB | 0.00 |
| Distance From Antenna In cm | 20.3 |

RESULTS OF CALCULATIONS

| | |
|--|--------|
| Ant. Gain less Coax Loss dBi | 2.90 |
| Distance From Antenna In Inches | 8.00 |
| EIRP (Watts) | 0.1459 |
| FCC Power Density Limit (mw/cm ²) | 0.47 |
| Calculated Power Density (mw/cm ²) | 0.0281 |

REFERENCE DATA

| | |
|---|--------|
| Pout dBm | 18.74 |
| Antenna Gain (non-log) | 1.95 |
| Coax loss (non-log) | 1.00 |
| General FCC Limit (mw/cm ²) | f/1500 |



Minimum Safe Distance From Antennas Based upon FCC OET Bulletin 65 and other FCC Sources

INPUT DATA

| | |
|-----------------------------|---------|
| Frequency MHz | 776 |
| Pout Watts | 0.14355 |
| Duty Cycle Percent | 100.0% |
| Ant. Gain dBi | 1.20 |
| Coax Loss dB | 0.00 |
| Distance From Antenna In cm | 20.3 |

RESULTS OF CALCULATIONS

| | |
|--|--------|
| Ant. Gain less Coax Loss dBi | 1.20 |
| Distance From Antenna In Inches | 8.00 |
| EIRP (Watts) | 0.1892 |
| FCC Power Density Limit (mw/cm ²) | 0.52 |
| Calculated Power Density (mw/cm ²) | 0.0365 |

REFERENCE DATA

| | |
|---|--------|
| Pout dBm | 21.57 |
| Antenna Gain (non-log) | 1.32 |
| Coax loss (non-log) | 1.00 |
| General FCC Limit (mw/cm ²) | f/1500 |



Minimum Safe Distance From Antennas Based upon FCC OET Bulletin 65 and other FCC Sources

INPUT DATA

| | |
|-----------------------------|---------|
| Frequency MHz | 824 |
| Pout Watts | 0.18408 |
| Duty Cycle Percent | 100.0% |
| Ant. Gain dBi | 2.48 |
| Coax Loss dB | 0.00 |
| Distance From Antenna In cm | 20.3 |

RESULTS OF CALCULATIONS

| | |
|--|--------|
| Ant. Gain less Coax Loss dBi | 2.48 |
| Distance From Antenna In Inches | 8.00 |
| EIRP (Watts) | 0.3258 |
| FCC Power Density Limit (mw/cm ²) | 0.55 |
| Calculated Power Density (mw/cm ²) | 0.0629 |

REFERENCE DATA

| | |
|---|--------|
| Pout dBm | 22.65 |
| Antenna Gain (non-log) | 1.77 |
| Coax loss (non-log) | 1.00 |
| General FCC Limit (mw/cm ²) | f/1500 |



Minimum Safe Distance From Antennas Based upon FCC OET Bulletin 65 and other FCC Sources

INPUT DATA

| | |
|-----------------------------|---------|
| Frequency MHz | 1850 |
| Pout Watts | 0.08299 |
| Duty Cycle Percent | 100.0% |
| Ant. Gain dBi | 6.12 |
| Coax Loss dB | 0.00 |
| Distance From Antenna In cm | 20.3 |

RESULTS OF CALCULATIONS

| | |
|--|--------|
| Ant. Gain less Coax Loss dBi | 6.12 |
| Distance From Antenna In Inches | 8.00 |
| EIRP (Watts) | 0.3396 |
| FCC Power Density Limit (mw/cm ²) | 1.00 |
| Calculated Power Density (mw/cm ²) | 0.0655 |

REFERENCE DATA

| | |
|---|-------|
| Pout dBm | 19.19 |
| Antenna Gain (non-log) | 4.09 |
| Coax loss (non-log) | 1.00 |
| General FCC Limit (mw/cm ²) | 1.00 |



Minimum Safe Distance From Antennas Based upon FCC OET Bulletin 65 and other FCC Sources

INPUT DATA

| | |
|-----------------------------|---------|
| Frequency MHz | 1710 |
| Pout Watts | 0.35975 |
| Duty Cycle Percent | 100.0% |
| Ant. Gain dBi | 2.80 |
| Coax Loss dB | 0.00 |
| Distance From Antenna In cm | 20.3 |

RESULTS OF CALCULATIONS

| | |
|--|--------|
| Ant. Gain less Coax Loss dBi | 2.80 |
| Distance From Antenna In Inches | 8.00 |
| EIRP (Watts) | 0.6855 |
| FCC Power Density Limit (mw/cm ²) | 1.00 |
| Calculated Power Density (mw/cm ²) | 0.1322 |

REFERENCE DATA

| | |
|---|-------|
| Pout dBm | 25.56 |
| Antenna Gain (non-log) | 1.91 |
| Coax loss (non-log) | 1.00 |
| General FCC Limit (mw/cm ²) | 1.00 |