



WILSON ELECTRONICS, LLC
 3301 E. Deseret Dr, St. George, UT 84790
 T. 1 800 204 4104 F. 1 435 673 0899 E. info@weboost.com
 www.weboost.com www.wilsonpro.com

June 26, 2020

Antenna Kitting Information Model 460062 Signal Booster

Accessory Kit Options

| Component | Type | Product Number | Gain (dBi) / Loss (dB) | | | | | |
|-----------------|--------------------|----------------|------------------------|-------------------|------------------|-------------------|-------------------|-------------------|
| | | | B12 700 MHz | B13 700 MHz | B5 800 MHz | B4 1700 MHz | B2 1900 MHz | B4 2200 MHz |
| Outdoor Antenna | Directional | 314475 | 7.5 | 7.5 | 7.3 | 8.8 | 8.8 | 8.8 |
| | | 314411 | 7.5 | 7.5 | 7.3 | 8.8 | 8.8 | 8.8 |
| | Omni | 304422 | 2 | 2 | 2 | 5 | 5 | 5 |
| | | 304423 | 2 | 2 | 2 | 5 | 5 | 5 |
| | | 304421 | 2 | 2 | 2 | 4 | 4 | 4 |
| | | 304424 | 2 | 2 | 2 | 4 | 4 | 4 |
| Outdoor Cable | Wilson 400 (75 ft) | 952375 | 2.6 | 2.6 | 2.8 | 4.3 | 4.6 | 5 |
| | RG-11 (75 ft) | 951175 | 3.1 | 3.1 | 3.4 | 5.5 | 6.0 | 6.6 |
| Indoor Cable | Wilson 400 (60 ft) | 952360 | 2.3 | 2.3 | 2.5 | 3.7 | 3.9 | 4.3 |
| | RG-11 (50 ft) | 951150 | 2.1 | 2.1 | 2.2 | 3.7 | 4.0 | 4.4 |
| Indoor Antenna | Dome | 304412 | 2 | 2 | 2 | 4 | 4 | 4 |
| | | 304419 | 2 | 2 | 2 | 4 | 4 | 4 |
| | Panel | 311135 | 5.2 | 5.2 | 4.4 | 10.1 | 10.6 | 8.2 |
| | | 311155 | 5.2 | 5.2 | 4.4 | 10.1 | 10.6 | 8.2 |

*All equivalent or lesser antennas and cables are suitable for use with 460062 signal boosters



WILSON ELECTRONICS, LLC
 3301 E. Deseret Dr, St. George, UT 84790
 T. 1 800 204 4104 F. 1 435 673 0899 E. info@weboost.com
 www.weboost.com www.wilsonpro.com

Accessory Kit Options

| Component | Type | Product Number | Gain/Loss | | | | | |
|-----------------|--------------------|----------------|-------------------|-------------------|------------------|-------------------|-------------------|-------------------|
| | | | B12 700 MHz | B13 700 MHz | B5 800 MHz | B4 1700 MHz | B2 1900 MHz | B4 2200 MHz |
| Outdoor Antenna | Panel | 314473 | 5.2 | 5.2 | 4.4 | 10.1 | 10.6 | 8.2 |
| | Directional | 301111 | 10 | 10 | 10.8 | -6.8 | -13.8 | -13.8 |
| | | 311228 | 12 | 12 | 12 | 12.9 | 13.1 | 11.2 |
| | | 314475 | 7.5 | 7.5 | 7.3 | 8.8 | 8.8 | 8.8 |
| | | 314445 | 7.2 | 7.2 | 6.9 | 8.9 | 8.4 | 9.2 |
| | Omni | 304423 | 2 | 2 | 2 | 5 | 5 | 5 |
| | | 304421 | 2 | 2 | 2 | 4 | 4 | 4 |
| Outdoor Cable | RG-6 (Qty: 2 50ft) | 290650 | 8.5 | 9 | 9.3 | 14.1 | 14.8 | 16 |
| Indoor Cable | RG-6 (50ft) | 290650 | 4.3 | 4.5 | 4.7 | 7.1 | 7.4 | 8 |
| Indoor Antenna | Dome | 304419 | 2 | 2 | 2 | 4 | 4 | 4 |
| | Panel | 301211 | -0.8 | -0.8 | 1.5 | 2.4 | 3.4 | 1.2 |
| | | 311155 | 5.2 | 5.2 | 4.4 | 10.1 | 10.6 | 8.2 |
| | | 314440 | 5.75 | 5.75 | 6 | 7.3 | 7.3 | 7.6 |
| | | 314444 | 5.75 | 5.75 | 6 | 7.3 | 7.3 | 7.6 |

*All equivalent or lesser antennas and cables are suitable for use with 460062 signal boosters

END OF REPORT