



3301 E. Deseret Drive
St. George, Utah 84790
wilsonelectronics.com
cellular@wilsonelectronics.com

Phone 1-800-204-4104 Fax 1-435-656-2432

To: CKC LABORATORIES

Attention: Randal Clark

AMPLIFIER DESCRIPTION: MODEL NUMBERS 804003 and 804004

FCC: PWO806WB56

IC: 4726A-806WB56

Frequency	806-821MHz Uplink	851-866MHz Downlink	
	43dB	50dB	60dB
Gain (up/down)	(43dB/43dB)	(50dB/50dB)	(60dB/60dB)
Flatness (up/down)	(+/- 4dB/+/-4dB)	(+/- 4dB/+/-6dB)	(+/- 4dB/+/-6dB)
Max RF (up/down)	(+31.7dBm/+10dBm)	(+31.7dBm/+10dBm)	(31.7dBm/+10dBm)
Noise Figure (down)	(3dB nominal)	(3dB nominal)	(3dB nominal)
Isolation Uplink/Downlink		More than 90dB	
Power Consumption		13.8V, 2A	

Supported Modulations: TDMA

Operational Description: The in building amplifier is a bidirectional linear amplifier that receives signals from a cell site and transmits them inside the building at a maximum RF downlink (RX) power of 10dbm (conducted). It also transmits signals from the phone back to the cell site at a maximum uplink (TX) power of +35dbm (conducted).

UPLINK PA RF3108:

Power consumption for all stated modulations **1.75A 5V 8.75watts TX 1.5watts**
(25% DUTY CYCLE)

DOWNLINK SGA-3586 MMIC:

Power consumption for all stated modulations **35MA 3.3V 80mw RX 10mw**

MAXIMUM POWER CONSUMPTION FOR AMPLIFIER: 2A 13.8V 27.6watts