

Show the worst case 100MHz middle channel in this appendix:

## 1. Frequency Stability

### 1.1 30\_Single\_Ant1

#### 1.1.1 Test Result

Band n48 Single NTN Ant1								
BW (MHz)	DL Frequency (MHz)	Test Mode	Temp. (°C)	Voltage (VDC)	Frequency Deviation (Hz)	Freq. vs. Rated (ppm)		Verdict
						Result	Limit	
CC1:100	CC1:3624.99	NR-FR1-TM1.1	25	40.8	25	0.007	≤ ±2.5	Pass
				48	31	0.009	≤ ±2.5	Pass
				55.2	32	0.009	≤ ±2.5	Pass
			-5	48	34	0.009	≤ ±2.5	Pass
			0	48	38	0.010	≤ ±2.5	Pass
			10	48	33	0.009	≤ ±2.5	Pass
			20	48	34	0.009	≤ ±2.5	Pass
			30	48	33	0.009	≤ ±2.5	Pass
		45	48	35	0.009	≤ ±2.5	Pass	
		NR-FR1-TM3.1	25	40.8	26	0.007	≤ ±2.5	Pass
				48	33	0.009	≤ ±2.5	Pass
				55.2	34	0.009	≤ ±2.5	Pass
			-5	48	35	0.010	≤ ±2.5	Pass
			0	48	37	0.010	≤ ±2.5	Pass
			10	48	32	0.009	≤ ±2.5	Pass
			20	48	33	0.009	≤ ±2.5	Pass
			30	48	31	0.009	≤ ±2.5	Pass
		45	48	36	0.01	≤ ±2.5	Pass	
		NR-FR1-TM3.1a	25	40.8	27	0.008	≤ ±2.5	Pass
				48	34	0.009	≤ ±2.5	Pass
				55.2	35	0.010	≤ ±2.5	Pass
			-5	48	36	0.01	≤ ±2.5	Pass
			0	48	38	0.011	≤ ±2.5	Pass
			10	48	33	0.009	≤ ±2.5	Pass
			20	48	34	0.009	≤ ±2.5	Pass
			30	48	32	0.009	≤ ±2.5	Pass
		45	48	37	0.010	≤ ±2.5	Pass	
		NR-FR1-TM3.2	25	40.8	28	0.008	≤ ±2.5	Pass
				48	35	0.010	≤ ±2.5	Pass
				55.2	36	0.010	≤ ±2.5	Pass
			-5	48	37	0.010	≤ ±2.5	Pass
			0	48	39	0.011	≤ ±2.5	Pass
			10	48	34	0.009	≤ ±2.5	Pass
			20	48	35	0.010	≤ ±2.5	Pass
			30	48	33	0.009	≤ ±2.5	Pass
		45	48	38	0.011	≤ ±2.5	Pass	