

RF EXPOSURE REPORT

REPORT NO.: SA971203L02

MODEL NO.: WG103

SERIES MODEL NO.: WG102v2

ACCORDING: FCC Guidelines for Human Exposure

IEEE C95.1

APPLICANT: NETGEAR, INC.

ADDRESS: 350 East Plumeria Drive San Jose, CA 95134

ISSUED BY: Bureau Veritas Consumer Products Services (H.K.)

Ltd., Taoyuan Branch

LAB ADDRESS: No. 47, 14th Ling, Chia Pau Tsuen, Lin Kou Hsiang,

Taipei Hsien 244, Taiwan, R.O.C.

TEST LOCATION: No. 19, Hwa Ya 2nd Rd, Wen Hwa Tsuen, Kwei

Shan Hsiang, Taoyuan Hsien 333, Taiwan, R.O.C.

Report No.: SA971203L02



RF EXPOSURE MEASUREMENT (MOBILE DEVICE)

1. INTRODUCTION

In this document, we try to prove the safety of radiation harmfulness to the human body for our product. The limit for Maximum Permissible Exposure (MPE) specified in FCC 1.1310 is followed. The Gain of the antenna used in this product is measured in a Fully Anechoic Chamber (FAC) calibrated for antenna measurement in ADT, and also the maximum total power input to the antenna is measured. Through the Friis transmission formula and the maximum gain of the antenna, we can calculate the distance, away from the product, where the limit of MPE is reached.

Although the Friis transmission formula is a far field assumption, the calculated result of that is an over-prediction for near field power density. We will take that as the worst case to specify the safety range.

2. RF EXPOSURE LIMIT

According to FCC 1.1310: The criteria listed in the following table shall be used to evaluate the environmental impact of human exposure to radio-frequency (RF) radiation as specified in 1.1307(b)

LIMITS FOR MAXIMUM PERMISSIBLE EXPOSURE (MPE)

FREQUENCY RANGE (MHz)	ELECTRIC FIELD STRENGTH (V/m)	MAGNETIC FIELD STRENGTH (A/m)	POWER DENSITY (mW/cm²)	AVERAGE TIME (minutes)	
(A)LIMITS FOR OCCUPATIONAL / CONTROL EXPOSURES					
300-1500			F/300	6 6	
1500-100,000			5		
(B)LIMITS FOR GENERAL POPULATION / UNCONTROLLED EXPOSURE					
300-1500			F/1500	30	
1500-100,000			1.0	30	

F = Frequency in MHz

Report No.: SA971203L02 2



3. FRIIS FORMULA

Friis transmission formula : $Pd = (Pout*G) / (4*pi*r^2)$

where

Pd = power density in mW/cm²

Pout = output power to antenna in mW

G = gain of antenna in linear scale

Pi = 3.1416

R = distance between observation point and center of the radiator in cm

If we know the maximum Gain of the antenna and the total power input to the antenna, through the calculation, we will know the MPE value at distance r.

Ref.: David K. Cheng, *Field and Wave Electromagnetics*, Second Edition, Page 640, Eq. (11-133).

4. EUT OPERATING CONDITION

The software provided by Manufacturer enabled the EUT to transmit and receive data at lowest, middle and highest channel individually.

5. CLASSIFICATION

The antenna of this product, under normal use condition, is at least 20cm away from the body of the user. Warning statement to the user for keeping at least 20cm or more separation distance with the antenna should be included in users manual. So, this device is classified as **Mobile Device**.

3

Report No.: SA971203L02



6. TEST RESULTS

6.1 ANTENNA GAIN

The maximum Gain measured in Fully Anechoic Chamber is 5dBi or 3.16228(numeric).

6.2 OUTPUT POWER INTO ANTENNA & RF EXPOSURE VALUE AT DISTANCE 20cm:

802.11b DSSS MODULATION

CHANNEL	CHANNEL FREQUENCY (MHz)	PEAK POWER OUTPUT (mW)	PEAK POWER OUTPUT (dBm)	Power Density (mW/cm²)	Limit of Power Density (mW/cm ²)
1	2412	100.693	20.03	0.063	1.000
6	2437	127.057	21.04	0.080	1.000
11	2462	89.331	19.51	0.056	1.000

802.11g OFDM MODULATION

CHANNEL	CHANNEL FREQUENCY (MHz)	PEAK POWER OUTPUT (mW)	PEAK POWER OUTPUT (dBm)	Power Density (mW/cm²)	Limit of Power Density (mW/cm ²)
1	2412	223.872	23.50	0.141	1.000
6	2437	357.273	25.53	0.225	1.000
11	2462	199.526	23.00	0.126	1.000

802.11g OFDM MODULATION (TURBO MODE)

CHANNEL	CHANNEL FREQUENCY (MHz)	PEAK POWER OUTPUT (mW)	PEAK POWER OUTPUT (dBm)	Power Density (mW/cm²)	Limit of Power Density (mW/cm ²)
6	2437	316.957	25.01	0.199	1.000

Report No.: SA971203L02 4