

RF Exposure Report

Report No.: SA150514C27B

FCC ID: PY315100302

Test Model: D7800

Received Date: Jun. 25, 2015

Test Date: Jun. 25 ~ Sep. 08, 2015

Issued Date: Sep. 09, 2015

Applicant: NETGEAR INC.

Address: 350 East Plumeria Drive, San Jose, CA 95134, USA

Issued By: Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch

Lab Address: No. 47-2, 14th Ling, Chia Pau Vil., Lin Kou Dist., New Taipei City, Taiwan, R.O.C.

Test Location: No. 19, Hwa Ya 2nd Rd., Wen Hwa Vil., Kwei Shan Dist., Taoyuan City 33383, TAIWAN (R.O.C.)



This report is for your exclusive use. Any copying or replication of this report to or for any other person or entity, or use of our name or trademark, is permitted only with our prior written permission. This report sets forth our findings solely with respect to the test samples identified herein. The results set forth in this report are not indicative or representative of the quality or characteristics of the lot from which a test sample was taken or any similar or identical product unless specifically and expressly noted. Our report includes all of the tests requested by you and the results thereof based upon the information that you provided to us. You have 60 days from date of issuance of this report to notify us of any material error or omission caused by our negligence, provided, however, that such notice shall be in writing and shall specifically address the issue you wish to raise. A failure to raise such issue within the prescribed time shall constitute your unqualified acceptance of the completeness of this report, the tests conducted and the correctness of the report contents. Unless specific mention, the uncertainty of measurement has been explicitly taken into account to declare the compliance or non-compliance to the specification. The report must not be used by the client to claim product certification, approval, or endorsement by TAF or any government agencies.



Table of Contents

Release Control Record	3
1 Certificate of Conformity	4
2 RF Exposure	5
2.1 Limits for Maximum Permissible Exposure (MPE).....	5
2.2 MPE Calculation Formula	5
2.3 Classification	5
3 Calculation Result of Maximum Conducted Power	6



A D T

Release Control Record

Issue No.	Description	Date Issued
SA150514C27B	Original release.	Sep. 09, 2015

1 Certificate of Conformity

Product: AC2600 WiFi VDSL/ADSL Modem Router

Brand: NETGEAR

Test Model: D7800

Sample Status: Engineering sample

Applicant: NETGEAR INC.

Test Date: Jun. 25 ~ Sep. 08, 2015


Standards: FCC Part 2 (Section 2.1091)

KDB 447498 D03

IEEE C95.1

The above equipment has been tested by **Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch**, and found compliance with the requirement of the above standards. The test record, data evaluation & Equipment Under Test (EUT) configurations represented herein are true and accurate accounts of the measurements of the sample's EMC characteristics under the conditions specified in this report.

Prepared by :


Polly Chien / Specialist

Date:

Sep. 09, 2015

Approved by :



Ken Liu / Senior Manager

Date:

Sep. 09, 2015

2 RF Exposure

2.1 Limits for Maximum Permissible Exposure (MPE)

Frequency Range (MHz)	Electric Field Strength (V/m)	Magnetic Field Strength (A/m)	Power Density (mW/cm ²)	Average Time (minutes)
Limits For General Population / Uncontrolled Exposure				
300-1500	F/1500	30
1500-100,000	1.0	30

F = Frequency in MHz

2.2 MPE Calculation Formula

$$P_d = (P_{out} * G) / (4 * \pi * r^2)$$

where

P_d = power density in mW/cm²

P_{out} = output power to antenna in mW

G = gain of antenna in linear scale

π = 3.1416

R = distance between observation point and center of the radiator in cm

2.3 Classification

The antenna of this product, under normal use condition, is at least 29cm away from the body of the user. So, this device is classified as **Mobile Device**.

3 Calculation Result of Maximum Conducted Power

Band	Frequency Band (MHz)	Max Power (dBm)	Antenna Gain (dBi)	Distance (cm)	Power Density (mW/cm ²)	Limit (mW/cm ²)
CDD Mode						
2.4GHz	2412	29.78	6.23	29	0.378	1
	2422	24.05	6.43	29	0.106	1
	2437	29.96	6.43	29	0.412	1
	2452	25.07	6.23	29	0.128	1
	2462	29.77	6.13	29	0.368	1
5GHz	5180	28.86	6.63	29	0.335	1
	5190	25.93	6.73	29	0.175	1
	5200	29.68	6.73	29	0.414	1
	5210	23.99	6.83	29	0.114	1
	5230	29.99	6.93	29	0.466	1
	5240	29.87	6.93	29	0.453	1
	5745	27.29	7.63	29	0.294	1
	5755	22.12	7.53	29	0.087	1
	5775	20.76	7.53	29	0.064	1
	5785	29.71	7.53	29	0.501	1
	5795	27.38	7.63	29	0.300	1
	5825	27.17	7.63	29	0.286	1

Note:

2412MHz: Directional gain = 0.21dBi + 10log(4) = 6.23dBi
 2422MHz: Directional gain = 0.41dBi + 10log(4) = 6.43dBi
 2437MHz: Directional gain = 0.41dBi + 10log(4) = 6.43dBi
 2452MHz: Directional gain = 0.21dBi + 10log(4) = 6.23dBi
 2462MHz: Directional gain = 0.11dBi + 10log(4) = 6.13dBi
 5180MHz: Directional gain = 0.61dBi + 10log(4) = 6.63dBi
 5190MHz: Directional gain = 0.71dBi + 10log(4) = 6.73dBi
 5200MHz: Directional gain = 0.71dBi + 10log(4) = 6.73dBi
 5210MHz: Directional gain = 0.81dBi + 10log(4) = 6.83dBi
 5230MHz: Directional gain = 0.91dBi + 10log(4) = 6.93dBi
 5240MHz: Directional gain = 0.91dBi + 10log(4) = 6.93dBi
 5745MHz: Directional gain = 1.61dBi + 10log(4) = 7.63dBi
 5755MHz: Directional gain = 1.51dBi + 10log(4) = 7.53dBi
 5775MHz: Directional gain = 1.51dBi + 10log(4) = 7.53dBi
 5785MHz: Directional gain = 1.51dBi + 10log(4) = 7.53dBi
 5795MHz: Directional gain = 1.61dBi + 10log(4) = 7.63dBi
 5825MHz: Directional gain = 1.61dBi + 10log(4) = 7.63dBi

Band	Frequency Band (MHz)	Max Power (dBm)	Antenna Gain (dBi)	Distance (cm)	Power Density (mW/cm ²)	Limit (mW/cm ²)
Beamforming_NSS1 Mode						
5GHz	5180	26.31	6.63	29	0.186	1
	5190	25.27	6.73	29	0.150	1
	5200	29.22	6.73	29	0.372	1
	5210	23.86	6.83	29	0.111	1
	5230	29.05	6.93	29	0.375	1
	5240	29.05	6.93	29	0.375	1
	5745	26.75	7.63	29	0.259	1
	5755	22.35	7.53	29	0.092	1
	5775	21.81	7.53	29	0.081	1
	5785	28.44	7.53	29	0.374	1
	5795	28.02	7.63	29	0.348	1
	5825	28.14	7.63	29	0.357	1

Note:

5180MHz: Directional gain = 0.61dBi + 10log(4) = 6.63dBi

5190MHz: Directional gain = 0.71dBi + 10log(4) = 6.73dBi

5200MHz: Directional gain = 0.71dBi + 10log(4) = 6.73dBi

5210MHz: Directional gain = 0.81dBi + 10log(4) = 6.83dBi

5230MHz: Directional gain = 0.91dBi + 10log(4) = 6.93dBi

5240MHz: Directional gain = 0.91dBi + 10log(4) = 6.93dBi

5745MHz: Directional gain = 1.61dBi + 10log(4) = 7.63dBi

5755MHz: Directional gain = 1.51dBi + 10log(4) = 7.53dBi

5775MHz: Directional gain = 1.51dBi + 10log(4) = 7.53dBi

5785MHz: Directional gain = 1.51dBi + 10log(4) = 7.53dBi

5795MHz: Directional gain = 1.61dBi + 10log(4) = 7.63dBi

5825MHz: Directional gain = 1.61dBi + 10log(4) = 7.63dBi

Band	Frequency Band (MHz)	Max Power (dBm)	Antenna Gain (dBi)	Distance (cm)	Power Density (mW/cm ²)	Limit (mW/cm ²)
Beamforming_NSS2 Mode						
5GHz	5180	27.57	3.62	29	0.124	1
	5190	25.49	3.72	29	0.079	1
	5200	29.96	3.72	29	0.221	1
	5210	25.18	3.82	29	0.075	1
	5230	29.87	3.92	29	0.226	1
	5240	29.97	3.92	29	0.232	1
	5745	27.25	4.62	29	0.146	1
	5755	22.84	4.52	29	0.052	1
	5775	20.76	4.52	29	0.032	1
	5785	29.65	4.52	29	0.247	1
	5795	28.49	4.62	29	0.194	1
	5825	28.60	4.62	29	0.199	1

Note:

5180MHz: Directional gain = 0.61dBi + 10log(4/2) = 3.62dBi

5190MHz: Directional gain = 0.71dBi + 10log(4/2) = 3.72dBi

5200MHz: Directional gain = 0.71dBi + 10log(4/2) = 3.72dBi

5210MHz: Directional gain = 0.81dBi + 10log(4/2) = 3.82dBi

5230MHz: Directional gain = 0.91dBi + 10log(4/2) = 3.92dBi

5240MHz: Directional gain = 0.91dBi + 10log(4/2) = 3.92dBi

5745MHz: Directional gain = 1.61dBi + 10log(4/2) = 4.62dBi

5755MHz: Directional gain = 1.51dBi + 10log(4/2) = 4.52dBi

5775MHz: Directional gain = 1.51dBi + 10log(4/2) = 4.52dB

5785MHz: Directional gain = 1.51dBi + 10log(4/2) = 4.52dBi

5795MHz: Directional gain = 1.61dBi + 10log(4/2) = 4.62dBi

5825MHz: Directional gain = 1.61dBi + 10log(4/2) = 4.62dB

CONCLUSION:

Both of the WLAN 2.4G & WLAN 5G can transmit simultaneously, the formula of calculated the MPE is:

CPD1 / LPD1 + CPD2 / LPD2 +etc. < 1

CPD = Calculation power density

LPD = Limit of power density

WLAN 2.4G + WLAN 5.0G = 0.412 + 0.501 = 0.913

Therefore, the maximum calculation of this situation is 0.913, which is less than the "1" limit.

---END---